

UNCLASSIFIED

AD 296 001

*Reproduced
by the*

**ARMED SERVICES TECHNICAL INFORMATION AGENCY
ARLINGTON HALL STATION
ARLINGTON 12, VIRGINIA**




UNCLASSIFIED

NOTICE: When government or other drawings, specifications or other data are used for any purpose other than in connection with a definitely related government procurement operation, the U. S. Government thereby incurs no responsibility, nor any obligation whatsoever; and the fact that the Government may have formulated, furnished, or in any way supplied the said drawings, specifications, or other data is not to be regarded by implication or otherwise as in any manner licensing the holder or any other person or corporation, or conveying any rights or permission to manufacture, use or sell any patented invention that may in any way be related thereto.

296 001

CATALOGED BY ASTIA
AS AD NO. 22601

RADIO CORPORATION OF AMERICA
SEMICONDUCTOR AND MATERIALS DIVISION
SOMERVILLE, N. J.



ASTIA
RECORDED
FEB 12 1963
TISIA

QUARTERLY REPORT NO. 2

for

GALLIUM ARSENIDE VARACTOR DIODES

THIS REPORT COVERS THE PERIOD

28 Sept. 1962 to 28 Dec. 1962

RADIO CORPORATION OF AMERICA

Semiconductor and Materials Division

Somerville, New Jersey

NAVY BUREAU OF SHIPS ELECTRONICS DIVISIONS

CONTRACT NO. NOBSR 87405

PROJECT SERIAL NO. SR-008031

TASK NO. 9349

31 January, 1962

Written By:

H. Kressel

Edited By:

L.R. Possemato

Approved By:

A. Blicher
A. Blicher, Manager
Special Projects
Development

G. A. Kupsky

G. A. Kupsky

D.J. Donahue
D.J. Donahue, Manager
Industrial Transistor
Development

DISTRIBUTION LIST

<u>Addressee</u>	<u>Copies</u>
Department of the Navy Bureau of Ships Semiconductor Group, Code 681A1A Washington 25, D.C. ATTN: Mr. A.H. Young	3
Department of the Navy Bureau of Ships, Code 335 Washington 25, D.C.	2
Department of the Navy Bureau of Naval Weapons, Code RREN-4 Washington 25, D.C.	1
Department of the Navy Bureau of Naval Weapons, Code RAAV-333 Washington 25, D.C.	1
Department of the Navy Office of Naval Research Chief of Naval Research, Code 427 Washington 25, D.C. ATTN: A.A. Shostak	1
Director U.S. Naval Research Laboratory Washington 25, D.C. ATTN: Code 2020	1
Director U.S. Naval Research Laboratory Washington 25, D.C. ATTN: A. Brodzinsky, Code 5210	1
Director U.S. Naval Research Laboratory Washington 25, D.C. ATTN: G. Abraham, Code 5266	1
Commander New York Naval Shipyard Material Laboratory, Code 923 Naval Base Brooklyn 1, New York	1
Commander U.S. Naval Ordnance Laboratory White Oak, Maryland ATTN: W.W. Scanlon	1

DISTRIBUTION LIST (Cont.)

<u>Addressee</u>	<u>Copies</u>
Commanding Officer U.S. Army Signal Research and Development Laboratory Solid State Division ATTN: SIGRA/SL-PF (H. Jacobs)	1
Commander Aeronautical Systems Division ATTN: R.D. Alberts ASRNEM, AFSC Wright-Patterson Air Force Base Dayton, Ohio	1
Commander, ESD (AFCRL) ATTN: R.P. Dolan, CRR-CSA L.G. Hanscom Field Bedford, Massachusetts	1
Ordnance Corps, Department of the Army Diamond Ordnance and Fuze Laboratories Connecticut Avenue & Van Ness Street, N.W. Washington 25, D.C. ATTN: T.M. Liimatainen	1
Director National Bureau of Standards Electronics and Electricity Division Electronic Engineering Section Washington 25, D.C. ATTN: Gustave Shapiro	1
Advisory Group on Electron Devices 346 Broadway, 8th. Floor New York 13, New York ATTN: H.J. Sullivan	3
Commander Armed Services Technical Information Agency ATTN: TIAI Arlington Hall Station Arlington 12, Virginia	10
Armour Research Foundation Technology Center Chicago 16, Illinois ATTN: J.W. Buttrey	1
Batelle Memorial Institute 505 King Avenue Columbus, Ohio ATTN: C.S. Pett	1

DISTRIBUTION LIST (Cont.)

<u>Addressee</u>	<u>Copies</u>
Bell Telephone Laboratories Murray Hill, New Jersey ATTN: R.M. Ryder	1
Hughes Products Semiconductor Division 500 Superior Avenue Newport Beach, California ATTN: E.L. Steele	1
IBM Components Laboratory Bldg. 701 - Dept. 677 Poughkeepsie, New York ATTN: J.E. Thomas, Jr.	1
Massachusetts Institute of Technology Lincoln Laboratory Lexington 73, Massachusetts ATTN: R.H. Rediker	1
Philco Corporation Lansdale Division Lansdale, Pa. ATTN: C.G. Thornton	1
Raytheon Company Research Division Library 28 Seyon Street Waltham 54, Massachusetts	1
Sylvania Electric Products, Inc. Semiconductor Division 100 Sytan Road Woburn, Massachusetts ATTN: T.A. Longo	1
Texas Instruments, Inc. Central Research and Engineering P.O. Box 5474 Dallas 22, Texas ATTN: Technical Reports Service	1
General Electric Company Semiconductor Products Department Electronics Park, Syracuse, New York ATTN: N. Holonyak	1

DISTRIBUTION LIST (Cont.)

<u>Addressee</u>	<u>Copies</u>
Microwave Associates, Inc. Burlington, Massachusetts ATTN: A. Uhlir, Jr.	1
Micro State Electronics Corporation 152 Floral Avenue Murray Hill, New Jersey ATTN: A. Kestenbaum	1
Microwave Semiconductor and Instruments, Inc. 116-06 Myrtle Avenue Richmond Hill 18, New York ATTN: A. Lederman	1
Stanford Research Institute Material Sciences Division Menlo Park, California ATTN: F.A. Halden	1
American Electronic Laboratories, Inc. Richardson Road Colmar, Pa.	1
Tyco Laboratories, Inc. Bear Hill Waltham 54, Massachusetts	1

TABLE OF CONTENTS

	<u>Part I</u>	<u>Page</u>
I.	PURPOSE	1
II.	TECHNICAL DISCUSSION.	2
	A. Device Specification.	2
	B. Device Design.	4
	1. Very Thin and Well Structures	4
	2. Epitaxial Diodes.	11
	C. Thermal Resistance.	12
	D. Electrical Measurements.	14
	1. Capacitance	14
	2. Cutoff Frequency	16
III.	CONCLUSIONS	18

Part II

I.	PROGRAM FOR NEXT PERIOD.	19
----	----------------------------------	----

LIST OF FIGURES

<u>Figure</u>	<u>Title</u>	<u>Page</u>
1	Breakdown Voltage vs. Minimum Capacitance for 100 mw Diode Input Power at 12 Gc (Best Conversion Efficiency)	3
2	Resistance vs. Pellet Thickness for Two Junction Diameters, D_j	5
3	Well Structure Cross Section.	7
4	Process Outline for Well Units.	8
5	Cross Section of Etched Well in GaAs Vapor Showing Diffused p^+ region (150X).	10
6	Reverse I-V Characteristics of an Epitaxial GaAs Diode Showing the Presence of Localized Breakdown (Layer Resistivity $\sim 5 \times 10^{16}$).. . . .	13
7	Capacitance-Voltage Curve for an Epitaxial Diode and Non-Epitaxial Diode Assuming $\phi = 1$ volt.	15
8	Smith Chart of a Typical Diode	17

LIST OF TABLES

<u>Number</u>	<u>Title</u>	<u>Page</u>
I	Characteristics of Very Thin Diodes.	6
II	Experiment Comparing Well Process to Standard.	11
III	Thermal Resistance of Gallium Arsenide Diodes.	14

ABSTRACT

During this quarter, emphasis was placed on improving cutoff frequencies of devices having breakdown voltages in excess of 14 volts. In addition to the use of epitaxial material, techniques were developed for mechanically controlling the thickness of the base region of the diodes. This approach has yielded substantial improvements in diode cutoff frequency.

PART I

I. PURPOSE

The purpose of this contract is to develop a series of gallium arsenide varactor diodes capable of yielding forty percent (40%) power conversion efficiency from 12 Gc to 24 Gc. Phase II of this contract is to develop a device that is able to meet the following circuit objectives:

- (a) Input frequency of 12 Gc
- (b) Output frequency of 24 Gc
- (c) Input power of 100 mw
- (d) Output power equal to or greater than 40 mw at 25°C

A total of ten units will be submitted to the Contracting Agency, together with all required reports.

II. TECHNICAL DISCUSSION

A. Device Specification

In the first quarterly report of this contract, expressions were derived for the power handling capability and conversion efficiency of a varactor diode. The maximum power input for optimum efficiency was shown to be:

$$P_{in} = \frac{1}{35} \omega C_{min} (\phi + V_B)^2 \dots \dots \dots (1)$$

where:

ω = input angular frequency

C_{min} = minimum junction capacitance

V_B = breakdown voltage

ϕ = built-in potential (1 volt for Gallium Arsenide)

Figure (1) shows the relationship between V_B and C_{min} which must be satisfied at 12 Gc for an input power level of 100 mw in order to obtain optimum conversion efficiency.

The conversion efficiency was shown to be determined by the ratio

$$\frac{f_{in}}{f_c (max)}$$

where:

$$f_{in} = \text{input frequency, } f_c (max) = \frac{1}{2 \pi R C_{min}}$$

R = diode series resistance

The impedance level of the circuit, was not considered in the derivation of Equation (1). It cannot, however, be neglected in practice. It is desirable to have the dynamic diode resistance at the input frequency much higher than the diode series resistance. C_{min} should therefore, be




FIGURE 1 BREAKDOWN VOLTAGE vs. MINIMUM CAPACITANCE FOR 100 mw
DIODE INPUT POWER AT 12 GC (BEST CONVERSION EFFICIENCY)

made as small as possible commensurate with power handling and power dissipation requirements.

To obtain 40% conversion efficiency, $\frac{f_{in}}{f_c(max)}$ must be equal to or

less than 0.050. At 12 Gc input frequency, $f_{c(max)}$ must therefore, be greater than 240 Gc.

B. Device Design

1. Very Thin and Well Structures

In the first report, it was shown that the use of epitaxial material offered the simplest means of producing high cutoff diodes. Serious technical difficulties still exist at this time, however, in controlling the characteristics of Gallium Arsenide epitaxial layers. An alternate approach to the use of epitaxial material is being investigated which consists in mechanically reducing the thickness of the base region directly under the junction.

Figure (2) is a plot of the resistance of the diode base region as a function of the base thickness, for two values of junction diameters. These values were obtained using the published solutions of the Laplace equation with appropriate boundary conditions. (D.P. Kennedy, J.A.P. Vol. 31, p. 1440, 1960).

It is evident that the resistance decreases most rapidly when the base thickness is under about one mil. When the resistance of the diffused region and of the contacts is minimized, substantial improvements in diode cutoff frequency are possible if very close control of the base thickness can be achieved. Attempts were made to lap or etch down pellets to a total thickness of about one mil. A number of excellent devices were produced in this manner, but yields were generally poor.




FIGURE 2 RESISTANCE VS. PELLET THICKNESS FOR TWO JUNCTION DIAMETERS, D_j

Most of the pellets crumbled during processing or were broken during alloying to the package.

The characteristics of the best very thin units fabricated this quarter are shown in Table I. The improvement of the lowest voltage

TABLE I

CHARACTERISTICS OF VERY THIN DIODES

C_{jo}	V_B	f_c (at V_B) [§]
0.647	13	330
0.365	32	390
0.636	30	380
0.412	34	360

§Extrapolated from cutoff frequency measured at -6 volts and 10 kmc/s

units (13 volts) was relatively small with thin base structures. This is to be expected since the ratio of junction radius to pellet radius is smaller than for devices made from lower resistivity material for a given value of capacitance. Figure (2) also shows that in order to bring about an appreciable resistance reduction in a one mil diameter junction, the base must be substantially thinner than for a 2.4 mil diameter unit.

An alternate approach has, therefore, been tried which consists of placing the junction either at the bottom of a well, etched to the desired depth on the wafer, or to etch a well on the reverse side of the wafer under the junction. With these techniques, the pellet is mechanically rugged since most of it is several mils thick, while the thickness of the base region under the junction may be closely controlled. Figure (3) is a drawing of the cross section of such a structure. The device is fabricated in the following manner as outlined




FIGURE 3 WELL STRUCTURE CROSS SECTION




FIGURE 4 PROCESS OUTLINE FOR WELL UNITS

in Figure (4).

1. The wafer is masked with wax, except for the desired well area.
2. The wafer is etched in aqua regia until the well is defined (about 1.5 mils deep). The wax is then cleaned off.
3. The wafer is diffused.
4. The back of the wafer is lapped down until the distance between the junction and the wafer bottom is about 0.5 mils or less.
5. The wafer is then scribed with the well located at the center of each pellet.

The subsequent operations are similar to the ones outlined in the first report. The p-contact is placed at the bottom of the well. During the electrolytic etching to define the junction, the diffused p^+ region is removed from all areas of the wafer except under the p-contact. Some problems have been experienced in accurately placing the contact inside the well, and also in controlling the well depth to close tolerances. In general, however, this process appears to be much more reproducible than the one in which the whole pellet thickness is reduced. Results achieved to date are very encouraging. Figure (5) is a photographic cross section of a well etched prior to diffusion. The diffused junction is outlined.

Table II compares one lot of well units with a control lot of 2 mil pellets made from the same crystal. The particular crystal used was of a rather high resistivity (.07 ohm-cm), in order to make the base resistance an appreciable part of the total diode resistance. The improvement brought about by the use of the well technique is, therefore, clearly discernible. Table II shows that the well units are about three times better than the control lot.



FIGURE 5 CROSS SECTION OF ETCHED WELL IN GALLIUM ARSENIDE VAPOR SHOWING
DIFFUSED p^+ REGION (150X)

TABLE II
EXPERIMENT COMPARING WELL PROCESS TO STANDARD

Well Units			Standard Units		
C_{jo} (pf)	V_B (volts)	f_c § (at V_B)	C_{jo} (pf)	V_B (volts)	f_c § (at V_B)
0.355	54	210	0.790	45	90
0.413	55	330	0.689	58	108
0.418	40	310	0.772	44	80
0.276	52	340	0.762	47	90

§ Extrapolated from cutoff frequency measured at - 6 volts and 10kmc/s

The resistance of the base region of the control lot is estimated to be approximately 5 ohms. When other resistances are considered, the computed cutoff frequency at breakdown is about 125 kmc/s close to the average measured value of 90 kmc/s.

The well units have base thicknesses of about .4 mils. The total resistance is, therefore, about 3.5 ohms, and the computed cutoff frequency at breakdown is 400 kmc/s. The agreement with the average measured values of 320 kmc/s is again reasonably close.

2. Epitaxial Diodes

Work has continued this quarter on epitaxial diodes. N-type layer resistances in the range of $3 \times 10^{16} \text{ cm}^{-3}$ to $8 \times 10^{16} \text{ cm}^{-3}$ have been used. The breakdown voltages measured on these devices were generally lower than those achieved using non-epitaxial Gallium Arsenide with similar carrier concentration. The reverse characteristic of epitaxial diodes have been found to be highly variable. A number of the diodes fabricated on low resistivity layers (10^{17} cm^{-3}) were soft

while typical non-epitaxial diodes are hard. The softness of the curves is believed to be caused by the presence of crystal defects. Some devices made on higher resistivity epitaxial layers gave evidence of the presence of localized breakdown similar to the effects found in silicon (microplasmas). (K.G. McKay "Avalanche Breakdown in Silicon", Phys. Review, Vol. 94, p. 877, 1954).

Figure (6) is an oscilloscope photograph of the discontinuous reverse I-V characteristics in the breakdown region of such a diode. The bulk breakdown appears to occur at about 18 volts, but the useful voltage range is limited to 12 volts.

The cutoff frequencies measured on the two and three best devices were in the order of 300 kmc at breakdown, with breakdowns varying from 9 to 18 volts. These are still below the values which can theoretically be expected. The cause of very high resistances found in some of the epitaxial units is not yet determined.

C. Thermal Resistance

The thermal resistance of a group of non-epitaxial diodes have been tested to determine the allowable power dissipation level. The data is shown in Table III. The allowable power dissipation is given by:

$$P_{(max)} = \frac{T_J (max) - T_A}{R_{th}}$$

where:


$T_J (max)$ = maximum allowable junction temperature

T_A = ambient temperature, and

R_{th} = thermal resistance of the device

$T_J (max)$ has been determined to be about 175°C. For $T_A = 25^\circ\text{C}$ the average calculated allowable power dissipation is in excess of one watt

2 MICROAMPERES/DIVISION



2 VOLTS/DIVISION

FIGURE 6 REVERSE I-V CHARACTERISTICS OF AN EPITAXIAL GALLIUM ARSENIDE DIODE
SHOWING THE PRESENCE OF LOCALIZED BREAKDOWN (LAYER RESISTIVITY $\sim 5 \times 10^{16}$)

per pf (zero bias) for the devices tested. This value assumes of course that an adequate heat sink is used.

Further measurements are being made on lower voltage diodes.

TABLE III

THERMAL RESISTANCE OF GALLIUM ARSENIDE DIODES

C_{jo} (pf)	V_B (volts)	Thermal Resistance °C/watt
0.813	51	90
1.060	63	91
0.764	58	91
0.765	82	112
0.604	76	102
0.850	37	94
0.637	60	146
0.449	55	148
0.805	68	161

D. Electrical Measurements

1. Capacitance

Careful measurements of capacitance as a function of reverse junction potential have been made at one mc on several epitaxial and non-epitaxial diodes. Figure (7) shows the capacitance-voltage characteristics of an epitaxial diode ($V_B = 18$ volts) and a non-epitaxial diode ($V_B = 24$ volts). The non-epitaxial diode shows a constant slope of $1/3$, indicating a normal spread of the space charge region. The epitaxial diode, however, has a break in the slope of the curve at about 7 volts, indicating that the spread of the space charge region begins to slow down at that point. This is not surprising since the




FIGURE 7 CAPACITANCE-VOLTAGE CURVE FOR AN EPITAXIAL DIODE AND NON-EPITAXIAL DIODE ASSUMING $\phi = 1$ volt

epitaxial layers are known to be generally graded. The first part of the curve yields an n factor of $1/2.5$, the remainder has a value of $1/3$.

2. Cutoff Frequency

Cutoff frequency measurements are being made using the technique outlined in the first report. The ΔQ is presently being measured between 0 volts and -2 volts, rather than between -1 volt and -6 volts, to enhance the accuracy of the measurement for high Q diodes. No substantial difference between the two methods have been found to date. Figure (8) is a Smith Chart plot of a typical diode.

17

III. CONCLUSIONS

Calculations, confirmed by experimental results, indicate that substantial improvements in series resistance may be achieved in non-epitaxial Gallium Arsenide diodes by using either thin structures or well structures. The second technique appears to be more reproducible. Continued work with epitaxial material indicates that the quality is still variable. While a small number of good devices were fabricated in the 8-18 volt range, they were not generally superior to the non-epitaxial units and were produced with a small yield.

Thermal resistance measurements indicate that the allowable power dissipation with adequate heat sinks for devices fabricated using 0.07 - 0.09 ohm-cm material is in excess of one watt per pf junction capacitance at zero bias.

The calculated characteristics required to meet the goals of Phase II of the contract have been met or exceeded by a number of the devices fabricated during this reporting period.

PART II

I. PROGRAM FOR NEXT PERIOD

- (A) Continued improvements in device structure to improve cutoff frequencies of devices with breakdown voltages in excess of 20 volts.
- (B) Further investigations of the properties of epitaxial diodes to determine the cause of the present limitations.
- (C) Improvements in device contacts to reduce series resistance.
- (D) Further measurements of thermal resistance of devices.