

AD-A054 875

WEAPONS RESEARCH ESTABLISHMENT SALISBURY (AUSTRALIA)
OBSERVATIONS OF A QUASI-PERIODIC INSTABILITY IN A LINEAR PREDIC--ETC(U)
AUG 77 D G NICHOL, R E BOGNER

F/G 17/2

UNCLASSIFIED

WRE-TR-1879(W)

NL

| OF |
AD
A054875



END
DATE
FILMED
7-78
DDC

FOR FURTHER TRAN

12

22
AN-000-937

14 WRE-TR-1879 (W)



DEPARTMENT OF DEFENCE

DEFENCE SCIENCE AND TECHNOLOGY ORGANISATION

WEAPONS RESEARCH ESTABLISHMENT

SALISBURY, SOUTH AUSTRALIA

AD A 054875

9 TECHNICAL REPORT, 1879 (W)

6 OBSERVATIONS OF A QUASI-PERIODIC INSTABILITY IN A LINEAR PREDICTION ANALYSIS OF VOICED SPEECH .

10 D.G. NICHOL R.E. BOGNER

DDC
JUN 12 1976
E

FILE COPY



12 18p.

Approved for Public Release.

* Department of Electrical Engineering, University of Adelaide.

COPY No. 34

11 AUG 77

371 700 Ave

APPROVED
FOR PUBLIC RELEASE

THE UNITED STATES NATIONAL
TECHNICAL INFORMATION SERVICE
IS AUTHORIZED TO
REPRODUCE AND SELL THIS REPORT

UNCLASSIFIED

AR-000-937

DEPARTMENT OF DEFENCE
DEFENCE SCIENCE AND TECHNOLOGY ORGANISATION
WEAPONS RESEARCH ESTABLISHMENT

TECHNICAL REPORT 1879 (W)

OBSERVATIONS OF A QUASI-PERIODIC INSTABILITY IN A LINEAR
PREDICTION ANALYSIS OF VOICED SPEECH

D.G. Nichol and R.E. Bogner*

SUMMARY

↳ A significant semiperiodic fluctuation of the vocal tract area functions derived by linear prediction of the speech waveform has been noted during apparently stationary voiced segments of speech. In one example some values of the area function varied over a range of 9:1 over a few pitch-periods. The phenomenon is attributed to 'beating' of the pitch-period and the time interval between successive computations which causes variations of the time relationship between glottal pulse and analysis window. This is supported by the fact that no fluctuations occur in the area function derived from natural or synthetic speech when the computation interval is equal to the pitch period. Any slight difference between the two leads to significant pulsations however. A simple theoretical model is used to show how the positioning of the analysis window can influence area function estimates.

↙ The problem can be largely overcome by using longer time windows (greater than 2.5 pitch periods), or alternatively by averaging the area functions over several adjacent intervals.


Approved for Public Release.

* Department of Electrical Engineering, University of Adelaide.

POSTAL ADDRESS: The Director, Weapons Research Establishment,
Box 2151, G.P.O., Adelaide, South Australia, 5001.

UNCLASSIFIED

A



DOCUMENT CONTROL DATA SHEET

Security classification of this page

UNCLASSIFIED

1 DOCUMENT NUMBERS

AR Number: AR-000-937

Report Number: WRE-TR-1879(W) ✓

Other Numbers:

2 SECURITY CLASSIFICATION

a. Complete Document: Unclassified

b. Title in Isolation: Unclassified

c. Summary in Isolation: Unclassified

3 TITLE OBSERVATIONS OF A QUASI-PERIODIC INSTABILITY IN A LINEAR PREDICTION ANALYSIS OF VOICED SPEECH ✓

4 PERSONAL AUTHOR(S):

D.G. Nichol
R.E. Bogner*

5 DOCUMENT DATE: August 1977

6 6.1 TOTAL NUMBER OF PAGES 20

6.2 NUMBER OF REFERENCES: 13

7 7.1 CORPORATE AUTHOR(S): Weapons Research Establishment

7.2 DOCUMENT (WING) SERIES AND NUMBER
Weapons Research and Development Wing TR-1879

8 REFERENCE NUMBERS

a. Task:

b. Sponsoring Agency:

9 COST CODE: 337069

10 IMPRINT (Publishing establishment): Weapons Research Establishment

11 COMPUTER PROGRAM(S) (Title(s) and language(s))

12 RELEASE LIMITATIONS (of the document): Approved for Public Release.

12.0	OVERSEAS	NO		P.R.	I	A		B		C		D		E
------	----------	----	--	------	---	---	--	---	--	---	--	---	--	---

Security classification of this page:

UNCLASSIFIED

13 ANNOUNCEMENT LIMITATIONS (of the information on these pages):

No limitation.

14 DESCRIPTORS:

a. EJC Thesaurus
Terms

Voice communication
Stability
Waveforms
Variations

b. Non-Thesaurus
Terms

15 COSATI CODES:

1702
2014

16 LIBRARY LOCATION CODES (for libraries listed in the distribution):

SW SR SD AACA NL

17 SUMMARY OR ABSTRACT:

(if this is security classified, the announcement of this report will be similarly classified)

A significant semiperiodic fluctuation of the vocal tract area functions derived by linear prediction of the speech waveform has been noted during apparently stationary voiced segments of speech. In one example some values of the area function varied over a range of 9:1 over a few pitch-periods. The phenomenon is attributed to 'beating' of the pitch-period and the time interval between successive computations which causes variations of the time relationship between glottal pulse and analysis window. This is supported by the fact that no fluctuations occur in the area function derived from natural or synthetic speech when the computation interval is equal to the pitch period. Any slight difference between the two leads to significant pulsations however. A simple theoretical model is used to show how the positioning of the analysis window can influence area function estimates.

The problem can be largely overcome by using longer time windows (greater than 2.5 pitch periods), or alternatively by averaging the area functions over several adjacent intervals.

ACCESSION for	
NTIS	Write Section <input checked="" type="checkbox"/>
DDC	Buff Section <input type="checkbox"/>
UNANNOUNCED	<input type="checkbox"/>
JUSTIFICATION	
BY	
DISTRIBUTION/AVAILABILITY CODES	
Dist.	Special
A	

TABLE OF CONTENTS

	Page No.
1. INTRODUCTION	1
2. EXPERIMENTAL RESULTS	1 - 2
2.1 The VTAF picture	1 - 2
2.2 Observations	2
3. ANALYSIS OF WINDOW POSITION EFFECTS	2 - 5
4. EXPERIMENTAL DIAGNOSIS	5 - 6
5. SUPPRESSING THE FLUCTUATIONS	6
6. CONCLUDING REMARKS	6
REFERENCES	7
TABLE 1. POLE POSITIONS IN TERMS OF FORMANT FREQUENCIES AND BANDWIDTHS (AFTER FANT(REF.13))	5

LIST OF FIGURES

1. Vocal tract area function for sentence "Speak to me now, bad kangaroo!"
- 2(a) Speech waveform for /ae/
- (b) Vocal tract area function for /ae/
3. Effect on windowed signal $s_w(n)$ of relative shift between signal and window
- (a) Window centred on signal
- (b) Window delayed with respect to signal
4. Approximation to a delayed window $w_d(n) = 0.58(1 + \cos \frac{2\pi}{128}(n-61))$ by a rising exponential 0.014×1.26^n
- 5(a) Physical tube model
- (b) Signal flow model
6. Pitch period and computation interval are equal but with different relative positions in each column
7. Changing position of pitch pulse within window leads to pulsations when $n_c = n_w$
8. Increasing n_w to $3.5 n_p$ suppresses the fluctuations, for synthetic vowel /ae/
9. Vocal tract area function for "Speak to me now, bad kangaroo!" for window $n_w = 3.5$ times pitch period n_p

1. INTRODUCTION

Several attempts have been made recently to use linear prediction analysis of speech for isolated word(ref.1,2) and spoken digit recognition(ref.3,4). The feature chosen for the recognition algorithm in these studies was the set of linear prediction coefficients. It is well known that an estimate of the vocal tract area function can be derived from these coefficients(ref.5,6,7) and the present paper arose from a study of the usefulness of this function for both speech and voice recognition. Because of the extensive information available from phonetic and articulatory studies of speech production it was believed that the vocal tract area function (VTAF) would be an advantageous feature for the pattern recognition process. To test this idea, and also to compare the various formulations of the linear prediction models, it was decided to display the VTAF as an intensity-modulated picture of vocal tract position versus time, with the area plotted as a grey-level. This is of course a similar display to the well known spectrogram. We shall refer to these displays as VTAF pictures.

Figure 1 shows a typical VTAF picture produced from real speech. The most obvious feature of this picture is the strong pulsations seen, for example, at the intervals labelled 2, 5 and 8. It is believed these pulsations are artifacts of the analysis as no evidence of them is apparent in the time series or spectrogram.

Before discussing this phenomenon in more detail we describe briefly the production of the pictures.

2. EXPERIMENTAL RESULTS

2.1 The VTAF picture

The first linear prediction model used in this study was that due to Wakita(ref.7). This is so-called auto-correlation technique and was chosen because, for non pitch-synchronous analysis, these formulations are generally more stable and robust than the "covariance" methods although for pitch-synchronous analysis the latter are capable of giving better estimates of the actual vocal tract(ref.8,9).

Suppose that the anti-aliasing filtered speech signal is sampled at frequency $f_s = 1/T$, and that n_w samples are included in each autocorrelation window and that a new computation of the VTAF is made every n_c samples. If m_l linear prediction coefficients are used then $m_v = m_l + 1$ vocal tract areas are produced at time intervals of t_c where

$$t_c = n_c T \tag{1}$$

Denoting the array of vocal tract areas $a_i(t)$ obtained at time t as a vector $\underline{a}(t)$ we have

$$\underline{a}(t) = a_1(t), a_2(t), a_3(t) \dots a_{m_v}(t) \tag{2}$$

In n successive estimates of $\underline{a}(t)$ are evaluated then the resulting sets of these $\underline{a}(t)$ may be regarded as an $(m \times n)$ matrix

$$\underline{A} = \begin{bmatrix} a_{11} & a_{12} & a_{1n} \\ a_{21} & a_{22} & a_{2n} \\ \cdot & \cdot & \cdot \\ \cdot & \cdot & \cdot \\ a_{m1} & \cdot & a_{mn} \end{bmatrix} \tag{3}$$

where we have written a_{mn} for $a_m(nT)$.

This matrix can be plotted as an $(m \times n)$ digital picture where the grey levels are assigned by some mapping from the values of the elements of A to the set of grey levels.

To produce figure 1 the values $f_s = 8192$ Hz, $m_V = 9$, $n_w = 64$, $n_c = 64$ and $n = 1024$ were used. Now a 9×1024 picture is a very cumbersome shape and so this was split into eight 9×128 subpictures, which for display purposes were interpolated (by a two-dimensional Fast Fourier Transform) into eight 36×512 subpictures. These eight subpictures were plotted, one below the other, as in figure 1 on an intensity-modulated CRT. The bottom of each subpicture represents the glottis and the top the lips. The grey levels have been assigned such that the larger the area the greater the whiteness. Thus the point of maximum constriction is the darkest region in each column. It should be noted that the Wakita model assumes a constant glottis area and thus the lower edge of each picture is a constant grey level. Some regions of the picture are blank. This is due to use of an energy-detecting algorithm which assigns arbitrary zero levels to the VTAF's when the total signal occurring in the time series window is below a given threshold (as during silences between utterances). Each subpicture represents 1 s of real time and thus 8 s is shown overall.

2.2 Observations

In figure 1 the occurrence of periods of pulsations is easily observed; the most obvious of these are indicated in the picture. The utterance shown in this picture is the phrase "Speak to me now, bad kangaroo!" repeated three times by an Australian female speaker. The observed pulsations occur during constant vowel segments where little or no real change in the vocal tract is occurring.

This is supported by an examination of the speech time series corresponding to the utterance. Figure 2(a) shows the speech waveform corresponding to the /ae / in 'bad' which for this speaker is remarkably stationary. The corresponding VTAF's are plotted in figure 2(b) and are clearly fluctuating, an effect which does not auger well for using the VTAF's in any automatic speech recognition process. The plots in figure 2(b) are in fact the square-root of the VTAF and thus the estimates of area actually vary by the order of 9:1 during this apparently stationary segment.

We had not observed this phenomenon previously, even though several VTAF pictures of Australian male speakers repeating the same phrase had been made. This suggested that the phenomenon may be sensitive to pitch period.

Now for linear prediction models of the Wakita type the analysis begins by windowing the time series by a Hanning weighting function. The only parameter which is changing during a stationary segment is thus the position of the glottal pulse within the Hanning window (unless the analysis is pitch-synchronous). We shall now examine this effect and show it can cause the observed phenomenon.

3. ANALYSIS OF WINDOW POSITION EFFECTS

We examine the effect of the time relationship between the autocorrelation window and the speech waveform (figure 3). To facilitate analysis we use a model comprising a second order (two junction, three section) vocal tract yielding an impulse response of the form

$$h(n) = r^n \cos n\omega T, n = 0, 1, 2, \dots \quad (4)$$

We use a window of the form

$$w(n) = \frac{1}{2} + \frac{1}{2} \cos \frac{2\pi(n-d)}{N}, n = -\frac{N}{2} \text{ to } \frac{N}{2} \quad (5)$$

where d is the delay whose effect is of interest, and N the duration of the window is large compared with $1/(r-1)$, i.e. the interval over which the impulse response has significant magnitude. The excitation is taken to be a unit pulse, and thus the model speech signal $s(n)$ is the same as $h(n)$.

This model is not realistic, but it does aid our appreciation of effects which can arise, and yields a sufficient explanation of our observations.

Figure 3 shows effects on the windowed signal $s_w(n)$ variation of the delay. Two cases are shown, viz.

- (a) Centred window, in which $w(n) \doteq 1$ over the effective duration of $s(n)$, i.e. we have $s_w(n) \doteq s(n)$
- (b) Delayed window, in which the curved rise of $w(n)$ progressively magnifies the signal, producing a compensation of the damping of $s(n)$.

Figure 4 shows for example the shape of the window

$$w_d(n) = 0.5[1 + \cos \frac{2\pi}{128}(n-61)] \quad (6)$$

compared with the exponential Rr_1^n with $R = 0.014$ and $r_1 = 1.26$, which were chosen in an ad hoc manner simply for demonstration purposes. The exponential appears to be a reasonable approximation to $w_d(n)$.

We see that for $s(n)$ of the form

$$s(n) = r_s^n \cos n\omega T \quad (7)$$

with $r < 1$ the delayed window would cause $s_w(n)$ to be approximately

$$s_w(n) = s(n)w_d(n) \doteq R(r_s r_1)^n \cos n\omega T \quad (8)$$

Now, for speech sampled at $10\,000\text{ s}^{-1}$, the value of r_s is likely to be in the range 0.985 to 0.9 (i.e. approximately 50 Hz to 300 Hz formant bandwidth respectively). Thus, the apparent value of the ratio corresponding to r_s in $s(n)$ as given by (7) becomes the value $r_s r_1$ in (8) and the latter may be grossly in error, and even exceed unity as with the example values of $r_1 = 1.26$ and $r_s = 0.9$.

Next we study the effect of a discrepancy in the value of r_s on the area function of a model vocal tract.

Figure 5 shows an acoustic tube (or transmission line model of a vocal tract in which there are three sections of area a_m , $m = 0$ at the lips end, 1 for the middle section and 2 at the glottis. There are thus two junctions whose volume velocity reflection coefficients μ_m , $m = 1$ and 2 are given by (ref.10)

$$\mu_m = \frac{a_{m-1} - a_m}{a_{m-1} + a_m} \quad (9)$$

The termination at the lips is assumed to be equivalent to a tube section of infinite area, resulting in a volume velocity reflection coefficient of -1. For convenience in analysis we associate all the delay (i.e. sum of delays for forward and backward travelling waves) with the backward travelling wave in each section. The physical model of figure 5(a) may then be represented by the signal flow model of figure 5(b).

Analysis of this model shows that the transfer function $H(z) = U_L(z)/U_G(z)$ is given by

$$H(z) = \frac{(1+\mu_1)(1+\mu_2)}{1+z^{-1}\mu_1(1+\mu_2)-z^{-2}\mu_2} \quad (10)$$

$$= \frac{4a_0a_1}{(a_0+a_1)(a_1+a_2)} \cdot \frac{1}{1+z^{-1}\left(\frac{2a_1}{a_1+a_2}\right)\left(\frac{a_0-a_1}{a_0+a_1}\right)+z^{-2}\left(\frac{a_2-a_1}{a_2+a_1}\right)} \quad (11)$$

The impulse response of this system is of the form

$$h(n) = h(0) r^n \cos n\omega T \quad (12)$$

where

$$h(0) = (1 + \mu_1)(1 + \mu_2) = \frac{4a_0 a_1}{(a_0 + a_1)(a_1 + a_2)}, \quad (13)$$

$$r^2 = -\mu_2 = \frac{a_2 - a_1}{a_2 + a_1}, \quad (14)$$

and

$$\cos \omega T = \frac{1}{2r} \mu_1 (1 + \mu_2) = \frac{1}{2r} \left(\frac{2a_2}{a_1 + a_2} \right) \left(\frac{a_0 - a_1}{a_0 + a_1} \right) \quad (15)$$

From (14) we see that, for this two junction model, the damping ratio r depends only on the reflection coefficient of the junction closest to the glottis, i.e. on the area ratio at this junction. We might query the physical meaning of the possibility that $a_2 - a_1 < 0$ i.e., $r^2 < 0$ in (14). Detailed analysis shows that the impulse response is then not oscillatory, corresponds to real poles, and is not of interest in the present study.

To apply this two junction model to realistic speech parameters we set the length of each section equal to half the length of the vocal tract, i.e. about 9 cm. The tie in with the previous discussion of the 10 000 Hz sampling rate, it is convenient to let each of the sections be equivalent to an each way delay of 3×10^{-4} s. The delay T in the second order model described by equation (8) is thus 6×10^{-4} s, and the relevant values of r for use in these equations are $(r_s r_1)^6$ or $(r_s)^6$. Of course this change in fact replaces the second order system by a 12th order system if the original sampling rate is maintained, since denominator factors of $H(z)$ in (12) of the form

$$(1 - z^{-1} r e^{j\omega T})$$

are replaced by factors of the form

$$(1 - z^{-6} r^6 e^{j6\omega T}).$$

Each of these factors results in 6 poles, but the base pole of each is the same as previously, i.e. at $z = r e^{j\omega T}$. From (14) we find

$$a_2 = \frac{1+r^2}{1-r^2} a_1 \quad (16)$$

and

$$\left. \frac{da_2}{a_2} \right|_{a_1} = \frac{4r}{1-r^4} \quad (17)$$

and

$$\left. \frac{da_1}{a_1} \right|_{a_2} = \frac{-4r}{1-r^4} \quad (18)$$

From (17) and also (18) we see that the proportional variation of either area a_1 or a_2 with r , while the other is fixed becomes very great as $r \rightarrow 1$. We found earlier that the effect of the delayed window on the apparent damping was sufficient to make r pass through unity, and thus the system may incur such great sensitivities. For example, varying r from 0.90 to 0.99 causes $\frac{a_2}{a_1}$ to change from 9.53 to 99.5. Clearly this effect is sufficient to account for variations as large as those observed in Section 2.2.

For completeness, we study the effect at the first junction. We note that ωT is not affected by the window delay phenomenon, and thus we set $d(\cos \omega T) = 0$ when differentiating (15).

We find

$$a_0 = a_1 \frac{1}{1+r^2} \cos \omega T \tag{19}$$

and

$$\left. \begin{array}{l} \frac{da_0}{a_0} \\ \frac{dr}{a_1} \end{array} \right| = \frac{1-r^2}{r(1+r^2)} \tag{20}$$

which shows that the area ratios at the first junction are not strongly influenced by r .

Note also that there is a gross effect on the initial value $h(0)$ or the windowed response. Via (13) we see that this can affect the product of the junction transmission coefficients i.e. $(1 + \mu_1)(1 + \mu_2)$. The effect on a particular feature however is not explicit.

For more complex vocal tract models, the effects are more complex, but we have demonstrated a sufficient mechanism to account for the observations. One previous study(ref.11) showed that under moderate variation of the pole dampings in a 5 pole signal, the resultant VTAF retained its gross features, but underwent a gradual smooth change.

4. EXPERIMENTAL DIAGNOSIS

To test these ideas, synthetic vowels were generated (in the computer) using an all-pole filter and known excitation function. Details of the synthesis algorithm used are given in Rogers(ref.12). The four poles used were derived from the values of formant positions and bandwidths given by Fant(ref.13) (Table 1).

TABLE 1. POLE POSITIONS IN TERMS OF FORMANT FREQUENCIES AND BANDWIDTHS (AFTER FANT(REF.13))

Vowel	First formant		Second formant		Third formant		Fourth formant	
	freq.	b-width	freq.	b-width	freq.	b-width	freq.	b-width
/ac/	616	57	1072	72	2430	130	3410	175
/e/	432	39	1959	95	2722	170	3500	325
/l/	222	60	2244	75	3140	240	3700	230
/p/	510	54	900	65	2400	100	3220	135
/N/	231	69	615	50	2375	110	3320	115

Figure 6 shows plots of the VTAF's obtained for the synthetic vowel /ae/ when the pitch period n_p has been made equal to the computation interval n_c . In each of the four columns however the 'phase' of the excitation function relative to the computation window is different (as indicated in the figure). Clearly the areas calculated vary with this phase. This means that when $n_p \neq n_c$ the area calculated from a constant waveform will fluctuate as the position of the excitation impulse changes within the window. Figure 7 shows this happening when $n_p = 0.8 n_c$ for five different synthetic vowels.

The reason this effect had not been observed in previous VTAF pictures of male speakers is believed to be that the computation interval used (64 samples, equivalent to 7.81 mS at 8192 Hz sampling rate) is quite close to the pitch period of the speakers analysed. Thus, fluctuations are not observed as the excitation function remains in a nearly constant position in the Hanning window. It should be remembered however that the errors may still be present in the analysis but not show up as fluctuations. For the female speaker $n_p \approx 0.9 n_c$ and the fluctuations are obvious (figure 1). This interpretation is supported by the fact that fluctuations did appear in male VTAF's that have been reprocessed with larger values of n_c .

5. SUPPRESSING THE FLUCTUATIONS

It appears from the above discussion that a partial cure for the problem of fluctuations would be to increase the size of the Hanning window used to estimate the autocorrelation function. This should improve the estimate of r_s . Figure 8 shows the synthetic vowel /ae/ as shown in figure 6 but with $n_w = 3.5 n_p$. We see that the variations are suppressed. To test this on real speech the VTAF picture (figure 1) was reprocessed with $n_w = 192$ (approximately $3.5 n_p$) and the result is shown in figure 9. The fluctuations have indeed been largely suppressed.

6. CONCLUDING REMARKS

The autocorrelation methods of linear prediction have a certain attraction in terms of robustness and economy of computing effort. We have shown that care must be taken in choosing lengths for the analysis, but provided this is done then consistent estimates of the vocal tract area are obtained. If Hanning windows of length $> 2.5 n_p$ are used, the resultant area functions appear to have the robustness desirable for automatic speech recognition, or for use in visual displays for speech training and phonetic studies.

REFERENCES

- | No. | Author | Title |
|-----|---------------------------------|--|
| 1 | Itakura, F. | "Minimum prediction residual principle applied to speech recognition"
IEEE Trans. Acoust. Speech and Signal Processing, Vol.23, pp.67-72, 1975 |
| 2 | Fujisaki, H. and Sato, Y. | "Evaluation and comparison of features in speech recognition"
Faculty Eng., Univ. of Tokyo, Japan, Annual Rep. Eng. Res. Inst., Vol. 73, pp.213-218, 1973 |
| 3 | Sambur, M.R. and Rabiner, L.R. | "A speaker - independent digital recognition system"
Bell Syst. Tech. J., Vol. 54, pp.81-102, 1975 |
| 4 | Rabiner, L.R. and Sambur, M.R. | "Some preliminary experiments in the recognition of connected digits"
IEEE Trans. Acoust. Speech and Signal Processing, Vol. 24, pp.170-182, 1976 |
| 5 | Atal, B.S. and Hanauer, S.L. | "Speech analysis and synthesis by linear prediction of the speech wave"
J. Acoust. Soc. Amer., Vol. 50, pp.637-655, 1971 |
| 6 | Markel, J.D. | "Formant trajectory estimation from a linear least-squares inverse filter formulation"
SCRL Monograph No. 7, Speech Communication Research Laboratory, Santa Barbara, 1971 |
| 7 | Wakita, H. | "Estimation of the vocal tract shape by optimal inverse filtering and acoustic/articulatory conversion methods"
SCRL Monograph No. 9, Speech Communication Research Laboratory, Santa Barbara, 1971 |
| 8 | Chandra, S. and Lin, W.C. | "Experimental comparison between stationary and non-stationary formulations of linear prediction applied to voiced speech analysis"
IEEE Trans. on Acous. Speech and Signal Processing, Vol. 22, pp.403-415, 1974 |
| 9 | Makhoul, J. | "Linear prediction: a tutorial review"
Proc. IEEE, Vol. 63, pp.561-580, 1975 |
| 10 | Markel, J.D. and Gray, A.H. | "Linear Prediction of Speech"
Springer-Verlag, Berlin 1976 |
| 11 | Bogner, R.E. and Rogers, J.A.V. | "Determination of Vocal Tract Area Functions from a Pole Description of Speech Spectra"
Proc. Internat. Conf. on Speech Communication and Processing, Boston, pp.368-371, 1972 |
| 12 | Rogers, J.A.V. | "Determination of Articulatory Parameters from Speech Waveforms"
Ph.D. Thesis, University of London, London, 1974 |
| 13 | Fant, G. | "Acoustic theory of speech production"
Mouton and Co., The Hague, Holland, 1960 |




Figure 1. Vocal tract area function for sentence "Speak to me now, bad kangaroo!"




Figure 2(a). Speech waveform for /ae/




Figure 2(b). Vocal tract area function for /ae/




Figure 3. Effect on windowed signal $s_w(n)$ of relative shift between signal and window




Figure 4. Approximation to a delayed window $w_d(n) = 0.58(1 + \cos \frac{2\pi}{128}(n-61))$ by a rising exponential 0.014×1.26^n




Figure 5(a). Physical tube model




Figure 5(b). Signal flow model




Figure 6. Pitch period and computation interval are equal but with different relative positions in each column




Figure 7. Changing position of pitch pulse within window leads to pulsation when $n_c = n_w$




Figure 8. Increasing n_w to $3.5 n_p$ suppresses the fluctuations, for synthetic vowel /ae/




Figure 9. Vocal tract area function for "Speak to me now, bad kangaroo!" for window $n_w = 3.5$ times pitch period n_p

DISTRIBUTION**EXTERNAL**

Copy No.

In United Kingdom

Defence Scientific and Technical Representative, London	1
---	---

In United States

Counsellor, Defence Science, Washington	2
---	---

In Australia

Chief Defence Scientist	3
-------------------------	---

Executive Controller, Australian Defence Scientific Service	4
---	---

Superintendent, Central Studies Establishment	5
---	---

Controller, Policy and Programme Planning Division	6
--	---

Superintendent, Defence Science Administration Division	7
---	---

Chief Superintendent, Aeronautical Research Laboratories	8
--	---

Chief Superintendent, Materials Research Laboratories	9
---	---

Defence Library, Campbell Park	10
--------------------------------	----

Library, Aeronautical Research Laboratories	11
---	----

Library, Materials Research Laboratories	12
--	----

Director, Joint Intelligence Organisation (DDSTI)	13
---	----

Superintendent, RAN Research Laboratory	14
---	----

Dr J.F. O'Callaghan, CSIRO Computing Research Division	15
--	----

Professor S. Kaneff, Australian National University, Canberra	16
---	----

Dr I.D.G. McLeod, Australian National University, Canberra	17
--	----

Dr B. Miller, Australian National University, Canberra	18
--	----

Professor B.D.O. Anderson, Newcastle University, N.S.W.	19
---	----

Professor F. Hirst, Adelaide University	20
---	----

Defence Information Services Branch (for microfilming)	21
--	----

Defence Information Services Branch for:

United Kingdom, Ministry of Defence, Defence Research Information Centre (DRIC)	22
---	----

United States, Department of Defense, Defense Documentation Center	23 - 34
--	---------

Canada, Department of National Defence, Defence Science Information Service	35
---	----

New Zealand, Department of Defence	36
------------------------------------	----

Australian National Library	37
-----------------------------	----

INTERNAL

Director	38
----------	----

Chief Superintendent, Weapons Research and Development Wing	39
---	----

Superintendent, Electronics Division	40
--------------------------------------	----

Superintendent, Propulsion and Marine Physics Division	41
--	----

Superintendent, Systems Analysis Division	42
---	----

Copy No.

Senior Principal Research Scientist, Marine Studies Composite	43
Principal Officer, Marine Physics Group	44
Principal Officer, Underwater Detection Group	45
Dr D.V. Wyllie, Marine Physics Group	46
Dr A.K. Steele, Underwater Detection Group	47
Dr A. Werner, Underwater Detection Group	48
Dr S.H. Anderson, Cybernetic Electronics Group	49
Mr J.S. Bell, Marine Physics Group	50
Mr J.C. Andrews, Marine Physics Group	51
Dr D.J. Parker, Systems Integration Group	52
Authors	53 - 54
P.M.D. Library	55 - 56
W.R.E. Library	57 - 58
Spares	59 - 65