

# SECRET

COLUMBIA UNIVERSITY  
HUDSON LABORATORIES  
CONTRACT No. 266(94)

6  
Array Effective Directivity Index with  
Gaussianly Perturbed Signal Wavefront.

Copy 39 of Copies

U. S. Navy Underwater Sound Laboratory  
Port Turnbull, New London, Connecticut

14 USL-TM-1170-10-59

USL Problem  
No. 1-501-02-00

ARRAY EFFECTIVE DIRECTIVITY INDEX WITH GAUSSIANLY  
PERTURBED SIGNAL WAVEFRONT

by

9 10 P. L. Stocklin

USL Technical Memorandum No. 1170-10-59

12 11 p.

17 25 January 1959

DDC  
AUG 6 1979  
RESOLV L

DISTRIBUTION STATEMENT A  
Approved for public release  
Distribution Unlimited

### INTRODUCTION

In the design of large arrays, the question arises of possible directivity index degradation due to a randomly perturbed signal wavefront. In this memorandum, the array effective directivity index is found for such a situation as a function of the number of array elements,  $N$ , and average interelement correlation functions, for signal and noise sound fields. Developments are given for the cases of independent perturbations and Markov-Gaussian correlated perturbations.

### DEVELOPMENT

Let  $A_i(t)$  be the voltage output of the  $i$ th omnidirectional element of an  $N$  element array, in the signal acoustic field. Each element may be assumed to be compensated (in time delay) for the non-perturbed wavefront. Due to a perturbation imposed on the wavefront during its passage through the medium, however, the output of the  $i$ th hydrophone differs in delay from that of the reference hydrophone by an amount  $\tau_i$ . For any hydrophone,  $\tau_i$  is assumed normally distributed with variance  $\sigma_{\tau}^2$  about the mean corresponding to the ideal wavefront.

We may thus represent the summed voltage output from the array for signal only,  $A_T(t)$ , as

$$A_T(t) = \sum_{i=1}^N A_i(t) = \sum_{i=1}^N A_0(t - \tau_i) \quad (1)$$

ADA 072191

DDC FILE COPY

/

## **DISCLAIMER NOTICE**

**THIS DOCUMENT IS BEST QUALITY  
PRACTICABLE. THE COPY FURNISHED  
TO DDC CONTAINED A SIGNIFICANT  
NUMBER OF PAGES WHICH DO NOT  
REPRODUCE LEGIBLY.**

UNCLASSIFIED

SECURITY CLASSIFICATION OF THIS PAGE (When Data Entered)

REPORT DOCUMENTATION PAGE		READ INSTRUCTIONS BEFORE COMPLETING FORM
1. REPORT NUMBER	2. GOVT ACCESSION NO. 1170-10-59	3. RECIPIENT'S CATALOG NUMBER
4. TITLE (and Subtitle) ARRAY EFFECTIVE DIRECTIVITY INDEX WITH GAUSSIANLY PERTURBED SIGNAL WAVEFRONT		5. TYPE OF REPORT & PERIOD COVERED Tech Memo
7. AUTHOR(s)		6. PERFORMING ORG. REPORT NUMBER
9. PERFORMING ORGANIZATION NAME AND ADDRESS Naval Underwater Systems Center New London, CT		8. CONTRACT OR GRANT NUMBER(s) Nonr-266(84)
11. CONTROLLING OFFICE NAME AND ADDRESS Office of Naval Research, Code 220 800 North Quincy St. Arlington, VA 22217		10. PROGRAM ELEMENT, PROJECT, TASK AREA & WORK UNIT NUMBERS
14. MONITORING AGENCY NAME & ADDRESS (if different from Controlling Office)		12. REPORT DATE 26 JAN 59
		13. NUMBER OF PAGES
		15. SECURITY CLASS. (of this report) UNCLASSIFIED
		15a. DECLASSIFICATION/DOWNGRADING SCHEDULE
16. DISTRIBUTION STATEMENT (of this Report)  Approved for public release; distribution unlimited.		
17. DISTRIBUTION STATEMENT (of the abstract entered in Block 20, if different from Report)		
18. SUPPLEMENTARY NOTES		
19. KEY WORDS (Continue on reverse side if necessary and identify by block number)		
20. ABSTRACT (Continue on reverse side if necessary and identify by block number)		

Accession For	RTIS GRA&I	
	DPC TAB	
Unannounced Justification		
By		
Distribution/		
Availability Codes		
Avail and/or Special	23	
Dist.	A	

USL Tech. Memo.  
No. 1170-10-59

where  $a_0(t)$  = reference hydrophone output in the signal field.

The mean-square signal voltage, then, is:

$$\begin{aligned} \overline{a_T^2(t)} &= \overline{\sum_{i=1}^N a_0(t-\tau_i) \cdot a_0(t-\tau_j)} \\ &= \overline{a_0^2(t)} \left[ N + \sum_{i=1}^N \sum_{j=1}^N s_0^2(\tau_i - \tau_j) \right] \end{aligned} \quad (2)$$

where  $s_0^2(t)$  = reference hydrophone normalized autocorrelation function for the signal field.

and the bar indicates time average.

It will be noted that a stationary time series is assumed for the hydrophone outputs. If it is further assumed that the probability of occurrence of the perturbation  $\tau_i$  at the  $i^{\text{th}}$  hydrophone is independent of the perturbation at all the other hydrophones, then the following definition of the average signal interelement correlation function,  $\overline{\psi_s}$ , has meaning:

$$\overline{\psi_s} = \frac{1}{N(N-1)} \sum_{\substack{i=1 \\ i \neq j}}^N \sum_{\substack{j=1 \\ j \neq i}}^N \psi_0(\tau_i - \tau_j) \quad (3)$$

Substituting from (3) into (2), then, gives:

$$\overline{a_T^2(t)} = \overline{a_0^2(t)} \left[ N + N(N-1) \overline{\psi_s} \right] \quad (4)$$

An exactly similar derivation may be made for the noise field (no properties of either field have yet been assumed), yielding:

$$\overline{n_T^2(t)} = \overline{n_0^2(t)} \left[ N + N(N-1) \overline{\psi_n} \right] \quad (5)$$

The effective directivity index, EDI, is related to the increased discrimination against noise of an array versus an omnidirectional hydrophone:

$$EDI = 10 \log_{10} \left\{ \left( \frac{A_1^2(\omega)}{n^2 P_0} \right) / \left( \frac{A_0^2(\omega)}{n_0^2 P_0} \right) \right\} \quad (6)$$

From (4) and (5) into (6), then

$$EDI = 10 \log_{10} \left\{ \frac{1 + (N-1) \bar{\Psi}_s}{1 + (N-1) \bar{\Psi}_n} \right\} \quad (7)$$

If the average interelement correlation function for the noise field is very small, as it is in most cases of interest, then

$$EDI \approx 10 \log_{10} \{ 1 + (N-1) \bar{\Psi}_s \} \quad (8)$$

#### RELATION OF $\bar{\Psi}_s$ TO PERTURBATION STATISTICS

$\bar{\Psi}_s$  is still not in a form useful for the desired computations. If  $N$  is a large number and the perturbations are independent, then we may replace the space (or ensemble) average  $\bar{\Psi}_s$  by the statistical average,  $\bar{\Psi}_s$ , where

$$\bar{\Psi}_s = \int_{-\infty}^{\infty} \Psi_0(\Delta\tau) \cdot p(\Delta\tau) d(\Delta\tau) \quad (9)$$

and  $\Delta\tau = \tau_i - \tau_j$  (any  $i \neq j$ )

This is an expected property of the wavefront which is quite reasonable to expect under the conditions we have assumed.

Let  $p(r_i)$ , for any  $i$ , be

$$p(r_i) = (2\pi\sigma_z^2)^{-\frac{1}{2}} \exp\left\{-\frac{r_i^2}{2\sigma_z^2}\right\} \quad (10)$$

Then, under our independence assumption,

$$p(\Delta r) = p(r_i - r_j) = (4\pi\sigma_z^2)^{-\frac{1}{2}} \exp\left\{-\frac{(\Delta r)^2}{4\sigma_z^2}\right\} \quad (11)$$

Substituting from (11) into (9),

$$\overline{s^2 \phi_0} = \overline{\phi_0^2} = (4\pi\sigma_z^2)^{-\frac{1}{2}} \int_{-\infty}^{\infty} \exp\left\{-\frac{(\Delta r)^2}{4\sigma_z^2}\right\} s^2 \phi_0(\Delta r) d(\Delta r) \quad (12)$$

Now, for single frequency or narrow band, we find (if  $\omega\tau \ll \pi$ )

$$s^2 \phi_0(\Delta r) \approx \cos(\omega\Delta r) \quad (13)$$

From (13) into (12), then

$$\overline{s^2 \phi_0} \approx (4\pi\sigma_z^2)^{-\frac{1}{2}} \int_{-\infty}^{\infty} \exp\left\{-\frac{(\Delta r)^2}{4\sigma_z^2}\right\} \cos \omega\Delta r d(\Delta r) \quad (14)$$

The average interelement normalized correlation function is thus the real-variable moment-generating function of the perturbation distribution. For the Gaussian case at hand, from (14),

$$\overline{s^2} \approx e^{-\omega^2 \sigma_c^2} \quad (15)$$

Substituting from (15) into (8), gives

$$EDI \approx 10 \log_{10} \left\{ 1 + (N-1) e^{-\omega^2 \sigma_c^2} \right\} \quad (16)$$

or, for single frequency, since  $\phi = \omega \tau$ ,  $\sigma_p = \omega \sigma_c$ , and

$$EDI \approx 10 \log_{10} \left\{ 1 + (N-1) e^{-\sigma_p^2} \right\} \quad (17)$$

Several limiting cases may be examined. First, if  $\sigma_c^2$  approaches 0, then

$$EDI \Big|_{\sigma_c^2 \rightarrow 0} \rightarrow 10 \log N \quad (18)$$

Secondly, if  $\sigma_c^2$  approaches infinity, then the last term on the right in (16) approaches zero, so the EDI approaches zero in this case. Since having  $\sigma_c^2$  go to infinity corresponds to complete destruction of the signal wavefront, this answer is intuitively satisfying.

In Figure 1, the EDI is plotted versus  $\sigma_p$  for various values of  $N$  from 32 to 32,000. When the product

$$(N-1) e^{-\sigma_p^2} \gg 1,$$

the db loss in EDI due to  $\sigma_p^2$  is independent of N. This occurs for the higher N's and lower  $\sigma_p^2$  toward the left of the figure.

### CORRELATED PERTURBATIONS

Wavefront perturbations correlated from hydrophone to hydrophone over the whole array create essential complications. It is possible to attack such a problem using first-order Markov theory as follows:

Let us assume the  $(i+1)^{th}$  perturbation is related to the  $i^{th}$  perturbation thus:

$$z_{i+1} = \rho z_i + \sqrt{1-\rho^2} y_{i+1}, \quad -1 \leq \rho \leq 1 \quad (19)$$

where  $\rho$  is a constant and  $y_{i+1}$  is a variable whose variance is the same as  $z_i$ , but which is random with respect to  $z_i$ . It is easily shown that  $\rho$  is the normalized cross correlation between  $z_{i+1}$  and  $z_i$  both of which possess the same variance. The argument may be extended to show that  $\rho^n$  is the normalized cross-correlation between the  $i^{th}$  and the  $(i+n)^{th}$  perturbations. For the Gaussian case (governed by a second-order Gaussian distribution, the so-called Markov-Gaussian condition) it can be easily shown, using a method suggested by B. F. Cron, that the distribution of the difference between the  $i^{th}$  and the  $(i+n)^{th}$  perturbations is Gaussian with mean zero and variance  $n\sigma_\Delta^2$  given by

$$n\sigma_\Delta^2 = \sigma_z^2 \left[ (1-\rho^n)^2 + (1-\rho^{2n}) \right] \quad (20)$$

As a check, we see that for  $\rho=0$ ,  $n\sigma_\Delta^2$  is twice  $\sigma_z^2$  and independent of n, which is the assumption used to derive (16) and (17). For  $\rho=1$ ,  $n\sigma_\Delta^2$  is zero, which means that we have again an ideal wavefront with no perturbations, and so no degradation in EDI.

To calculate the effect on EDI, let us start from (2). We must replace (3) by a series of equations, resulting for the second term of (2), in

$$\sum_{\substack{i=1 \\ i \neq j}}^N \rho_0 (z_i - z_j) = 2 \sum_{n=1}^{N-1} (N-n) \cdot \rho_0^n \{ \Delta z_n \} \quad (21)$$

where  $(A^n)_n$  indicated the difference of perturbations from elements  $n$  elements apart.

Now, since we still have to do with Gaussian distributions, as in (14), but ones in which the variances are different, we can immediately write down from (15) that

$$s_{\sigma}^2(A^n) = e^{-\frac{\omega^2 \sigma_a^2}{2}} = e^{-\omega^2 \sigma_a^2 \left\{ (1-\rho^n)^2 + (1-\rho^{2n}) \right\} / 2} \quad (22)$$

Substituting from (22) into (21) and (2) then gives:

$$\overline{A_p^2(\theta)} = \overline{A_0^2(\theta)} \left[ N + 2 \sum_{n=1}^{N-1} (N-n) e^{-\omega^2 \sigma_a^2 \left\{ (1-\rho^n)^2 + (1-\rho^{2n}) \right\} / 2} \right] \quad (23)$$

and, with the assumption of negligible noise correlation (if this is not true, an equation similar to (7) must be used), there finally results, for the case of correlated perturbations,

$$\text{EDI} \approx 10 \log_{10} \left[ 1 + 2 \sum_{n=1}^{N-1} (1 - \frac{n}{N}) e^{-\omega^2 \sigma_a^2 \left\{ (1-\rho^n)^2 + (1-\rho^{2n}) \right\} / 2} \right] \quad (24)$$

where  $\rho^n$  is the normalized cross-correlation between perturbations from elements  $n$  apart,  $N$  is the number of array elements, and  $\sigma_a^2$  is the variance of the perturbation distribution for (any) one element output.

OSL Tech. Memo.  
No. 1170-10-59

Interest has been expressed in obtaining an expression like (24), from which the EDI may be developed for specific assumptions. No further discussion will be given here, other than to indicate that when a Maclaurin series approximation to the exponential is permissible, computational difficulties can probably be eased.

*Philip L. Stocklin.*

P. L. Stocklin

USL Tech. Memo.  
No. 1170-10-59.

DISTRIBUTION LIST

Internal

USL Code 100  
101  
105  
108  
900  
905  
1100  
1105  
1110  
1170  
1170A  
1200  
1205  
1210  
1231  
1300  
1310  
1330  
1350  
1400  
1410  
1463 (5)

B. F. Cron  
L. T. Einstein  
W. R. Schumacher

5-10-68

FIGURE I

Decrease of Effluent

The City of New York (C.F.T.) has conducted a study of the problem of effluent control in the Hudson River Basin.

Effluent reduction (150-170) is

the maximum amount available for treatment of effluent from the Hudson River Basin.

It is to be noted that the maximum amount available for treatment of effluent from the Hudson River Basin is 150-170.

Random reduction of effluent from the Hudson River Basin is

N  
31,000

3200

320

30

