



Research and Development Technical Report

DELET-TR-80-0260-1

403 MHz SAW OSCILLATOR

D. J. Dodson
TRW Inc
One Space Park
Redondo Beach, CA 90278

March 1981

First Interim Report for Period 5 May 1980 - 10 November 1980

Approved for Public Release;
Distribution Unlimited

ERADCOM

US ARMY ELECTRONICS RESEARCH AND DEVELOPMENT COMMAND
FORT MONMOUTH, NEW JERSEY 07703

AD A 097 C 5

DTIC FILE COPY

APR 10 1981

A

81 4 10 066

HISATM 195-16

NOTICES

Disclaimers

The citation of trade names and names of manufacturers in this report is not to be construed as official Government indorsement or approval of commercial products or services referenced herein.

Disposition

Destroy this report when it is no longer needed. Do not return it to the originator.

HICK-FM-644-76

UNCLASSIFIED

SECURITY CLASSIFICATION OF THIS PAGE (When Data Entered)

REPORT DOCUMENTATION PAGE		READ INSTRUCTIONS BEFORE COMPLETING FORM
1. REPORT NUMBER DELET-TR-80-0260-1	2. GOVT ACCESSION NO. AD-A097675	3. RECIPIENT'S CATALOG NUMBER
4. TITLE (and Subtitle) 403 MHz SAW Oscillator	5. TYPE OF REPORT & PERIOD COVERED Interim Report, 5 May-1980 ~~the 10 November 1980~~	6. PERFORMING ORG. REPORT NUMBER
7. AUTHOR(s) D.J. Dodson	8. CONTRACT OR GRANT NUMBER(s) DAAK20-80-C-0260 A	
9. PERFORMING ORGANIZATION NAME AND ADDRESS TRW Inc. DSSG One Space Park Redondo Beach, California 90278	10. PROGRAM ELEMENT, PROJECT, TASK AREA & WORK UNIT NUMBERS 612705.H94.A1.11.01	
11. CONTROLLING OFFICE NAME AND ADDRESS Director, US Army Electronics Tech & Devices Lab ATTN: DELET-MA-A Fort Monmouth, NJ 07703	12. REPORT DATE March 1981	13. NUMBER OF PAGES 80
14. MONITORING AGENCY NAME & ADDRESS (if different from Controlling Office)	15. SECURITY CLASS. (of this report) UNCLASSIFIED	15a. DECLASSIFICATION DOWNGRADING SCHEDULE
16. DISTRIBUTION STATEMENT (of this Report) Approved for Public Release; Distribution Unlimited		
17. DISTRIBUTION STATEMENT (of the abstract entered in Block 20, if different from Report)		
18. SUPPLEMENTARY NOTES		
19. KEY WORDS (Continue on reverse side if necessary and identify by block number) Surface Acoustic Wave Devices SAW Oscillator Quartz		
20. ABSTRACT (Continue on reverse side if necessary and identify by block number) This contract provides for a twelve (12) month program for the investigation and exploratory development of a 200 mW, SAW stabilized oscillator which can be frequency and amplitude modulated. The oscillator is to have its center frequency at 403 MHz and be tunable over a + 3 MHz bandwidth. Trade-off design studies have been performed to determine techniques which will provide the most effective interaction of essential oscillator components, i.e., SAW delay-line, phase shifter, coupler and amplifier, to provide a high degree of frequency stability. A significant effort was made to implement the required		

DD FORM 1 JAN 73 1473

EDITION OF 1 NOV 65 IS OBSOLETE

UNCLASSIFIED

SECURITY CLASSIFICATION OF THIS PAGE (When Data Entered)

UNCLASSIFIED

SECURITY CLASSIFICATION OF THIS PAGE(When Data Entered)

circuit functions in a low-cost printed circuit approach rather than utilize high-cost commercially available components, since the oscillator is intended for use in an expendable application.

Specific tasks addressed to date include: Mask and SAW delay line design and fabrication. Assembly of a DC circuit board as required for electronic tuning, modulation, compensation and regulation. Integration and test of a complete breadboard oscillator. Extensive circuit characterization.

UNCLASSIFIED

SECURITY CLASSIFICATION OF THIS PAGE(When Data Entered)

CONTENTS

	<u>Page</u>
1. SUMMARY	1
2. OSCILLATOR DESIGN	2
3. CIRCUIT DESIGN AND PERFORMANCE	12
a. SAW Delay Line	12
b. Loop Amplifier	15
c. Phase Shifter	31
d. ILO	43
4. CONCLUSION	53
Appendix A	54
Appendix B	57
Appendix C	66

Classification Page

1
2
3
4
5
6
7
8
9
10

A

LIST OF FIGURES

Figure No.		Page
2-1	Oscillator Block Diagram	3
2-2	SAW Delay Line: Multiple Modes	5
2-3	SAW Delay Line: Single Mode	6
2-4	Saw Delay Line Oscillator	6
2-5	Output Power vs Gain Margin	7
2-6	Oscillator Phase Noise for Gain Margin of 1 dB	8
2-7	Oscillator Phase Noise for Gain Margin of 4 dB	8
2-8	Oscillator Phase Noise for Gain Margin of 10 dB	9
3-1	Schematic of 403 MHz SAW Delay Line	14
3-2	403 MHz SAW Unmatched Passband and Phase	16
3-3	403 MHz SAW Unmatched Passband and Phase	17
3-4	403 MHz SAW Unmatched Reflection Coefficients	18
3-5	Photograph of Packaged SAW	19
3-6	403 MHz SAW Delay Line	20
3-7	403 MHz SAW Matched Passband and Phase	21
3-8	403 MHz SAW Matched Reflection Coefficients	22
3-9	403 MHz SAW Amplifier	23
3-10	Photograph of Breadboard Circuit	24
3-11	403 MHz SAW Amplifier, Gain vs Frequency	25
3-12	Loop Amplifier P_{OUT} vs P_{IN} (12V Bias)	26
3-13	Loop Amplifier P_{OUT} vs P_{IN} (9V Bias)	27
3-14	403 MHz SAW Amplifier, Gain vs Frequency	28
3-15	403 MHz SAW Amplifier, Phase vs Frequency	29
3-16	403 MHz SAW Amplifier, Phase vs Frequency	30
3-17	Phase Shifter Block Diagram	31
3-18	Coupler Schematic	34
3-19	403 MHz Twisted Wire Coupler	36
3-20	Coupler Load	37
3-21	Varactor Reflection Coefficient	38
3-22	Computer-Predicted Load Reflection Coefficients	39
3-23	Measured Load Reflection Coefficients	40
3-24	Photograph of Breadboard Phase Shifter	41
3-25	403 MHz Breadboard Double Phase Shifter	42
3-26	Phase Shifter Tuning Characteristics	44
3-27	403 MHz ILO	45

LIST OF FIGURES (Continued)

<u>Figure No.</u>		<u>Page</u>
3-28	Photograph of ILO Breadboard Circuit	46
3-29	Injection Locking Bandwidth vs Injection Power	47
3-30	Injection Locking Bandwidth vs Temperature	48
3-31	Output Power vs Frequency	49
3-32	ILO Amplitude Modulation Time Waveforms	50-51
3-33	ILO Amplitude Modulation Frequency Spectrum	52

LIST OF TABLES

<u>Table No.</u>		<u>Page</u>
1-1	Oscillator Performance Specifications	1
2-1	Measured Variations in Absolute Phase	10
2-2	Oscillator Specifications	11

1. SUMMARY

The objective of this program is the development of a 403 MHz surface acoustic wave oscillator suitable for use in an expendable radiosonde. Due to the extreme temperature range (-70°C to $+70^{\circ}\text{C}$) the radiosonde must operate in and the simultaneous deployment of many radiosondes operating within a limited bandwidth, temperature stability is the oscillator's most critical performance parameter. Stability of 200 ppm or better is required. The circuit is also required to tune from 400 MHz to 406 MHz, transmit 200 mW (+23 dBm), and be capable of both amplitude and frequency modulation. Specified performance is outlined in Table 1-1.

Table 1-1. Oscillator Performance Specifications

Parameter	Specification	Comment
Frequency	400-406 MHz	Settable to 50 ppm
Stability	200 ppm	-70°C to $+70^{\circ}\text{C}$
Modulation		
PAM	0 to 2000 pps	
FM	100 KHz Modulation Frequency	300 KHz/V Modulation Sensitivity
Output Power	200 mW	50 ohm load
Frequency Pulling	$\leq \pm 20$ ppm	$Z_L = 25$ to 75 ohms
Power Supply	24V $\pm 10\%$ <2.5 watts	Other supply voltages can be considered

During the first six months of the program the oscillator design has been completed, and all the individual RF subcircuits have been designed, fabricated and tested. These circuits include the SAW delay line, loop amplifier, phase shifter, and an injection locked oscillator. This report discusses overall

oscillator design, and gives a detailed description of the design and performance of the various subcircuits of the oscillator. The oscillator design is described in Section 2, while the design and performance of the individual subcircuits are described in Section 3. Measured performance not found in Section 3 can be found in the Appendix.

2. OSCILLATOR DESIGN

A block diagram of the 403 MHz SAW Stabilized Oscillator is shown in Figure 2-1. The circuit consists of a relatively low power, tunable SAW oscillator driving an injection locked oscillator, plus associated DC circuitry. The SAW oscillator produces approximately 20 mW (+13 dBm) RF power, tunable from 400 MHz to 406 MHz. Both mechanical tuning for frequency selection and electronic tuning for frequency modulation are employed. The injection locked oscillator which is locked to the SAW oscillator output produces an RF output in excess of 200 mW (+23 dBm). The ILO therefore provides approximately 10 dB of gain. Bias switching circuitry in the ILO is used for pulse amplitude modulation (PAM). The DC circuitry (not yet designed) will consist of a voltage regulator to minimize frequency pushing, tuning and frequency modulation circuitry, and a temperature compensation network to compensate for both varactor reactance changes and SAW delay variation with temperature.

The heart of this circuit is clearly the SAW oscillator. The conditions for oscillation in this circuit are (1) gain around the loop must exceed all losses and (2) phase around the loop must equal a multiple of 2π radians. These conditions can be expressed as

$$L_S(f) + L_I(f) \geq G(f,A) \quad (2.1)$$

and

$$\frac{2\pi f_N^2}{V} + \phi = 2N\pi \quad (2.2)$$

where

f_N = oscillation frequencies

d = center-to-center transducer separation

V = surface wave velocity

ϕ = phase shift through all elements except SAW delay line

N = an integer

$L_S(f)$ = insertion loss of SAW delay line

$L_I(f)$ = insertion loss of feedback loop components

$G(f,A)$ = amplifier gain as a function of and output level, A

A = output power level




Figure 2-1. Oscillator Block Diagram

The frequency of oscillation can be determined from equation (2.2)

$$f_N = \frac{V}{\lambda} \left(N - \frac{\tau}{2\pi} \right) \quad (2.3)$$

It is possible for multiple solutions to equations (2.1) and (2.2) to exist as shown in Figure 2-2 where many solutions to the phase condition exist within the SAW passband. For single-mode operation, the SAW delay line is designed such that there is only one solution for equation (2.2) which is in the passband of the delay line. Such a design is shown in Figure 2-3. As a general rule, the loss associated with the feedback loop components, $L_I(f)$, and the amplifier gain, $G(f,A)$, are slowly varying functions of frequency over a broad range around the frequency for which the oscillator is being designed, and the SAW response, $L_S(f)$, is a very strong function of frequency. The SAW oscillator is designed so that the combination of SAW delay line loss plus amplifier gain exceeds unity over a desired frequency band around the desired operating frequency. As long as only one solution to (2.2) falls within the passband response of the SAW delay line, single mode operation of the SAW oscillator is guaranteed.

The loop amplifier shown in Figure 2-4 provides gain to overcome losses around the loop - thereby meeting the first condition for oscillation (equation (2.1)). The amplifier is designed to have linear gain well in excess of the loop losses. The required gain margin is a function of the saturation characteristics of the amplifier chain, but typically must be greater than 4 dB. Measurements made at TRW have shown that a minimum of 4 dB gain margin will provide maximum output power and minimum phase noise. The effect of gain margin on oscillator output power and phase noise is shown in Figures 2-5 through 2-8. For a circuit with adequate gain margin, the oscillator output power will equal the saturated output power of the amplifier minus the power coupled back into the loop.




Figure 2-2. SAW Delay Line: Multiple Modes




Figure 2-3. SAW DELAY LINE: SINGLE MODE




Figure 2-4. SAW DELAY LINE OSCILLATOR




Figure 2-5. Output Power vs Gain Margin




Figure 2-6. Oscillator Phase Noise for Gain Margin of 1 dB




Figure 2-7. Oscillator Phase Noise for Gain Margin of 4 dB




Figure 2-8. Oscillator Phase Noise for Gain Margin of 10 dB

The second condition for oscillation, equation (2.2), is met through use of the phase shifter shown in Figure 2-4. The frequency of oscillation is set by varying ω in (2.3). It is necessary for the phase shifter to provide adequate phase variation to tune across the required frequency band. This phase variation will be defined by the phase slope of the delay line. It is generally necessary to provide tuning phase in excess of that required for any given SAW to accommodate the variation in absolute transmission phase from SAW to SAW. It is reasonable to expect variations in absolute delays for SAWs to be as large as $\pm 0.1\lambda$. For typical delay lines of 100λ electrical length, this equates to $\pm 36^\circ$ variation in transmission phase. The data from measurements of 16 delay lines shown in Table 2-1 demonstrates typical variation in absolute phase. It is often required that a full 360° of phase shift be provided to accommodate tuning range and variation from SAW to SAW.

Table 2-1. MEASURED VARIATIONS IN
ABSOLUTE PHASE

SAW IDENTIFICATION	DESIGN FREQUENCY	TRANSMISSION PHASE	MAXIMUM PHASE DIFFERENCE
B11 R21 B11 R11	555.0 MHz	76.5 112.5 119.0 80.0	36°
B12 P22 R12 R42	560.0	128.0 176.6 145.0 162.0	59.4°
R13 R23 P33 R13	563.0	103.0 125.5 125.0 152.0	40°
R14 P14 R14 B44	565.0	157.5 144.0 98.0 155.0	107°

Based on these general considerations, specifications for the individual oscillator subcircuits have been generated. These specifications are shown in Table 2-2.

Table 2-2. OSCILLATOR SPECIFICATIONS

<u>Circuit</u>	<u>Parameter</u>	<u>Specified Performance</u>	<u>Comments</u>
Delay Line	Center Frequency	403 $\pm$ 0.150 MHz	ST-cut quartz
	3 dB Bandwidth	6.3 MHz	
	Loss (Matched)	$\leq$ 20 dB	
	Delay	$\sim$ 100 ns	
Loop Amp	Frequency Band	>350-450 MHz	
	Gain	$\geq$ 40 dB	
	P _{SAT}	$\geq$ 16.5 dBm	
	VSWR (In,Out)	$\leq$ 2.5:1	
	V _{Supply}	12V	
Phase Shifter	Loss	<3 dB	Two cascaded phase shifters to be used
	Phase Shift	>180°	
	Tuning Voltage	T-10V	
Power Splitter	Coupling	3.0 dB	
	Loss	$\leq$ 0.5 dB	
ILO	Natural Frequency	403 MHz	200 mW
	Power Out	$\geq$ +23 dBm	
	Injection Locking Bandwidth	$\sim$ 16 MHz	Greater locking range may be required to accomodate temperature effects
	P _{INj}	+13 dBm	
	V _{Supply}	12V	

As these specifications imply, a 12V supply will be used throughout. All of the transistor circuitry would perform optimally with a 12V supply. Only the varactors in the phase shifter would benefit from using the full 24V available and due to the varactor C-V relationship, this benefit is small. The 12V supply was therefore chosen to conserve power.

A review of Table 2-1 points out key features of the design. The loop amplifier gain of 40 dB exceeds the 30 dB loop loss by 10 dB. This is adequate to drive the amplifier well into saturation and provides margin for SAW and phase shifter variations. The delay in the SAW implies a mode spacing of 1.0 MHz. If 20 ns of delay in other components in the loop is assumed the mode spacing would be reduced to 8.3 MHz. This is well in excess of the 7 MHz 3 dB bandwidth of the SAW. Two phase shifters will be used in cascade. A single phase shifter (of the design contemplated) will produce no more than 250° phase shift. Therefore, two are required to produce a 360° phase shift. The ILO will lock over a range far in excess of the 6 MHz operating band. This is to account primarily for the drift in ILO natural frequency with temperature.

In the following section the design and performance of these individual circuits is discussed in detail.

3. CIRCUIT DESIGN AND PERFORMANCE

a. 403 MHz SAW Delay Line

It is required that the 403 MHz SAW oscillator be operated with one stable single mode output and be tunable over the 400 MHz to 406 MHz frequency range. To achieve this, the specifications for the SAW delay line were set as follows:

Center Frequency	403.0 $\pm$ 0.15 MHz
3 dB Bandwidth	6.3 $\pm$ 0.1 MHz
Time Delay	0.10 $\pm$ 0.01 μ sec
Insertion Loss (matched)	$\leq$ 20 dB
Substrate	ST Quartz
Temperature Stability	
Turnover Temperature (T_0)	$-10^\circ\text{C} \leq T_0 \leq 10^\circ\text{C}$
2nd Order Temperature Coefficient	$-3.2 \times 10^{-8}/(^\circ\text{C})^2$

The ST-cut of quartz was chosen because it is one of the most temperature stable SAW substrates available. Its turnover temperature (T_0) for the free surface condition is near 23°C. However, with metal loading (approximately 700 Å aluminum), T_0 is expected to be lowered near 0°C. The 3 dB bandwidth requirement is set so that in addition to covering the operating frequency range, there is a 0.2 MHz margin to allow for center frequency variation in the SAW device.

The most critical parameter in the SAW requirement is the time delay. In the present case, the time delay has been specified to be much shorter than that normally considered necessary for single mode operation. This is because the external time delay in the oscillator loop due to elements other than the SAW delay line can be a significant portion of the total delay. Preliminary results indicate that for the proposed SAW oscillator, external delay amount to at least 20 ns. This will increase the total loop delay to approximately 0.12 to 0.13 μsec. The mode spacing of the oscillator will thus be on the order of 7 MHz and not the 10 MHz which one would get if the external delay is neglected. With 7 MHz mode spacing, single mode operation can be achieved if the amplifier gain is set properly.

To meet these specifications, the delay line was designed to consist of one long and one short transducer, closely spaced one next to the other. The 3 dB bandwidth is largely defined by the long transducer. The transducers are both designed to operate at the fundamental frequency and contain split fingers to minimize reflection among fingers. The center-to-center separation between transducers is $40.3 \lambda_0$, where λ_0 is the acoustic wavelength.

The other design parameters are shown in the following table:

	<u>Input Transducer</u>	<u>Output Transducer</u>
Number of Finger Pairs	30	50
Acoustic Aperture	$45 \lambda_0$	$45 \lambda_0$
Finger Width	$1.3 \mu\text{m}$	$1.3 \mu\text{m}$

The unmatched insertion loss of such a device should be approximately 40 dB. Upon matching, it can be reduced to 18 dB or less.

The schematic of the SAW delay line is shown in Figure 3-1. A ground bar has been placed between the transducers to cut down the direct electrical feedthrough.




Figure 3-1. SCHEMATIC OF 403 MHz SAW DELAY LINE

This delay line has been designed, fabricated and tested. Performance of the unmatched delay line is shown in Figures 3-2 through 3-4. The circuit has been packaged in a TO-5 can to minimize size and cost. A photograph of the packaged SAW is shown in Figure 3-5. Matching networks for the SAW have also been designed, built, and tested. A schematic of the matched circuit is shown in Figure 3-6. Performance of the matched delay line is shown in Figures 3-7 and 3-8.

b. Loop Amplifier

The loop amplifier is used to provide gain to overcome losses in all other loop elements. A schematic of the amplifier used for the SAW oscillator is shown in Figure 3-9. The circuit is a three-stage, lumped element design using two BFR 91 transistors and one MRF 559. The MRF 559 is used in the amplifier output stage to provide saturated output power in excess of 40 mW (+16 dBm). A lumped element design was used to minimize circuit size. Distributed matching networks would have required more volume than available.

This circuit has been designed, built, and tested. A photograph of the breadboard circuit is shown in Figure 3-10. Test results for the amplifier are shown in Figures 3-11 through 3-16. Figure 3-11 shows linear gain in excess of 40 dB for temperatures ranging from -70°C to $+70^{\circ}\text{C}$. Saturation characteristics for the circuit are shown in Figures 3-12 and 3-13. Saturated gain for input power of +18 dBm is shown in Figure 3-14. Transmission phase through the amplifier for linear and saturated operating conditions is shown in Figures 3-15 and 3-16, respectively.

All of the data shown above has also been taken as a function of supply voltage. Results indicate that the transmission phase of the amplifiers is sensitive to supply voltage particularly at temperature extremes. The supply to the amplifier will therefore be regulated to 9V.




Figure 3-2. 403 MHz SAW Unmatched Passband and Phase




Figure 3-3. 403 MHz SAW Unmatched Passband and Phase

NAME 403 MHZ SAW SN1	TITLE IN T05	DWG. NO
SMITH CHART FORM 82-BSPR-9-66		DATE
KAY ELECTRIC COMPANY PINE BROOK N.J. © 1966 PRINTED IN USA		

IMPEDANCE OR ADMITTANCE COORDINATES




Figure 3-4. 403 MHz SAW Unmatched Reflection Coefficients

A MEGA-CHART




Figure 3-5. PHOTOGRAPH OF PACKAGED SAW




Figure 3-6. 403 MHz SAW DELAY LINE




Figure 3-7. 403 MHz SAW Matched Passband and Phase

NAME 403 MHZ SAW SNI	TITLE IN T05 MATCHED	DWG. NO
SMITH CHART FORM 82-BSPR(9-66) KAY ELECTRIC COMPANY PINE BROOK N.J. ©1966 PRINTED IN USA		DATE

IMPEDANCE OR ADMITTANCE COORDINATES




Figure 3-8. 403 MHz SAW Matched Reflection Coefficients

A MEGA-CHART




Figure 3-10. PHOTOGRAPH OF BREADBOARD CIRCUIT




Figure 3-11. 403 MHz SAW AMP, $V_{CC} = 12V$, $P_{IN} = -40$ dBm




Figure 3-12. LOOP AMPLIFIER P_{OUT} vs P_{IN} (12V Bias)




Figure 3-13. LOOP AMPLIFIER P_{OUT} vs P_{IN} (9V Bias)




Figure 3-14. 403 MHz SAW AMP, $V_{CC} = 12V$, $P_{IN} = -18$ dBm




Figure 3-15. 403 MHz SAW AMP, $V_{CC} = 12V$, $P_{IN} = -40$ dBm




Figure 3-16. 403 MHz SAW AMP, $V_{CC} = 12V$, $P_{IN} = -18 \text{ dBm}$

As the results show, the loop amplifier as designed is adequate for use in the SAW oscillator. A comparison of the measured and required performance is shown below:

<u>Parameter</u>	<u>Required Performance</u>	<u>Measured Performance</u>
Frequency Band	> 350-450 MHz	> 350-450 MHz
Gain	> 40 dB	42-48 dB
P_{SAT}	+16.5 dBm	+14.5 dBm* (9V bias)
VSWR (In,Out)	$\leq 2.5:1$	$\leq 2.0:1$
V_{Supply}	12V	12V (regulated to 9V)

*The saturated output power with 12V bias is +17.5 dBm. The ILO has been designed to operate with lower injected power.

c. Phase Shifter

The phase shifter block diagram is shown in Figure 3-17.




Figure 3-17. PHASE SHIFTER BLOCK DIAGRAM

The circuit consists of a hybrid coupler loaded with tunable, reflective loads. In this design, power incident at port 1 is split with equal amplitude, and 90° relative phase between ports 2 and 3. Since the loads at ports 2 and 3 are reflective, the power incident on these loads from ports 2 and 3 is reflected back into the coupler. The reflected signals experience a phase shift associated with the reflection coefficient of the loads, and since the loads are tunable this phase shift can be varied. The reflected signals entering the coupler at ports 2 and 3 add in phase at port 4 and add out of phase (cancel) at port 1. Therefore, this circuit will transfer a signal incident at port 1 to port 4 with a phase shift which is a function of the reflection coefficient of the loads.

To better understand the operation of this circuit, let $V_{1in} = Ae^{j\omega t}$ be the signal input to port 1. Then $V_{2out} = \frac{A}{\sqrt{2}} e^{j\omega t}$ and $V_{3out} = \frac{A}{\sqrt{2}} e^{j(\omega t + \pi/2)}$; i.e., half of the power input to port 1 goes to each of ports 2 and 3. If the networks connected to ports 2 and 3 have reflection coefficients of Γ_1 and Γ_2 , respectively, then the signals input to ports 2 and 3 are given as

$$V_{2in} = \frac{A}{\sqrt{2}} e^{j\omega t} \Gamma_1 \quad (3.1)$$

$$V_{3in} = \frac{A}{\sqrt{2}} e^{j(\omega t + \pi/2)} \Gamma_2 \quad (3.2)$$

After traveling through the quadrature hybrid again, the signal levels out of ports 1 and 4 are given by

$$V_{1out} = \frac{A}{2} [e^{j\omega t} \Gamma_1 + e^{j(\omega t + \pi/2)} \Gamma_2] \quad (3.3)$$

$$V_{4out} = \frac{A}{2} [e^{j(\omega t + \pi/2)} \Gamma_1 + e^{j(\omega t + \pi/2)} \Gamma_2] \quad (3.4)$$

It is now apparent that if $\angle_1 = \angle_2$, V_{1out} equals zero and all power incident at port 1 appears at port 4. More importantly, notice that V_{4out} is a function of the load reflection coefficients. The relative phase of the output signal is therefore determined by the phase of the load reflection coefficient.

In practice the loads are made identical but some small difference in reflection coefficient will exist. The loads also will be lossy. Consider the case where loads are neither equal nor ideal. Let

$$\Gamma_1 = \rho e^{j\angle_1} \quad (3.5)$$

$$\Gamma_2 = \rho e^{j\angle_2} \quad (3.6)$$

For this case

$$V_{4out} = \frac{A\rho}{2} [e^{j(\omega t + \pi/2)}(e^{j\angle_1} + e^{j\angle_2})] \quad (3.7)$$

or

$$V_{4out} = A\rho \cos \frac{\angle_1 - \angle_2}{2} e^{j(\omega t + \pi/2 + \frac{\angle_1 + \angle_2}{2})} \quad (3.8)$$

The phase shift from port 1 to port 4 is therefore $\frac{\pi}{2} + \frac{\angle_1 + \angle_2}{2}$. The loss through the phase shifter is $20 \log (\rho \cos \frac{\angle_1 - \angle_2}{2})$ dB. For small differences in the angles of the reflection coefficients, $\angle_1$ and $\angle_2$, the loss will be determined by ρ . For a 90° difference in $\angle_1$ and $\angle_2$, 3 dB of additional loss will occur.

The design of the hybrid coupler itself can be either distributed or lumped. For this application a lumped element design was chosen to minimize size. A schematic of this coupler is shown in Figure 3-18




Figure 3-18 COUPLER SCHEMATIC

For this design

$$Z_0 = \sqrt{\frac{L}{C}} \quad (3-9)$$

and

$$\omega_0 = \frac{1}{\sqrt{LC}} \quad (3-10)$$

where

Z_0 = characteristic impedance

ω_0 = radian frequency at center band.

For the phase shifter, $\omega_0 = 2\pi(403 \times 10^6)$, and $Z_0 = 50\Omega$. Therefore

$$Z_0 = \sqrt{\frac{L}{C}} = 50 \quad (3-11)$$

$$\omega_0 = \frac{1}{\sqrt{LC}} = 2\pi(403 \times 10^6) \quad (3-12)$$

and

$$\begin{aligned} L &= 19.7 \text{ nH} \\ C &= 7.9 \text{ pF} \end{aligned} \quad (3-13)$$

This coupler has been built and tested. Tests indicate that using 10 pF capacitors will produce an equal -3.7 dB power split with relative phase of 88°. Using 8.2 pF capacitors produces a 90° relative phase split but the

amplitude split is unbalanced by 0.4 dB to -3.6 dB and -4.0 dB. Measured results for a breadboard coupler are shown in Figure 3-19.

The design of the circuit which will load the hybrid coupler is shown in Figure 3-20. This load consists of a shunt inductance, a varactor, and a DC blocking capacitor. The reflection coefficient of the load is

$$\rho = \frac{Z_L - Z_0}{Z_L + Z_0} \quad (3.14)$$

where

$$Z_L = \text{load impedance} \left(\frac{Z_{\text{ind}} Z_{\text{cap}}}{Z_{\text{ind}} + Z_{\text{cap}}} \right)$$

$$Z_0 = \text{system characteristic impedance (50 ohms typical)}$$

The choice of inductor and varactor will determine the maximum phase variation of the phase shifter and tuning range of the oscillator. For maximum phase variation, the inductor-varactor combination is designed to resonate in the center of the varactor's tuning range. However, such a design results in a nonlinear phase-voltage relationship due to the nonlinear capacitance-voltage relationship of the varactor. To simplify temperature compensation and to insure more linear frequency modulation, it is desirable to design a load with a near linear phase voltage relationship. By increasing the inductance value such that LC resonance occurs at the lower extreme of the capacitance range, a more linear relationship is achieved. Such a design has been investigated for this application but total phase shift was found to be inadequate.




Figure 3-19. 403 MHz TWISTED WIRE COUPLER




Figure 3-20. COUPLER LOAD

To select the LC combination most suitable the varactor diodes were first characterized. Reflection coefficient as a function of voltage is shown in Figure 3-21. Note that using the varactor alone would produce only a 60° phase shift for a 0-10V tuning range. This characterization also indicates the diodes have approximately 0.5 ohm series resistance which will contribute to the overall phase shifter loss. To resonate this capacitance an inductor of approximately 8 nH was used. Assuming 0.02 ohm series resistance in the inductor, a computer model of this load predicted the performance shown in Figure 3-22. This compares well with the measured results shown in Figure 3-23

The total phase shifter, consisting of the coupler and the loads discussed above, has been constructed and tested. A photograph of the breadboard phase shifter is shown in Figure 3-24. Test results for two such phase shifters cascaded are shown in Figure 3-25. This figure is a plot of both loss and phase through the circuit as a function of tuning voltage. The data shows loss varying from approximately 5 dB at 0.5V down to 2 dB at 10V. The decreasing loss results from a decrease in diode series resistance with increasing reverse bias. The data also shows phase varying from 18° at 0.5V to $+180^\circ$ at just below 2V, to -36° at 5V and back to $+18^\circ$ at 10V. A full 360° shift has been realized with this cascade of two phase shifters.

One of the difficulties encountered when using varactor diodes is their capacitance variation with temperature. This variation translates into a change in reflection coefficient and therefore a change in phase through the circuit.

NAME	TITLE	DWG. NO
SMITH CHART FORM 82-BSPR 9-66	KAY ELECTRIC COMPANY PINE BROOK N.J. ©1966 PRINTED IN USA	DATE

IMPEDANCE OR ADMITTANCE COORDINATES





Figure 3-21. VARACTOR REFLECTION COEFFICIENT

Figure 3-22.
COMPUTER-PREDICTED LOAD REFLECTION COEFFICIENTS

C (@V)	b		Loss
	Magnitude	Angle	
5.0	.995	122.8	-.05
10.0 (@ 6V)	.981	100.5	-.17
15.0 (@ 3V)	.936	59.4	-.57
20.0 (@ 2V)	.867	-7.2	-1.24
25.0 (@ 1V)	.865	-69.9	-1.26
30.0	.896	-106.3	-.95
35.0	.920	-126.2	-.73
40.0	.934	-138.0	-.59
45.0	.944	-145.7	-.50
50.0 (@ 0V)	.950	-151.1	-.44

NAME	TITLE	DWG. NO
SMITH CHART FORM 82-BSPR(9-66)	KAY ELECTRIC COMPANY, PINE BROOK, N.J. © 1966 PRINTED IN USA	DATE

IMPEDANCE OR ADMITTANCE COORDINATES





Figure 3-23. MEASURED LOAD REFLECTION COEFFICIENTS




Figure 3-24. PHOTOGRAPH OF BREADBOARD PHASE SHIFTER




Figure 3-25. 403 MHz BREADBOARD DOUBLE PHASE SHIFTER

The frequency of the oscillator therefore will drift with temperature.

Tests have been run on the full phase shifter to characterize temperature performance. The detailed results are included in the Appendix for reference and are summarized with the graph in Figure 3-26. It is the frequency drift with temperature caused by variation in phase which requires that a temperature compensation network be used. The compensating voltage will be summed with the tuning and modulation voltages and applied to the varactor. As mentioned earlier the DC circuit including the temperature compensation network has not yet been designed.

As the results in this section indicate, the design of the phase shifter is complete and performance is adequate for the SAW oscillator application. A comparison of measured and required performance is shown below.

Parameter	Requirement	Performance
Frequency	4.0-4.86 MHz	4.0-4.8 MHz
Phase Shift	360	360
Gain	6 dB	1.5 to 5 dB
Tuning Voltage	1-10V	1-10V

d. Injection Locked Oscillator

The injection locked oscillator (ILO) is used to amplify the output of the SAW oscillator to the required 200 mW (+23 dBm). Pulse amplitude modulation is also accomplished in the ILO. A schematic of the circuit is shown in Figure 3-27.

The oscillator is of the form of a Colpitts with a resonant tank in the collector circuit and feedback to the emitter. The injection locking signal is applied to the emitter-base junction.




Figure 3-27. 403 MHz ILO

This circuit has been designed, built and tested. A photograph of the breadboard circuit is shown in Figure 3-28. Test results are shown in Figures 3-29 through 3-31. Figure 3-29 is a plot of injection locking bandwidth vs injection locking power. Figure 3-30 shows injection locking bandwidth vs temperature. Output power vs frequency is shown in Figure 3-31.

Pulse amplitude modulation characteristics are shown in Figures 3-32 and 3-33. Time waveforms are shown in Figures 3-32a through 3-32e, while frequency spectrum is shown in Figures 3-33a through 3-33d.

As the data shows, the ILO is adequate for this application. A comparison of measured and required performance is shown below:

<u>Parameter</u>	<u>Requirement</u>	<u>Performance</u>
Center Frequency	403 MHz	403 MHz (adjustable)
Power Out	23 dBm	>+24 dBm
Injection Locking Bandwidth	16 MHz	49 MHz (@ 25°C, +12 dBm)
P_{inj}	+13 dBm	+12 dBm
V_{supply}	+12V	+12V




Figure 3-28. PHOTOGRAPH OF ILO BREADBOARD CIRCUIT




Figure 3-29. INJECTION LOCKING BANDWIDTH vs INJECTION POWER




Figure 3-30. INJECTION LOCKING BANDWIDTH vs TEMPERATURE







Figure 3-31. OUTPUT POWER vs FREQUENCY




(a) Modulation Frequency = 30 Hz




(b) Modulation Frequency = 300 Hz



(c) Modulation Frequency = 3 kHz




(d) Modulation Frequency = 30 KHz




(e) Modulation Frequency = 300 KHz


Figure 3-32. ILO AMPLITUDE MODULATION TIME WAVEFORMS (Continued)



(a) 200 MHz Sweep Width



(b) 1 MHz Sweep Width



(c) 100 kHz Sweep Width

Figure 3-33. ILO AMPLITUDE MODULATION FREQUENCY SPECTRUM
(MODULATION FREQUENCY = 10 KHz)

4.0 CONCLUSION


The RF circuitry described in this report has been adequately developed to be used in the construction of the 403 MHz SAW Oscillator. A number of difficulties which were encountered during the circuit development should be noted. The initial loop design did not adequately take into account the delay in loop components other than the SAW. The margin in mode spacing was therefore inadequate to assure a single oscillator output frequency. Both the SAW matching circuit and the loop amplifier contributed significantly to this additional delay. The sensitivity of the loop amplifier phase to bias - in the saturated operating condition - was also not anticipated. Regulation of the amplifier bias was added after this phenomenon was observed (see Appendix B). The phase shifter construction was not trivial. Performance of the circuit is dependent on both the inductance and coupling of the coil wires. Turns per inch and twists per inch are both critical. Once these parameters are determined, construction and performance of the coupler are very repeatable.

One observation regarding the temperature stability of the oscillator circuitry should be made. The requirement for FM has made achieving the required stability challenging. Frequency modulation requires electronic tuning in the oscillator loop. The varactors used for this tuning are the most unstable components in the oscillator. It is primarily their capacitance variation with temperature which requires a temperature compensation network to be used. Were the radiosonde system to require AM only, a mechanical phase shifter could be used for tuning and the stability of the oscillator would primarily reflect the SAW delay line temperature variation and not that of the phase shifter. Designing a mechanical phase shifter is far easier than compensation for the varactors.


APPENDIX A

SAW PERFORMANCE vs TEMPERATURE MEASUREMENTS


MATCHED SAW PASSBAND VARIATION WITH TEMPERATURE




MATCHED SAW PHASE vs TEMPERATURE



APPENDIX B
AMPLIFIER PERFORMANCE
VS
SUPPLY VOLTAGE AND TEMPERATURE



403MHz SAW AMP $V_{CC}=11V$ $P_{in}=-40dBm$



483 MIL. CAV. AND 1.0000000000000000

70

50

GAIN (dB)

30

10

-10

+ 30%

+ 30%


+ 30%

+ 30%


+ 30%




425 MHz SAW AVE. LOSS 18 dBm




403 MHz SAW AMP V500-1037 + 500-4203-00




425 MHz 100 dB 70-137 MHz -40 dBm



403 MHz BW AM 1000000 Hz



423 415 300 200 100 0 -100 -200 -300 -400 -500 -600 -700 -800 -900 -1000 -1100 -1200 -1300 -1400 -1500 -1600 -1700 -1800 -1900 -2000 -2100 -2200 -2300 -2400 -2500 -2600 -2700 -2800 -2900 -3000 -3100 -3200 -3300 -3400 -3500 -3600 -3700 -3800 -3900 -4000 -4100 -4200 -4300 -4400 -4500 -4600 -4700 -4800 -4900 -5000 -5100 -5200 -5300 -5400 -5500 -5600 -5700 -5800 -5900 -6000 -6100 -6200 -6300 -6400 -6500 -6600 -6700 -6800 -6900 -7000 -7100 -7200 -7300 -7400 -7500 -7600 -7700 -7800 -7900 -8000 -8100 -8200 -8300 -8400 -8500 -8600 -8700 -8800 -8900 -9000 -9100 -9200 -9300 -9400 -9500 -9600 -9700 -9800 -9900 -10000



APPENDIX C

PHASE SHIFTER CHARACTERISTICS

LOSS (dB)

67

2

0

-2

-4

-6

10V

5V

2V

1.75V

1.0V


0.5V

0.5V

1.0V

PHASE (Deg.)

180



1.75V

90



1V

0



0.5V

10V




5V

-90


-180




2V




422 MHz JMW PHASE SHIFTER $V_t = 1.0V$




423 MHz LOCAL PHASE SHIFTER $V_0=2.0V$




403 MHz DUAL PHASE DIFFERENCE




423 MHz DIAL PHASE DIFFERENCE




403 MHz DUAL PHASE SHIFTER $V_t = .5V$




4033 MHz DUAL PHASE SHIFTER $V_t=1.0V$




403 MHz DUAL PHASE SHIFTER $V_b = 2.0V$



403 MHz DUAL PHASE SHIFTER V_{DS} 6.0V



423 MILS PHASE SHIFTER $V_0 = 10.0V$



ELECTRONICS TECHNOLOGY AND DEVICES LABORATORY
MANDATORY CONTRACT DISTRIBUTION LIST

101	Defense Technical Information Center ATTN: DTIC-TCA Cameron Station (Bldg 5) Alexandria, VA 22314	001	Arlington, VA 22212
012		602	Cdr. Night Vision & Electro-Optics ERADCOM ATTN: DELNV-D Fort Belvoir, VA 22060
203	GIDEP Engineering & Support Dept TE Section PO Box 398 NORCO, CA 91760	001	
001		603	Cdr. Atmospheric Sciences Lab ERADCOM ATTN: DELAS-SY-S White Sands Missile Range, NM 88002
205	Director Naval Research Laboratory ATTN: CODE 2627 Washington, DC 20375	001	
001		607	Cdr. Harry Diamond Laboratories ATTN: DELHD-CO, TD (In Turn) 2800 Powder Mill Road Adelphi, MD 20783
301	Rome Air Development Center ATTN: Documents Library (TILD) Griffiss AFB, NY 13441	001	
001		609	Cdr. ERADCOM ATTN: DRDEL-CG, CD, CS (In Turn) 2800 Powder Mill Road Adelphi, MD 20783
437	Deputy for Science & Technology Office, Asst Sec Army (R&D) Washington, DC 20310	001	
001		612	Cdr. ERADCOM ATTN: DRDEL-CT 2800 Powder Mill Road Adelphi, MD 20783
438	HQDA (DAMA-ARZ-D/Dr. F.D. Verderame) Washington, DC 20310	001	
001		680	Commander US Army Electronics R&D Command Fort Monmouth, NJ 07703
482	Director US Army Materiel Systems Analysis Actv ATTN: DRXSY-MP Aberdeen Proving Ground, MD 21005	1	DELET-MQ
001		1	DELEW-D
563	Commander, DARCOM ATTN: DRCDE 5001 Eisenhower Avenue Alexandria, VA 22333	1	DELET-DD
001		1	DELSO-L (Tech Library)
564	Cdr. US Army Signals Warfare Lab ATTN: DELSW-OS Vint Hill Farms Station Warrenton, VA 22186	2	DELSO-L-S (STINFO)
001		20	DELET-MA-A
705	Advisory Group on Electron Devices 201 Varick Street, 9th Floor New York, NY 10014	1	DELET-MF
002		681	Commander US Army Communications R&D Command ATTN: USMC-LNO Fort Monmouth, NJ 07703
579	Cdr. PM Concept Analysis Centers ATTN: DRCPM-CAC Arlington Hall Station	001	

ELECTRONICS TECHNOLOGY AND DEVICES LABORATORY
SUPPLEMENTAL CONTRACT DISTRIBUTION LIST
(ELECTIVE)

103	Code R123, Tech Library DCA Defense Comm Engrg Ctr 1800 Wiehle Ave Reston, VA 22090	475	Cdr, Harry Diamond Laboratories ATTN: Library 2800 Powder Mill Road Adelphi, MD 20783
001		001	
104	Defense Communications Agency Technical Library Center Code 205 (P. A. Tolovi) Washington, DC 20305	477	Director US Army Ballistic Research Labs ATTN: DRXBR-LB Aberdeen Proving Ground, MD 21005
001		001	
206	Commander Naval Electronics Laboratory Center ATTN: Library San Diego, CA 92152	455	Commandant US Army Signal School ATTN: ATSH-UD-MS-E Fort Gordon, GA 30905
001		001	
207	Cdr, Naval Surface Weapons Center White Oak Laboratory ATTN: Library Code WX-21 Silver Spring, MD 20910	422	Commander US Army Yuma Proving Ground ATTN: STEYP-MTD (Tech Library) Yuma, AZ 85364
001		001	
314	Hq, Air Force Systems Command ATTN: DLCA Andrews Air Force Base Washington, DC 20331	507	Cdr, AVRADCOM ATTN: DRSAV-E PO Box 209 St. Louis, MO 63166
001		001	
403	Cdr, MICOM Redstone Scientific Info Center ATTN: Chief, Document Section Redstone Arsenal, AL 35809	511	Commander, Picatinny Arsenal ATTN: SARPA-FR-5, -ND-A-4, -TS-S (In Turn) Dover, NJ 07801
001		001	
406	Commandant US Army Aviation Center ATTN: ATZQ-D-MA Fort Rucker, AL 36362	515	Project Manager, REMBASS ATTN: DRCPM-RBS Fort Monmouth, NJ 07703
001		001	
407	Director, Ballistic Missile Defense Advanced Technology Center ATTN: ATC-R, PO Box 1500 Huntsville, AL 35807	517	Commander US Army Satellite Communications Agcy ATTN: DRCPM-SC-3 Fort Monmouth, NJ 07703
001		001	
418	Commander HQ, Fort Huachuca ATTN: Technical Reference Div Fort Huachuca, AZ 85613	518	TRI-TAC Office ATTN: TT-SE Fort Monmouth, NJ 07703
001		001	

ELECTRONICS TECHNOLOGY AND DEVICES LABORATORY
SUPPLEMENTAL CONTRACT DISTRIBUTION LIST (CONT)
(ELECTIVE)

519	Cdr. US Army Avionics Lab AVRADCOM ATTN DAVAA-D	608	Commander ARRADCOM DRDAR-TSB-S
001	Fort Monmouth, NJ 07703	001	Aberdeen Proving Ground, MD 21005
520	Project Manager, FIREFINDER ATTN DRCPM-FF	614	Cdr, ERADCOM ATTN: DRDEL-LL, -SB, -AP (In Turn)
001	Fort Monmouth, NJ 07703		2800 Powder Mill Road
521	Commander Project Manager, SOTAS ATTN DRCPM-STA	001	Adelphi, MD 27083
001	Fort Monmouth, NJ 07703	617	Cdr, ERADCOM ATTN: DRDEL-AQ
531	Cdr. US Army Research Office ATTN DRXRO-PH (Dr. Lontz) DRXRO-IP (In Turn)		2800 Powder Mill Road
	PO Box 12211	001	Adelphi, MD 20783
001	Research Triangle Park, NC 27709	619	Cdr, ERADCOM ATTN: DRDEL-PA, -ILS, -ED (In Turn)
556	HQ. TCATA Technical Information Center ATTN: Mrs. Ruth Reynolds		2800 Powder Mill Road
001	Fort Hood, TX 76544	001	Adelphi, MD 20783
568	Commander US Army Mobility Eqp Res & Dev Cmd ATTN DRDME-R	701	MTI — Lincoln Laboratory ATTN: Library (RM A-082)
001	Fort Belvoir, VA 22060		PO Box 73
604	Chief Ofc of Missile Electronic Warfare Electronic Warfare Lab, ERADCOM	002	Lexington, MA 02173
001	White Sands Missile Range, NM 88002	703	NASA Scientific & Tech Info Facility Baltimore/Washington Intl Airport
606	Chief Intel Materiel Dev & Support Ofc Electronic Warfare Lab, ERADCOM	001	PO Box 8757, MD 21240
001	Fort Meade, MD 20755	704	National Bureau of Standards Bldg 225, RM A-331
			ATTN: Mr. Leedy
		001	Washington, DC 20231
		707	TACTEC Batelle Memorial Institute
			505 King Avenue
		001	Columbus, OH 43201

**ELECTRONICS TECHNOLOGY AND DEVICES LABORATORY
SUPPLEMENTAL CONTRACT DISTRIBUTION LIST (CONT)
(ELECTIVE)**

Coordinated Science Laboratory University of Illinois Urbana, Illinois 61801 ATTN: Dr. Bill J. Hunsinger	(1)	Anderson Laboratories, Inc. 1280 Blue Hills Ave ATTN: Dr. A.A. Comparini Bloomfield, Conn. 06002	(1)
Dr. J.S. Bryant OCD ATTN: DARD-ARP Washington, DC 20310	(1)	Mr. Henry Friedman RADC/OCTE Griffiss AFB, NY 13440	(1)
Dr. R. LaRosa Hazeltine Corporation Greenlawn, New York 11740	(1)	US Army Electronics R&D Cmd CS&TA Laboratory Special Sensors Div DELCS-S (Robbiani) Fort Monmouth, NJ 07703	(6)
General Electric Co. Electronics Lab Electronics Park Syracuse, NY 13201 ATTN: Mr. S. Wanuga	(1)	General Dynamics, Electronics Division P.O. Box 81127 San Diego, CA 92138 ATTN: Mr. R. Badewitz	(1)
Air Force Cambridge Labs ATTN: CRDR (Dr. P. Carr & Dr. A.J. Budreau) Bedford, MA 01730	(2)	Texas Instruments, Inc. P.O. Box 5936 13500 N. Central Expressway Dallas, Texas 75222 ATTN: Dr. L.T. Clairborne	(2)
Mr. R. Weglein Hughes Research Laboratories 3011 Malibu Canyon Road Malibu, California 90265	(1)	Raytheon Company Research Division 28 Seyon Street Waltham, Massachusetts 02154 ATTN: Dr. M.B. Schulz	(1)
Mr. H. Bush CORC RADC Griffiss Air Force Base New York 13440	(1)	Sperry Rand Research Center 100 North Road Sudbury, Massachusetts 01776 ATTN: Dr. H. Van De Vaart	(1)
Mr. G. Judd Hughes Aircraft Company Ground Systems Group Bldg 600/MS D235 1901 W. Malvern Fullerton, CA 92634	(1)	Microwave Laboratory W.W. Hansen Laboratories of Physics Stanford University Stanford, CA 94305 ATTN: Dr. H.J. Shaw	(2)
Commander, AFAL ATTN: Mr. W.J. Edwards, TEA Wright-Patterson AFB, Ohio 45433	(1)		

ELECTRONICS TECHNOLOGY AND DEVICES LABORATORY

SUPPLEMENTAL CONTRACT DISTRIBUTION LIST (CONT)

(ELECTIVE)

Westinghouse Electric Corp. Research & Development Center Beulah Road Pittsburgh, PA 15235 ATTN: Dr. B. McAvoy	(1)	Science Center Rockwell International Thousand Oaks, CA 91360	(1)
TRW Defense and Space Sys Group One Space Park Redondo Beach, CA 90278 ATTN: Dr. R.S. Kagiwada	(1)	AMES Laboratory 215 Reactor Bldg Iowa State University Ames, Iowa 50011 ATTN: Dr. K Lakin	(1)
Dr. Fred S. Hickernell Integrated Circuit Facility Motorola Government Electronics Division 8201 East Mc Dowell Road Scottsdale, AZ 85257	(1)	SAWTEK, Inc. P.O. Box 7756 2451 Shader Road Orlando, Florida 32854 ATTN: Mr. S. Miller	(1)
Dr. F. Cho Integrated Circuit Facility Motorola Government Electronics Division 8201 East McDowell Road Scottsdale, AZ 85257	(1)	Dr. William J. Tanski Sperry Research Center 100 North Road Sudbury, MA 01776	(1)
McGill University ATTN: G.W. Farnell Montreal 110, Canada	(1)	Dr. William R. Shreve HP Laboratories 1501 Page Mill Road Palo Alto, CA 94304	(1)
Advanced Technology Center, Inc. Subsidiary of LTV Aerospace Corp P.O. Box 6144 Dallas, Texas 75222 ATTN: Mr. A.E. Sobey	(1)	D. Chrissotimos, Code 763 National Aeronautics & Space Administration Goddard Space Flight Center Greenbelt, MD 20771	(1)
United Aircraft Research Labs ATTN: Dr. Thomas W. Grudkowski East Hartford, Conn. 06108	(1)	Naval Research Laboratories Code 5237 Washington, DC 20375 ATTN: Dr. D. Webb	(1)
US Army Missile Command DRSMI-REL Redstone Arsenal, Al 35809 ATTN: G.J. Rast, Jr.	(1)	HQ ESD (DRI) L.G. Hanscom AFB Bedford, MA 01731	(1)

ELECTRONICS TECHNOLOGY AND DEVICES LABORATORY
SUPPLEMENTAL CONTRACT DISTRIBUTION LIST (CONT)

(ELECTIVE)

Army Materials and Mechanics Research
Center (AMMRC)
Watertown, MA 02172
ATTN: DMXMR-EO (1)

Commander, Picatinny Arsenal
ATTN: SARPA-FR-S
Bldg 350
Dover, NJ 07801 (2)

A. Kahan
RADC/ESE
Hanscom AFB
Bedford, MA 01731 (1)

END

DATE
FILMED

5 81

DTIC