

Precodings for Transmission Rate Increasing in MIMO Single Carrier Block Transmissions

Shusuke Narieda and Katsumi Yamashita

Graduate School of Engineering, Osaka Prefecture University, Sakai,
Osaka, Japan.

summary

In wireless communication systems, multi-input multi-output (MIMO) wireless, which exploits the spatial diversity, is known as a cost-effective solution for high data rate. In the MIMO systems, the linear precoder and decoder, which is the joint processing at the transmitter and receiver sides and decomposes the MIMO channel to the parallel flat fading subchannels i.e., eigenmode, is introduced to achieve performance improvement[1], [2].

Under the assumption that the channel state information is known, the linear precoder is designed in accordance with various criteria, i.e., the maximization of the output capacity[3], [4], the minimization of the mean square error (MSE) and weighted MSE[5], [6] and the minimization of a probability of error[5], [7], [8]. In various criteria for reducing the probability of error, maximum likelihood (ML) decision rule based criterion precoder (ML precoder)[5] minimizes the probability of error by maximizing the minimum distance between symbol hypotheses and is designed to keep the bit error rate (BER) at the maximum tolerable BER[3] by discarding the eigenmode which is unacceptable the maximum tolerable BER condition, at last, the number of remainder eigenmodes, i.e., useful eigenmodes, determines the transmission rate. However, when the maximum tolerable BER is chosen to be a low value($\approx 10^{-9}$), the number of the useful eigenmodes will be seriously constrained. As a consequence, the transmission rate may be decreased.

In this paper, for the MIMO block transmission systems, we propose a precoding method aiming at increasing the transmission rate. In order to increase the transmission rate, we employ two kinds of the ML precoder. One is conventional precoding method with the ML precoder which has a precoded symbol length equal to a frame length(CPC). Another one is a novel precoding method, in which several ML precoder are arranged in parallel(PPC). The ML precoder employed in the PPC is designed using the MIMO channel matrix consisted of the direct wave only are arranged in parallel and has a precoded symbol length equal to the number of transmit antennas. The precoded symbols for one frame is constructed of the precoded symbols generated from each ML precoders, at last, the precoded symbol length of the PPC is the summation of the precoded symbol lengths of each ML precoder in the PPC and equal to the precoded symbol length of the CPC.

We investigate the effect of the precoded symbol length of one ML precoder on the resulting transmission rate and show that the transmission rate increasing can be

Report Documentation Page				Form Approved OMB No. 0704-0188	
Public reporting burden for the collection of information is estimated to average 1 hour per response, including the time for reviewing instructions, searching existing data sources, gathering and maintaining the data needed, and completing and reviewing the collection of information. Send comments regarding this burden estimate or any other aspect of this collection of information, including suggestions for reducing this burden, to Washington Headquarters Services, Directorate for Information Operations and Reports, 1215 Jefferson Davis Highway, Suite 1204, Arlington VA 22202-4302. Respondents should be aware that notwithstanding any other provision of law, no person shall be subject to a penalty for failing to comply with a collection of information if it does not display a currently valid OMB control number.					
1. REPORT DATE 01 JAN 2005		2. REPORT TYPE N/A		3. DATES COVERED -	
4. TITLE AND SUBTITLE Precodings for Transmission Rate Increasing in MIMO Single Carrier Block Transmissions				5a. CONTRACT NUMBER	
				5b. GRANT NUMBER	
				5c. PROGRAM ELEMENT NUMBER	
6. AUTHOR(S)				5d. PROJECT NUMBER	
				5e. TASK NUMBER	
				5f. WORK UNIT NUMBER	
7. PERFORMING ORGANIZATION NAME(S) AND ADDRESS(ES) Graduate School of Engineering, Osaka Prefecture University, Sakai, Osaka, Japan				8. PERFORMING ORGANIZATION REPORT NUMBER	
9. SPONSORING/MONITORING AGENCY NAME(S) AND ADDRESS(ES)				10. SPONSOR/MONITOR'S ACRONYM(S)	
				11. SPONSOR/MONITOR'S REPORT NUMBER(S)	
12. DISTRIBUTION/AVAILABILITY STATEMENT Approved for public release, distribution unlimited					
13. SUPPLEMENTARY NOTES See also ADM001846, Applied Computational Electromagnetics Society 2005 Journal, Newsletter, and Conference.					
14. ABSTRACT					
15. SUBJECT TERMS					
16. SECURITY CLASSIFICATION OF:			17. LIMITATION OF ABSTRACT UU	18. NUMBER OF PAGES 2	19a. NAME OF RESPONSIBLE PERSON
a. REPORT unclassified	b. ABSTRACT unclassified	c. THIS PAGE unclassified			

achieved by switching the precoding method with higher transmission rate depending on the channel conditions. Also, since the proposed method require to design two types of the ML precoder, the computational cost is very high. In order to reduce the computational cost in the proposed method, we propose a computationally efficient ML precoder switching algorithm which requires only some lower bounds of the extreme eigenvalue.

The effect of the proposed method is proved theoretically, also its validity is demonstrated by the computer simulations.

References

- [1] J. Yang and S. Roy, "On joint transmitter and receiver optimization for multiple-input-multiple-output (MIMO) transmission systems," *IEEE Trans. Commun.*, vol. 42, pp. 3221-3231, Dec. 1994.
- [2] G. G. Raileigh and J. M. Cioffi, "Spatio-temporal coding for wireless communications," *IEEE Trans. Commun.*, vol. 46, pp. 357-366, Mar. 1998.
- [3] A. Scaglione, S. Barbarossa, and G. B. Giannakis, "Filterbank transceivers optimizing information rate in block transmissions over dispersive channels," *IEEE Trans. Inform. Theory*, vol. 45, pp. 1019-1032, Apr. 1999.
- [4] T. M. Cover and J. A. Thomas, *Elements of Information Theory*. New York: Wiley, 1991.
- [5] A. Scaglione, P. Stoica, S. Barbarossa, G. B. Giannakis, "Optimal designs for space-time linear precoders and decoders," *IEEE Trans. Signal Processing*, vol. 50, no. 5, pp. 1051-1064, May 2002.
- [6] H. Sampath, P. Stoica, and A. Paulraj, "Generalized linear precoder and decoder design for MIMO channels using the weighted MMSE criterion," *IEEE Trans. Communications*, vol. 49, no. 12, pp. 2198-2206, Dec. 2001.
- [7] Y. Ding, T. N. Davidson, Z-Q. Luo and K. M. Wang, "Minimum BER block precoders for zero-forcing equalization," *IEEE Trans. Signal Processing*, vol. 51, pp. 2410-2423, Sept. 2003.
- [8] D. P. Palomar, J. M. Cioffi and M. A. Lagunas, "Joint Tx-Rx beamforming design for multicarrier MIMO channels: a unified framework for convex optimization," *IEEE Trans. Signal Processing*, vol. 51, pp. 2381-2401, Sept. 2003.