



A Numerical Technique for Removing Residual Gate-source Capacitances When Extracting Parasitic Inductance for GaN High Electron Mobility Transistors (HEMTs)

by Benjamin Huebschman and Pankaj B. Shah

ARL-TN-0428

March 2011

NOTICES

Disclaimers

The findings in this report are not to be construed as an official Department of the Army position unless so designated by other authorized documents.

Citation of manufacturer's or trade names does not constitute an official endorsement or approval of the use thereof.

Destroy this report when it is no longer needed. Do not return it to the originator.

Army Research Laboratory

Adelphi, MD 20783-1197

ARL-TN-0428

March 2011

A Numerical Technique for Removing Residual Gate-source Capacitances When Extracting Parasitic Inductance for GaN High Electron Mobility Transistors (HEMTs)

Benjamin Huebschman and Pankaj B. Shah
Sensors and Electron Devices Directorate, ARL

REPORT DOCUMENTATION PAGE				Form Approved OMB No. 0704-0188	
Public reporting burden for this collection of information is estimated to average 1 hour per response, including the time for reviewing instructions, searching existing data sources, gathering and maintaining the data needed, and completing and reviewing the collection information. Send comments regarding this burden estimate or any other aspect of this collection of information, including suggestions for reducing the burden, to Department of Defense, Washington Headquarters Services, Directorate for Information Operations and Reports (0704-0188), 1215 Jefferson Davis Highway, Suite 1204, Arlington, VA 22202-4302. Respondents should be aware that notwithstanding any other provision of law, no person shall be subject to any penalty for failing to comply with a collection of information if it does not display a currently valid OMB control number. PLEASE DO NOT RETURN YOUR FORM TO THE ABOVE ADDRESS.					
1. REPORT DATE (DD-MM-YYYY) March 2011		2. REPORT TYPE		3. DATES COVERED (From - To)	
4. TITLE AND SUBTITLE A Numerical Technique for Removing Residual Gate-source Capacitances When Extracting Parasitic Inductance for GaN High Electron Mobility Transistors (HEMTs)				5a. CONTRACT NUMBER	
				5b. GRANT NUMBER	
				5c. PROGRAM ELEMENT NUMBER	
6. AUTHOR(S) Benjamin Huebschman and Pankaj B. Shah				5d. PROJECT NUMBER	
				5e. TASK NUMBER	
				5f. WORK UNIT NUMBER	
7. PERFORMING ORGANIZATION NAME(S) AND ADDRESS(ES) U.S. Army Research Laboratory ATTN: RDRL-SER-E 2800 Powder Mill Road Adelphi, MD 20783-1197				8. PERFORMING ORGANIZATION REPORT NUMBER ARL-TN-0428	
9. SPONSORING/MONITORING AGENCY NAME(S) AND ADDRESS(ES)				10. SPONSOR/MONITOR'S ACRONYM(S)	
				11. SPONSOR/MONITOR'S REPORT NUMBER(S)	
12. DISTRIBUTION/AVAILABILITY STATEMENT Approved for public release; distribution unlimited.					
13. SUPPLEMENTARY NOTES					
14. ABSTRACT The design of monolithic microwave integrated circuits (MMIC) is dependent on the ability to generate accurate device models. Prior knowledge of the external parasitic components is required to determine the small signal model of the intrinsic device. A simple technique for determining and correcting for the gate-source capacitance during the extraction of the series inductance will be presented. This technique has worked well when integrated into existing small signal extraction procedures.					
15. SUBJECT TERMS AlGaIn, extraction, GaN, gate inductance, high electron mobility transistor (HEMT), intrinsic device, parasitic, small-signal model					
16. SECURITY CLASSIFICATION OF:			17. LIMITATION OF ABSTRACT UU	18. NUMBER OF PAGES 16	19a. NAME OF RESPONSIBLE PERSON Benjamin Huebschman
a. REPORT Unclassified	b. ABSTRACT Unclassified	c. THIS PAGE Unclassified			19b. TELEPHONE NUMBER (Include area code) (301) 394-0242

Contents

List of Figures	iv
Acknowledgment	v
1. Introduction	1
2. Theory	1
3. Measured Results and Analysis	3
4. Conclusion	5
5. References	6
Distribution List	7

List of Figures

Figure 1. Simplified equivalent circuit model for HEMT in the forward bias with pad capacitances removed.	2
Figure 2. Comparison of calculated gate inductance as determined by different methods.	3
Figure 3. Extracted parasitic inductances plotted versus frequency.	4
Figure 4. Modeled S-parameters compared with measured values (a) measured and modeled S-parameters plotted on the Smith chart (b) measure and modeled S11 plotted on the Smith chart (c) magnitude (dB) for S11 and S22 from 10 to 50 GHz	4

Acknowledgment

Authors would like to acknowledge the support of the Defense Advanced Research Projects Agency's (DARPA) Wide Band-Gap Semiconductor Technology Initiative (WBGSTI).

INTENTIONALLY LEFT BLANK.

1. Introduction

As gallium nitride (GaN) high electron mobility transistors (HEMTs) begin to realize their performance potential, and to transition from experimental devices to commercial applications, accurate device models are required to design monolithic microwave integrated circuits (MMICs) based on this technology (1–3). There have been a number of reports of successful methods for generating small signal models (4, 5). The technique, which will be outlined further, follows a recently published method, but modifies the step during which the series parasitic elements are calculated.

To determine the series parasitics, the gate is forward-biased with respect to the drain and the source, and V_{ds} is set to zero. According to existing parasitic extraction methods, when a device is biased in this manner, the intrinsic device can be approximated as a short circuit. However, in (4) it is observed that a residual gate source capacitance remains that appears to be in series with the gate elements. An earlier method proposes that the effect from the capacitor is small and can be ignored, while (5) calculates a predicted value for the capacitance under this bias. Ignoring C_{gs} , or calculating the value based on knowledge of the device fabrication, produces frequency dependent values for the equivalent circuit model components that do not correspond with the proper frequency response of lumped elements. In this report, we describe a numerical technique that has proven useful for directly determining C_{gs} from measured data in order to determine series parasitics.

2. Theory

The parasitic shunt (pad) capacitances were determined according to the procedure described in (4). The device is forward-biased and the S-parameters were measured. The shunt capacitances were de-embedded and the data are transformed into a z-matrix. The simplified model neglecting channel resistance of the device in the forward-bias condition is shown in figure 1.




Figure 1. Simplified equivalent circuit model for HEMT in the forward bias with pad capacitances removed.

The Z parameters for the circuit in figure 1 are given by

$$z_{11} = R_g + R_s + j\omega(L_g + L_s) - \frac{j}{\omega C_{gs}} \quad (1)$$

$$z_{12} = z_{21} = R_s + j\omega L_s \quad (2)$$

$$z_{22} = R_d + R_s + j\omega(L_d + L_s).$$

Based on these equations, the parameter values can be calculated:

$$R_s = \text{Re}(z_{12}) \quad (3)$$

$$R_g = \text{Re}(z_{11}) - R_s \quad (4)$$

$$R_d = \text{Re}(z_{22}) - R_s \quad (5)$$

$$L_s = \frac{\text{Im}(z_{22})}{\omega} \quad (6)$$

$$L_d = \frac{\text{Im}(z_{22})}{\omega} - L_s \quad (7)$$

$$L_g = \frac{\text{Im}(z_{11})}{\omega} - L_s + \frac{1}{\omega^2 C_{gs}}. \quad (8)$$

These values are directly calculated from the measured data, with the exception of the last equation. C_{gs} is an unknown value. With the knowledge of C_{gs} , the entire set of series parasitic elements can be determined.

The technique for determining C_{gs} is as follows:

$$X_{11} = \text{Im}(z_{11}) \quad (9)$$

$$\frac{X_{11}}{\omega} = (L_s + L_g) - \frac{1}{C_{gs}\omega^2} \quad (10)$$

$$\frac{d \frac{X_{11}}{\omega}}{d\omega} = \frac{2}{C_{gs}\omega^3} \quad (11)$$

$$C_{gs} = \frac{2}{\omega^3 \frac{d \frac{X_{11}}{\omega}}{d\omega}} = \frac{2}{\omega^3 \frac{\Delta \frac{\text{Im}(z_{11})}{\omega}}{\Delta \omega}} \quad (12)$$

The numerical differentiation of $\text{Im}(z_{11})/\omega$ was performed using the following equation:

$$\frac{\Delta x_i}{\Delta \omega} = \frac{x_{i+1} - x_{i-1}}{2\Delta \omega} \quad (13)$$

It should be mentioned that the differentiation of discrete values is the equivalent of a high-pass filter. If the data are noisy, the derivative might be dominated by the high frequency components of the noise. The easiest way to eliminate this problem is to reduce the number of samples, which functions as a filter for the noise.

3. Measured Results and Analysis

The modified extraction process was performed on several devices from several different wafers. A comparison of the values of L_g as determined by different methods is shown in figure 2. The calculations differ by the manner in which C_{gs} is calculated. The method described in (5) disregards the value of C_{gs} . In (4), C_{gs} is calculated based on the knowledge of the fabrication process of the device. The numerically determined value follows the procedure described above.




Figure 2. Comparison of calculated gate inductance as determined by different methods.

The series parasitic values are plotted as a function of frequency in figure 3. As is shown in figures 2 and 3, the value L_g , when calculated using this technique, does not show a frequency dependence, which is consistent with a linear equivalent circuit model.




Figure 3. Extracted parasitic inductances plotted versus frequency.

The extracted values were used in the model shown previously to reproduce the S-parameters. The parasitic shunt capacitances were embedded. The modeled S-parameters are compared to the measured S-parameters of the forward-biased device and close agreement is observed, as shown in figure 4.




Figure 4. Modeled S-parameters compared with measured values (a) measured and modeled S-parameters plotted on the Smith chart, (b) measure and modeled S_{11} plotted on the Smith chart, and (c) magnitude (dB) for S_{11} and S_{22} from 10 to 50 GHz.

The new technique has a number of advantages:

1. The calculated value of L_g does not show the frequency dependence that is observed when L_g is determined by the other methods. This is more consistent with the linear model of the inductor when used in the equivalent circuit model.

2. This method determines the gate inductance based on the frequency response of the z -parameter and does not require any special information about the device or additional measurement to determine C_{gs} .
 3. The lack of frequency dependence in the calculated value of L_g results in a measurement that can be performed at lower frequencies without the requirement for a Q band vector network analyzer (VNA). This reduces the capital requirements to perform the measurement.
 4. This method can be applied generally to any series resistor, inductor, and capacitor circuit. The example provided demonstrates the usefulness when extracting parasitics from GaN HEMTs, but the method described could be applied to any unknown series RLC circuit.
-

4. Conclusion

A method of determining the residual capacitance as a necessary step to calculating the series parasitic elements was examined. A new method for determining the residual gate capacitance based on the frequency dependence of the impedance is being used at ARL. The value for C_{gs} was used to calculate a series gate inductance that does not depend on frequency. The results of the model reproduced from the equivalent circuit model agree well with the measured data. The method described can be applied generally to determine the component values for a RLC, for which the impedance parameters are known or can be determined.

5. References

1. Darwish, A. M.; Boutros, K.; Luo, B.; Huebschman, B. D.; Viveiros, E.; Hung, H. A. AlGaIn/GaN Ka-Band 5-W MMIC Amplifier. *IEEE Trans. On Microwave Theory and Tech.* **2006**, 54 (12), 4456–4463.
2. Darwish, A. M.; Boutros, K.; Luo, B.; Huebschman, B. D.; Viveiros, E.; Hung, H. A. 4-watt Ka-band AlGaIn/GaN Power Amplifier MMIC. *in Proc. IEEE MTT-S Int.Microw. Symp. Dig.*, June 2006, 730–733.
3. Mishra, U. K.; Shen Likun; Kazior, T. E.; Yi-Feng Wu. GaN-based RF Power Devices and Amplifiers. *Proc. of the IEEE* **Feb. 2008**, 96 (2), 287–305.
4. Shealy, J. R.; Wang, J.; Brown, R. Methodology for Small-signal Model Extraction of AlGaIn HEMTs. *IEEE Trans. Electron Devices* **July 2008**, 55 (7), 1603–1613.
5. Chigaeva, E.; Walthes, W.; Wiegner, D.; Grözing, M.; Schaich, F.; Wieser, N.; Berroth, M. Determination of Small-signal Parameters of GaN-based HEMTs. *in Proc. IEEE/Cornell Conf. High Performance Devices*, 2000, 115–122.

No. of Copies	Organization
1 ELEC	ADMNSTR DEFNS TECHL INFO CTR ATTN DTIC OCP 8725 JOHN J KINGMAN RD STE 0944 FT BELVOIR VA 22060-6218
1 CD	OFC OF THE SECY OF DEFNS ATTN ODDRE (R&AT) THE PENTAGON WASHINGTON DC 20301-3080
1	US ARMY INFO SYS ENGRG CMND ATTN AMSEL IE TD A RIVERA FT HUACHUCA AZ 85613-5300
1	COMMANDER US ARMY RDECOM ATTN AMSRD AMR W C MCCORKLE 5400 FOWLER RD REDSTONE ARSENAL AL 35898-5000
1	US ARMY RSRCH LAB ATTN RDRL CIM G T LANDFRIED BLDG 4600 ABERDEEN PROVING GROUND MD 21005-5066
11	US ARMY RSRCH LAB ATTN IMNE ALC HRR MAIL & RECORDS MGMT ATTN RDRL CIM L TECHL LIB ATTN RDRL CIM P TECHL PUB ATTN RDRL SER E B HUEBSCHMAN ATTN RDRL SER E P SHAH ATTN RDRL SER E T FARMER ATTN RDRL SER E R DEL ROSARIO ATTN RDRL SER E C WAIYAKI ATTN RDRL SER E K MCKNIGHT ATTN RDRL SER E R KAUL ATTN RDRL SER E J PENN ADELPHI MD 20783-1197

Total: 16 (1 ELEC, 1 CD, 14 HCs)

INTENTIONALLY LEFT BLANK.