

AD A 039768

12

Revision
to
DNA EMP PREFERRED TEST PROCEDURES
(DNA 3286H)

February 1977

Instructions

The recipient is requested to remove the following pages
from his/her copy of DNA 3286H and add the following pages:

Remove

DD Form 1473 (Report
date September 1976)
i through ii
9 through 10
I-9 through I-12
D-1 through D-10

Add


DD Form 1473 (Report
date February 1977)
i through ii
9 through 10
15-1 through 15-40
I-9 through I-12
D-1 through D-10

AD NU.
DDC FILE COPY.

DISTRIBUTION STATEMENT A
Approved for public release
Distribution Unlimited

DDC
RECEIVED
MAY 19 1977
B

DISCLAIMER NOTICE



THIS DOCUMENT IS BEST QUALITY AVAILABLE. THE COPY FURNISHED TO DTIC CONTAINED A SIGNIFICANT NUMBER OF PAGES WHICH DO NOT REPRODUCE LEGIBLY.

UNCLASSIFIED

SECURITY CLASSIFICATION OF THIS PAGE (When Data Entered)

REPORT DOCUMENTATION PAGE		READ INSTRUCTIONS BEFORE COMPLETING FORM
1. REPORT NUMBER DNA 3286H-	2. GOVT ACCESSION NO.	3. RECIPIENT'S CATALOG NUMBER
4. TITLE AND SUBTITLE EMP PREFERRED TEST PROCEDURES (Selected Electronic Parts)		5. TYPE OF REPORT & PERIOD COVERED Handbook
6. AUTHOR J.E. Bridges W.C. Emberson V.P. Nanda W.C. Wells L.B. Townsend M.B. Gagner L.C. Peach P.L.E. Uslenghi		7. PERFORMING ORG. REPORT NUMBER IITRI Projs. E6230, E6261; 8. CONTRACT OR GRANT NUMBER DNA 001-72-C-0089 DNA 001-73-C-0149 DNA 001-75-C-0201
9. PERFORMING ORGANIZATION NAME AND ADDRESS IIT Research Institute 10 West 35th Street Chicago, Illinois 60616		10. PROGRAM ELEMENT PROJECT TASK AREA & WORK UNIT NUMBERS NWED Subtasks K99QAXEB097-07 and R99QAXEB097-51
11. CONTROLLING OFFICE NAME AND ADDRESS Director Defense Nuclear Agency Washington, D.C. 20305		12. REPORT DATE Feb 1977
14. MONITORING AGENCY NAME & ADDRESS (if different from Controlling Office)		13. NUMBER OF PAGES 602
15. SECURITY CLASS. of this report UNCLASSIFIED		15a. DECLASSIFICATION DOWNGRADING SCHEDULE
16. DISTRIBUTION STATEMENT of this Report Approved for public release; distribution unlimited.		
17. DISTRIBUTION STATEMENT of the abstract entered in Block 20, if different from Report Review of this material does not imply Department of Defense indorsement of factual accuracy or opinion.		
18. SUPPLEMENTARY NOTES This work sponsored by the Defense Nuclear Agency under Subtasks NWED K99QAXEB09707 and NWED R99QAXEB09751. Destroy this report when it is no longer needed. Do not return to sender.		
19. KEY WORDS (Continue on reverse side if necessary and identify by block number) EMP Hardening EMP Specification EMP Tests EMP Current Injection EMP Hardening Component EMP Modular/Subsystem Tests EMP Surge Arresters EMP Upset/Damage EMP Filters Surge Arrester Characterization		
20. ABSTRACT (Continue on reverse side if necessary and identify by block number) EMP preferred test procedures are provided to evaluate and characterize the performance of: 1) filters 6) shielded enclosures 2) surge arresters 7) conduit systems 3) gaskets 8) transformers and inductors 4) vents 9) resistors 5) coaxial cables & connectors		

UNCLASSIFIED

SECURITY CLASSIFICATION OF THIS PAGE (When Data Entered)

6. PERFORMING ORG. REPORT NUMBER (Continued)

and E6323

19. KEY WORDS (Continued)

Filter Characterization

EM Gaskets

EM Vents

Coaxial Cable Shields

Shielded Coaxial Connectors

Shielded Enclosures

Shielded Rooms

Conduits

Resistor Damage

Capacitor Damage

Inductor Damage

Transformer Damage

Resistor Characterization

Inductor Characterization

Surge Arrester Damage

Filter Damage

Gasket Shielding Characterization

Surface Transfer Impedance

Surface Transfer Admittance

E-Field Shielding

Effectiveness

H-Field Shielding

Effectiveness

Conduit Couplers

Capacitor Characterization

Transformer Characterization

20. ABSTRACT (Continued)

10) capacitors

11) electronic modules

12) computers

13) analog modules

Topics covered are experiment design, documentation, typical induced EMP transients, current injection testing, and the specific test procedures to evaluate the EMP behavior for each type of electronic component.

NTIS	White Section	☒
DDC	Buff Section	☐
UNANNOUNCED		☐
JUSTIFICATION		
BY		
1. SUBJECT, AVAILABILITY CODES		
2. AVAIL. Subj. SPECIAL		
A		

UNCLASSIFIED

SECURITY CLASSIFICATION OF THIS PAGE (When Data Entered)

SUMMARY

IIT Research Institute, under contract to the Defense Nuclear Agency. (DNA001-72-C-0084, DNA001-73-C-0149 and DNA001-75-C-0201), has developed EMP PREFERRED TEST PROCEDURES for selected electronic components. This is part of a continuing program to formulate and recommend procedures by which EMP test data may be obtained and reported.

In this connection, it is important to realize what these preferred procedures are and what they are not. They are a formal recognition of good practices and methods based on sound physical principles which can lead to useful EMP data. They provide a means of communicating useful information among workers in a large multidisciplined technology.

These preferred procedures are not necessarily cook-book simplifications and are not intended to be a "MIL-SPEC" or a panacea for designers of hardened systems. The EMP PREFERRED TEST PROCEDURES require some experience and intelligence on the part of the experimenter. These are somewhat different than "MIL-SPEC" testing which can usually be implemented by a responsible technician. The procedures emphasize the electrical test aspects. Some general guidance as to limits and other environmental aspects is provided; however, these are more properly considered in terms of the requirements for a specific system, such as design specifications. The procedures are designed to employ readily available or easily constructed laboratory equipment--generally operating below 100,000 volts and 100 MHz--and to be conducted in ordinary room-size laboratory space.

The material contained in this document is considered the best available and, where possible, it represents a consensus of recognized practices. Based on discussions with prominent members of the EMP community as well as other experts, preliminary outlines of the procedures were devised and actual tests conducted to validate the procedures. A draft of the procedures was then circulated among cognizant professionals in a number of organizations, and revised as needed to

harmonize various viewpoints. While the results in this document are based on the experience of a number of active recognized professionals, it must be noted that all possible situations could not be considered. Clearly, it is not the intent of this document to impose "National EMP Standards and Limits." Even if these were desirable, it would not be appropriate to do so today because of the rapid changes taking place in the state-of-the-art. In this regard, it is important that others take an active part in supplying additional information to effect improvements.

Much of the work presented in the first three sections in this edition of the EMP PREFERRED TEST PROCEDURES was summarized directly from DNA Document 2028H, entitled "TREE Preferred Procedures." IIT Research Institute, therefore, gratefully acknowledges the efforts of Mr. Richard H. Thatcher and Mr. Michael L. Green at the Battelle-Columbus Laboratories for their efforts on DNA 2028H.

Discussions were also held with staff members of a number of organizations in EMP hardening. All organizations cannot be acknowledged, but include U.S. Army Electronics Command, Picatinny Arsenal, Naval Surface Weapons Center, Harry Diamond Laboratories, Defense Civil Protection Agency, Construction Engineering Research Laboratory, Boeing Aircraft Corporation, Lockheed Corporation, International Rockwell, General Semiconductor Industries, Siemens Corporation, Signalite, Joslyn Electronic Systems, Electro-Data Technology, Sandia Laboratory, and Stanford Research Institute.

The principle contributors to this document are Mr. J. E. Bridges, Mr. W. C. Emberson, Mr. V. P. Nanda, Dr. L. C. Peach, Mr. L. B. Townsend, Dr. P. L. E. Uslenghi, Dr. W. C. Wells and Mr. M. B. Gagner. Major W. Adams, Major W. Dean and Captain W. D. Wilson of DNA provided overall program review. The technical management was provided by Mr. I. N. Mindel and Dr. E. W. Weber. Much of the laboratory work was conducted by Mr. S. Smandra, Dr. J. Herro and Dr. Y. Shiau.

TABLE OF CONTENTS (Continued)

<u>Section</u>	<u>Page</u>
14.4.2 Equipment	14-23
14.4.3 Measurement Procedure	14-25
14.4.4 Data Format	14-25
14.5 Stand Off Voltage Test Procedure	14-29
14.5.1 Scope	14-29
14.5.2 Equipment	14-29
14.5.3 Test Fixture	14-31
14.5.4 Precautions	14-34
14.5.5 Measurement Procedure	14-34
14.5.6 Sample Data and Data Format	14-36
14.6 References	14-39
15. TEST PROCEDURES FOR CURRENT INJECTION FOR ELECTRONIC MODULES	15-3
15.1 Introduction	15-3
15.1.1 Purpose	15-3
15.1.2 Scope	15-3
15.2 Module Testing to EMP Specifications	15-5
15.2.1 Applicability	15-5
15.2.2 Direct Pulse Injection Test Procedure	15-6
15.2.2.1 Scope	15-6
15.2.2.2 Test Equipment and Setup	15-6
15.2.2.3 Precautions	15-10
15.2.2.4 Data Format	15-12
15.3 Module Testing Without Specification	15-13
15.3.1 Applicability	15-13
15.3.2 CW Test Procedure	15-15
15.3.2.1 Scope	15-15
15.3.2.2 Test Equipment	15-15
15.3.2.3 Precautions	15-18
15.3.2.4 Data Format	15-18
15.3.3 Direct Pulse Injection Test Procedure	15-18

TABLE OF CONTENTS (Continued)

<u>Section</u>	<u>Page</u>
15.4 Acceptance/System Level Testing.	15-22
15.4.1 Applicability.	15-22
15.4.2 Bulk Injection Test Procedure.	15-23
15.4.2.1 Scope	15-23
15.4.2.2 Test Equipment and Setup	15-23
15.4.2.3 Precautions.	15-26
15.4.2.4 Data Format.	15-29
15.5 Additional Considerations for Testing Digital and Special Analog Modules	15-30
15.6 References	15-39
APPENDIX A	A-1
INDEX	I-1
DISTRIBUTION LIST	D-1

15. TEST PROCEDURES FOR CURRENT INJECTION
FOR ELECTRONIC MODULES

15. TEST PROCEDURES FOR CURRENT INJECTION FOR ELECTRONIC MODULES

15.1 Introduction

15.1.1 Purpose

The purpose of this chapter is to provide a guidelines for interim preferred EMP test procedures to determine the effects of EMP induced voltage/current transients on modular equipment. No new procedures have been developed under this program and it is assumed that future work in the EMP testing area will produce new and better techniques.

Throughout, the emphasis is on simplicity and on the use of readily available laboratory instruments. A major objective in this effort has been to review and evaluate the many existing EMP test techniques and select the minimum set necessary to satisfy the needs of many different users. Thus, the procedures described here are a subset of the EMP test methods currently in use.

15.1.2 Scope

There are two major aspects to determining the effects of EMP current/voltage transients on modular equipments, i.e., (1) inducing the EMP transient, and (2) detecting/measuring the effect(s) of that transient. Since the techniques required to detect and measure these effects are determined by the function of the specific module and since this chapter is concerned with the EMP testing of modules in general, the topic of detection and measurement is beyond the scope of this chapter. Techniques for detection and measurement of the effects must be developed by an individual familiar with the function and circuitry of the specific module. Thus, this chapter is concerned only with the techniques required to produce the effects of EMP induced transients as accurately as possible.

The principal topics to be considered include the simulation of EMP waveforms, methods of introducing the simulated pulses

into the module, techniques for terminating cables connected to the modules and means of synchronizing the pulse delivery with operation of a multi-state unit under test.

The many techniques currently in use have been surveyed through discussion with a number of companies currently involved in EMP testing and evaluated by running a battery of tests on each of three representative modules.

As many test techniques as possible have been examined.* Two methods have been used to introduce the EMP:

- Bulk-current injection
- Direct (pin-to-case) injection.

In the direct injection method several different waveshapes were utilized:

- $\pm$ square pulses
- CW RF
- Damped RF sinusoids (Figure 15.2B)
- RF burst (Figure 15.3B).

The representative modules used to evaluate the EMP test techniques were:

- A Nova 1220 minicomputer
- A HP-462 broadband RF preamplifier
- A HP-6429 dc power supply.

These units represent digital, in-EMP-band analog, and out-of-EMP band analog equipment, respectively. For digital equipment, various terminal conditions, such as high impedance versus low impedance, were investigated.

* Free field EMP pickup tests have not been considered, as such tests are a measure of the quality of the enclosure rather than the module. Enclosure testing is covered in Chapter 10.

15.2 Module Testing to EMP Specifications

15.2.1 Applicability

This type of testing is applicable to testing programs with any of the following objectives:

- Verifying the hardness of each module terminal to a specified EMP.
- Providing data for hardening design/redesign.
- Providing data to identify failures within the module due to a specified EMP.
- Verifying overall module hardness to a specified EMP (i.e., system level testing) when the methods of Section 15.4 are not practical.

At present, module testing to EMP specification is the principal type of EMP testing being done. The magnitudes and spectral contents of the injected signals are specified by the Program Office for the system in which the module is being utilized. Generally, the specifications take one of two formats:

- Pin-to-case voltage/current specification
- Bulk current specification.

The Direct Pulse Injection test, Section 15.2.2 shall be used for this type of testing. Pin-to-case injection is recommended. Thus, pin-to-case specifications automatically describe the required frequencies and amplitudes for the test pulses.

Bulk current specifications, however, require conversion to a pin-to-case format. For high impedance terminations, it has been shown¹ that a good rule of thumb for determining worst case terminal voltages, given a bulk current, is to multiply the specified bulk current by 100 V/A, i.e., given a bulk current of 3 amperes, the voltage appearing between the module terminals and the case will be 300 volts or less. For low impedance terminations (where impedance $\approx 100\Omega$), current becomes the limiting factor such that the pulse current shall not exceed the specified bulk current. Thus, for the

example 3 ampere bulk current, the simulated EMP pulses are to be limited to 300 volts or 3 amperes, whichever occurs first.

For balanced inputs/outputs, pin-to-pin injection shall also be utilized. However, maximum pin-to-pin pulse voltage shall be reduced to 20 dB below the maximum pin-to-case voltage determined above. Every pin should be tested except in cases of extreme redundancy, such as a computer data bus. In such cases, it is necessary to test only two or three lines to insure that the effects are the same for all.

15.2.2 Direct Pulse Injection Test Procedures

15.2.2.1 Scope

Direct pulse injection tests are used to determine the effects of EMP transients on electronic modules at a fairly detailed level (i.e., for each terminal).

As discussed in the Introduction, this chapter is concerned primarily with providing techniques for simulating EMP transients and for introducing these transients into the module in a fashion that will duplicate the effects of an actual EMP as accurately as possible. Methods for detecting and measuring these effects are discussed only in the general case.

15.2.2.2 Test Equipment and Setup

Figure 15.1 illustrates the basic test setup for generating and introducing simulated EMP transients onto the terminals of a module.

A signal source, which is discussed in greater detail below, is used to produce the desired transient waveshape. This signal is amplified to the required level by a broadband RF power amplifier. This amplifier should have a power rating of at least 100 watts and a frequency range of approximately 10 kHz to 200 MHz. The IFI 402 is an example of such an amplifier.

The output of the amplifier is the simulated EMP which is coupled to the terminal of interest. This simulated EMP may




Fig. 15.1 BASIC DIRECT INJECTION TEST SETUP

be coupled onto the terminal capacitively as shown in Figure 15.1, inductively (i.e., with a current transformer) or directly.

The module is to be tested in an operational state, i.e., energized and functioning. Thus, it is necessary to terminate the cable from the unit under test. Ideally, the actual unit(s) that would terminate the cable in a real system should be used as the load. In reality, this is often impossible since the actual load units may be unknown, unavailable or sensitive to EMP transients. In such cases it is necessary to simulate the actual or anticipated load impedances, voltage levels, control signals, etc., to the unit under test. Load impedances generally may be simulated with simple RC networks. The simulation of voltage levels or control signals, however, requires the attention of someone familiar with the unit under test.

A dual beam oscilloscope should be used to monitor the transient voltage and current on the terminal being tested.

Figure 15.2A illustrates the equipment setup for generating damped RF sinusoids. A typical waveform and its associated spectral distribution are shown in Figures 15.2B and 15.2C, respectively. This waveform may be used for damage or upset testing.

An RF generator, such as the HP8601A, is used to provide CW RF. This unit is set to the desired test frequency.

For upset testing, the RF (AUX in Figure 15.2A) may be used to trigger the pulser; however, it is necessary to use some timing or counting circuits (shown as optional trigger) so that the EMP transients will be generated at a low duty cycle. A repetition rate of 1 kHz is suitable.

Alternately, the pulser may be free running at a repetition rate of 1 kHz. This method is simpler but does not synchronize the pulser (i.e., the double exponential envelope) with the RF.

For damage testing, the pulser should be operated single shot.




Fig. 15.2A TYPICAL TEST SETUP FOR GENERATING DAMPED SINUSOIDS




Fig. 15 2B DAMPED SINUSOID WAVEFORM



Fig 15 2C DAMPED SINUSOID SPECTRUM

A pulser with a rise time of less than two (2) nanoseconds shall be used, e.g., the HP215A. The pulsewidth is set equal to the rise time of the desired double exponential envelope. For general testing, this shall be 10 ns as shown in the figure.

This pulse is then passed through a simple pulse-shaping network to obtain the double exponential envelope. The capacitor shall be chosen to provide an RC time constant that reduces the amplitude of the damped sinusoid to 50% of its peak amplitude within 5 to 10 cycles of RF. The diode shall be a high speed device such as an HP hot carrier diode.

The envelope pulse is amplified and inverted with a broadband RF preamplifier, such as the HP462A.

Finally, a double-balanced mixer, such as the Minicircuits DAY-1, is used as a modulator, thus providing damped RF sinusoids at its output.

Figure 15.3A illustrates the test setup for generating RF bursts. Figures 15.3B and 15.3C illustrate a typical waveform and spectral distribution, respectively. This waveform is simpler to generate and is suitable for upset testing. It is not preferred for damage testing, however, as this waveform contains more energy for a given amplitude than does the more realistic damped sinusoid waveform.

In this setup the RF generator, optional trigger and double-balanced mixer are used in the same manner as previously discussed. The main difference is that the output of the pulser is used directly to modulate the RF. The pulse amplitude is to be approximately 1 volt and the pulse duration shall be between 5 and 10 RF cycles. As in the previous setup, a low duty cycle is recommended. Hence, a repetition rate of 1 kHz should be used.

15.2.2.3 Precautions

Double-balanced mixers are linear only over a small range of input amplitudes. Thus, the envelope of the damped sinusoid




Fig. 15.3A TYPICAL TEST SET-UP FOR GENERATING RF BURSTS




Fig. 15.3B RF BURST WAVEFORM




Fig. 15.3C RF BURST SPECTRUM

output will not be identical to the modulating envelope. Prior to the start of testing it will be necessary to adjust the amplitude and duration of the modulating envelope in order to achieve the desired output.

Some portion of the simulated EMP current will flow toward the load rather than toward the unit under test. In general, the load impedance and the cable impedance will not be matched, so reflections will occur. Thus, in order to avoid misinterpretation of the signal observed at the module terminal, it is important that the test system be configured in a manner that takes these reflections into account. This may be accomplished by making the cable very long so that the reflections do not return during the time the terminal is being observed, or by making the cable very short so that the reflected and direct signals are very nearly coincident. Since it is convenient to be able to view the unit under test-cable-load as a lumped parameter system, the short cable approach is preferred. Thus, to insure that the round trip transit time on the cable is short compared to the 10 ns EMP rise time, the cable length should be limited to two feet.

Ground loops must be avoided. One source of trouble is grounding via instrument power line cords, particularly if the unit under test is powered by ac. To avoid such loops, the chassis grounds for both the instruments and the unit under test should be floating from ac ground.

15.2.2.4 Data Format

There are basically two types of raw data to be recorded. One is data describing the EMP transient introduced into the terminal. The voltage at and current into the terminal are to be recorded. Polaroid pictures of the oscilloscope display will be suitable. The second type of data is that which describes the effects of the EMP transient. The test engineer must be responsible for determining the most suitable means of recording this information since the test engineer is the one who defines what effects are to be measured.

This data shall be reduced to a meaningful format, preferably graphical. Generally, it is best to graph the minimum transient voltage/current/power/energy versus the log of frequency required to produce a given effect. For example, Figure 15.4 illustrates the minimum voltage required to upset a digital integrated circuit versus the log of frequency. This example is for a qualitative effect (i.e., either upset or not upset). Quantitative effects (i.e., percent distortion, energy of spurious output, etc.) should be presented as a family of curves; each curve for a different amplitude or degree of effect.

When testing to a given specification, it is possible that specification-level pulses will produce no significant effects for some or all of the terminals (i.e., some or all of the terminals are not susceptible to the given EMP). This information should be presented in a tabular format with appropriate raw data appended.

15.3 Module Testing Without Specification

15.3.1 Applicability

The purpose of this type of testing is to assess the overall hardness of a module to cable-coupled EMP transients, as opposed to the tests in the previous section which are designed to validate a particular module to a given specification. This type of testing is applicable to testing programs with any of the following objectives:

- Providing EMP hardness data for comparing competitive modules;
- Providing data for the design of terminal protection;
- Determining EMP "safety margins" provided by terminal protection.

It is recommended that both the CW Test and the Direct Pulse Injection Test be performed.




Fig. 15.4 EXAMPLE DATA FORMAT FOR DIRECT INJECTION TESTING

The CW Test is not an EMP test. Rather, it is used to measure the input impedance of each pin versus frequency, and to measure terminal-to-terminal transfer functions as necessary. The data from these measurements will be used by the test engineer to aid in selecting test frequencies for the direct pulse injection test, i.e., the CW test determines critical test frequencies such as minimum impedance points, maximum impedance points and resonance points.

For both of these tests, pin-to-case injection is recommended. In the case of differential signals, pin-to-pin injection shall also be used. Every pin should be tested except in cases of extreme redundancy, such as a computer data bus. In such cases it is necessary to test only two or three lines to insure that the effects are the same for all.

15.3.2 CW Test Procedure

15.3.2.1 Scope

CW tests are used to measure the impedance versus frequency of the module terminals and to measure the transfer function between two terminals versus frequency. The results of these tests are useful for selecting test frequencies for direct injection testing of EMP transients.

15.3.2.2 Test Equipment

Figure 15.5 illustrates the test setup for measuring the terminal impedance versus frequency. This requires a swept frequency generator and a network analyzer such as the Hewlett-Packard 8601A and 8407A, respectively. The current probe is connected to the reference channel and the voltage probe to the test channel. Connected in this fashion, the network analyzer subtracts the logarithm of the terminal current from the log of the terminal voltage and displays the log of the terminal impedance. Some units, such as the 8407A, also display phase.

Figure 15.6 is an example of a test setup to measure the transfer function between two terminals. In this case, a power splitter is required to obtain the reference signal.




Fig. 15.5 SWEPT FREQUENCY TERMINAL IMPEDANCE MEASUREMENT TEST SET-UP




Fig. 15.6 SWEPT FREQUENCY TRANSFER FUNCTION MEASUREMENT TEST SET-UP

15.3.2.3 Precautions

The test equipment must be calibrated. The basic calibration is to replace the unit under test with a 50 Ω termination as shown in Figure 15.7. The network analyzer is then adjusted to read 50 Ω and 0° of phase angle at low frequencies. The response should be flat over the full working range of frequency. Where this is not the case, simple corrections can be applied to the recorded data.

The input impedance of the terminals is to be measured both with the module energized and turned off. When energized, it will be necessary to provide dc blocking capacitors if dc is present on the terminal. The impedance of digital output circuits should be plotted in both the high and low states.

15.3.2.4 Data Format

The basic data to be recorded are the magnitude and phase of the terminal impedance, Z_T , as a function of frequency. Measurements should be made over a three decade frequency range from 100 kHz to 100 MHz. Polaroid pictures of the network analyzer display will be suitable. Figure 15.8 shows the magnitude and phase of the terminal impedance for the output terminal of the HP462A amplifier. Note the spaces provided to identify the unit under test, test setup, terminal and test conditions. In this case, the test was performed with power on, as indicated in the figure.

Not all terminals have impedances as well behaved as are those of the HP462A. Figure 15.9 shows the terminal impedance of a digital output driver in its low state. Note the resonance points, especially the sharp dip at 2 MHz. When present, such resonance points should be noted for future use as they will be specifically selected as test points in the direct injection test.

15.3.3 Direct Pulse Injection Test Procedure

This test is the same as that of Section 15.2.2. The only




Fig. 15.7 CALIBRATION OF SWEPT FREQUENCY SYSTEM




Figure 10-10



Figure 10-11

Figure 10-12

NOTE: When the signal is
terminated, the signal is
not present.


Bright trace

Display key: 1000
Amplitude: 1000


Dim trace

Pulse trace: 1000
Phase: 1000

NOTE: Gain control - 1000



0.1 to 1.1 MHz



1.0 to 11.7 MHz

Figure 1.9

DATE OCT 10 1963
 TIME 10:00
 TERMINAL 10
 DISPLAY REF 1000000000
 AMPLITUDE 1000000000
 DIM TRACE
 PHASE OFFSET 0.000000
 PHASE 0.000000
 NOTE POWER 10



1.0 to 11.7 MHz

difference is in the selection of test pulse frequencies and amplitudes.

For module testing without a specification, the Direct Pulse Injection Test shall be executed at a minimum of 12 frequencies, i.e., four test frequencies per decade between 100 kHz and 100 MHz. The resonance points determined by the CW test shall be among these frequencies.

Test pulse amplitudes should range from a level which causes no significant effects to the level that causes module destruction.

15.4 Acceptance/System Level Testing

15.4.1 Applicability

The purpose of this type of test is to verify the overall hardness of a module or a modular system to a specified EMP. While it would be ideal to expose the entire system to a free field, threat level EMP simulator to perform this type of test, such an approach is not always practical or feasible, nor is such a simulator always readily available to the test engineer.

In such cases it is recommended that the Bulk Injection Test be utilized. Typical applications of this test include:

- Quality assurance testing of modules;
- Field testing;
- Testing interfaces between systems, i.e., umbilical between aircraft and aircraft carrier;
- System acceptance testing when use of free field simulators is not practical.

This type of testing (simulator or bulk injection) is very popular, as it provides for current distribution within the system, reflections at interfaces and possible synergistic effects due to simultaneous pulses arriving on several pins. Such testing is intended as a benchmark, a final verification

to account for effects not easily simulated by other methods. Since system configurations are changed with time, an overall testing program should utilize this type of test in addition to and not in place of the more detailed tests discussed earlier.

15.4.2 Bulk Injection Test Procedure

15.4.2.1 Scope

Bulk injection tests are used to determine the gross effects of EMP transients on electronic modules or entire systems, by injecting a specified bulk current on the interconnecting cable(s). This current distributes among the individual conductors according to the impedances which terminate the conductors. Thus, every pin in the associated interface is tested simultaneously. If data is required for individual pins, it is recommended that the direct injection test, Section 15.2, be used.

15.4.2.2 Test Equipment and Setup

In bulk injection testing, there are two techniques for coupling the simulated EMP to the interconnecting cable(s), i.e., inductive and capacitive. Both of these techniques provide loose coupling between the pulser and the unit under test, and therefore do not alter the normal operation of the unit under test. In either case, it is recommended that the damped RF sinusoid waveshape be used for simulating the EMP. The magnitudes and frequencies for the bulk current transients are to be specified by the Program Office for the system in which the module is being used.

For laboratory testing, either coupling technique is suitable. For in-situ testing on actual systems, however, inductive coupling is preferred due to the relatively small size of the coupling transformer and because these transformers may be clamped around the cable being tested without disconnecting the cable. Figure 15.10 illustrates the typical test setup for performing bulk injection with inductive coupling.




Fig. 15.10 BULK INJECTION TEST SETUP WITH INDUCTIVE COUPLING

This technique utilizes a current transformer to couple energy from the pulser to the cable. These transformers must be carefully designed to deliver the required current without going into saturation.

Because of the loose coupling technique being utilized, the pulser must be capable of generating damped RF sinusoid pulses at very high power levels. These pulses may be generated by the same method described in Section 15.2.2.2. To achieve the desired bulk current, however, the power requirement on the broadband RF amplifier will generally be in excess of 1 kw. Alternately, a high voltage capacitive discharge type pulser may be used.

The current at the terminal of interest should be monitored with an oscilloscope. A broadband current probe, such as the Stoddart 91550-1, will be required.

The module is to be tested in an operational state, i.e., energized and functioning. Thus, it is necessary to terminate the cable from the unit under test. This termination is also required to insure that the bulk current distributes correctly among the cable conductors. Ideally, the actual unit(s) that would terminate the cable in a real system should be used as the load. This generally is possible when performing in-situ tests on a real system, but is often impossible when performing laboratory tests, since the actual load units may be unknown, unavailable or sensitive to EMP. In such cases, it is necessary to simulate the actual or anticipated load impedances, voltage levels, control signals, etc., to the unit under test. Load impedances generally may be simulated with simple passive networks. The simulation of voltage levels or control signals, however, requires the attention of someone familiar with the unit under test.

For laboratory testing, the unit under test and the load shall be affixed to a common ground plane to provide a low impedance return for the injected current. For in-situ testing

of modules affixed to metallic structures (i.e., ships, aircraft, etc.), this is unnecessary since the structure will provide a return path.

Figure 15.11 illustrates some typical RF burst voltage and current waveforms injected on a computer data bus with the inductive coupling technique. These traces were redrawn from oscilloscope photographs to improve clarity. The waveforms appear only as envelopes in the photographs so the phase relationships in the figure may be incorrect. Note that this is not the recommended waveform for EMP testing and is used here only as an example.

Figure 15.12 illustrates a typical test setup for bulk injection with capacitive coupling. In this technique, the pipe acts as one plate of a capacitor and the cable conductors form the other plate. The pipe should be 4 to 8 feet long and several inches in diameter.

Since the pipe over the ground plane forms a section of transmission line, the pipe must be terminated with resistor R_T to prevent ringing.

Except for the coupling technique, this test setup and the previous test setup are the same.

15.4.2.3 Precautions

Since the simulated EMP is coupled to the system via the test cables, the construction and shielding of the test cables are to be the same as the construction and shielding of the actual or anticipated system cables. Some important factors are the following:

- Are signals carried on twisted pairs or individual leads?
- What is the number of ground leads?
- Is the cable shielded?
- Is shielding braided or solid?

Input Current 1 Amp/div.


Bulk Current .1 Amp/div.

Voltage At High Impedance
Terminal 1 Volt/div.

Current At High Impedance
Terminal 10 mA/div.

Voltage At Low Impedance
Terminal 1 Volt/div.

Current At Low Impedance
Terminal .1 Amp/div.



Note: Phase Relationships May Be Incorrect

Fig. 15.11 REPRESENTATIVE BULK INJECTION WAVEFORMS




Fig. 15.12 BULK INJECTION TEST SETUP WITH CAPACITATIVE COUPLING

Improper grounding can be a source of significant errors. When performing laboratory tests it is important that the unit under test and the load be affixed to a common, low impedance ground plane. This is generally not necessary when performing in-situ tests in which case the current is allowed to return via the natural path(s).

The test engineer must be careful to insure that the instrumentation is not detecting false signals, i.e., picking up cross-talk between cables or detecting radiated energy. This is a particular problem when performing bulk testing because of the high power level being used. Often it is necessary to locate the instrumentation in a shielded enclosure to prevent radiated energy from interfering with the measurements. All cables between the instrumentation and the test setup must be well shielded or optical data links may be used.

15.4.2.4 Data Format

There are basically two types of raw data to be recorded. One is data describing the bulk current introduced into the terminal. Polaroid pictures of the oscilloscope display will be suitable. The second type of data is that which describes the effects of the EMP transient. The test engineer must be responsible for determining the most suitable means of recording this information since the test engineer is the one who defines what effects are to be measured.

This data shall be reduced to a meaningful format. Bulk injection testing is often used to perform pass/fail tests. Such information may be presented in a tabular format showing frequency, current and pass/fail for each test point. Raw data should be appended or at least retained in good order by the test engineer. Alternately, it may be necessary to provide data that indicates at what level of bulk current a particular effect occurs. This information should be reduced to a graphical format which plots the minimum bulk injection current required to produce a given effect versus the log of frequency.

For example, Figure 15.13 illustrates the minimum bulk current required to cause upset on a computer interface versus the log of frequency. This example is for a qualitative effect (i.e., either upset or not upset). Quantitative effects (i.e., percent of distortion, energy of spurious output, etc.) should be presented as a family of curves; each curve for a different amplitude or degree of effect.

15.5 Additional Considerations for Testing Digital and Special Analog Modules

Digital modules will possess some or all of the following characteristics:


- Input/output impedance which is nonlinear with input/output voltage;
- Numerous states with potentially different levels of sensitivity;
- Memory.

Some analog devices, such as FET analog switches, also possess some of these characteristics and shall be treated accordingly.

Three topics are considered in this section:

- Techniques for simulating digital loads;
- Techniques for synchronizing pulse delivery with operation of a multistate machine;
- Use of software in testing.

In both the Direct Pulse Injection Test and the Bulk Injection Test it is important that the test cables be terminated in actual or simulated loads. While actual loads are preferred, simulation is often necessary. Since digital devices exhibit different impedances in the high and low states, it is required that each terminal be tested high and low. For upset testing, the simplest approach is to construct a dummy load module utilizing switches and standard interface gates for the



Bulk Current Upset Threshold Vs. Frequency For Computer I/O Bus

Fig. 15.13 EXAMPLE DATA FORMAT FOR BULK INJECTION TESTING

appropriate logic family. Figure 15.14 illustrates this method as applied to the TTL family. If damage level testing is being done, a more durable load should be constructed from discrete components. Generally, the manufacturer's literature will provide schematics for such circuits. Figure 15.15 illustrates this approach. The devices shall be selected with breakdown voltages higher than those of the interface devices in the unit under test.

Figure 15.16 illustrates, in block form, the concept of synchronizing the pulser with operation of a multistate unit under test. For units with hard wired logic, i.e., modules which do not operate under software control, a suitable signal from the unit under test may be buffered and used to trigger the pulser. If no such signal exists, it is necessary to decode some combination of signals within the unit which define the state to be tested. Care must be taken to avoid creating a ground loop. If the control signal(s) must be carried over a distance of more than a few feet, an optical fiber link is recommended.

When testing computers, i.e., modules which operate under software control, many additional tests are available.

Two unique methods of triggering the pulser are available. One is to utilize an idle interface to control triggering the pulser. An output instruction, directed to the unused terminal, will trigger the pulser. This allows complete program control over delivery of the simulated EMP. This approach is similar to that described in Figure 15.16, and is used in the program segment in Figure 15.17. Alternately, an advanced trigger from the pulser can be used to interrupt the computer and cause it to branch to the appropriate test routine. Naturally this latter technique applies only to computer with interrupt handling features. For single shot testing, either method is equally applicable.

For upset testing, however, the former method is more




Fig. 15.14 TYPICAL SIMULATED DIGITAL LOAD FOR UPSET TESTING




Fig. 15 15 TYPICAL SIMULATED DIGITAL LOAD FOR DAMAGE TESTING




Fig. 15.16 SYNCHRONIZING PULSER WITH OPERATION OF MULTISTATE MODULE

0001 .MAIN
005000

6663 207

:TELETYPE TEST ROUTINE

STAT: 10051

```

SUBC 2.2      :CLEAR ACC
LDA 0,EXC    :LOAD CODE INTO ACC
TST:         :CLEAR A13
STA 3,STF    :CLEAR TEST POINTER
NOP 5E       :SEND TRIGGER PULSE

```

First Emp Is Triggered Here
... And Arrives Here

:LONGER READING:
 :NO. WAIT UNTIL DONE

Check For Upset

Second Emp Is Triggered Here
... And Arrives Here

Check For Upset:

Third Emp Is Triggered Here
And Arrives Here.

Check For Upset.

```
050327 230453      CHECKS GOOD...NEXT CHAR AFTER  
LDA     2.2       :LOAD Z INTO ACC  
SUB     2.2-ONE   :SUBTRACT IF CHAR NOT Z  
JMP     DONE      :CHAR=Z...TEST COMPLETE  
INC     2.0       :FORM NEXT CHAR IN SEQUENCE  
JMP     TST1      :...AND START OVER  
LDA     1.PASSX   :LOAD AC1 WITH MSG ADDRESS...  
JSR     MSG        :...GO TO OUTPUT SUBROUTINE  
         :...END OF MESSAGE  
         :...MESSAGE REPAIRED
```

Fig 15 17 SAMPLE PROGRAM SEGMENT FOR EMP TESTING OF COMPUTER

suitable. Since the pulser is under program control, a series of pulses can be utilized with the computer halting only when an upset condition is detected. The test may then be repeated at the upset level on a single shot basis and the waveforms recorded. This approach will save a significant amount of time over a strictly single shot method.

In either case, diagnostic software should be utilized to detect and perhaps isolate the upset or damage. Such programs are constructed using instructions which exercise the circuitry or operation under investigation. The program segment in Figure 15.17 is an example which illustrates the basic approach to diagnostic testing. The instruction "NIOP 52" generates an output signal to trigger the pulser as discussed above. Thus, the simulated EMP will always occur during the instruction immediately following the NIOP 52. In this example, we are testing the instructions at locations 5006, 5020, and 5024 which are input from teletype, load memory from register and load register from memory respectively. The data input/loaded is always predefined and after each EMP the register or memory location under consideration is checked. If the contents are not correct, an error message is output to the display, otherwise the test is repeated. After approximately 50 repetitions, the computer will output a pass message and halt, allowing the technician to increase power, change frequency, etc., before resuming the test.

The example tests only three of the computer's instructions. Figure 15.18 illustrates the timing of the three trigger pulses generated by the program. In an actual program, however, it will be necessary to test many different instructions such that a reasonable cross-section of the computer's possible states are examined.

Simulated EMP

Timing Pulse
From Computer




Fig. 15.18 EXAMPLE OF TIMING FOR SYNCHRONIZED PULSING

15.6 References

W. E. Boettcher, et al., Electromagnetic Pulse Handbook for Missiles and Aircraft in Flight, (Albuquerque, New Mexico: Sandia Laboratories, 1972). pp. 271-276. (SC-M-710346)

INDEX (Continued)

	Page
Test Procedures for Conduit and Couplings	
Frequency Domain Test Procedure	11-31
Data Format	11-33
Precautions	11-33
Scope	11-31
Test Fixture and Equipment	11-31
General	11-5
Characterization of Conduit Shielding	11-8
Definitions of Fundamental Shield	
Transfer Functions	11-5
Performance Criteria	11-9
Types of Tests	11-13
Introduction	11-3
Time Domain Test Procedures	11-15
Data Format	11-22
Precautions	11-21
Scope	11-15
Test Fixture and Equipment	11-15
Test Procedures for Current Injection for Electronic Modules	
Acceptance/System Level Testing	15-22
Applicability	15-22
Bulk Injection Test Procedure	15-23
Data Format	15-29
Precautions	15-26
Scope	15-23
Test and Equipment	15-23
Additional Considerations for Testing Digital and Special Analog Modules	15-30
Introduction	15-3
Purpose	15-3
Scope	15-3
Module Testing to EMP Specifications	15-5
Applicability	15-5
Data Format	15-12
Direct Pulse Injection Test Procedure	15-6
Precautions	15-10
Scope	15-6
Test Equipment and Setup	15-6
Module Testing Without Specification	15-13
Applicability	15-13
CW Test Procedure	15-15
Data Format	15-18
Direct Pulse Injection Test Procedure	15-18
Precautions	15-18

INDEX (Continued)

	Page
Scope	15-15
Test Equipment	15-15
References	15-39
Test Procedures for EM Gaskets	
CW/Swept Frequency Test Procedure	7-29
Data Format	7-31
Measurement Precautions	7-31
Scope	7-29
Test Fixture	7-29
Test Setup	7-29
EM Gaskets	7-5
Characteristics of EM Penetration at	
EM Gaskets	7-6
Consideration in Testing Shielding Performance	
of Gaskets	7-13
Gasket Shielding Performance Measures	7-9
General Characteristic of EM Gaskets	7-5
Introduction	7-3
Test Procedures for EM Gaskets	7-3
Transient Test Procedures	7-17
Data Format	7-24
Measurement Precautions	7-22
Scope	7-17
Test Fixture	7-17
Test Setup	7-22
Test Procedures for EM Vent Shields	
CW/Test Procedures	8-33
Data Format	8-35
Measurement Equipment	8-33
Measurement Precautions	8-34
Scope	8-33
Sensor Characterization	8-34
Test Fixture	8-33
General	8-5
Characteristics of Vents and Screens	8-5
Construction of Vents and Screens	8-5
Definitions	8-13
Equivalent Dipole Model	8-15
Performance	8-7
Types of Tests	8-17
Introduction	8-3
Test Procedures for EM Vent Shields	8-3
Transient Test Procedure	8-19
Data Format	8-29

INDEX (Continued)

	<u>Page</u>
Field Sensor Characterization.	8-27
Measurement Equipment.	8-22
Measurement Precautions.	8-28
Scope.	8-19
Suggested Test Fixture	8-19
Transient Response Measurements, Protective Devices.	5-25
Transitional Point	5-7
Uniform Test Procedure for Shielded Enclosures	
General Background.	10-5
Characteristics.	10-5
Definitions	10-8
Performance Criteria	10-6
Type of Tests.	10-9
Introduction.	10-3
Large Loop Test	10-15
Basic Measurement Procedure.	10-19
Data Reporting and Reduction	10-20
Detector	10-18
Preliminary Procedures and Precautions	10-18
Simulation of the Field in Absence of Enclosure	10-19
Source of Magnetic Field	10-15
Test Equipment and Setup	10-15
Small Loop Test	
Data Reduction	10-26
Detector	10-21
Introduction	10-21
Measurement Precautions.	10-21
Measurement Procedure.	10-23
Simulation of the Field in Absence of Enclosure	10-25
Source of Magnetic Field	10-21
UHF Test Procedure	10-33
Detector	10-33
Introduction	10-33
Measurement Procedure.	10-37
Precautions.	10-36
Simulation of the Free Field in Absence of Enclosure	10-38
Source of UHF Electromagnetic.	10-33
Useful Scattering Relationships.	6-29
Varistors, Standard Steady State Calibration Circuit for	5-17
V _C , Typical Circuit for Measuring.	5-37
V _E , Typical Circuit for Measuring.	5-11
Vertical Monopole Antennas	4-4

INDEX (Continued)

	<u>Page</u>
V _{PB} , Typical Circuit Configuration for Measuring.	5-32
V _{SB} , Typical Circuit for Measurement of	5-10
Voltage-Current Characteristics (V-I Curve), Hard Limiters	5-15
Voltage-Current Characteristics (V-I Curve), Soft Limiters	5-16
Y Parameter	6-19
Z Parameter	6-19
Zener Diode	5-5

DISTRIBUTION LIST

DEPARTMENT OF DEFENSE

Director
Armed Forces Radiobiology Research Institute
Defense Nuclear Agency
ATTN: Tech. Lib.
ATTN: Robert E. Carter

Commander in Chief
U.S. European Command, JCS
ATTN: Tech. Lib.
ATTN: ECIG PI

Commander in Chief, Pacific
JCS
ATTN: J-2, Box 13

Director
Defense Advanced Rsch. Proj. Agency
ATTN: Tech. Lib.

Director
Defense Civil Preparedness Agency
Assistant Director for Research
ATTN: Admin. Off.
ATTN: TS AED
ATTN: RE(EO)

Defense Communication Engineer Center
ATTN: Code R729; C. Stansberry
ATTN: Code R124C; Tech. Lib.

Director
Defense Communications Agency
ATTN: Code 930; Monte L. Burgett, Jr.
ATTN: CCIC C672; Franklin D. Moore
ATTN: Code 540.5
ATTN: Code 430
ATTN: Code 950
ATTN: Tech. Lib.

Defense Documentation Center
Cameron Station
12 cy ATTN: TC

Commander
Defense Electronic Supply Center
ATTN: ECS
ATTN: Tech. Lib.

Assistant to the Secretary of Defense
Atomic Energy
ATTN: Doc. Con.

Director
Defense Intelligence Agency
ATTN: DB-4C; Edward O'Farrell
ATTN: DS-4B
ATTN: Tech. Lib.

Director
Defense Nuclear Agency
ATTN: DNST
ATTN: RAEV
ATTN: STSI, Archives
ATTN: RATN
ATTN: STVL
3 cy ATTN: STTL; Tech. Lib.

DEPARTMENT OF DEFENSE (Continued)

Commander
Field Command
Defense Nuclear Agency
ATTN: FCPR

Director
Interservice Nuclear Weapons School
ATTN: Doc. Con.
ATTN: Tech. Lib.

Director
Joint Strat. Tgt. Planning Staff, JCS
ATTN: JPST
ATTN: STINFO, Lib.

Chief
Livermore Division, Fld. Command DNA
Lawrence Livermore Laboratory
ATTN: FCPRL

National Communications System
Office of the Manager
ATTN: NCS-15; Charles D. Bodson

Director
National Security Agency
ATTN: Orland O. Van Ganten, R 415
ATTN: TDI
ATTN: Tech. Lib.

OMCS 4-6
The Pentagon
ATTN: 4-6, FSD-2

DEPARTMENT OF THE ARMY

Asst. Chief of Staff for Intelligence
ATTN: DAMA-IAS; Jack T. Blackwell

Program Manager
BMD Program Office
ATTN: DACS-BMT; John Shea

Commander
BMD System Command
ATTN: Tech. Lib.
ATTN: BDMSC-TEN; Noah J. Hurst

Dep. Chief of Staff for Rsch. Dev. & Acq.
ATTN: DAMA-CSM-N; LTC G. Ogden

Commander
Harry Diamond Laboratories
ATTN: DRXDO-NP; Francis N. Wimentz
ATTN: DRXDO-EM; John F. Sweton
ATTN: DRXDO-EM; John Bombardt
ATTN: DRXDO-RB; Joseph R. Miletta
ATTN: DRXDO-TR; Edward E. Conrad
ATTN: DRXDO-RC; Robert B. Oswald, Jr.
ATTN: DRXDO-RCC; John A. Rosado
ATTN: DRXDO-FM; Robert E. McCoskey
ATTN: DRXDO-RCC; John F. Thompkins
ATTN: DRXDO-TL; Tech. Lib.

DEPARTMENT OF THE ARMY (Continued)

Commander

U.S. Army Mat. Dev. & Readiness Cmt.
ATTN: DRCDL-D, Lawrence Flynn
ATTN: Tech. Lib.

Commander

Protonix Arsenal

ATTN: Human Posternal
ATTN: SMUPA-ND-N-1
ATTN: SMUPA-IR-S-P, Ruth Nicolaudes
ATTN: SARPA-ND-C-E, Anna Nordio
ATTN: SMUPA-ND-D-B, Edward J. Arber
ATTN: SMUPA-ND-D-C-2
ATTN: SMUPA-ND-W
ATTN: SMUPA-QA-N, P. G. Olivieri
ATTN: SMUPA-1N, Burton V. Franks
ATTN: SARPA-1S-E-E, Abraham Grinoch
ATTN: Tech. Lib.

Commander

IRASANA

ATTN: AIAA-FAC, Francis N. Wmains

Commander

Redstone Scientific Information Ctr.

ATTN: DRSMI-RBD, Clara T. Rogers

Director

U.S. Army Ballistic Research Labs.

ATTN: DRXBR-X, Julius J. Meszaros
ATTN: DRXBR-VL, John W. Kinch
ATTN: DRNRD-BVL, David L. Rigoan
ATTN: DRXBR-AM, W. R. VanAntwerp
ATTN: Tech. Lib., Edward Baucy

Commander

U.S. Army Mat. & Mechanics Rsch. Ctr.

ATTN: DRXMR-III, John F. Dignam
ATTN: Tech. Lib.

Chief

U.S. Army Communications Sys. Agency

ATTN: SCCM-AD-SV, Lib.

Commander

U.S. Army Computer Systems Command

ATTN: Tech. Lib.

Commander

U.S. Army Electronics Command

ATTN: DRSEL-NL-D
ATTN: DRSEL-GG-TD, W. R. Werk
ATTN: DRSEL-CE, T. Preiffer
ATTN: DRSEL-CT-HDK, Abraham E. Cohen
ATTN: DRSEL-TL-ME, M. W. Pomerantz
ATTN: DRSEL-TL-EN, Robert Lux
ATTN: DRSEL-TL-IR, Edwin T. Hunter
ATTN: DRSEL-TL-MD, Gerhart K. Gaulé
ATTN: DRSEL-TL-IR, Robert A. Freiberg
ATTN: DRSEL-WL-D
ATTN: DRSEL-PL-ENV, Hans A. Bomke

Commander

U.S. Army Communications Cmt.

ATTN: ACC-FD-M, Lawrence E. Cork
ATTN: Tech. Lib.

DEPARTMENT OF THE ARMY (Continued)

Division Engineer

U.S. Army Engr. Div., Missouri River

ATTN: MRDEL-MC, Floyd L. Hazlett

Commander in Chief

U.S. Army Europe and Seventh Army

ATTN: Tech. Lib.

Director

U.S. Army Materiel Sys. Analysis Actv.

ATTN: Tech. Lib.
ATTN: DRXSY-CC, Donald R. Barthol

Commander

U.S. Army Missile Command

ATTN: DRCPM-PE-EG, William B. Johnson
ATTN: DRCPM-EC-EK, Howard H. Henriksen
ATTN: DRCPM-PL-EX, Wallace O. Wagner
ATTN: DRSMI-RGP, Hugh Green
ATTN: DRSI-RGP, Victor W. Ruwe
ATTN: Tech. Lib.

Commander

U.S. Army Mobility Equip. R&D Ctr.

ATTN: Tech. Lib.
ATTN: STSEB-HHD, Franklin P. Good
ATTN: SMFEB-ES, Robert S. Brantly, Jr.
ATTN: STSEB-RN, Donald B. Dinger
ATTN: STSEB-MW, John W. Bond, Jr.

Commandant

U.S. Army Field Artillery School

ATTN: Tech. Lib.

Commander

U.S. Army Nuclear Agency

ATTN: Col. Deverall
ATTN: Tech. Lib.

Commander

U.S. Army Security Agency

Arlington Hall Station

ATTN: Tech. Lib.
ATTN: IACDA-EW
ATTN: IARD-T, Robert H. Burkhardt

Commander

U.S. Army Tank Automotive Command

ATTN: DRCPM-GCM-SW, Lyle A. Wolcott
ATTN: DRSTA-RHM, 1LT Peter A. Hasek
ATTN: Tech. Lib.

Commander

U.S. Army Test and Evaluation Comd.

ATTN: Tech. Lib.
ATTN: DRSTE-EL, Richard L. Kolchin
ATTN: DRSTE-NB, Russell R. Galasso

Commander

U.S. Army Training and Doctrine Comd.

ATTN: Tech. Lib.
ATTN: ATORI-OP-SD

Project Officer

U.S. Army Tac. Comm. Systems

U.S. Army Electronics Command

ATTN: DRCPM-ATC/COL Dobbins

DEPARTMENT OF THE ARMY (Continued)

Commander

White Sands Missile Range

ATTN: STEWS-TE-NT, Marvin P. Squires

ATTN: Tech. Lib.

Communications

U.S. Army Signal School

ATTN: AFSC CTD CS, Capt Alexander

ATTN: Tech. Lib.

DEPARTMENT OF THE NAVY

Chief of Naval Operations

ATTN: Code 604C3, Robert Pracesi

ATTN: OP 985

Chief of Naval Research

ATTN: Code 464, Thomas P. Quinn

ATTN: Code 427

ATTN: Code 464, R. Grace Joiner

ATTN: Tech. Lib.

Officer-in-Charge

Civil Engineering Laboratory

Naval Construction Battalion Center

ATTN: Code 131

ATTN: Tech. Lib.

Commander

Naval Air Systems Command

ATTN: Tech. Lib.

ATTN: AIR-250F, LCDR Hugo Hart

Commander

Naval Electronic Systems Command

Naval Electronic Systems Cnd. Hqs.

ATTN: PME 117-1

ATTN: Code 5032, Charles W. Neill

ATTN: PME 117-21

ATTN: PME 117-215A, Gunter Brunhart

ATTN: Tech. Lib.

Commander

Naval Electronics Laboratory Center

ATTN: Code 3100, E. E. McCown

ATTN: Code 2200 I, Verne E. Hildebrand

ATTN: Tech. Lib.

ATTN: H. F. Wong

ATTN: Code 2400, S. W. Lichtman

Commanding Officer

Naval Intelligence Support Ctr.

ATTN: NISC-45

ATTN: Tech. Lib.

ATTN: P. Alexander

Superintendent (Code 1424)

Naval Postgraduate School

ATTN: Code 2124, Tech. Rpts. Librarian

Director

Naval Research Laboratory

ATTN: Code 7770, Leslie S. Levine

ATTN: Code 2627, Doris R. Folen

ATTN: Code 6627, Charles S. Guenzler

ATTN: Code 4004, Emanuel L. Brancato

ATTN: Code 7701, Jack D. Brown

ATTN: Code 6634, James C. Ritter

ATTN: Code 2027, Tech. Lib.

DEPARTMENT OF THE NAVY (Continued)

Commander

Naval SEA Systems Command

ATTN: SEA-9934, Riley B. Lane

Commander

Naval Ship Engineering Center

ATTN: Code 617402, Edward F. Duffy

ATTN: Tech. Lib.

Commander

Naval Surface Weapons Center

ATTN: Code 244

ATTN: Code WR43

ATTN: Code 434, Edwin R. Rothburn

ATTN: Code WA50, John H. Malloy

ATTN: Code 434, Edwin B. Dean

ATTN: Code 223, L. Libello

ATTN: Code WA504, Navy Spec. Prgrams. Off.

6 cy ATTN: Code WX21, Tech. Lib.

Commander

Naval Surface Weapons Center

Dahlgren Laboratory

ATTN: Tech. Lib.

Naval Weapons Engr. Support Activity

Washington Navy Yard

ATTN: E S A 70

Commanding Officer

Naval Weapons Evaluation Facility

ATTN: Lawrence R. Oliver

ATTN: Code ATG, Mr. Stanley

Commanding Officer

Naval Weapons Support Center

ATTN: Code 7024, James Ramsey

ATTN: Tech. Lib.

Commander

Naval Weapons Center

ATTN: Code 533, Tech. Lib.

Director

Strategic Systems Project Office

ATTN: NSP-230, David Gold

ATTN: NSP-43, Tech. Lib.

ATTN: NSP-2431, Gerald W. Hoskins

ATTN: NSP-2342, Richard L. Coleman

ATTN: NSP-27331, Phil Spector

ATTN: SP 2701, John W. Pitsenberger

Commander

U.S. Naval Coastal Systems Laboratory

ATTN: Code 774, Edgar E. Parker

Commander-in-Chief

U.S. Pacific Fleet

ATTN: Doc. Con.

DEPARTMENT OF THE AIR FORCE

Commander

ADC DE

ATTN: DEEDS, Joseph C. Brannan

ATTN: DDEEN

DEPARTMENT OF THE AIR FORCE (Continued)

Commander

ADCOM XPD

ATTN: XPDQ

ATTN: XPDQ, Mr. G. Kuch

AF Geophysics Laboratory, AFSC

ATTN: J. Emery Cornner

AF Weapons Laboratory, AFSC

ATTN: LLC

ATTN: LLA

ATTN: DYN, Donald C. Wunsch

ATTN: FL, John Darrach

ATTN: SUI

ATTN: LLP, Carl L. Baum

ATTN: SAI

ATTN: SAR

ATTN: FLA, J. P. Castillo

ATTN: LL

ATTN: LL (Lab.)

ATTN: SA

AFIAC

ATTN: Tech. Lib.

ATTN: TFS, Mr. Marion F. Schneider

Headquarters

Air Force Systems Command

ATTN: DICA

ATTN: Tech. Lib.

Commander

Air University

ATTN: AUL LSE-70-250

Commander

ASD

ATTN: 4950 Test W TZMH, Peter T. Marth

ATTN: Tech. Lib.

Air Force Avionics Laboratory, AFSC

ATTN: Tech. Lib.

Headquarters

Electronic Systems Division, (AFSC)

ATTN: INDC

ATTN: YSEV

ATTN: DCD, Satin IV

ATTN: Tech. Lib.

ATTN: XRR1

ATTN: AWEL

Commander

Foreign Technology Division, AFSC

ATTN: TD-RTA, Lib.

ATTN: ETET, Capt Richard C. Husemann

HQ USAF/IG

ATTN: IGSPB, George Paseur

HQ USAF/RD

ATTN: RDQPN

Commander

Ogden Air Logistics Center

ATTN: Tech. Lib.

DEPARTMENT OF THE AIR FORCE (Continued)

Commander

Rome Air Development Center, AFSC

ATTN: LMLTD, Doc. Lib.

SAMSO DY

ATTN: DYS

SAMSO IN

ATTN: IND, L. J. Dady

SAMSO MN

ATTN: MNNG, Capt David L. Strobel

ATTN: MNMH, B. Stewart

ATTN: MNMH, Mr. M. Barm

SAMSO SK

ATTN: SKF, Peter H. Stoller

Commander in Chief

Strategic Air Command

ATTN: NRI-STINFO, Lib.

ATTN: DEF, Frank N. Dousha

ATTN: XPFS, Mr. Bruno G. Stephan

Commander

Sacramento Air Logistics Center

ATTN: Tech. Lib.

ENERGY RESEARCH & DEVELOPMENT ADMINISTRATION

Division of Military Application

U.S. Energy Resch. & Dev. Admin.

ATTN: Doc. Con. for Class. Tech. Lib.

University of California

Lawrence Livermore Laboratory

ATTN: Louis F. Wouters, L-18

ATTN: F. K. Miller, L-156

ATTN: Tech. Info. Dept., L-3

ATTN: B. Latorre

Los Alamos Scientific Laboratory

ATTN: Doc. Con. for Bruce W. Noel

ATTN: Doc. Con. for John S. Malik

ATTN: Doc. Con. for J. Arthur Freed

ATTN: Doc. Con. for Richard L. Wakefield

ATTN: Doc. Con. for Reports Lib.

Sandia Laboratories

ATTN: Doc. Con. for 3141, Sandia Rpt. Coll.

ATTN: Doc. Con. for Org. 9353, R. L. Parker

U.S. Energy Resch. & Dev. Admin.

Albuquerque Operations Office

ATTN: Doc. Con. for WSSB

ATTN: Doc. Con. for Tech. Lib.

Union Carbide Corporation

Holifield National Laboratory

ATTN: Paul R. Barnes

ATTN: Doc. Con. for Tech. Lib.

Sandia Laboratories

Livermore Laboratory

ATTN: Doc. Con. for Tech. Lib.

OTHER GOVERNMENT AGENCIES

Department of Commerce
National Bureau of Standards
ATTN: Tech. Lib.
ATTN: Jackson C. French

Central Intelligence Agency
ATTN: RD SL 464, 6418, Hq. Bldg., for Tech. Lib.
ATTN: William A. Decker

Administrator
Defense Electric Power Admin.
Department of the Interior
ATTN: Doc. Con.

NASA
Lewis Research Center
ATTN: Lib.

DEPARTMENT OF DEFENSE CONTRACTORS

Aerocut Electro-Systems Co., Div.
Aerocut-General Corporation
ATTN: Tech. Lib.
ATTN: Thomas D. Hainscome

Aeromtronic Ford Corporation
Aerospace & Communications Ops.
ATTN: E. R. Poncelet, Jr.
ATTN: Tech. Info. Section
ATTN: Ken C. Attinger

Aeromtronic Ford Corporation
Western Development Laboratories Div.
ATTN: Donald R. McMorrow, MS 630
ATTN: Lib.
ATTN: Samuel R. Crawford
ATTN: J. T. Mattingley

Aerospace Corporation
ATTN: Julian Reinheimer
ATTN: J. J. J. J. J.
ATTN: Irving M. Garfunkel
ATTN: C. B. Pearlston
ATTN: Norman D. Stockwell
ATTN: Melym J. Bernstein
ATTN: Lib.
ATTN: Bal Krishan

Avco Research & Systems Group
ATTN: Rsch. Lib. A830, Rm. 7201
ATTN: Robert S. Caldwell, 2R-00
ATTN: David L. Dye, MS 87-75
ATTN: Donald W. Egelkrout, MS 2R-00

Battelle Memorial Institute
ATTN: STOLAC
ATTN: Tech. Lib.

The Bendix Corporation
Research Laboratories Division
ATTN: Tech. Lib.
ATTN: Mgr. Prgm. Dev., Donald J. Niehaus

The Bendix Corporation
Communication Division
ATTN: Doc. Con.

DEPARTMENT OF DEFENSE CONTRACTORS (Continued)

The Bendix Corporation
Navigation and Control Division
ATTN: Tech. Lib.
ATTN: George Gartner

The EDM Corporation
ATTN: T. H. Neighbors
ATTN: Tech. Lib.

The EDM Corporation
ATTN: Tech. Lib.
ATTN: William Driven

The Boeing Company
ATTN: Aerospace Lib.
ATTN: D. E. Isbell
ATTN: David Kemle
ATTN: Howard W. Wackeln, MS 17-11

Booz-Allen and Hamilton, Inc.
ATTN: Tech. Lib.
ATTN: Raymond J. Christer

Brown Engineering Company, Inc.
Cummings Research Park
ATTN: John M. McSwain, MS 18
ATTN: Tech. Lib., MS 12, P. Shelton

Burroughs Corporation
Federal and Special Systems Group
ATTN: Tech. Lib.
ATTN: Angelo J. Mauriello

Charles Stark Draper Laboratory, Inc.
ATTN: Tech. Lib.
ATTN: Kenneth Fertig

Cincinnati Electronics Corporation
ATTN: C. R. Stamp
ATTN: Lois Hammond
ATTN: Tech. Lib.

Computer Sciences Corporation
ATTN: Tech. Lib.

Computer Science Corporation
ATTN: Richard H. Duckhaut
ATTN: Alvin L. Scholt

Cutler-Hammer, Inc.
ATTN: Central Tech. Files, Anne Anthony

University of Denver
Colorado Seminary
ATTN: Sec. Officer for Fred P. Venditti
ATTN: Sec. Officer for Tech. Lib.
ATTN: Sec. Officer for Ron W. Buchanan

The Dikewood Corporation
ATTN: Tech. Lib.
ATTN: L. Wayne Davis
ATTN: K. Lee

Effects Technology, Inc.
ATTN: Edward John Steele
ATTN: Tech. Lib.

DEPARTMENT OF DEFENSE CONTRACTORS (Continued)

EG&G, Inc.
Allouette Division
ATTN: Tech. Lib.
ATTN: Hilda R. Hoffman

Electronic Communications, Inc.
Subsidiary of NCR
ATTN: John L. Daniel, MS 22

ESI, Inc.
ATTN: Tech. Lib.
ATTN: William Metzger

E. Systems, Incorporated
Greenville Division
ATTN: Library, 8-00100

Exp. & Math. Physics Consultants
ATTN: Thomas M. Jordan

Fairchild Camera and Instrument Corp.
ATTN: Sec. Dept. for 2-233, David K. Myers
ATTN: Sec. Dept. for Tech. Lib.

Fairchild Industries, Inc.
Sherman Fairchild Technology Center
ATTN: Leonard J. Schreiber
ATTN: Tech. Lib.

The Franklin Institute
ATTN: Tech. Lib.
ATTN: Ranie R. Thompson

Garrett Corporation
ATTN: Tech. Lib.
ATTN: Robert E. Weir, Dept. 93-9

General Dynamics Corp.
Convair Division
ATTN: Keith Blair

General Electric Company
Re-Entry & Environmental Systems Div.
ATTN: Ray E. Anderson
ATTN: John W. Palchetsky, Jr.
ATTN: Tech. Lib.

General Electric Company
Ordnance Systems
ATTN: Joseph J. Reidl

General Electric Company
TEMPO Center for Advanced Studies
ATTN: Royden R. Rutherford
ATTN: DASIAC
ATTN: William McSamara

General Electric Company
Aerospace Electronics Systems
ATTN: Charles M. Hewison, DROP 624
ATTN: W. J. Patterson, DROP 233
ATTN: Tech. Lib.
ATTN: George Francis, DROP 233

General Electric Company
ATTN: David W. Pepin, DROP 160
ATTN: Tech. Lib.

DEPARTMENT OF DEFENSE CONTRACTORS (Continued)

General Electric Company
HMDS
ATTN: Doc. Cont. for C-100 CA

General Electric Company TEMPO
ATTN: DASIAC for W. Woodruff

General Dynamics Corp.
Electronic Division
ATTN: Tech. Lib.

General Dynamics Corp.
Pomona Operations
ATTN: Tech. Lib.

General Electric Company
Space Div.
Valley Forge Space Ctr.
ATTN: Dante M. Tasci
ATTN: Larry L. Chasen
ATTN: Joseph C. Peden
ATTN: Daniel Edelman
ATTN: James P. Spratt
ATTN: John R. Greenbaum
ATTN: Tech. Info. Ctr.

General Research Corporation
ATTN: Tech. Info. Office
ATTN: John Lee, Jr.
ATTN: Robert D. Hill

Grumman Aerospace Corporation
ATTN: Tech. Lib.
ATTN: Jerry Rogers

Georgia Institute of Technology
Georgia Tech. Research Institute
ATTN: R. Curry

Georgia Institute of Technology
Office of Contract Administration
ATTN: Resch. Security Coordinator for Res. & Sec.
Coord. for Hugh Denny

GTE Sylvania, Inc.
Electronics Systems Grp-Eastern Div.
ATTN: Leonard L. Blaisdell
ATTN: Charles A. Thornhill, Librarian
ATTN: James A. Waldon

GTE Sylvania, Inc.
ATTN: Herbert A. Ullman
ATTN: Charles H. Ramsbottom
ATTN: Comm. Syst. Div., Emil P. Motchok
ATTN: A S M Dept., S. E. Perlman
ATTN: H & V Group, Mario A. Nurefora

Hercules, Incorporated
Bacchus Plant
ATTN: 100K-26-W, R. Woodruff

DEPARTMENT OF DEFENSE CONTRACTORS (Continued)

Harris Corporation

Harris Semiconductor Division

ATTN: Tech. Lib.
ATTN: Wayne F. Abare, MS 16-111
ATTN: Carl E. Davis, MS 17-229
ATTN: Charles Denton, Jr., MS 1-500
ATTN: T. L. Clark, MS 1010

Honeywell Incorporated
Government and Aeronautical
Products Division

ATTN: R. J. Kell, MS S2572
ATTN: Tech. Lib.

Honeywell Incorporated
Aerospace Division

ATTN: Tech. Lib.
ATTN: Harrison H. Noble, MS 725-5A
ATTN: James D. Allan

Hazeltine Corporation

ATTN: Tech. Info. Ctr., M. Waite
ATTN: Edwin A. Smith, Dept. 85-85
ATTN: Kevin McCarthy, 0-85-71
ATTN: L-365, Dept. 81-20
ATTN: Benjamin T. Kimura, Dept. 81-14
ATTN: Philip J. Hart, Dept. 81-14
ATTN: D. M. Tellep
ATTN: Hans L. Schneemann

Honeywell Incorporated
Radiation Center

ATTN: Tech. Lib.

Hughes Aircraft Company
Centinela and Teale

ATTN: Dan Binder, MS 6-D147
ATTN: John B. Singletary, MS 6-D133
ATTN: Kenneth R. Walker, MS D157
ATTN: Billy W. Campbell
ATTN: Tech. Lib.

Hughes Aircraft Company
Space Systems Division

ATTN: Harold A. Boyte, MS A1080
ATTN: Edward C. Smith
ATTN: William W. Scott
ATTN: Tech. Lib.

ITT Research Institute

Electromag. Computability Anal. Ctr.

ATTN: ACOAT
ATTN: Tech. Lib.

ITT Research Institute

ATTN: Irving N. Mindel
ATTN: Tech. Lib.
ATTN: Mark B. Gagner
ATTN: W. C. Wells
ATTN: L. C. Peach
ATTN: W. C. Emberson
ATTN: L. B. Townsend
ATTN: P. L. E. Uslenghi
ATTN: V. P. Nanda

Institute for Defense Analyses

ATTN: IDA, Librarian, Ruth S. Smith

DEPARTMENT OF DEFENSE CONTRACTORS (Continued)

Ion Physics Corporation

ATTN: Robert D. Evans
ATTN: B. Myde
ATTN: Tech. Lib.

IRI Corporation

ATTN: Tech. Lib.
ATTN: R. L. Mertz

Jacor

ATTN: Eric P. Weemas
ATTN: Ralph H. Stahl

Johns Hopkins University

Applied Physics Laboratory

ATTN: Tech. Lib.
ATTN: Peter E. Partridge

Kaman Sciences Corporation

ATTN: Library
ATTN: John R. Hoffman
ATTN: Frank H. Shelton
ATTN: Albert P. Bridges
ATTN: Walter E. Ware
ATTN: Donald H. Bryce
ATTN: W. Foster Rich

Litton Systems, Inc.
Amecom Division

ATTN: Tech. Lib.

Litton Systems, Inc.
Data Systems Division

ATTN: Tech. Lib.

Litton Systems, Inc.

Guidance & Control Systems Division

ATTN: John P. Retzler
ATTN: Val J. Ashby
ATTN: Tech. Lib.

Lockheed Missiles & Space Co., Inc.

ATTN: Tech. Lib.
ATTN: Solomon E. Singer, Dept. 81-04
ATTN: Samuel L. Larmuty, Dept. 85-85
ATTN: George F. Heath, D 81-14

Lockheed Missiles and Space Company

ATTN: Clarence F. Kooi, Dept. 52-11
ATTN: Tech. Info. Ctr., D Coll.

LTV Aerospace Corporation

Michigan Division

ATTN: James F. Sanson, B-2
ATTN: Tech. Lib.

LTV Aerospace Corp.

Vought Systems Division

ATTN: Tech. Data Ctr.

Martin Marietta Aerospace

Orlando Division

ATTN: William W. Mraz, MP-413
ATTN: Jack M. Ashford
ATTN: Mona C. Griffith

M.I.T. Lincoln Laboratory

ATTN: Leona Loughlin, Librarian, A-082

DEPARTMENT OF DEFENSE CONTRACTORS (Continued)

Martin Marietta Corporation

Denver Division

ATTN: Research Lab. 9617, Jay R. McKee
ATTN: Ben L. Graham, MS DO 451
ATTN: Paul G. Kase

Maxwell Laboratories, Inc.

ATTN: Tech. Lab.
ATTN: Victor Fargo

McDonnell Douglas Corporation

ATTN: Tom Ender
ATTN: Tech. Lab.

McDonnell Douglas Corporation

ATTN: Paul H. Duncan, Jr.
ATTN: Stanley Schneider
ATTN: W. R. Spark
ATTN: A. P. Venditt
ATTN: Tech. Lab. Services

Mission Research Corporation

ATTN: Conrad L. Longmire
ATTN: William C. Hart
ATTN: Daniel F. Higgins

Mission Research Corporation

ATTN: David E. Merowether
ATTN: Tech. Lab.

Mission Research Corporation-San Diego

ATTN: V. A. J. Van Lint

The Mitre Corporation

ATTN: M. E. Fitzgerald
ATTN: Library
ATTN: Theodore Jarvin
ATTN: Louis Brickmore

National Academy of Sciences

ATTN: National Materials Advisory Bd. for
R. S. Shaw

Northrop Corporation

Electronic Division

ATTN: Boyce L. Ahlport
ATTN: George H. Towner
ATTN: Vincent R. DeMartino
ATTN: John M. Reynolds
ATTN: Tech. Lab.

Northrop Corporation

Northrop Research and Technology Ctr.

ATTN: Orle L. Curtis, Jr.
ATTN: David N. Pocock
ATTN: Lab.
ATTN: James P. Raymond

Northrop Corporation

Electronic Division

ATTN: Joseph D. Russo
ATTN: Tech. Lab.

Palisades Inst. for Resch. Services, Inc.

ATTN: Records Supervisor

Perkin-Elmer Corporation

ATTN: Tech. Lab.

DEPARTMENT OF DEFENSE CONTRACTORS (Continued)

Physics International Company

ATTN: Doc. Cont. for Bernard H. Bernstein
ATTN: Doc. Cont. for Tech. Lab.
ATTN: Doc. Cont. for Jek. H. Huntington

Procedyne Corporation

ATTN: Peter Horowitz
ATTN: Tech. Lab.

The Rand Corporation

ATTN: Cullen Crum
ATTN: Tech. Lab.

Raytheon Company

ATTN: Ganadhar H. Joshi
ATTN: Library

RCA Corporation

Government & Commercial Systems

Astro Electronics Division

ATTN: George J. Brucker
ATTN: Tech. Lab.

RCA Corporation

Government & Commercial Systems

Missile & Surface Radar Division

ATTN: Eleanor K. Daly
ATTN: Tech. Lab.
ATTN: Andrew L. Warren

RCA Corporation

Camden Complex

ATTN: R. W. Rostrom, 13-5-2
ATTN: E. Van Keuren
ATTN: Tech. Lab.

R & D Associates

ATTN: William R. Graham, Jr.
ATTN: Tech. Lab.
ATTN: S. Clay Rogers
ATTN: Leonard Schlessinger
ATTN: Richard R. Schaefer
ATTN: William J. Karzas
ATTN: Gerald K. Schlegel
ATTN: B. Gage

Research Triangle Institute

ATTN: Sec. Officer for Eng. Div., Mayrant
Simons, Jr.

Rockwell International Corporation

ATTN: N. J. Rudie, FA53
ATTN: J. Spetz
ATTN: Tech. Lab.
ATTN: L. Apodaca, FA53
ATTN: James F. Bell, HA10
ATTN: George C. Messenger, FB61
ATTN: Donald J. Stevens, FA70
ATTN: K. F. Hull
ATTN: J. L. Monroe, Dept. 243-027, Div. 031

Sanders Associates, Inc.

ATTN: Moe L. Attel, NCA 1-3236
ATTN: 1-6270, R. G. Despathy, SR P E
ATTN: Tech. Lab.

Science Applications, Inc.

ATTN: R. Parkinson
ATTN: Tech. Lab.

DEPARTMENT OF DEFENSE CONTRACTORS (Continued)

Science Applications, Inc.
Baltimore Division
ATTN: Tech. Lib.
ATTN: Noel R. Byrn

Science Applications, Inc.
ATTN: J. Roger Hill
ATTN: Richard L. Knight

Science Applications, Incorporated
ATTN: William L. Chadsey

Simulation Physics, Inc.
ATTN: John R. Uglan
ATTN: Roger G. Little

The Singer Company
ATTN: Irwin Goldman

The Singer Company (Data Systems)

Sperry Rand Corporation
Sperry Division
ATTN: Tech. Lib.
ATTN: Paul Marzattolo
ATTN: Charles L. Craig

Sperry Rand Corporation
Univac Division
ATTN: James A. Inda, MS 1125
ATTN: Tech. Lib.

Stanford Research Institute
ATTN: Philip J. Dolan
ATTN: Arthur Lee Watson

Stanford Research Institute
ATTN: MacPherson Morgan
ATTN: Tech. Lib.

Sunstrand Corporation
ATTN: Curtis B. White

Systems, Science and Software
ATTN: Tech. Lib.

Systems, Science and Software, Inc.
ATTN: Tech. Lib.
ATTN: Andrew R. Wilson

Syston-Donner Corporation
ATTN: Gordon B. Dean
ATTN: Harold D. Morris
ATTN: Tech. Lib.

Texas Instruments, Inc.
ATTN: Tech. Lib.
ATTN: Donald J. Manus, MS 72

Texas Tech. University
ATTN: Travis L. Simpson

TRW Systems Group
ATTN: Aaron H. Sarevsky, RI-2144
ATTN: O. E. Adams, RI-1144
ATTN: H. H. Holloway, RI-2036
ATTN: Jerry L. Labell, RI-1144
ATTN: Tech. Info. Center/S-1930
2 cy ATTN: Robert M. Webb, MS RI-1150

DEPARTMENT OF DEFENSE CONTRACTORS (Continued)

TRW Systems Group
San Bernardino Operations
ATTN: E. B. Ray, 527 710

TRW Semiconductors
Division of TRW, Inc.
ATTN: Ronald N. Clarke
ATTN: Tech. Lib.

United Technologies Corporation
Norden Division
ATTN: Tech. Lib.

United Technologies Corporation
Hamilton Standard Division
ATTN: Raymond G. Giguere
ATTN: Tech. Lib.

Vector Research Associates
ATTN: W. A. Radasky

Vardon Associates
ATTN: D. C. Lawrence
ATTN: Tech. Lib.

Westinghouse Electric Corporation
Astronautical Laboratory
ATTN: Tech. Lib.

Westinghouse Electric Corporation
Defense & Electronic Systems Ctr.
ATTN: Henry P. Kalapaca
ATTN: Tech. Lib.

Westinghouse Electric Corporation
Research & Development Ctr.
ATTN: Tech. Lib.

Rockwell International Corporation
ATTN: E. B. Yates

Rockwell International Corporation
Space Division
ATTN: TIC, D 41-092, A301

Raytheon Company
ATTN: Harold L. Flescher
ATTN: Tech. Lib.
ATTN: James R. Weckback

Intl. Tel. & Telegraph Corporation
ATTN: Alexander T. Richardson
ATTN: Def. Sp. Group, J. Gulack
ATTN: Tech. Lib.