

AD-A076 953

AMERICAN ELECTRONIC LABS INC FARMINGDALE NJ F/G 14/2
ELECTROMAGNETIC RADIATION SYSTEM (EMRS) FOR SUSCEPTIBILITY TEST--ETC(U)
AUG 79 M V STONE DAAB07-76-C-0332

UNCLASSIFIED

AD
A076953

CORADCOM-76-0332-10

MI



END
DATE
FILMED

12-79

DDC



12
SE

AD A 076953

DDC FILE COPY

RESEARCH AND DEVELOPMENT TECHNICAL REPORT
CORADCOM- 76-0332-10

LEVEL III
4063399

ELECTROMAGNETIC RADIATION SYSTEM (EMRS)
FOR SUSCEPTIBILITY TESTING

Margaretta Stone
AMERICAN ELECTRONIC LABORATORIES, INC.
P.O. Box 691
Farmingdale, NJ 07727

August 1979

Quarterly Report for Period: 1 January 1979 - 31 March 1979

DISTRIBUTION STATEMENT:

Approved for public release; distribution unlimited

Prepared for:

CENCOMS

DDC
RECEIVED
NOV 19 1979
A

CORADCOM

US ARMY COMMUNICATION RESEARCH & DEVELOPMENT COMMAND
FORT MONMOUTH, NEW JERSEY 07703

9 11 16 015

NOTICES

Disclaimers

The citation of trade names and names of manufacturers in this report is not to be construed as official Government indorsement or approval of commercial products or services referenced herein.

Disposition

Destroy this report when it is no longer needed. Do not return it to the originator.

UNCLASSIFIED

SECURITY CLASSIFICATION OF THIS PAGE (When Data Entered)

REPORT DOCUMENTATION PAGE		READ INSTRUCTIONS BEFORE COMPLETING FORM
1. REPORT NUMBER 18 CORADCOM-76-0332-10	2. GOVT ACCESSION NO.	3. RECIPIENT'S CATALOG NUMBER
4. TITLE (and Subtitle) 6 ELECTROMAGNETIC RADIATION SYSTEM (EMRS) FOR SUSCEPTIBILITY TESTING	5. TYPE OF REPORT & PERIOD COVERED 9 Quarterly Report, 1 Jan. 1979 - 31 March 1979	6. PERFORMING ORG. REPORT NUMBER
7. AUTHOR(s) 10 Margaretta V. Stone	8. CONTRACT OR GRANT NUMBER(s) 15 DAAB07-76-C-0332	
9. PERFORMING ORGANIZATION NAME AND ADDRESS American Electronic Laboratories, Inc. P.O. Box 691, Framingdale, NJ 07727	10. PROGRAM ELEMENT, PROJECT, TASK AREA & WORK UNIT NUMBERS 6.72.01.A 16 ILZ62701 AH92 C1 071 C8	
11. CONTROLLING OFFICE NAME AND ADDRESS CORADCOM, CENCOMS DRDCO-COM-RY-3 Fort Monmouth, NJ 07703 12 411	12. REPORT DATE 11 Aug 1979	
14. MONITORING AGENCY NAME & ADDRESS (if different from Controlling Office) 17 21	13. NUMBER OF PAGES 8	
	15. SECURITY CLASS. (of this report) UNCLASSIFIED	
15a. DECLASSIFICATION/DOWNGRADING SCHEDULE		
16. DISTRIBUTION STATEMENT (of this Report) Approved for public release; distribution unlimited		
17. DISTRIBUTION STATEMENT (of the abstract entered in Block 20, if different from Report)		
18. SUPPLEMENTARY NOTES		
19. KEY WORDS (Continue on reverse side if necessary and identify by block number) Electromagnetic Compatibility, Electromagnetic Energy Electromagnetic Radiation System (EMRS)		
20. ABSTRACT (Continue on reverse side if necessary and identify by block number) The function of the Electromagnetic Radiation System (EMRS) is to generate electromagnetic energy to produce a constant field strength that can be automatically scanned as a function of frequency. The design objective is to cover the frequency range of 30 Hz to 40 GHz with field intensities up to 200 volts per meter. This report describes system equipment status and results of performance tests in the demonstration frequency ranges of 30-60 MHz, 1.0-2.1 GHz, 2.1-4.0 GHz and 12.4-18.0 GHz. 411 024		

DD FORM 1 JAN 73 1473

EDITION OF 1 NOV 55 IS OBSOLETE

UNCLASSIFIED

SECURITY CLASSIFICATION OF THIS PAGE (When Data Entered)

1. INTRODUCTION

This report describes the activities and developments concerning PHASE II of the Electromagnetic Radiation System (EMRS) Program during the period of 1 January 1979 through 31 March 1979. The purpose of Phase II of the EMRS program is to develop the hardware to demonstrate the feasibility of the theoretical design considered in Phase I.

II. STATUS OF EMRS EQUIPMENT

All major equipment comprising the EMRS demonstration system has been received, with the exception of the tunable bandpass filter for the 12.4 GHz to 18.0 GHz frequency range. This item is expected to be delivered during May 1979.

The tunable bandpass filter for the 2.1 GHz to 4.0 GHz frequency range had to be returned to the manufacturer for repairs. The repaired unit is expected to be returned to AEL during April 1979.

Accession For	
NTIS	☒
DDC TAB	☐
Unannounced	☐
Justification	
By	
Distribution/	
Availability Codes	
Dist	Availand/or special
A	

III. PROGRESS DURING REPORT PERIOD

During this period, the Hewlett-Packard 8495H programmable attenuator, which was returned to the manufacturer for repair, was returned to AEL in proper operating condition. It was reinstalled in the EMRS control panel and used in applicable system tests.

Work continued on the redesign and finalization of the AEL-built external automatic levelling loop circuit.

Tests of the system were performed, in accordance with the EMRS Test Plan dated July 1978, to measure functions which required the tunable filters received so far. Results of tests, for all four demonstration bands, are shown in Tables 1 through 4, and summarized as follows:

Table 1 shows that the 30 MHz to 60 MHz EMRS demonstration system met requirements specified in the test plan for the following tests: Frequency Accuracy, Scan Rate Limits, External AM and FM Modulation, High Level Radiated Output and Level Variation, Non-Radiated Output and Level Variation and Signal Purity. It did not meet all requirements for External Pulse Modulation and Low Level Radiated Output.

Table 2 shows that the 1 GHz to 2.1 GHz EMRS demonstration system met requirements specified in the test plan for the following tests: Frequency Accuracy, Scan Rate Limits, External AM Modulation, most External FM Modulation, High Level Radiated Output and Level Variation, Non-Radiated Output and Level Variation and Signal Purity. It did not meet all requirements for External FM Modulation, External Pulse Modulation and Low-Level Radiated Output.

During tests of the 1 GHz to 2.1 GHz tracking filter, it was found that the method used to detect and track the RF signal input to the tracking filter limits the modulation to some degree. An investigation was conducted to determine and define the limitations. It was found that the only type of modulation which

was affected because of the filter was FM, and that the only limitation was in FM deviation. FM deviation with the filter was limited to a maximum of ± 32 MHz, which meets all specified limits except the requirement for ± 75 MHz deviation with modulation frequencies of DC to 100 Hz.

Table 3 shows that the 2.1 GHz to 4.0 GHz EMRS demonstration system met requirements specified in the test plan for the following tests: Frequency Accuracy, External FM, High Level Radiated Output and Level Variation and Non-Radiated Output and Level Variation. It did not meet all requirements for External AM, External Pulse Modulation and Low Level Radiated Output and Level Variation. Tests for Scan Rate and Signal Purity, in this frequency range, will be performed after the tunable filter is repaired by the manufacturer and returned to AEL. Additional tests will be performed at that time to make certain that high level radiated output, with the filter installed, complies with the 200 volt per meter requirements. Tests will also be performed to determine whether installation of the filter imposes any limitations on modulation capabilities.

Table 4 shows that the 12.4 GHz to 18 GHz EMRS demonstration system met requirements specified in the test plan for the following tests: Frequency Accuracy, External AM, External FM, High Level Radiated Output and Level Variation and Non-Radiated Output and Level Variation. It did not meet all requirements for External Pulse Modulation. Tests for Scan Rate, Low Level Radiated Output and Signal Purity will be performed after the tunable filter is received from the manufacturer. Tests will also be performed to determine whether installation of the filter imposes any limitations on high level radiated output or on modulation capabilities.

IV. FUTURE PLANS

During the next reporting period, the following activities are anticipated:

1. Finalization of the external automatic levelling circuit and tests of its performance relative to all EMRS frequency bands.
2. Receipt of the repaired 2.1 GHz to 4 GHz filter and performance of tests which require it.
3. Receipt of the 12.4 GHz to 18 GHz filter and performance of tests which require it.
4. Finalization of the EMRS system and quality control inspection.
5. Completion of test report to reflect tests to be performed in the next period.
6. Preparation of other required software on the finalized EMRS system.

TABLE 1 - SUMMARY OF EMRS TEST RESULTS, 30-60 MHZ FREQUENCY BAND

<u>TEST PLAN PARA.</u>	<u>TEST DESCRIPTION</u>	<u>REQUIREMENT</u>	<u>RESULTS</u>
5.1.2	Frequency Accuracy	Manual: + 10 MHz Auto: ± 15 MHz	Meets requirements Meets requirements
5.1.3	Scan Rate Limits (Automatic Sweep)	Less than or equal to 5 seconds/octave to over 100 seconds per octave	Meets requirements
5.1.4	External Modulation:		
	AM	0-100%, DC-150 kHz	Meets requirements
	FM	+ 20 MHz, DC-100 Hz ± 5 MHz, 100Hz-1MHz ± 2 MHz, 1-2 MHz	Meets requirements Meets requirements Meets requirements
	Pulse, Rise Time	50 nanoseconds	20 nS minimum with internal levelling (Note 1)
	Pulse, Fall Time	50 nanoseconds	Over 20 nS with in- ternal levelling (Note 1)
	Pulse Width	50 nS - 50 mS	100 nS - 20 mS with internal levelling (Notes 1 and 2)
5.1.5	Radiated Output:		
	High	200 V/M ± 3 dB	Meets requirements
	Low	1 mV/M ± 3 dB	(Note 3)
5.1.6	Non-Radiated Output	10 watts ± 3 dB	Meets requirements
5.1.7	Signal Purity	Harmonic & spurious emission at least 100 dB below fundamental	Meets requirements

- NOTES: 1. With external levelling, too much overshoot and ringing occurred. Levelling circuit is being redesigned.
2. System functions with longer pulses but output level varies if duty cycle exceeds 50%. Meets requirements with lower duty cycle.
3. System dynamic range is 40 dB, for 2 V/M minimum output. Adding external Hewlett-Packard 8447D amplifier to levelling loop adds 26 dB to dynamic range, for a minimum of 100 mV/M.

TABLE 2 - SUMMARY OF EMRS TEST RESULTS, 1-2.1 GHZ FREQUENCY BAND

<u>TEST PLAN PARA.</u>	<u>TEST DESCRIPTION</u>	<u>REQUIREMENT</u>	<u>RESULTS</u>
5.2.2	Frequency Accuracy	Manual: ± 10 MHz Auto: ± 15 MHz	Meets requirements Meets requirements
5.2.3	Scan Rate Limits (Automatic Sweep)	Less than or equal to 5 seconds/octave to more than 100 seconds per octave	Meets requirements
5.2.4	External Modulation:		
	AM	0-100%, DC-150 kHz	Meets requirements
	FM	± 75 MHz, DC-100 Hz ± 5 MHz, 100Hz-1MHz ± 2 MHz, 1-2 MHz	(Note 1) Meets requirements Meets requirements
	Pulse, Rise Time	50 nanoseconds	20 nS minimum with internal levelling (Note 2)
	Pulse, Fall Time	50 nanoseconds	Over 20 nS with inter- nal levelling (Note 2)
	Pulse Width	50 nS - 50 mS	100 nS - 20 mS with internal levelling (Notes 2 and 3)
5.2.5	Radiated Output:		
	High	200 V/M ± 3 dB	Meets requirements
	Low	1 mV/M ± 3 dB	(Note 4)
5.2.6	Non-Radiated Output	+30 dBm ± 3 dB	Meets requirements
5.2.7	Signal Purity	Harmonic & spurious emission at least 100 dB below fundamental	Meets requirements

- NOTES: 1. With filter installed, deviation is limited to ± 32 MHz.
2. With external levelling, too much overshoot and ringing occurs. Level-
ling circuit is being redesigned.
3. System functions with longer pulses, but output level varies if duty
cycle exceeds 50%. Meets requirements with lower duty cycle.
4. System dynamic range is 44 dB, for 1.3 V/M minimum output.

TABLE 3 - SUMMARY OF EMRS TEST RESULTS, 2.1-4.0 GHZ FREQUENCY BAND

<u>TEST PLAN PARA.</u>	<u>TEST DESCRIPTION</u>	<u>REQUIREMENT</u>	<u>RESULTS</u>
5.3.2	Frequency Accuracy	Manual: + 20 MHz Auto: ± 30 MHz	Meets requirements Meets requirements
5.3.3	Scan Rate Limits (Automatic Sweep)	Less than or equal to 5 seconds/octave to more than 100 seconds/octave	Awaiting delivery of filter
5.3.4	External Modulation:		
	AM	0-100%, DC-150 kHz	See Note 1
	FM	+ 75 MHz, DC-100 Hz ± 5 MHz, 100 Hz - 1 MHz ± 2 MHz, 1-2 MHz	Meets requirements
	Pulse, Rise Time	50 nanoseconds	20 nS minimum with internal levelling (Note 2)
	Pulse, Fall Time	50 nanoseconds	Over 20 nS with inter- nal levelling (Note 2)
	Pulse Width	50 nS - 50 mS	100 nS - 20 mS with internal levelling (Notes 2 and 3)
5.3.5	Radiated Output:		
	High	200 V/M ± 3 dB	Meets requirements
	Low	1 mV/M ± 3 dB	See Note 4
5.3.6	Non-Radiated Output	+30 dBm ± 3 dB	Meets requirements
5.3.7	Signal Purity	Harmonics and spur- ious emission at least 100 dB below fundamental	Awaiting delivery of filter

- NOTES:
1. Modulation applied directly to generator limited to 60% maximum. Modulation applied to external AM circuitry will go to 100% but distortion is high (many extraneous signals).
 2. With external levelling, too much overshoot and ringing were found. Levelling circuit is being redesigned.
 3. System functions with longer pulses, but output level varies if duty cycle exceeds 50%. Meets requirements with lower duty cycle.
 4. System dynamic range is 40 dB, for 2 V/M minimum output.

TABLE 4 - SUMMARY OF EMRS TEST RESULTS, 12.4 GHZ - 18 GHZ FREQUENCY RANGE

<u>TEST PLAN PARA.</u>	<u>TEST DESCRIPTION</u>	<u>REQUIREMENT</u>	<u>RESULTS</u>
5.4.2	Frequency Accuracy	Manual: ± 50 MHz Auto: ± 70 MHz	Meets requirements Meets requirements
5.4.3	Scan Rate Limits (Automatic Sweep)	Less than or equal to 5 seconds/octave to more than 100 seconds/octave	Awaiting delivery of filter
5.4.4	External Modulation:		
	AM	0-100%, DC-150 kHz	Meets requirements
	FM	± 75 MHz, DC-200 Hz ± 5 MHz, DC-200 kHz	Meets requirements
	Pulse, Rise Time	50 nanoseconds	30 nS with both external and internal levelling
	Pulse, Fall Time	50 nanoseconds	70 nS with external levelling, 4 uS with internal levelling
	Pulse Width	50 nS - 50 mS	100 nS - 10 mS with internal and external levelling
5.4.5	Radiated Output:		
	High	200 V/M ± 3 dB	Meets requirements
	Low	1 mV/M ± 3 dB	Awaiting delivery of filter
5.4.6	Non-Radiated Output	+30 dBm ± 3 dB	Meets requirements
5.4.7	Signal Purity	Harmonics and spur- ious emission at least 100 dB below fundamental	Awaiting delivery of filter