

AD-A188 930


PROTOTYPE REAL-TIME MONITOR USER'S MANUAL(U)
CARNEGIE-MELLON UNIV PITTSBURGH PA SOFTWARE ENGINEERING
INST R VAN SCOY ET AL NOV 87 CMU/SEI-87-TR-37
ESD-TR-87-200 F19628-85-C-0003


1/1

UNCLASSIFIED

F/8 12/5

NL






MICROCOPY RESOLUTION TEST CHART
NATIONAL BUREAU OF STANDARDS 1963 A

Technical Report
CMU/SEI-87-TR-37
ESD-TR-87-200

(2)

DTIC FILE COPY



Carnegie-Mellon University
Software Engineering Institute

Prototype Real-Time Monitor: User's Manual

Roger Van Scoy
Charles Pinta
Timothy Coddington
Richard D'Ippolito
Kenneth Lee
Michael Rissman

November 1987

AD-A188 930

DTIC
ELECTE
JAN 27 1988
S D

DISTRIBUTION STATEMENT A

Approved for public release
Distribution Unlimited

Technical Report

CMU/SEI-87-TR-37

ESD-TR-87-200

November 1987

Prototype Real-Time Monitor: User's Manual



Roger Van Scoy
Charles Plinta
Timothy Coddington
Richard D'Ippolito
Kenneth Lee
Michael Rissman

Dissemination of Ada Software Engineering Technology

Accession for	
NTIS CR431	☒
DTIC TAB	☐
Unannounced	☐
Justification	
By	
Distribution	
Availability	
Dist	Availability for Special
A-1	



Approved for public release.
Distribution unlimited.

Software Engineering Institute
Carnegie Mellon University
Pittsburgh, Pennsylvania 15213

This technical report was prepared for the


SEI Joint Program Office
ESD/XRS
Hanscom AFB, MA 01731

The ideas and findings in this report should not be construed as an official DoD position. It is published in the interest of scientific and technical information exchange.

Review and Approval

This report has been reviewed and is approved for publication.

FOR THE COMMANDER


Karl Shingler
SEI Joint Program Office

This work was sponsored by the U.S. Department of Defense.

This document is available through the Defense Technical Information Center. DTIC provides access to and transfer of scientific and technical information for DoD personnel, DoD contractors and potential contractors, and other U.S. Government agency personnel and their contractors. To obtain a copy, please contact DTIC directly: Defense Technical Information Center, Attn: FDRA, Cameron Station, Alexandria, VA 22304-6145.

Copies of this document are also available through the National Technical Information Services. For information on ordering, please contact NTIS directly: National Technical Information Services, U.S. Department of Commerce, Springfield, VA 22161.

Unix is a registered trademark of Bell Laboratories. VMS is a trademark of Digital Equipment Corporation.

Table of Contents

1. Basic Concepts	3
1.1. Definitions	3
1.2. Command Summary	3
1.3. Prototype Restrictions	4
2. Selecting Ada Variables	5
3. Variable Manipulation	7
4. Page Definition	9
5. Page Management	13
6. Page Control	15
Appendix A. Command Language Summary	17
Appendix B. Generating an RTM System	27
B.1. Create the Variable Database	27
B.2. Create the Type Database	30
B.3. Create the Compute_Address Procedure	32
B.4. Customize the System Dependencies	35
B.5. Customize the Processor Configuration	37
B.6. Tune the System Generation Parameters	38
B.7. Connect the RTM and Application Together	39
References	41
Index	43

1 2 3 4 5 6 7 8 9 10 11 12 13 14 15 16 17 18 19 20 21 22 23 24 25 26 27 28 29 30 31 32 33 34 35 36 37 38 39 40 41 42 43 44 45 46 47 48 49 50 51 52 53 54 55 56 57 58 59 60 61 62 63 64 65 66 67 68 69 70 71 72 73 74 75 76 77 78 79 80 81 82 83 84 85 86 87 88 89 90 91 92 93 94 95 96 97 98 99 100 101 102 103 104 105 106 107 108 109 110 111 112 113 114 115 116 117 118 119 120 121 122 123 124 125 126 127 128 129 130 131 132 133 134 135 136 137 138 139 140 141 142 143 144 145 146 147 148 149 150 151 152 153 154 155 156 157 158 159 160 161 162 163 164 165 166 167 168 169 170 171 172 173 174 175 176 177 178 179 180 181 182 183 184 185 186 187 188 189 190 191 192 193 194 195 196 197 198 199 200 201 202 203 204 205 206 207 208 209 210 211 212 213 214 215 216 217 218 219 220 221 222 223 224 225 226 227 228 229 230 231 232 233 234 235 236 237 238 239 240 241 242 243 244 245 246 247 248 249 250 251 252 253 254 255 256 257 258 259 260 261 262 263 264 265 266 267 268 269 270 271 272 273 274 275 276 277 278 279 280 281 282 283 284 285 286 287 288 289 290 291 292 293 294 295 296 297 298 299 300 301 302 303 304 305 306 307 308 309 310 311 312 313 314 315 316 317 318 319 320 321 322 323 324 325 326 327 328 329 330 331 332 333 334 335 336 337 338 339 340 341 342 343 344 345 346 347 348 349 350 351 352 353 354 355 356 357 358 359 360 361 362 363 364 365 366 367 368 369 370 371 372 373 374 375 376 377 378 379 380 381 382 383 384 385 386 387 388 389 390 391 392 393 394 395 396 397 398 399 400 401 402 403 404 405 406 407 408 409 410 411 412 413 414 415 416 417 418 419 420 421 422 423 424 425 426 427 428 429 430 431 432 433 434 435 436 437 438 439 440 441 442 443 444 445 446 447 448 449 450 451 452 453 454 455 456 457 458 459 460 461 462 463 464 465 466 467 468 469 470 471 472 473 474 475 476 477 478 479 480 481 482 483 484 485 486 487 488 489 490 491 492 493 494 495 496 497 498 499 500 501 502 503 504 505 506 507 508 509 510 511 512 513 514 515 516 517 518 519 520 521 522 523 524 525 526 527 528 529 530 531 532 533 534 535 536 537 538 539 540 541 542 543 544 545 546 547 548 549 550 551 552 553 554 555 556 557 558 559 560 561 562 563 564 565 566 567 568 569 570 571 572 573 574 575 576 577 578 579 580 581 582 583 584 585 586 587 588 589 590 591 592 593 594 595 596 597 598 599 600 601 602 603 604 605 606 607 608 609 610 611 612 613 614 615 616 617 618 619 620 621 622 623 624 625 626 627 628 629 630 631 632 633 634 635 636 637 638 639 640 641 642 643 644 645 646 647 648 649 650 651 652 653 654 655 656 657 658 659 660 661 662 663 664 665 666 667 668 669 670 671 672 673 674 675 676 677 678 679 680 681 682 683 684 685 686 687 688 689 690 691 692 693 694 695 696 697 698 699 700 701 702 703 704 705 706 707 708 709 710 711 712 713 714 715 716 717 718 719 720 721 722 723 724 725 726 727 728 729 730 731 732 733 734 735 736 737 738 739 740 741 742 743 744 745 746 747 748 749 750 751 752 753 754 755 756 757 758 759 760 761 762 763 764 765 766 767 768 769 770 771 772 773 774 775 776 777 778 779 780 781 782 783 784 785 786 787 788 789 790 791 792 793 794 795 796 797 798 799 800 801 802 803 804 805 806 807 808 809 810 811 812 813 814 815 816 817 818 819 820 821 822 823 824 825 826 827 828 829 830 831 832 833 834 835 836 837 838 839 840 841 842 843 844 845 846 847 848 849 850 851 852 853 854 855 856 857 858 859 860 861 862 863 864 865 866 867 868 869 870 871 872 873 874 875 876 877 878 879 880 881 882 883 884 885 886 887 888 889 890 891 892 893 894 895 896 897 898 899 900 901 902 903 904 905 906 907 908 909 910 911 912 913 914 915 916 917 918 919 920 921 922 923 924 925 926 927 928 929 930 931 932 933 934 935 936 937 938 939 940 941 942 943 944 945 946 947 948 949 950 951 952 953 954 955 956 957 958 959 960 961 962 963 964 965 966 967 968 969 970 971 972 973 974 975 976 977 978 979 980 981 982 983 984 985 986 987 988 989 990 991 992 993 994 995 996 997 998 999 1000

List of Figures

Figure 4-1: Edit Menu	9
Figure 4-2: Form Attributes Menu	10
Figure 4-3: VT100 Keypad Definition	10
Figure 4-4: Field Definition Menu	10
Figure 4-5: Field Definition Conventions	11
Figure B-1: Initialize_Database Procedure	28
Figure B-2: <i>Example of Generating Variable Information</i>	31
Figure B-3: Code Fragment That Defines a Type Database Entry	33
Figure B-4: Generic Conversion Package for Integers	34
Figure B-5: Code Fragment That Instantiates Integer Conversions	35
Figure B-6: Code Fragment That Performs Integer Conversions	36
Figure B-7: Simple Compute_Address Procedure	37
Figure B-8: Process_Buffer Procedure for Two CPUs	38
Figure B-9: Application to RTM Connection	39

Prototype Real-Time Monitor: User's Manual

Abstract. This report defines the user interface to the prototype real-time monitor (RTM). It defines the concepts and commands needed by a software engineer to use the RTM. In addition to defining the user interface, the report explains the steps needed to tailor the RTM to work with the user's application.

Intended Audience

The manual is intended for software engineers familiar with the Ada^{®1} language and the concepts involved with software integration and testing.

Associated Documents

- *Reference Manual for the Ada Programming Language* [Ada 83]
- *Prototype Real-Time Monitor: Requirements* [D'Ippolito 87]
- *Prototype Real-Time Monitor: Design* [Van Scoy 87a]
- *Prototype Real-Time Monitor: Ada Code* [Van Scoy 87b]
- *User's Manual for a Form Generator System in Ada* [Texas Instruments 85a]
- *User's Manual for an ANSI X3.64 Compatible Virtual Terminal in Ada* [Texas Instruments 85b]

Context of Report

The prototype RTM described in this report was built to address two specific technical questions raised by the Ada Simulator Validation Program (ASVP) contractors:

1. How can user tools find, access, and display data hidden in the bodies of Ada applications?
2. How can user tools be layered on top of Ada applications?

The prototype is documented by this report because the ASVP contractors had a need for a monitor tool, but did not have the contract resources to develop one. The prototype RTM is intended to be a simple tool that is easily rehosted and extended. It is not intended to be an example of what a well-documented system should include. Since it was a prototyping effort, no standard documentation or development methods were applied. Also, we did not attempt to solve all the traditional "monitor" problems.

¹Ada is a registered trademark of the U.S. Government (Ada Joint Program Office)

1. Basic Concepts

The real-time monitor, in its simplest form, is a tool which a software engineer can use to read and write data memory in an executing application. The tool allows the engineer to do this without requiring any prior knowledge about which memory locations (i.e., variables) need to be operated on. The RTM has **no** explicit control over the application. This particular monitor is called real-time because it is intended to be used in conjunction with real-time applications and run in whatever spare time is available to the processor. In this way, it will not adversely perturb the essential timing of the application. Some of the operations required to set up a monitoring session may require a considerable amount of CPU time and user thought and can be done without the active participation of the application; these can legitimately be considered off-line functions.

1.1. Definitions

The following definitions describe the basic concepts which are elaborated in the remainder of this document.

Variable	A legal Ada variable that exists in the application and can be monitored.
Variable Database	The collection of all variables in the application that are accessible to the user through the RTM.
Page	A collection of variables that are read and displayed to the user as a unit.

1.2. Command Summary

The commands used by the user to control RTM operations can be summarized as follows:

CHECK	Checks all the variables on a page for existence and accessibility.
EDIT	Creates or modifies a page.
READ	Accesses a single variable in the application.
SET	Assigns a new value to a single variable in the application.
START	Begins reading a page of variables from the application and periodically displays the page to the user.
STOP	Terminates the reading of a page begun by a START command.
QUIT	Terminates the RTM.

The full description of the commands, including examples, can be found in Appendix A, starting on page 17.

1.3. Prototype Restrictions

One important point to keep in mind is that this manual describes a prototype RTM, not a production-quality RTM. As such, a number of simplifications and restrictions to the RTM have been made. These restrictions are:

- Single display device
 - VT100 type terminal
 - 80 columns by 24 lines
 - lines 1 - 19 for use by user
 - lines 20 - 24 for use by RTM
 - keyboard input only
- No simultaneous input and output to the display device (i.e., screen updating halts during user command entry).
- Only integer, real, and enumeration types can be displayed (more complex types can be displayed by breaking them down into these components, or the user can implement display routines for more complex structures).
- Ada **task** type variables are not accessible for display or modification.
- Ada **access** type variables are not accessible for display or modification, but the underlying objects are accessible (i.e., the RTM does not display the address that is the value of an **access** type).
- Ada **constants** are not accessible for modification.
- Generation of the variable database and associated conversion routines are the responsibility of the user.
- Only one page of variables can be displayed (i.e., be active) at a time.

2. Selecting Ada Variables

Selection of Ada variables (objects) for page definition or variable manipulation purposes is accomplished by specifying the full Ada variable name² using dot notation, which represents the object of interest. For example, an Ada variable **process_controlling_parameter** in a package **Controller_A** which is "withed" by the main procedure **Real_Time_Application** would be specified as follows:

Real_Time_Application.Controller_A.process_controlling_parameter

All Ada variables referenced by the user are checked for existence in the variable database when:

- a START command is issued
- a CHECK command is issued
- a READ command is issued
- a SET command is issued

This checking is done by attempting to locate the variable in the variable database. If a variable cannot be found in the database, an error message is issued in all cases. If this happens when processing a READ or SET command, the command is ignored. If this happens in a START command, the variable is deleted from the display page, but any legal variables on the page will be processed normally.

²No shorthand notation is available in the prototype RTM.

3. Variable Manipulation

The user can interactively view and modify data on an individual variable basis. This is done using the following commands:

- | | |
|-------------|---|
| READ | Reads the current value of the specified Ada variable and displays it on the user's terminal. |
| SET | Replaces the current value of the user-specified Ada variable with the user-specified value. |

The values displayed will reflect the type of Ada variable, and similarly, the value expected for input must reflect the type of Ada variable. Both of these commands perform one-time-only operations (which is different from the START command that initiates a continuing operation).

1 2 3 4 5 6 7 8 9 10 11 12 13 14 15 16 17 18 19 20 21 22 23 24 25 26 27 28 29 30 31 32 33 34 35 36 37 38 39 40 41 42 43 44 45 46 47 48 49 50 51 52 53 54 55 56 57 58 59 60 61 62 63 64 65 66 67 68 69 70 71 72 73 74 75 76 77 78 79 80 81 82 83 84 85 86 87 88 89 90 91 92 93 94 95 96 97 98 99 100 101 102 103 104 105 106 107 108 109 110 111 112 113 114 115 116 117 118 119 120 121 122 123 124 125 126 127 128 129 130 131 132 133 134 135 136 137 138 139 140 141 142 143 144 145 146 147 148 149 150 151 152 153 154 155 156 157 158 159 160 161 162 163 164 165 166 167 168 169 170 171 172 173 174 175 176 177 178 179 180 181 182 183 184 185 186 187 188 189 190 191 192 193 194 195 196 197 198 199 200 201 202 203 204 205 206 207 208 209 210 211 212 213 214 215 216 217 218 219 220 221 222 223 224 225 226 227 228 229 230 231 232 233 234 235 236 237 238 239 240 241 242 243 244 245 246 247 248 249 250 251 252 253 254 255 256 257 258 259 260 261 262 263 264 265 266 267 268 269 270 271 272 273 274 275 276 277 278 279 280 281 282 283 284 285 286 287 288 289 290 291 292 293 294 295 296 297 298 299 300 301 302 303 304 305 306 307 308 309 310 311 312 313 314 315 316 317 318 319 320 321 322 323 324 325 326 327 328 329 330 331 332 333 334 335 336 337 338 339 340 341 342 343 344 345 346 347 348 349 350 351 352 353 354 355 356 357 358 359 360 361 362 363 364 365 366 367 368 369 370 371 372 373 374 375 376 377 378 379 380 381 382 383 384 385 386 387 388 389 390 391 392 393 394 395 396 397 398 399 400 401 402 403 404 405 406 407 408 409 410 411 412 413 414 415 416 417 418 419 420 421 422 423 424 425 426 427 428 429 430 431 432 433 434 435 436 437 438 439 440 441 442 443 444 445 446 447 448 449 450 451 452 453 454 455 456 457 458 459 460 461 462 463 464 465 466 467 468 469 470 471 472 473 474 475 476 477 478 479 480 481 482 483 484 485 486 487 488 489 490 491 492 493 494 495 496 497 498 499 500 501 502 503 504 505 506 507 508 509 510 511 512 513 514 515 516 517 518 519 520 521 522 523 524 525 526 527 528 529 530 531 532 533 534 535 536 537 538 539 540 541 542 543 544 545 546 547 548 549 550 551 552 553 554 555 556 557 558 559 560 561 562 563 564 565 566 567 568 569 570 571 572 573 574 575 576 577 578 579 580 581 582 583 584 585 586 587 588 589 590 591 592 593 594 595 596 597 598 599 600 601 602 603 604 605 606 607 608 609 610 611 612 613 614 615 616 617 618 619 620 621 622 623 624 625 626 627 628 629 630 631 632 633 634 635 636 637 638 639 640 641 642 643 644 645 646 647 648 649 650 651 652 653 654 655 656 657 658 659 660 661 662 663 664 665 666 667 668 669 670 671 672 673 674 675 676 677 678 679 680 681 682 683 684 685 686 687 688 689 690 691 692 693 694 695 696 697 698 699 700 701 702 703 704 705 706 707 708 709 710 711 712 713 714 715 716 717 718 719 720 721 722 723 724 725 726 727 728 729 730 731 732 733 734 735 736 737 738 739 740 741 742 743 744 745 746 747 748 749 750 751 752 753 754 755 756 757 758 759 760 761 762 763 764 765 766 767 768 769 770 771 772 773 774 775 776 777 778 779 780 781 782 783 784 785 786 787 788 789 790 791 792 793 794 795 796 797 798 799 800 801 802 803 804 805 806 807 808 809 810 811 812 813 814 815 816 817 818 819 820 821 822 823 824 825 826 827 828 829 830 831 832 833 834 835 836 837 838 839 840 841 842 843 844 845 846 847 848 849 850 851 852 853 854 855 856 857 858 859 860 861 862 863 864 865 866 867 868 869 870 871 872 873 874 875 876 877 878 879 880 881 882 883 884 885 886 887 888 889 890 891 892 893 894 895 896 897 898 899 900 901 902 903 904 905 906 907 908 909 910 911 912 913 914 915 916 917 918 919 920 921 922 923 924 925 926 927 928 929 930 931 932 933 934 935 936 937 938 939 940 941 942 943 944 945 946 947 948 949 950 951 952 953 954 955 956 957 958 959 960 961 962 963 964 965 966 967 968 969 970 971 972 973 974 975 976 977 978 979 980 981 982 983 984 985 986 987 988 989 990 991 992 993 994 995 996 997 998 999 1000

4. Page Definition

The RTM provides basic page definition facilities that allow the user to define pages for data collection purposes (i.e., a page to be monitored).

The user creates and modifies pages by using the EDIT command. All page editing is done via a forms management system that allows the user to move around the screen using cursor keys and to define the variables on the page using the keypad. Additional detailed information on how editing a page/form is accomplished can be found in the *User's Manual for a Form Generator System in Ada* [Texas Instruments 85a]. What follows is a brief overview of the process and a detailing of the conventions expected by the RTM.

A page, as discussed earlier, is a collection of variables that are read and displayed as a group. The creation of this group is done by the forms management system. This system views each page as a form, and on that form are fields (which the RTM treats as variable names). Thus, the creation of a page consists of creating a new form (page) and defining the fields (variables) that will reside on that form (page).

The first step in defining a new page is to issue the EDIT(); command. The RTM will then respond with the menu shown in Figure 4-1.

```
The Interactive Form Generator
  Choose "one" of the following:
    C - create a new form
    L - load an external form
    E - edit the current form
    M - modify the form's attributes
    S - save the current form
    Q - quit
  Selection: _____
```

Figure 4-1: Edit Menu

These options are rather self explanatory:

- C Creates a new form and puts the user into edit mode.
- L Recalls a previously saved form for editing.
- E Edits the form currently in memory (useful for making incremental changes to a form and available only after a C or L command).
- M Edits the characteristics of the form, such as row/column dimensions and screen position.
- S Stores a form on disk.
- Q Exits the editing session (not the RTM).

When a new page is created, the user is asked to determine the form's attributes using the menu shown in Figure 4-2.

Here is where the prototype restrictions on screen size have an impact. The user should not (the

Form Size	Rows: _____	Columns: _____
Form Position	Row: _____	Column: _____
Clear Screen Option:	_____	(Yes, No) _____

Figure 4-2: Form Attributes Menu

RTM cannot enforce this, that is why it is a convention) define a form that overlaps lines 20 through 24, which are reserved by the RTM.

Once the form/page attributes are set (which can be changed later using the M option above), a completely blank page is presented to the user. The user is now free to move about the screen using the cursor keys. Text can now be typed anywhere on the screen. This text will form the trim for the page, but does not constitute a variable. To place a variable on the screen, the user must position the cursor where the variable is to be placed and using the keypad shown in Figure 4-3, enter a 7. (There is a complete discussion of all the keypad commands in the *Forms Generator User's Manual* [Texas Instruments 85a].) The RTM responds with the menu in Figure 4-4.

+-----+-----+-----+-----+			
PF1	PF2	PF3	PF4
Command	Help	Exit	Delete
+-----+-----+-----+-----+			
7	8	9	-
Create	Modify	Delete	Delete
Field	Field	Field	Eoln
+-----+-----+-----+-----+			
4	5	6	,
Copy	Move		Delete
Field	Field		Char
+-----+-----+-----+-----+			
1	2	3	
Copy	Move		Enter
Line	Line		
+-----+-----+-----+			Accept
0		.	Form
Insert		Insert	
Line		Char	
+-----+-----+-----+-----+			

Figure 4-3: VT100 Keypad Definition

Field name:	_____	
Field length:	_____	
Character:	_____	(1 - alphabetic, 2 - numeric)
limits	_____	3 - alphanumeric, 4 - not limited)
Display:	_____	(1 - normal 2 - secondary)
rendition	_____	3 - reverse 4 - underline)
Field mode:	_____	(1 - input/output 2 - output only)
Initial value:	_____	

Figure 4-4: Field Definition Menu

What the RTM expects the user to enter in these fields is shown in Figure 4-5.

Field name:	full Ada path name of variable
Field length:	display size, in characters, of object
Character	
limits:	4
Display	
rendition:	user's choice
Field mode:	2
Initial value:	not used

Figure 4-5: Field Definition Conventions

The user can create as many or as few fields as will fit into the 19 lines available. When all the variables are entered as fields, the field definition mode is terminated by entering a PF3 from the keypad, at which point the main editing menu is presented again. At this point, the user must explicitly save the page by issuing the S command shown in Figure 4-1 and supply a name for the page. Once saved, the page is available for later use by the RTM for display purposes or subsequent modification by editing.

A command closely related to EDIT is CHECK. Since the forms management system has no direct knowledge of the variable database maintained by the RTM, the CHECK command should be used after editing a page to insure that all the variables defined on the page are accessible to the RTM.

These two commands also allow pages to be created and checked off line, i.e., without an executing application. This allows the time-consuming page editing operation to take place prior to using the RTM to debug or tune an application. It can also save CPU time in those cases where the RTM and the application are required to share a CPU, or where the RTM is rapidly updating the display.

5. Page Management

The capabilities for managing all the pages defined by the user are split between the forms management system discussed previously and the host computer operating system. The basic capabilities of page management are:

Page Operation	Method
----------------	--------

Copy	This can be done two ways:
------	----------------------------

- via the forms management system by loading using the L option, editing the form, and then storing the form (using the S option) under a new name
- via the operating system by using the a copy command (like copy on VMS systems or cp on UNIX systems)

Delete	This is done by simply deleting the appropriate page at the operating system level. Neither the RTM nor the forms management system imposes any form/page naming conventions on the user, so it is incumbent upon the user to keep track of page names. Perhaps the easiest solution to organizing pages is to create a page directory, and always execute the RTM from that directory.
--------	---

Directory	Again, this is handled at the operation system level and it is the user's responsibility to know the difference between page file names and any other file names in the directory.
-----------	--

6. Page Control

Once the user has created a page that specifies Ada variables for data collection purposes, the page can be activated for display purposes using the START command. The data collection and screen refresh both take place at the update rate specified in the command. Once the START command is issued, data collection and displaying take place automatically, without user intervention. The START also places the terminal into an asynchronous input mode. The normal mode of input is for the RTM> prompt to be available to the user all times, but when a page is actively being displayed, this interferes with output of data. To alleviate this problem, no prompt is presented to the user. This does not mean that the user has lost control of the RTM; the user simply has to hit any key and the RTM> prompt will appear and a command can be entered.

This also accomplishes a hold/resume option for page updating. While the RTM is waiting for the user to enter a command, no updates are being done to the screen. Once a command is entered and processed, updating of the screen resumes (assuming the page was not terminated, which we discuss below). Thus, a hold (cease updating) is a return, and a resume (restart updating) is a second return.

Once a page is no longer needed on the display, it can be terminated using a STOP command. This removes the page from the display, terminates collection of the data from the variables specified on the page, and returns the RTM to normal input mode (since only one page can be active in the prototype).

1 2 3 4 5 6 7 8 9 10 11 12 13 14 15 16 17 18 19 20 21 22 23 24 25 26 27 28 29 30 31 32 33 34 35 36 37 38 39 40 41 42 43 44 45 46 47 48 49 50 51 52 53 54 55 56 57 58 59 60 61 62 63 64 65 66 67 68 69 70 71 72 73 74 75 76 77 78 79 80 81 82 83 84 85 86 87 88 89 90 91 92 93 94 95 96 97 98 99 100 101 102 103 104 105 106 107 108 109 110 111 112 113 114 115 116 117 118 119 120 121 122 123 124 125 126 127 128 129 130 131 132 133 134 135 136 137 138 139 140 141 142 143 144 145 146 147 148 149 150 151 152 153 154 155 156 157 158 159 160 161 162 163 164 165 166 167 168 169 170 171 172 173 174 175 176 177 178 179 180 181 182 183 184 185 186 187 188 189 190 191 192 193 194 195 196 197 198 199 200 201 202 203 204 205 206 207 208 209 210 211 212 213 214 215 216 217 218 219 220 221 222 223 224 225 226 227 228 229 230 231 232 233 234 235 236 237 238 239 240 241 242 243 244 245 246 247 248 249 250 251 252 253 254 255 256 257 258 259 260 261 262 263 264 265 266 267 268 269 270 271 272 273 274 275 276 277 278 279 280 281 282 283 284 285 286 287 288 289 290 291 292 293 294 295 296 297 298 299 300 301 302 303 304 305 306 307 308 309 310 311 312 313 314 315 316 317 318 319 320 321 322 323 324 325 326 327 328 329 330 331 332 333 334 335 336 337 338 339 340 341 342 343 344 345 346 347 348 349 350 351 352 353 354 355 356 357 358 359 360 361 362 363 364 365 366 367 368 369 370 371 372 373 374 375 376 377 378 379 380 381 382 383 384 385 386 387 388 389 390 391 392 393 394 395 396 397 398 399 400 401 402 403 404 405 406 407 408 409 410 411 412 413 414 415 416 417 418 419 420 421 422 423 424 425 426 427 428 429 430 431 432 433 434 435 436 437 438 439 440 441 442 443 444 445 446 447 448 449 450 451 452 453 454 455 456 457 458 459 460 461 462 463 464 465 466 467 468 469 470 471 472 473 474 475 476 477 478 479 480 481 482 483 484 485 486 487 488 489 490 491 492 493 494 495 496 497 498 499 500 501 502 503 504 505 506 507 508 509 510 511 512 513 514 515 516 517 518 519 520 521 522 523 524 525 526 527 528 529 530 531 532 533 534 535 536 537 538 539 540 541 542 543 544 545 546 547 548 549 550 551 552 553 554 555 556 557 558 559 560 561 562 563 564 565 566 567 568 569 570 571 572 573 574 575 576 577 578 579 580 581 582 583 584 585 586 587 588 589 590 591 592 593 594 595 596 597 598 599 600 601 602 603 604 605 606 607 608 609 610 611 612 613 614 615 616 617 618 619 620 621 622 623 624 625 626 627 628 629 630 631 632 633 634 635 636 637 638 639 640 641 642 643 644 645 646 647 648 649 650 651 652 653 654 655 656 657 658 659 660 661 662 663 664 665 666 667 668 669 670 671 672 673 674 675 676 677 678 679 680 681 682 683 684 685 686 687 688 689 690 691 692 693 694 695 696 697 698 699 700 701 702 703 704 705 706 707 708 709 710 711 712 713 714 715 716 717 718 719 720 721 722 723 724 725 726 727 728 729 730 731 732 733 734 735 736 737 738 739 740 741 742 743 744 745 746 747 748 749 750 751 752 753 754 755 756 757 758 759 760 761 762 763 764 765 766 767 768 769 770 771 772 773 774 775 776 777 778 779 780 781 782 783 784 785 786 787 788 789 790 791 792 793 794 795 796 797 798 799 800 801 802 803 804 805 806 807 808 809 810 811 812 813 814 815 816 817 818 819 820 821 822 823 824 825 826 827 828 829 830 831 832 833 834 835 836 837 838 839 840 841 842 843 844 845 846 847 848 849 850 851 852 853 854 855 856 857 858 859 860 861 862 863 864 865 866 867 868 869 870 871 872 873 874 875 876 877 878 879 880 881 882 883 884 885 886 887 888 889 890 891 892 893 894 895 896 897 898 899 900 901 902 903 904 905 906 907 908 909 910 911 912 913 914 915 916 917 918 919 920 921 922 923 924 925 926 927 928 929 930 931 932 933 934 935 936 937 938 939 940 941 942 943 944 945 946 947 948 949 950 951 952 953 954 955 956 957 958 959 960 961 962 963 964 965 966 967 968 969 970 971 972 973 974 975 976 977 978 979 980 981 982 983 984 985 986 987 988 989 990 991 992 993 994 995 996 997 998 999 1000

Appendix A: Command Language Summary

Conventions Used in this Appendix

The command syntax shown in this appendix is that of an Ada procedure call (see Section 6.4 in [Ada 83]); that is, all RTM commands are invoked by an Ada procedure call, which implies that case and spacing are not significant. Several additional conventions in defining the command syntax:

Convention	Meaning
####	any legal Ada variable name
....	any legal page name
nnnn	any Ada value (integer, real, enumeration, etc.)
x.xx	any legal real number
my_variable	any Ada code
x.y.foo	any user-entered text
Enter Data>	any RTM generated output

In this appendix, the basic format for each command is:

- synopsis
- syntax
- parameters, if needed
- description
- examples
- exceptions, if needed

CHECK

CHECK

Checks the Ada variables on the specified page for availability in the variable database.

SYNTAX

CHECK (*Page* => *page_spec*);

PARAMETERS

page_spec

- Specifies the page on which checking is to take place. This *page_spec* may include a path name for the page file (as shown below).
-

DESCRIPTION

The CHECK command retrieves the specified page for analysis. This analysis consists of checking the Ada variables defined on the page for existence in the variable database.

This command can be used in conjunction with the EDIT command to develop the pages of Ada variables off line. These pages can be created using the page editor, and then checked against the variables available in the variable database, with appropriate changes made using the page editor. This off-line activity will allow the user to prepare for the monitoring process ahead of time.

EXAMPLES

- ① *Check (Page => [rtm.page_definition]test_page);*
Checks the Ada variables specified on the page, test_page, for existence in the variable database.
-

EXCEPTIONS

Variable not found: ####

Illegal mode for variable: ####

Error in accessing page: ****

EDIT

Places the user in the page editor.

SYNTAX

EDIT (**;**);

DESCRIPTION

The EDIT command places the user into the page editor. This allows the user to create new pages, load existing pages, edit pages, and save the edits. It also allows the user to modify attributes of the page. See Chapter 4, Page Definition, for more details.

Once a page is created by the user, it can then be used for monitoring purposes. See Chapter 6, Page Control, for more details.

EXAMPLES

❶ *Edit ();*

Places the forms management system menu on the display (shown in Figure 4-1.)

EXCEPTIONS

None.

QUIT

QUIT

Exits the current RTM session.

SYNTAX

QUIT ();

DESCRIPTION

The QUIT command exits the current monitoring session and returns the user to operating system or application control.

EXAMPLES

- ❶ `Quit();` Terminates the current RTM session.
-

EXCEPTIONS

None.

READ

Reads the current value of the specified Ada variable and displays it on the user's terminal.

SYNTAX

READ (*Name => ada_variable*);

PARAMETERS

ada_variable

The name of the Ada variable that the user wants read.

DESCRIPTION

The READ command reads the current state of the Ada variable specified by the user and displays it on the user's terminal. This command is used to examine the values of individual Ada variables in the application being monitored on a one-time basis. This command can be issued before and/or after setting an Ada variable (see the SET command) to check the value of the Ada variable.

EXAMPLES

- ① *Read(Name => engine.rpm);*
 The Variable: engine.rpm
 has the value: 6032.24
 Reads the current value of the Ada variable engine.rpm and displays it on the user's terminal.
- ② *Read(Name => test_stub.my_record.integer_part);*
 The Variable: test_stub.my_record.integer_part
 has the value: 194
 Reads the current value of the integer_part component of the record my_record and displays it on the user's terminal.
- ③ *Read(Name => fuel_system.status(tank_1));*
 The Variable: fuel_system.status(tank_1)
 has the value: full
 Reads the current value of the tank_1 component of the array status and displays it on the user's terminal.
- ④ *Read(Name => my_pointer);*
 The Variable: my_pointer
 has the value: 1657
 Reads the current value of the object pointed at by my_pointer and displays it on the user's terminal.

READ

EXCEPTIONS

Variable not found: ###

SET

Sets the Ada variable to the specified value.

SYNTAX

SET (*Name => ada_variable,*
 Value => value);

PARAMETERS

ada_variable

The name of the Ada variable whose value the user wants modified.

value

The new value which the user wishes the Ada variable to have.

DESCRIPTION

The SET command overwrites the current value of the Ada variable with the value specified by the user. The value specified by the user must be compatible with the type of the Ada variable.

This command can be issued to set up process-controlling parameters before the application begins, or it can be used in conjunction with the READ command to fine-tune the system as it is running.

Note: Since the state of the application cannot be determined when the operation is performed, this command should be used cautiously.

EXAMPLES

- ❶ `Set (Name=>engine.rpm<, Value=>4000.00);`
Sets the value of engine.rpm to 4000.00.
 - ❷ `Set (engine.rpm, 4000.00);`
Same as the above example without named association.
-

EXCEPTIONS

Variable not found: ####

Illegal value: nnnn

START

START

Starts collection of data based on the specified page of Ada variables for display.

SYNTAX

START (*Page => page_spec,*
 Update_Rate => value);

PARAMETERS

- ***page_spec***

Specifies the page which identifies the Ada variables to be collected and displayed. The *page_spec* may contain a path name to the page.

value

Optional parameter which specifies, as a real number, the rate at which the data are collected and written to the display device. The default value is 2.0 seconds. The usable range is from 0.01 (once every hundredth of a second) to 60.0 (once every minute).

DESCRIPTION

The START command begins collecting the values of the Ada variables defined on the user-specified page and displays them on the user's terminal. The rate at which the data are displayed is user controllable by specifying the *Update_Rate* parameter (in the prototype, the display *update_rate* is also the data sampling rate). If this optional parameter is not specified, then a default update rate of two seconds is assumed.

Prior to data collection each variable on the page is located in the variable database. If an Ada variable is not available for examination (i.e., it is not in the variable database), then:

1. The value is not accessible
 2. It will be dropped from the collection list
 3. An error message will appear on the page (i.e., the user's terminal) where the data was to be placed.
-

EXAMPLES

① *Start (Page => EngineVariables, Update_Rate => 0.2);*

Starts data collection of the Ada variables on page *EngineVariables* and displays them on the default display device with the data being updated every 0.2 seconds.

EXCEPTIONS

Variable not found: ####

Error in accessing page: ****

Maximum number of active pages in use.
STOP command must be issued first.

Bad update_rate, reenter in x.xx format

STOP

STOP

Stop data collection and display of the named page.

SYNTAX

STOP (*Page* => *page_spec*);

PARAMETERS

page_spec

Specifies the page on which data collection is currently taking place.

DESCRIPTION

The STOP command terminates the collection of data based on a page which is actively collecting data for display and removes the page from the screen.

EXAMPLES

- ❶ *Stop(control_parameters);*
 Stops data collection of the Ada variables on the page *control_parameters*
 (assuming a START command for the page has been previously issued).
-

EXCEPTIONS

Page not currently active: ****

No active pages

Appendix B: Generating an RTM System

This appendix outlines the basic steps that are needed to build a monitor for an application. Since each application is unique, these steps must be repeated for every application because it is easier to customize the RTM to meet the needs of each application than to force the application into a set mold dictated by the RTM.

The basic steps for generating the RTM system are:

- Create the variable database.
- Create the type database.
- Create the `compute_address` procedure.
- Customize the system dependencies.
- Customize the processor configuration.
- Tune the system generation parameters.
- Connect the RTM and application together.

Each of these steps is discussed in detail in its own section later. All of these steps, with the exception of the tuning step, involve changing the bodies of the various packages.

Conventions Used in This Document

The conventions used in this document are listed in the left-hand column below; their associated meanings are listed in the right-hand column.

code	Ada language construct
package	Ada package name
subsystem	Ada subsystem
COMMAND	RTM command

B.1. Create the Variable Database

The creation of the variable database involves two packages: the *variable_database* package, which is responsible for creating and managing the variable database as a structure, and the *library_interface* package, which is responsible for generating the variable information stored in the database.

Two procedures comprise the *variable_database*:

Initialize_database: Creates and populates the database (see Figure B-1).

find: Traverses the database.

The variable database is built automatically by **Initialize_Database** during elaboration of the RTM. These routines depend on the interface provided by the *library_interface* package and do not change as part of the customization of the RTM.

```

with Unchecked_Deallocation;
- Use the service "unchecked_deallocation."
-
with Types_Manager;
- Use the service "find."
-
separate (Variable_Database)
procedure Initialize_Database is
-|.....
-| Description:
-| This module is responsible for building the variable database
-| by whatever means are available.
-|
-| Parameter Description:
-| none
-|
-| Notes:
-| All of the system dependent issues related to obtaining
-| data object addresses have be isolated in these packages:
-| Library_interface: for static data information.
-| Address_generator: for dynamic data information.
-| These are the packages that must be changed to reflect the
-| system configuration and environment.
-|.....
procedure Free is new Unchecked_Deallocation
  (Library_Interface.Variable_Representation, The_Variable);

Variable_Position: Library_Interface.Variable_Iterator;
Node_Root: Db.Tree;
Found_Variable: Boolean;
The_Next_Variable: The_Variable;
begin
-
- The basic operation is the same for all the variables:
- Build a variable_representation record.
- Insert the record into the tree.
- Repeat for all variables.
-
Library_Interface.Make_Iterator(Variable_Position);
while Library_Interface.More(Variable_Position) loop
begin
  The_Next_Variable := new Library_Interface.Variable_Representation,
  Library_Interface.Get_Next
    (The_Iterator => Variable_Position,
     Variable_Information => The_Next_Variable all );
  The_Next_Variable.Data_Type := Types_Manager.Find
    (Name => The_Next_Variable.Variable_Type);
  Db.Insertnode(N => The_Next_Variable,
    T => Variable_Database,
    Root => Node_Root,
    Exists => Found_Variable);
exception
  when Types_Manager.Type_Not_Found =>
    Free (The_Next_Variable);
end ;
end loop ;
end Initialize_Database;

```

Figure B-1: Initialize_Database Procedure

The *library_interface* is responsible for supplying the information needed by the RTM. This information, as a minimum, consists of:

variable_name: The full Ada path name of the variable. This path name must go to the record component level if such a variable is to be available for monitoring.

base_address: The static address of the variable in application memory.

type_name: The name of the data type used in the variable declaration. This name must match the character string used to identify the type in the *types_manager* package (see Section B.2).

The manner in which this information is generated is irrelevant to the RTM. To illustrate how the *library_interface* package is used, the code for *Initialize_database* is shown in Figure B-1. In words, Figure B-1 embodies using the *library_interface* to build the database; these steps are:

1. Make an iterator (using *make_iterator*).
2. While there are more variables to process (indicated by a true value for *more* loop):
 - a. get the next variable information (*variable_representation* of the next variable, using *get_next*)
 - b. get the type of the variable (using *find*)
 - c. insert the variable into the variable database

This simple algorithm describes the entire process of building the variable database and illustrates that the *variable_database* knows nothing about the data in the structure or about how the data are generated. Its only concern is that the information is supplied using the interface:

variable_representation: Type that supplies the variable information (outlined above) plus any miscellaneous information needed (or available).

make_iterator: Responsible for doing all the preparation necessary to generate variable information. It then returns an iteration control variable which is used by *get_next* to select the next variable to generate information on and by *more* to determine if all of the available variable information has been retrieved. This variable is private to the *library_interface* package and has no significance outside the body of the package; therefore it can be used to represent anything the *library_interface* needs internally to collect the variable information.

get_next: Takes the iteration variable and generates a *variable_representation* record. The manner in which this is accomplished is irrelevant to the RTM. The existing version uses standard Ada facilities and is based on the assumption that the system is executing on one processor. For a two-CPU configuration, some kind of parsing of an address map would have to be substituted for this body. There is no order implied by the manner in which variables are returned; the *variable_database* package simply builds the structure to tie all the data together.

More: takes the iteration variable and returns a true value when more variables are available and a false value when all the variables have been processed. Again, the exact nature of how this is determined is dependent on how the variable information is generated.

The approach used in the prototype is applicable only to a single processor configuration. In this approach, the *library_interface* "withs" in all the packages of interest to the user. The package then lists all the variables visible along with their Ada data types; the `'address`³ attribute is then used to return the address of the variable (as an integer). The code that implements the *library_interface* package for this case is shown in Figure B-2.⁴ Clearly, this approach has some severe restrictions:

- Only package-level objects can be monitored (no local or package-body data are visible).
- It does not work in a multiple processor system.
- Every item to monitor must be placed in the database by hand; this implies that all record components and array references must be expanded (which creates an unnecessarily large database).

A number of other solutions to the database problem are possible, and in fact must be actively pursued for multiple CPU systems. Something as simple as a linker load map showing where all the static variables are allocated can be parsed and used to populate the variable database. Clearly, a better solution (possibly the best solution) is access to the compiler and linker output used by a symbolic debugger. The availability of this level of detailed information vastly increases the number of items that can be monitored and reduces the tedium that the prototype approach implies.

B.2. Create the Type Database

The *types_manager* package contains all the type information that the RTM needs to know. When we discuss types, we are referring to the Ada data types associated with the variables in the variable database. To be in the variable database, a variable's declared data type must be in the type database; without this correspondence, the RTM does not know enough about the variable to extract it from the application or display it to the user.

The type database is entirely constructed by hand (again, access to compiler-generated information would alleviate this problem) primarily because informing the RTM about a new type requires program changes to the body of *types_manager*. The best way to illustrate the information needed by the *types_manager* is to examine the code fragment shown in Figure B-3.

The type information is held in two structures: `valid_type_name` and `type_representation`. The explanation and examples shown in Figure B-3 illustrate how a type is entered into the database:

³Care must be taken in the use of `'address` attribute since it may need to be adjusted to obtain the true address of the data.

⁴This approach has to be entirely crafted by hand and is not the recommended approach

```

with System;
-- Use type "address."
--
with Unchecked_Conversion;
-- Use service "unchecked_conversion."
--
with Test_Stub;
-- Use data objects defined here for testing the monitor.
--

package body Library_Interface is
--
-- Used to convert all the system addresses into integers so that
-- they can be stored in the variable database. In a system where
-- an address map is used, this routine will need to be reimplemented.
--
function Get_Address is new Unchecked_Conversion
(Source => System.Address,
Target => Integer);
--/*****

procedure Make_Iterator (The_Iterator: in out Variable_Iterator) is
begin
    The_Iterator := 0;
end Make_Iterator;
--/*****

procedure Get_Next (The_Iterator: in out Variable_Iterator;
    Variable_Information: out Variable_Representation) is
begin
    case The_Iterator is
        when 0 =>
            Variable_Information.Variable_Name(1..20) := "test_stub.my_integer";
            Variable_Information.Base_Address := Get_Address(Test_Stub.My_Integer'Address);
            Variable_Information.Variable_Type(1..7) := "integer";
        when 1 =>
            Variable_Information.Variable_Name(1..17) := "test_stub.my_real";
            Variable_Information.Base_Address := Get_Address(Test_Stub.My_Real'Address);
            Variable_Information.Variable_Type(1..5) := "float";
        when others =>
            null;
    end case;
    The_Iterator := The_Iterator + 1;
end Get_Next;
--/*****

function More (The_Iterator: in Variable_Iterator) return Boolean is
begin
    if The_Iterator <= 1 then
        RETURN True;
    else
        RETURN False;
    end if;
end More;

end Library_Interface;

```

Figure B-2: Example of Generating Variable Information

- An enumeration name for the type is created (in `valid_type_name`).
- A representation record for the type is created (in `type_representation`).
- A string name is defined for the type in the package body (this is the name returned by `library_interface`).

The only restriction on types is that enumeration types (from the application being monitored) must be declared in the body of package `types_manager`; this can be done by "withing" in the package that declares the type or by manually redefining the type. This restriction does not apply to `Integers` and `floats`, since they are universal base types.

Once the type is defined, the generic conversion routine for the base type must be instantiated for the new type (the `convert_integers` generic is shown in Figure B-4). The generic is instantiated with the source type (a type that the RTM understands), a default display width, and a low-level conversion procedure (shown in Figure B-5). After instantiation, integer bit strings can be converted to display strings by reference to `rtm_integers.make_string` (shown in Figure B-6), or a string can be converted to a bit string by using `rtm_integers.make_value` (also shown in Figure B-6). The complete version of the `case` statements shown in Figure B-6 contains an entry for every type defined in `valid_type_name` and invokes the generic instantiation appropriate for each type.

Finally, the `default_integer_conversion` procedure shown in Figure B-5 is critical for proper multi-CPU processing. In a single CPU system, the approach shown in Figure B-5 is correct — that is, take an address and return the integer at that address. In a multi-CPU system, this may not be correct, especially when the underlying type representation is different between the RTM processor and the application processor(s). This situation requires the conversion routine to map the target (application processor) bit representation into the host (RTM processor) bit representation. It is the responsibility of this low-level function to supply the generic conversion package with a bit representation it understands.

B.3. Create the `Compute_Address` Procedure

The `compute_address` procedure is an important abstraction for the system since it combines the information from the `variable_database` and the `types_manager` to generate effective addresses for variables. In the simple case used by the prototype (shown in Figure B-7), address computation simply requires that the variable be located in the variable database and its base address returned (since every available variable and its base address are in the database). In a more sophisticated case, where a debugger interface is available or a more powerful parser is used (implying that address offsets are computed), the `compute_address` procedure can be modified to accommodate this without impacting the RTM code. This isolation of address computation allows for more powerful methods to be incorporated as they become available.


```

with Test_Stub;

package body Types_Manager is
--
-- Define the names of all the legal types.
--
type Valid_Type_Name is (Integers, Floats, Rtm_Enum1, Rtm_Record);
--
-- Define all the data needed about each type:
-- type_name_as_string -> A character string version of the type name.
-- This must match exactly with the type as it
-- exists in the application program, where the
-- type_name is a convenient enumeration literal
-- for this type.
-- type_name -> An enumeration literal for the type.
-- type_length -> The size of the type in smallest units.
-- display_width -> Number of characters needed to display a value
-- of the type: integer := 25;
-- indirection_level -> An integer that indicates how many levels of
-- indirect access the type represents.
--
type Type_Representation is record
  Type_Name_As_String: String(1..256);
  Type_Name: Valid_Type_Name;
  Type_Length: Integer := 0;
  Display_Width: Integer := 25;
  Indirection_Level: Integer := 0;
end record;
--
-- Define the table that holds all the type information; define
-- type_name_as_string in body.
--
Number_Of_Valid_Types: Valid_Rtm_Type := 4;
Valid_Rtm_Types: array (1..Number_Of_Valid_Types) of Type_Representation =
  ((Type_Name_As_String => (others => ''),
    Type_Name => Integers, Type_Length => 1,
    Display_Width => 10, Indirection_Level => 0),
   (Type_Name_As_String => (others => ''),
    Type_Name => Floats, Type_Length => 1,
    Display_Width => 10, Indirection_Level => 0),
   (Type_Name_As_String => (others => ''),
    Type_Name => Rtm_Enum1, Type_Length => 1,
    Display_Width => 5, Indirection_Level => 0),
   (Type_Name_As_String => (others => ''),
    Type_Name => Rtm_Record, Type_Length => 2,
    Display_Width => 20, Indirection_Level => 0));

--/.....
--/
--/ Package Body
--/
--/ The body is responsible for initializing the string versions
--/ of all the type names.
--/
--/.....

begin
  Valid_Rtm_Types(1).Type_Name_As_String(1..7) := "integer";
  Valid_Rtm_Types(2).Type_Name_As_String(1..5) := "float";
  Valid_Rtm_Types(3).Type_Name_As_String(1..9) := "rtm_enum1";
  Valid_Rtm_Types(4).Type_Name_As_String(1..10) := "rtm_record";
end Types_Manager;

```

Figure B-3: Code Fragment That Defines a Type Database Entry

```

with System;
-- Need the type "Address."
--
package Conversions is
--
-- Signals that the value in the character string is the wrong type
-- for the variable.
--
Illegal_Value: exception ;

generic
--
-- Default Width of the generated character strings.
Width: Positive := 15;
--
-- Integer type source, This is the host machine's type.
type Source_Representation is range <>;
--
-- Low-level conversion routine needed to convert from the target
-- representation to the host representation of the source type.
-- (referred to as source_representation)
with function Target_Conversion (Raw_Value: in System.Address)
return Source_Representation;

package generic package Convert_Integers is

  procedure Make_String (Raw_Value: in System.Address;
                        Field_Size: in Integer;
                        Value: out String);
--|.....
--| Description:
--| Make_string takes a binary bit string and converts it into
--| an integer character string.
--|
--| Parameter Description:
--| raw_value -> The address of the binary bit string to be
--| converted.
--| field_size -> The number of characters needed in the output
--| string.
--| value -> The character image of the binary bit string as
--| an integer.
--|.....

  procedure Make_Value (Raw_Value: in String;
                       Value: in System.Address);
--|.....
--| Description:
--| Make_value takes an integer character string and converts it into a
--| binary bit string.
--|
--| Parameter Description:
--| raw_value -> The character string to be converted.
--| value -> The address where the resulting bit string is to be
--| stored.
--|.....

end Convert_Integers;

end Conversions;

```

Figure B-4: Generic Conversion Package for Integers

```

with Conversions;

package body Types_Manager is

  type Integer_Pointer is access Integer;
  function Address_To_Integer_Pointer is new Unchecked_Conversion
    (Source => System.Address,
     Target => Integer_Pointer);

  function Default_Integer_Conversion (Raw_Value: in System.Address)
    return Integer is
  --|.....
  --| Description:
  --| Convert from a bit string at a system address to an integer
  --| value. This is valid for a one-CPU configuration
  --| only.
  --|
  --| Parameter Description:
  --| raw_value -> The address of the bit string to convert.
  --|.....
    Value_Pointer: Integer_Pointer;
  begin
    Value_Pointer := Address_To_Integer_Pointer(Raw_Value);
    RETURN Value_Pointer.all;
  end Default_Integer_Conversion;
pragma Inline (Default_Integer_Conversion);
--
-- Create the package to convert from bit strings to integers.
--
  package Rtm_Integers is new Conversions.Convert_Integers
    (Width => 15,
     Source_Representation => Integer,
     Target_Conversion => Default_Integer_Conversion);

end Types_Manager;

```

Figure B-5: Code Fragment That Instantiates Integer Conversions

B.4. Customize the System Dependencies

One system dependency that must be addressed is the virtual terminal interface. This interface is based on a UNIX termcap style definition file for controlling the terminal functions. This definition file is `tcf.tcf`. This file is already set up for a VT100 style terminal; therefore, the existence of a VT100 emulation mode will greatly facilitate the rehosting of this subsystem.

Package `sysdep_body` is the only VAX VMS-dependent package. It is used exclusively to do synchronous and asynchronous character I/O to the user's terminal. This package is part of the virtual terminal interface, and the body will need to be reimplemented to operate in a non-VAX VMS environment.

Package `sysdep_body`⁵ is written in Ada and executes under VMS. At the lowest level of implementation, it uses the VMS system services. A system service call is issued to create a channel

⁵This package body is part of the *virtual terminal subsystem* [Texas Instruments 85b].

```

separate (Types_Manager)
procedure Convert_String_To_Value (Data_Type: in Valid_Rtm_Type;
                                   Raw_Data: in System.Address;
                                   The_Value: in String) is

begin
  case Valid_Rtm_Types(Data_Type).Type_Name is
    when Integers =>
      Rtm_Integers.Make_Value (The_Value,Raw_Data);
    when others =>
      null;
  end case;
exception
  when Conversions.Illegal_Value =>
    RAISE Illegal_Value;
  when others =>
    RAISE;
end Convert_String_To_Value;

-----

separate (Types_Manager)
procedure Convert_Value_To_String (Data_Type: in Valid_Rtm_Type;
                                   Raw_Data: in System.Address;
                                   Number_Of_Chars: in Integer;
                                   The_Value: out String) is

begin
  The_Value := (The_Value'range => '');
  case Valid_Rtm_Types(Data_Type).Type_Name is
    when Integers =>
      Rtm_Integers.Make_String (Raw_Value => Raw_Data,
                                Field_Size => Number_Of_Chars,
                                Value => The_Value);
    when others =>
      null;
  end case;
end Convert_Value_To_String;

```

Figure B-6: Code Fragment That Performs Integer Conversions

to a device, and QIO calls are issued to perform character read and write operations on the device. *Starlet* and *Condition_Handling* are VAX Ada library packages that allow easy interfacing of the VMS system services to the RTM.

Since the system dependencies are all tied to VAX VMS, a few words on rehosting to a UNIX environment are in order. First, to rehost to a UNIX-based system, all the QIO system calls must be replaced. UNIX-equivalent system calls will replace the VMS service calls in procedures *open*, *get*, and *put* of package *sysdep_body*. VMS's I/O channels might be considered equivalent to a File Descriptor in UNIX with access to the keyboard established by using the UNIX *open* system call. Character level reads and writes to the terminal can be performed using *text_io* procedures after setting the keyboard to "RAW" mode (via an *ioctl* call); this will allow characters to be obtained unedited from the keyboard driver without a terminating carriage return (or newline); the *virtual terminal subsystem* and *forms management subsystem* perform all character interpretation.

```

function Compute_Address (Variable_Name: In String)
    return Address_Representation is
-/*.....
-| Description:
-|   This module takes the database identifier of a variable and
-|   computes the address of the variable.
-|
-| Parameter Description:
-|   the_variable -> Name of variable for which address is needed.
-|   return       -> Computed address of the variable.
-|
-| Notes:
-|   No address offset is computed since all accessible variables are
-|   in the database, and the base_address already has the offset
-|   taken into account.
-/*.....
    The_Variable: Variable_Database.The_Variable;
    Address: Address_Generator.Address_Representation := Null_Address;
    Address_Offset: constant Integer := 0;
    Data_Length: Integer;
    Access_Flag: Boolean;
begin
    The_Variable := Variable_Database.Find(Variable_Name);
    Types_Manager.Get_Type_Information (The_Variable.Data_Type,
                                        Data_Length,
                                        Access_Flag);
    Address := (The_Variable.Base_Address,
               Address_Offset,
               Access_Flag);
    RETURN Address;
end Compute_Address;

```

Figure B-7: Simple Compute_Address Procedure

B.5. Customize the Processor Configuration

The RTM-to-application interface is handled by the *rtm_core* module. On a single CPU, the prototype is currently setup correctly. For a two-CPU configuration, the *rtm_core* package will need to be duplicated. One copy will reside with the RTM on the host processor, and the second copy will reside with the application on the target processor.

On the host processor, the processing in the *process_buffer* module needs to be removed and should look like Figure B-8. The following need to take place:

1. Transfer the command and data buffers to the target, and
2. Wait for the command and data buffers to become available.

There are two stubbed modules, *send_buffer* and *get_buffer*, which need to be implemented to accomplish this transfer.

On the target processor, the **process_buffer** module needs to be integrated into the top-level executive or the timing controller of the application. It is then given an execution time-slice periodically. During this time-slice it will:

1. Look for the availability of a command buffer.
2. Process all the commands in the buffer (this is why the **core_buffer_size** parameter is so critical: it controls the maximum amount of time the *rtm_core* will ever use to execute).
3. Mark the buffer as available and transfer it back to the host.

Again, the **send_buffer** and **get_buffer** modules must be implemented to correctly complete transferring the buffers between the processors (which is not a trivial exercise).

```
procedure Process_Buffer is
begin
--
-- Send the command and data buffers to the rtm_core and wait
-- for their return.
--
  Get_Buffer;
  Send_Buffer;

end Process_Buffer;
```

Figure B-8: **Process_Buffer** Procedure for Two CPUs

B.6. Tune the System Generation Parameters

The parameters available for tailoring the RTM to suit the local environment are contained in the package *sysgen*. They are:

smallest_unit: The type which represents the smallest addressable or most efficiently addressable unit on the target processor. All type sizes (discussed in Section B.2) are defined in terms of this unit. For example, on the VAX running VMS, the most efficient addressable unit is a 32-bit word or the standard integer; thus all types in the RTM type database are defined as multiples of this 32-bit "smallest unit."

core_buffer_size: The size of the command and data buffers that communicate between the RTM and the *rtm_core* (which resides in the target processor along with the application). This limits the number of deposit and extract operations that the *rtm_core* can process during a time-slice and should be tailored to reflect the minimum time-slice that the *rtm_core* will have available.

processor_count: The number of processors being used in the system. It is either one or two (a two implies that the work discussed in the Section B.5 must be implemented).

default_rtm_device: The default disk directory where the RTM will look for page files, unless an explicit path name is supplied.

B.7. Connect the RTM and Application Together

Once all the previously discussed customizations are in place, the final piece of work is connecting the RTM and application together to form a working system. The exact nature of this connection depends on the number of processors in the system. We will show an example from the single processor case and discuss the extensions needed for the multiple processor case.

The simplest way to connect the system together is shown in Figure B-9 (this example assumes a non-real-time application). This example illustrates the key steps:

1. `real_time_monitor.setup_rtm` must be invoked before invoking the RTM, since this performs all the system initializations required by the RTM.
2. `real_time_monitor.rtm` invokes the RTM for one pass of its processing loop. Two points to note about this interaction are:
 - If the user is entering a command, control will not return to the application program until after the command has been entered and processed.
 - If a page is active, one page update will occur (assuming it is time to update the page).
3. `real_time_monitor.terminate_rtm` exception signals that a QUIT command has been issued and indicates that a call `real_time_monitor.closeout_rtm` is required (to properly exit the RTM).

This approach to connection only works well with non-real-time applications because there is no mechanism to control the amount of time the RTM uses.

```
with Text_io; use Text_io;
with Test_Stub;
with Real_Time_Monitor;

procedure Appl is
begin
  loop
    Test_Stub.Go;
    begin
      Real_Time_Monitor.Rtm;
    exception
      when Real_Time_Monitor.Terminate_Rtm =>
        Put_Line("RTM terminated, application still running");
    end ;
  end loop ;
end Appl;
```

Figure B-9: Application to RTM Connection

In a real-time situation on a single processor (i.e., both the RTM and application are running on one CPU), the application and RTM must be individually invoked from an operating system task that has the ability to time-slice the two processes. The application must be allowed to execute as required. The RTM is executed and suspended as time permits (i.e., whenever the application is idle and has signaled this fact to the operating system task).

The multiple processor situation implies a critical need for real-time execution of the application.

In many respects this is the simplest case. In this situation, the RTM (modified as described in Section B.5) can be executing on its own CPU and communicating with the application (which is executing on one or more CPUs) over a high-speed bus. This allows everything to execute as needed, with minimum perturbation of the application and no slow down in the RTM's user interface.

References

- [Ada 83] *American National Standard Reference Manual for the Ada Programming Language*, ANSI/MIL-STD-1815A-1983, 1983.
- [D'Ippolito 87] D'Ippolito, R., K. Lee, C. Plinta, M. Rissman, and R. Van Scoy. *Prototype Real-Time Monitor: Requirements*. Technical Report CMU/SEI-87-TR-36, Software Engineering Institute, November, 1987.
- [Texas Instruments 85a] *User Manual for a Form Generator System in Ada*. Equipment Group - ACSL, P.O. Box 801, MS 8007, McKinney, TX 75609, 1985.
- [Texas Instruments 85b] *User Manual for an ANSI X3.64 Compatible Virtual Terminal in Ada*. Equipment Group - ACSL, P.O. Box 801, MS 8007, McKinney, TX 75609, 1985.
- [Van Scoy 87a] Van Scoy, R., C. Plinta, T. Coddington, R. D'Ippolito, K. Lee, and M. Rissman. *Prototype Real-Time Monitor: Design*. Technical Report CMU/SEI-87-TR-38, Software Engineering Institute, November, 1987.
- [Van Scoy 87b] Van Scoy, R. *Prototype Real-Time Monitor: Ada Code*. Technical Report CMU/SEI-87-TR-39, Software Engineering Institute, November, 1987.

1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000

AD-A 188 930

REPORT DOCUMENTATION PAGE

1a. REPORT SECURITY CLASSIFICATION UNCLASSIFIED		1b. RESTRICTIVE MARKINGS NONE	
2a. SECURITY CLASSIFICATION AUTHORITY N/A		3. DISTRIBUTION/AVAILABILITY OF REPORT APPROVED FOR PUBLIC RELEASE DISTRIBUTION UNLIMITED	
2b. DECLASSIFICATION/DOWNGRADING SCHEDULE N/A			
4. PERFORMING ORGANIZATION REPORT NUMBER(S) CMU/SEI-87-TR-37		5. MONITORING ORGANIZATION REPORT NUMBER(S) ESD-TR-87-200	
6a. NAME OF PERFORMING ORGANIZATION SOFTWARE ENGINEERING INSTITUTE	6b. OFFICE SYMBOL (If applicable) SEI	7a. NAME OF MONITORING ORGANIZATION SEI JOINT PROGRAM OFFICE	
6c. ADDRESS (City, State and ZIP Code) CARNEGIE MELLON UNIVERSITY PITTSBURGH, PA 15213		7b. ADDRESS (City, State and ZIP Code) ESD/XRS1 HANSCOM AIR FORCE BASE, MA 01731	
8a. NAME OF FUNDING/SPONSORING ORGANIZATION SEI JOINT PROGRAM OFFICE	8b. OFFICE SYMBOL (If applicable) SEI JPO	9. PROCUREMENT INSTRUMENT IDENTIFICATION NUMBER F1962885C0003	
6c. ADDRESS (City, State and ZIP Code) CARNEGIE MELLON UNIVERSITY SOFTWARE ENGINEERING INSTITUTE JPO PITTSBURGH, PA 15213		10. SOURCE OF FUNDING NOS.	
11. TITLE (Include Security Classification) PROTOTYPE REAL-TIME MONITOR: USER'S MANUAL		PROGRAM ELEMENT NO. N/A	TASK NO. N/A
		PROJECT NO. N/A	WORK UNIT NO. N/A
12. PERSONAL AUTHOR(S) VAN SCOY, ET AL			
13a. TYPE OF REPORT FINAL	13b. TIME COVERED FROM TO	14. DATE OF REPORT (Yr., Mo., Day) NOVEMBER 1987	15. PAGE COUNT 48
16. SUPPLEMENTARY NOTATION			
17. COSATI CODES		18. SUBJECT TERMS (Continue on reverse if necessary and identify by block number)	
FIELD	GROUP	SUB. GR.	
		ADA, REAL-TIME MONITOR, COMMAND LANGUAGE, PORTABILITY, USER INTERFACE	
19. ABSTRACT (Continue on reverse if necessary and identify by block number) THIS RPEORT DEFINES THE USER INTERFACE TO THE PROTOTYPE REAL-TIME MONITOR (RTM). IT DEFINES THE CONCEPTS AND COMMANDS NEEDED BY A SOFTWARE ENGINEER TO USE THE RTM. IN ADDITION TO DEFINING THE USER INTERFACE, THE REPORT EXPLAINS THE STEPS NEEDED TO TAILOR THE RTM TO WORK WITH THE USER'S APPLICATION.			
20. DISTRIBUTION/AVAILABILITY OF ABSTRACT UNCLASSIFIED/UNLIMITED ☒ SAME AS RPT. ☐ DTIC USERS ☒		21. ABSTRACT SECURITY CLASSIFICATION UNCLASSIFIED, UNLIMITED	
22a. NAME OF RESPONSIBLE INDIVIDUAL KARL SHINGLER	22b. TELEPHONE NUMBER (Include Area Code) (412) 268-7630	22c. OFFICE SYMBOL SEI JPO	

END

3-88

DTIC