

UNCLASSIFIED

DTIC FILE COPY

SECURITY CLASSIFICATION OF THIS PAGE

2

REPORT DOCUMENTATION PAGE

Form Approved
OMB No. 0704-0188

1a. REPORT SECURITY CLASSIFICATION

UNCLASSIFIED

1b. RESTRICTIVE MARKINGS

3. DISTRIBUTION/AVAILABILITY OF REPORT

Unlimited

AD-A201 303

5. MONITORING ORGANIZATION REPORT NUMBER(S)

AFOSR-TR- 88-1169

6a. NAME OF PERFORMING ORGANIZATION
The Regents of the University
of California6b. OFFICE SYMBOL
(If applicable)

7a. NAME OF MONITORING ORGANIZATION

AFOSR/PKD

6c. ADDRESS (City, State, and ZIP Code)
Sponsored Projects Office
Berkeley, California 947207b. ADDRESS (City, State, and ZIP Code)
Building 410
Bolling Air Force Base
Washington, D.C. 20332-64488a. NAME OF FUNDING/SPONSORING
ORGANIZATION
AFOSR/NE8b. OFFICE SYMBOL
(If applicable)

9. PROCUREMENT INSTRUMENT IDENTIFICATION NUMBER

AFOSR ~~Grant~~ #85-02308c. ADDRESS (City, State, and ZIP Code)
Building 410
Bolling Air Force Base
Washington, D.C. 20332-6448

10. SOURCE OF FUNDING NUMBERS

PROGRAM
ELEMENT NO.

61103F

PROJECT
NO.

2305

TASK
NO.

C3

WORK UNIT
ACCESSION NO.

11. TITLE (Include Security Classification)

Quantum limits of Superconducting Heterodyne Receivers

12. PERSONAL AUTHOR(S)

Richards, Paul L.

13a. TYPE OF REPORT

Final

13b. TIME COVERED

FROM 5/15/85 TO 5/14/88

14. DATE OF REPORT (Year, Month, Day)

1988 September 23

15. PAGE COUNT

11

16. SUPPLEMENTARY NOTATION

17. COSATI CODES

FIELD

GROUP

SUB-GROUP

18. SUBJECT TERMS (Continue on reverse if necessary and identify by block number)

19. ABSTRACT (Continue on reverse if necessary and identify by block number)

Not required.

DTIC
ELECTE
OCT 28 1988
S E D

20. DISTRIBUTION/AVAILABILITY OF ABSTRACT

☐ UNCLASSIFIED/UNLIMITED ☐ SAME AS RPT. ☐ DTIC USERS

21. ABSTRACT SECURITY CLASSIFICATION

22a. NAME OF RESPONSIBLE INDIVIDUAL

Weinstock

22b. TELEPHONE (Include Area Code)

(202) 767-4933

22c. OFFICE SYMBOL

NE

September 23, 1988

FINAL TECHNICAL REPORT TO THE
AIR FORCE OFFICE OF SCIENTIFIC RESEARCH

Grant No. USAF-AFOSR-85-0230

"Quantum Limits of Superconducting Heterodyne Receivers"

Period: May 15, 1985 - May 14, 1988

P.L. Richards

Professor of Physics
University of California
Berkeley, California 94720

Accession For	
NTIS GRA&I	
DTIC TAB	
Unannounced	
Justification	
By	
Distribution/	
Availability Codes	
Dist	Avail and/or Special
A-1	

Overview

An investigation of the behavior of superconducting heterodyne receivers in the quantum limit can be carried out using very low leakage tunnel junctions and relatively low frequencies, such as W-band. Alternatively, very low capacitance small-area junctions with moderate leakage can be used at much higher frequencies. It is necessary in either case to make precise measurements of mixer noise and gain. It is also essential to make precise determinations of the embedding admittances in order to permit comparison between experiment and theory. In addition, extensive computer software must be written in order to carry out the comparisons with quantum mixer theory.

In this project, the technology has been developed for both approaches to the study of the quantum limits of SIS heterodyne mixers. All of the factors necessary to make these comparisons in a W-band waveguide mixer have been in place since early 1977. Due to delays in the production at Yale of the special low leakage

tunnel junctions required, however, the measurements were postponed until late 1988. — /

Much more extensive development of lithographed quasioptical mixers was necessary for the high frequency approach. Measurements of mixer performance in the quantum limit began at the end of the third grant year and were continued throughout 1988. Computer modeling began in mid-1988. A part of this program, which is testing small area junctions made at Berkeley will not begin until mid-1989.

Technology that is important for the optimization of practical SIS mixers for heterodyne receivers has been developed at every stage of this project and has been reported in a series of publications as well as invited and contributed papers at scientific meetings.

Summary of Progress

In collaboration with the Yale group, an extensive computer program was developed for theoretical modeling of SIS mixers. This program was used with considerable success to analyze measurements¹⁰ made using a K_a -band mixer equipped with novel low-leakage Ta junctions.^{13,16} Unfortunately, detailed testing of the quantum mixer theory could not be carried out because information about the embedding admittances in this mixer was not sufficiently accurate and because quantum effects were not sufficiently developed at this low frequency.

Under previous funding, construction had begun of a system designed to permit accurate measurements of mixer gain and noise at 90 GHz. Construction of this system was completed successfully.⁴

Tests were carried out on a W-band waveguide mixer block which can be tuned from 2.7 - 3.7mm (80-100 GHz) with a single mechanical adjustment.³ This mixer block has been very well characterized by studies of large-scaled models so detailed theoretical modeling of quantum limited mixers should be possible. It also has very favorable properties for use in practical SIS receivers.^{8,9,11} This mixer has an instantaneous bandwidth of ~3GHz and uses an IF transformer with high input impedance (500 - 700 Ω). When used with 2x2(μ m)² Pb-based junctions from NBS Boulder this mixer gave a DSB gain of 8-12 dB, which is the highest ever seen in an SIS mixer. It also gave mixer noise temperatures of T_m (DSB) of 6-15K, which are the lowest yet observed at these frequencies.¹²

In order to observe strong quantum effects, arrangements were made to have tunnel junctions for this mixer fabricated at Yale using a Ta-Ta oxide-Pb technology which has extremely low leakage current.⁵ The first such junctions received from Yale were tested, but gave very poor performance¹⁴ because of an error in the optical lithography. Due to problems with personnel turnover in the Yale group, the next generation of junctions will not be available until 9/88, beyond the period of this grant. This delay

has been very regrettable because the combination of Ta junctions and the well characterized W-band mixer block promises to give the first example of an SIS mixer operating strongly in the quantum limit. This work will be continued under the sponsorship of another agency.

The alternative approach to the observations of strong quantum effects is to use junctions with moderate leakage at near millimeter and submillimeter wavelengths. Since waveguide structures become very small and difficult to build at submillimeter wavelengths, a parallel development was carried out of SIS quasiparticle mixers with planar lithographed geometries. A quasi-optical test apparatus was developed¹⁷ in order to evaluate such mixers at frequencies from 90 to 270 GHz. This apparatus includes cryogenic hot-cold loads at the IF in order to accurately measure mixer noise and gain. A special approach was devised for probing the DC response of quantum mixer junctions and an automatic computer fitting program was developed for comparing the DC response of pumped mixers to quantum theory in order to deduce accurate embedding admittances. These techniques were used to evaluate several types of planar lithographed mixer with bow-tie and log-periodic antennas at W-band. They included mixers made with a single junction, a single junction tuned with a microstrip stub, series arrays of 5 junctions, and series arrays of 5 junctions tuned with a parallel wire inductor. The mixers were fabricated at NBS Boulder using Pb-based and Nb-based junction technologies.

In all cases the measured coupling coefficient and the bandwidth agreed well with calculations based on simple equivalent circuits models and on the nominal parameters of the structures. Measurements were made of mixer gain and noise and comparisons were made to the performance of waveguide mixers with similar types of junction.¹⁷ These comparisons indicate that there is a 6-7 dB loss between the cryostat window and the terminals of the bow-tie antenna. When corrected for this loss, the gains of the bow-tie mixers were comparable to the waveguide mixers, but the noises were higher by factors of 2-4.

Preparations were made for improvements in the optical system to reduce the input coupling losses. Tests of the improved system will be carried out under the sponsorship of another agency. Detailed computer modeling of the performance of these planar quasi-optical mixers was begun, but is being continued under other sponsorship.

The first steps were taken to operate planar quasi-optical SIS mixers at frequencies of 180 and 270 GHz. Harmonic generators were assembled which extended the frequency range of the quasi-optical mixer test apparatus. Planar lithographed mixers with quasi-optical RF matching structures were produced at NBS Boulder for operation at the second and third harmonic of W-band. A novel technique using the SIS junction as a direct detector and a Fourier transform infrared spectrometer as a source was used to evaluate the performance of these coupling structures.^{15,18}

Preliminary results show good performance up to 180 GHz, and evidence of resonant RF coupling at 270 GHz. These experiments are being continued under other sponsorship.

The NBS junction technology could not produce junctions small enough to couple directly to submillimeter wavelengths. In order to produce such junctions a project was established with Prof. T. Van Duzer at Berkeley under the JSEP program. A student of Van Duzer's is fabricating very small Nb trilayer junctions with lithographed antennas and matching structures. He will then participate in measurements in my laboratory. These experiments will be carried out under other sponsorship.

Publications

1. P. L. Richards, Analog Superconducting Electronics, Physics Today, March 1986 pp. 54/62.
2. P. L. Richards, Superconducting Receivers for Molecular Line Astronomy, Bull. Am. Phys. Soc. 31(3), 308 (1986).
3. D. G. Crété, A. V. Räisänen, W. R. McGrath, P. L. Richards, and F. L. Lloyd, Low-Noise 80-115 GHz SIS Mixers with a Single Tuning Element, Digest of the 11th Int. Conf. on Infrared and Millimeter Waves, p. 327 (1986).
4. W. R. McGrath, A. V. Räisänen, and P. L. Richards, Variable-Temperature Loads for Use in Accurate Noise Measurements of Cryogenically-Cooled Microwave Amplifiers and Mixers, Int. J. Infrared and Millimeter Waves 7, 543 (1986).
5. D. W. Face, D. E. Prober, W. R. McGrath, and P. L. Richards, High Quality Tantalum Superconducting Tunnel Junctions for Microwave Mixing in the Quantum Limit, Applied Phys. Lett. 48, 1098 (1986).
6. D. G. Crété, W. R. McGrath, P. L. Richards, and F. L. Lloyd, Performance of Arrays of SIS Junctions in Heterodyne Mixers, IEEE Trans. Microwave Theory Tech. MTT-35, 435 (1987).
7. P. L. Richards, D. G. Crété, Li Xizhi, W. R. McGrath, D. W. Face, D. Prober, and F. L. Lloyd, Advances in SIS Quasiparticle Mixers, 1986 Applied Superconductivity Conference Final Program and Abstracts, p.44 (1986).
8. A. V. Räisänen, D. G. Crété, P. L. Richards, and F. L. Lloyd, Low Noise SIS Mixer with Gain for 80-115 GHz, European Space Agency Workshop Proc. ESA SP-260, 255 (1986).
9. A. V. Räisänen, D. G. Crété, P. L. Richards, and F. L. Lloyd, Wide-Band Ultra Low Noise mm-Wave Mixers with a Single Tuning Element, 16th European Microwave Conf. Proc. p. 252 (1986).
10. W. R. McGrath, P. L. Richards, D. W. Face, D. E. Prober, and F. L. Lloyd, Performance of mm-Wave SIS Mixers Employing Pb-Alloy and Ta/PbBi Tunnel Junctions, Digest of the 11th Int. Conf. on Infrared and Millimeter Waves, p.330 (1986).
11. A. V. Räisänen, D. G. Crété, P. L. Richards, and F. L. Lloyd, Wide-Band, Low Noise MM-Wave SIS Mixers with a Single Tuning Element, Int. J. Infrared and Millimeter Waves 7(12), 1835 (1986).
12. A. V. Räisänen, D. G. Crété, P. L. Richards, and F. L. Lloyd, A 100 GHz SIS Quasiparticle Mixer with 10 dB Coupled Gain, IEEE MTT-S Digest II, 929 (1987).

13. D. W. Face, W. R. McGrath, P. L. Richards, and D. E. Prober, Accurate Experimental and Theoretical Comparison Between Superconducting Mixers Showing Strong and Weak Quantum Effects, ISEC'87 Extended Program and Abstracts p. 286 (1987).
14. G.-J. Cui, D. W. Face, E. K. Track, D. E. Prober, A. V. Räisänen, D. G. Crété, and P. L. Richards, High Quality Ta/PbBi Tunnel Junctions for 85-110 GHz SIS Mixer Experiments, IEEE Trans. Magn. MAG-23, 688 (1987).
15. Qing Hu, C. A. Mears, P. L. Richards, and F. L. Lloyd, Measurement of Integrated Tuning Elements for SIS Mixers with Fourier Transform Spectrometer, Bull. Am. Phys. Soc. 33, 223 (1988).
16. W. R. McGrath, P. L. Richards, D. W. Face, D. E. Prober, and F. L. Lloyd, Accurate Experimental and Theoretical Comparisons Between SIS Mixers Showing Weak and Strong Quantum Effects, J. Applied Physics 63, 2479 (1988).
17. Li Xizhi, P. L. Richards, and F. L. Lloyd, SIS Quasiparticle Mixers with Bow-Tie Antennas, Int. J. Infrared and Millimeter Waves 9, 101 (1988).
18. Qing Hu, C. A. Mears, P. L. Richards, and F. L. Lloyd, Measurement of Integrated Tuning Elements for SIS Mixers with a Fourier Transform Spectrometer, Int. J. Infrared and Millimeter Waves 9, 303 (1988).

Personnel Associated with the Effort

1985-1986

D. G. Crété, Visitor
A. V. Räisänen, Visitor
Li, Xizhi, Visitor
P. L. Richards, Professor
M. Crommie, Graduate Student Research Assistant
D. Chrzan, Graduate Student Research Assistant

1986-1987

D. G. Crété, Visitor
A. V. Räisänen, Visitor
P. L. Richards, Professor
Q. Hu, Postgraduate Research Physicst
C. Mears, Graduate Student Research Assistant

1987-1988

A. V. Räisänen, Visitor
P. L. Richards, Professor
Q. Hu, Postgraduate Research Physicist
C. Mears, Graduate Student Research Assistant

Interactions, Coupling Activities

Invited Talks

P. L. Richards, Josephson Junctions and SIS Detectors, ARO Workshop on Submillimeter Wave Detectors and Receivers, Minneapolis, MN, September 3, 1985.

P. L. Richards, Superconducting Receivers for Molecular Line Astronomy, March Meeting of the American Physical Society, Las Vegas, NV, 31 March-4 April 1986, Bull. Am. Phys. Soc. 31(3), 308 (1986).

P. L. Richards, Superconducting Quasiparticle Tunnel Junctions as Quantum Limited Detectors and Mixers for Microwave Radiation, Seminar, Department of Electrical Engineering and Computer Science, U.C. Berkeley, February 26, 1986.

P. L. Richards, SIS Mixers, West Coast Superconductive Electronics Meeting, Berkeley, CA, March 7, 1986.

P. L. Richards, Superconducting Microwave Heterodyne Receivers Approaching the Quantum Limit, Physics Department Colloquium, Stanford University, Palo Alto, CA, May 20, 1986.

D. W. Face, SIS Mixers in the Quantum Limit, March Meeting of the American Physical Society, 31 March-4 April 1986, Las Vegas, NV, Bull. Am. Phys. Soc. 31(3), 493 (1986).

P. L. Richards, Progress in the Development of SIS Quasiparticle Mixers, Applied Superconductivity Conference, Baltimore, Maryland, 9/28 - 10/3/86.

P. L. Richards, Superconductive Mixers, Air Force Applications of Cryoelectronics, Dayton, Ohio, October 30, 1986.

P. L. Richards, SIS Quasiparticle Mixers, Joint Services Electronics Programs Review, Berkeley, November 5, 1986.

P. L. Richards, RF Impedance Matching Structures for Planar SIS Mixers, Submillimeter (Terahertz) Receiver Technology Conference, Lake Arrowhead, Calif., April 7-8, 1987.

P. L. Richards, Superconducting Detectors, Seminar at Santa Barbara Research Center, Goleta, Calif., May 28, 1987.

P. L. Richards, Superconducting Detectors for Infrared and Microwaves, Seminar at Rockwell International Science Center, Thousand Oaks, CA, July 20, 1987.

Also at Hughes Aircraft Co., Space and Communications Group, El Segundo, CA, July 21, 1987.

P. L. Richards, Far Infrared and Submillimeter Devices, Seminar at the Radio Research Laboratory, Tokyo, Japan, February 3, 1988.

Also at the Advanced Telecommunications Research Institute International, Osaka, Japan, February 10, 1988.

P. L. Richards, Superconducting Detectors for Infrared and Millimeter Waves, Conference on Lasers and Electro-Optics (CLEO'88), Anaheim, CA, April 25, 1988.

Also at One Day Workshop on Superconductivity and Microwaves, 1988 IEEE MTT-S International Microwave Symposium, New York, N.Y., May 22, 1988.

Contributed Talks

A. V. Räisänen, W. R. McGrath, P. L. Richards, and F. L. Lloyd, A Simple Integrated Matching Element for SIS Quasiparticle Mixers, IEEE 1985 MTT-S International Microwave Symposium, St. Louis, Mo., June 4, 1985.

D. W. Face, D. E. Prober, W. R. McGrath, and P. L. Richards, Tantalum Based Superconducting Tunnel Junctions for Low-Noise, SIS Millimeter Wave Receivers, 1985 US-Japan Workshop on Josephson Junction Electronics, Kauai, Hawaii, June 18-19, 1985.

A. V. Räisänen, D. G. Crété, P. L. Richards, and F. L. Lloyd, Wide-Band Ultra Low Noise mm-Wave Mixers with a Single Tuning Element, 16th European Microwave Conference, Dublin, Ireland, 8-12 September 1986.

G.-J. Cui, D. W. Face, E. K. Track, D. E. Prober, A. V. Räisänen, D. G. Crété, and P. L. Richards, High Quality Ta/PbBi Tunnel Junctions for 85-110 GHz SIS Mixer Experiments, Applied Superconductivity conference, Baltimore, Maryland, 9/28-10/3/86.

D. G. Crété, A. V. Räisänen, W. R. McGrath, P. L. Richards, and F. L. Lloyd, Low-Noise 80-115 GHz SIS Mixers with a Single Tuning Element, 11th Int. Conf. on Infrared and mm-waves, Pisa, Italy, 20-24 October 1986.

W. R. McGrath, P. L. Richards, D. W. Face, D. E. Prober, and F. L. Lloyd, Performance of mm-Wave SIS Mixers Employing Pb-Alloy and Ta/PbBi Tunnel Junctions, Pisa, Italy, 20-24 October 1986.

A. V. Räisänen, D. G. Crété, P. L. Richards, and F. L. Lloyd, A 100 GHz SIS Quasiparticle Mixer with 10 dB Coupled Gain, 1987 IEEE International Microwave Symposium, Las Vegas, Nevada, June 9-11, 1987.

D. W. Face, W. R. McGrath, P. L. Richards, and D. E. Prober, Accurate Experimental and Theoretical Comparison Between Superconducting Mixers Showing Strong and Weak Quantum Effects, 1987 International Superconductivity Electronics Conference, Tokyo, Japan, August 28-29, 1987.

A. V. Räisänen, D. G. Crété, P. L. Richards, and F. L. Lloyd, A 100 GHz SIS Mixer with High Transducer Gain and Low Noise, Open Symposium of Millimeter Technology in Telecommunications, Remote Sensing and Radio Astronomy, XXII General Assembly of the U.R.S.I., Tel Aviv, Israel, August 24-September 2, 1987.

Qing Hu, C. A. Mears, P. L. Richards, and F. L. Lloyd, Measurement of Integrated Tuning Elements for SIS Mixers with Fourier Transform Spectrometer, American Physical Society March Meeting, New Orleans, LA, March 21-25, 1988.

Statement

There were no inventions or patents disclosures during this grant period.