

AD-A226 739

PORT DOCUMENTATION PAGE

2

1a. SECURITY CLASSIFICATION AUTHORITY		1b. RESTRICTIVE MARKINGS	
2a. DECLASSIFICATION/CONTINUING SCHEDULE		3. DISTRIBUTION/AVAILABILITY OF REPORT	
2b. DECLASSIFICATION/CONTINUING SCHEDULE		Approved for public release; distribution unlimited.	
4. PERFORMING ORGANIZATION REPORT NUMBER		5. MONITORING ORGANIZATION REPORT NUMBER(S)	
AFOSR		AFOSR-TR- 90 0938	
6a. NAME OF PERFORMING ORGANIZATION		7a. NAME OF MONITORING ORGANIZATION	
University of Missouri- St. Louis		Air Force Office of Scientific Research	
6c. ADDRESS (City, State and ZIP Code)		7b. ADDRESS (City, State and ZIP Code)	
8001 Natural Bridge Rd. St. Louis, MO 63121 Physics Dept		BLDG. 410, Bolling AFB Washington, DC 20332	
8a. NAME OF FUNDING/SPONSORING ORGANIZATION		9. PROCUREMENT INSTRUMENT IDENTIFICATION NUMBER	
AFOSR		Grant AFOSR-89-0416	
8c. ADDRESS (City, State and ZIP Code)		10. SOURCE OF FUNDING NOS.	
Bldg 410 Bolling AFB DC 20332-6448		PROGRAM ELEMENT NO. PROJECT NO. TASK NO. WORK UNIT NO.	
61102F		2305 CT	
11. TITLE (Include Security Classification)			
Quantum 1/f Noise in High Technology Applications Including Ultrasmall Structures and Devices			
12. PERSONAL AUTHOR(S)			
Dr. Peter H. Handel (Tel. 314/553-5021)			
13a. TYPE OF REPORT		13b. TIME COVERED	
First Annual Report		FROM 6/15/89 TO 6/14/90	
14. DATE OF REPORT (Yr., Mo., Day)		15. PAGE COUNT	
7/1/90		43	
16. SUPPLEMENTARY NOTATION			
17. COSATI CODES			
18. SUBJECT TERMS (Continue on reverse if necessary and identify by block number)			
Quantum 1/f Noise Theory, 1/f Noise, Electronic Noise in Semiconductor Devices, Quantum 1/f Effect, Bipolar Transistors, Noise in Ultrasmall Devices, Chaos, Nonlinear Dynamics			
19. ABSTRACT (Continue on reverse if necessary and identify by block number)			
Quantum 1/f noise is a basic property of physical cross sections and process rates and a form of quantum chaos in the nonlinear system of the charged particles plus the electromagnetic field. Therefore the present report starts with a consideration of the general problem of 1/f spectra in nonlinear systems, derives for the first time a general sufficient criterion which tells us if a system will show 1/f noise, and applies the new criterion to transport in semiconductors, in metals, on highways, and in quantum electrodynamics. In all these cases 1/f spectra follow from the same criterion, in the same way. This is, for the first time, a unifying principle. In addition, the report contains the first rigorous first principles derivation of quantum 1/f mobility fluctuations in semiconducting materials (analytical) and reference to a Monte Carlo simulation of the same problem. Finally, a solution for the long-standing problem of quantum 1/f noise in the collector of BJT's is proposed.			
20. DISTRIBUTION/AVAILABILITY OF ABSTRACT		21. ABSTRACT SECURITY CLASSIFICATION	
UNCLASSIFIED/UNLIMITED ☒ SAME AS RPT. ☐ DTIC USERS ☐		UNCLASSIFIED	
22a. NAME OF RESPONSIBLE INDIVIDUAL		22b. TELEPHONE NUMBER	
Dr. Gerald Witt		(Include Area Code) 202/767-4932	
		22c. OFFICE SYMBOL	
		NE	

QUANTUM 1/f NOISE IN HIGH TECHNOLOGY APPLICATIONS INCLUDING ULTRASMALL STRUCTURES AND DEVICES

FIRST ANNUAL REPORT

July 15, 1989 - July 14, 1990

AFOSR Grant #89-0416

July 15, 1990

Abstract

Accession For	
NTIS GRA&I	☒
DTIC TAB	☐
Unannounced	☐
Justification	
By	
Distribution/	
Availability Codes	
Dist	Avail and/or Special
A-1	



The fundamental fluctuations of physical cross sections and process rates in Quantum Electrodynamics are known as quantum 1/f effect, are limiting most high-technology applications, and are described by the simple quantum 1/f formula for the fractional spectral density, $S(f)=\alpha A/fN$. In spite of their basic character, they are a special case of 1/f chaos in nonlinear systems. The present report provides for the first time a sufficient criterion for the presence of a 1/f spectrum in a nonlinear system, proves its sufficient character, and exemplifies it for the current carriers in semiconductors, for electrons in metals, for cars on the highway, and for the nonlinear system of particle and field in electrodynamics. The report gives some of the rigorous first principles analytical calculation results for the quantum 1/f mobility fluctuations in electronic materials such as Si, GaAs, $Hg_{1-x}Cd_xTe$, etc., derived for the first time here under the present grant, on the basis of the quantum 1/f cross correlation formulas derived under the previous AFOSR Grant 85-0130. These quantum 1/f results give the conventional quantum 1/f noise as an analytical function of temperature, applied field, and all the physical parameters of the semiconductor material, allowing for optimization of the material for any given application. For the quantum 1/f noise in $Hg_{1-x}Cd_xTe$ we also developed a Monte Carlo computer simulation, which is currently being tested and improved, and which will be compared with results calculated analytically. Finally, a suggestion is presented, which provides an explanation of the discrepancies which have been noticed in the collector current 1/f noise of bipolar junction transistors.

CONTENTS

Abstract	2
I. Introduction	4
II. A sufficient Criterion for $1/f$ Noise in Nonlinear Systems	5
III. Examples	9
III.1 Classical Turbulence Theory for the Current Carriers in Semiconductors	9
III.2 Turbulence Theory for Drude Electrons in Metals	14
III.3 Theory of Highway Traffic Fluctuations	15
III.4 Quantum $1/f$ Noise (QED)	21
IV. Analytical Calculation of Mobility Fluctuations in Semiconductors, based on the Quantum $1/f$ Cross Correlation Formula	22
IV.1 Impurity Scattering	23
IV.2 Acoustic Electron-Phonon Scatterining	24
IV.3 Non-Polar Optical Phonon Scattering	25
V. Calculation of Collector $1/f$ Noise in BJT's	25
VI. References	27
VII. Papers Published During this Grant Period	29
VIII.General Quantum $1/f$ Bibliography	31

I. INTRODUCTION

Progress has been achieved during 1989 and 1990 in the study of nonlinear systems which generate chaotic $1/f$ fluctuations, in the application of the Quantum $1/f$ Theory¹⁻³ to various materials used in small and ultrasmall electronic devices, and in the application of the Quantum $1/f$ Theory to electronic devices.

The close similarity of the classical and quantum $1/f$ theories, and the initial development of the quantum $1/f$ theory by the author out of his efforts to quantize his classical turbulence theory, have led to sustained efforts of the author aimed to integrate all his theories as various forms or realizations of a fundamental notion of chaos in nonlinear systems. During this grant period, these efforts finally beared fruits. A general sufficient criterion was formulated, allowing to identify the nonlinear systems which exhibit $1/f$ spectra. This criterion is presented for the first time in Sec. II below. It is followed in Sec. III by examples, in which the criterion is applied to the classical and quantum mechanical forms of the author's $1/f$ noise theory. These examples clarify the physical meaning of the new criterion.

For the practical application of the Quantum $1/f$ Theory it is necessary to derive the quantum $1/f$ fluctuations of various kinetic (transport) coefficients which characterize the materials used in electronic and microelectronic applications, from the author's fundamental quantum $1/f$ formula. The latter is applicable only to cross sections and rates of elementary processes. Most important is the calculation of mobility fluctuations in Si, GaAs and $\text{Hg}_{1-x}\text{Cd}_x\text{Te}$. An earlier calculation (Kousik, Van Vliet, Handel, 1985) of mobility fluctuations in Si and GaAs is replaced in Sec. IV by a more rigorous calculation, based on the new quantum $1/f$ cross-correlations, developed under the previous AFOSR Grant, and presented in the Final Technical Report AFOSR -85-0130. The new calculation yields increased $1/f$ noise, and is in very good agreement with the experiment. Although not presented here yet, we also performed a Monte Carlo simulation for HgCdTe during this period. The simulation has yet to be improved and compared with the experiment.

Finally, we have tried to improve the application of quantum 1/f theory to the collector noise of bipolar transistors. This short calculation is presented in Sec. V.

In the same time, many new contributions to the quantum 1/f theory and experiment were published by other workers in the field, considerably advancing the field of infra-quantum physics and quantum 1/f noise in high-technology applications. These new contributions, as well as new PhD thesis work in this field and contributions presented at the IV Conference on Quantum 1/f Noise and other Low-Frequency Fluctuations, are included in the updated General Quantum 1/f Bibliography appended to this Report.

II. A SUFFICIENT CRITERION FOR 1/F NOISE IN NONLINEAR SYSTEMS

Consider a n-dimensional nonlinear system described in terms of the dimensionless function $Y(x,t)$ by the m^{th} order nonlinear dynamical equation

$$dY/dt + F(x, Y, dY/dx_1 \dots dY/dx_n, d^2Y/dx_1^2 \dots d^mY/dx_n^m) = 0 \quad (1)$$

If

$$\begin{aligned} F[\lambda x, Y, dY/(\lambda dx_1) \dots dY/(\lambda dx_n), d^2Y/(\lambda dx_1)^2 \dots d^mY/(\lambda dx_n)^m] \\ = \lambda P F(x, Y, dY/dx_1 \dots dY/dx_n, d^2Y/dx_1^2 \dots d^mY/dx_n^m) \end{aligned} \quad (2)$$

for any real number λ , Eq. (1) is said to be homogeneous. Performing a Fourier transformation with respect to the vector x , we get in terms of the Fourier-transformed wavevector k the nonlinear integro-differential equation

$$dy(k,t)/dt + G[k, y(k,t), k_1 y(k,t) \dots k_n y(k,t), k_1^2 y(k,t) \dots k_n^m y(k,t)] = 0, \quad (3)$$

where $y(k,t)$ is the Fourier transform of $Y(x,t)$. Due to Eq. (2), G satisfies the relation

$$G[\lambda \mathbf{k}, \mathbf{y}, \lambda k_1 \mathbf{y} \dots \lambda k_n \mathbf{y}, (\lambda k_1)^2 \mathbf{y} \dots (\lambda k_n)^m \mathbf{y}] \\ = \lambda P G[\mathbf{k}, \mathbf{y}, k_1 \mathbf{y} \dots k_n \mathbf{y}, k_1^2 \mathbf{y} \dots k_n^m \mathbf{y}]. \quad (4)$$

Eq. (3) can thus be rewritten in the form

$$dy/d(t/\lambda P) + G[\lambda \mathbf{k}, \mathbf{y}, \lambda k_1 \mathbf{y} \dots \lambda k_n \mathbf{y}, (\lambda k_1)^2 \mathbf{y} \dots (\lambda k_n)^m \mathbf{y}] = 0, \quad (5)$$

Taking $\lambda=1/k$, where $k=|\mathbf{k}|=(x_1^2+\dots+x_n^2)^{1/2}$, and setting $kPt=z$, we notice that k has been eliminated from the dynamical equation, and only $\mathbf{k}/k$ is left. This means that there is no privileged scale left for the system in $\mathbf{x}$ or $\mathbf{k}$ space, other than the scale defined by the given time t , and expressed by the dependence on z . We call this property of the dynamical system "*sliding-scale invariance*".

In certain conditions, instabilities of a solution of Eq. (1) may generate chaos, or turbulence. In a sufficiently large system described by the local dynamical equation (1), in which the boundary conditions become immaterial, homogeneous, isotropic turbulence, (chaos) can be obtained, with a spectral density determined only by Eq. (1). The stationary autocorrelation function $A(\tau)$ is defined as an average over the turbulent ensemble

$$A(\tau) = \langle \mathbf{Y}(\mathbf{x}, t) \mathbf{Y}(\mathbf{x}, t+\tau) \rangle = \int \langle \mathbf{y}(\mathbf{k}, t) \mathbf{y}(\mathbf{k}, t+\tau) \rangle d^n \mathbf{k} = \int u(\mathbf{k}, z) d^n \mathbf{k} \quad (6)$$

Here we have introduced the scalar

$$u(\mathbf{k}, z) = \langle \mathbf{y}(\mathbf{k}, t) \mathbf{y}(\mathbf{k}, t+\tau) \rangle \quad (7)$$

of homogeneous, isotropic chaos (turbulence), which depends only on $|\mathbf{k}|$ and $z=kP\tau$. All integrals are from minus infinity to plus infinity. The chain of integro-differential equations for the correlation functions of any order obeys the same sliding-scale invariance which we have noticed in the fundamental dynamical equation above. *Therefore, in isotropic, homogeneous, conditions, u can only depend on k and z .* Furthermore, the

direct dependence on k must reflect this sliding-scale invariance, and is therefore of the form

$$u(k,z) = k^{-n}v(z). \quad (8)$$

Indeed, only this form insures that $u(k,z)d^n k$ and therefore also the corresponding integrals and multiple convolutions in k space have the necessary sliding-scale invariance.

According to the Wiener-Khintchine theorem, the spectral density is the Fourier-transform of $A(t)$,

$$S_y(f) = \int e^{2\pi i f \tau} A(\tau) d\tau = (1/f) \int e^{2\pi i t'} \int k'^{-n} v(z) d^n k' dt' = C/f, \quad (9)$$

where we have set $f\tau=t'$, $k^n=fk'^n$, $z=k^n\tau=k'^n t'$, and the integral

$$C = \int e^{2\pi i t'} \int k'^{-n} v(z) d^n k' dt' = \int e^{2\pi i t'} \int k''^{-n} v(k''^n) d^n k'' dt' \quad (10)$$

is independent of f . We have defined the vector $k''=t'^{1/n} k$.

In conclusion, we have shown that if the equation

$$dY/dt + F(x, Y, dY/dx_1 \dots dY/dx_n, d^2Y/dx_1^2 \dots d^m Y/dx_n^m) = 0 \quad (11)$$

with

$$F[\lambda x, Y, dY/(\lambda dx_1) \dots dY/(\lambda dx_n), d^2Y/(\lambda dx_1)^2 \dots d^m Y/(\lambda dx_n)^m] = \lambda P F(x, Y, dY/dx_1 \dots dY/dx_n, d^2Y/dx_1^2 \dots d^m Y/dx_n^m) \quad (12)$$

admits, in the limit of weak dissipation, quasistationary homogeneous isotropic chaotic (turbulent) solutions which are practically independent of the nature of the instabilities or bifurcations (or even stirring forces) which have caused the chaotic state, the corresponding spectral density must be proportional to $1/f$.

We note that the solution (7) leads to a weak (logarithmic) divergence of the integral over k in the last form of Eq. (6) and in Eq. (9). This seems to contradict the fact that in practical applications the autocorrelation

function $A(t)$ is finite, and its value at $t=0$ is usually given in the problem at hand. However, in practice one never deals with an infinite volume, and the physical wave-vectors are also limited. For instance in fluid dynamics, wave vectors exceeding the reciprocal average distance between neighboring fluid molecules correspond to thermal motions, and are therefore no longer meaningful for the hydrodynamic treatment. Due to its logarithmic character, the divergence is thus without practical importance. Nevertheless, for a given level of chaos $A(0)$, we can construct an approximate solution

$$u(k,z)=k^{r-n}v(z), \quad (13)$$

with $0 < r < 1$, which avoids the divergence at $k=0$. To get the correct chaos level with $k < k_0$, k_0 being an upper cutoff, we set

$$u=r[A(0)/v(0)]k_0^{-r}k^{r-n}v(z). \quad (14)$$

This yields for $t=0$ the result $A(0)$ when we integrate over $d^n k$ with an upper limit k_0 . We notice that r is present both as a general factor, and as a small defect in the exponent of k . This is a general feature, present both in classical and quantum nonlinear systems with $1/f$ noise. In the limit $r \rightarrow 0$, the approximate solution tends to become exact. In the classical homogeneous, isotropic, turbulence theory, r can be arbitrarily small, while in the quantum $1/f$ theory (quantum electrodynamics), $r = \alpha A = (2\alpha/3\pi)(\Delta v/c)^2 \ll 1/137$ is the well-defined infrared exponent of the process, with $\alpha = e^2/\hbar c = 1/137$, as we know from the theory of infrared radiative corrections.

III. EXAMPLES

The general criterion developed in the preceeding section will now be illustrated on the basis of some examples.

III.1 Classical Turbulence Theory for the Current Carriers in Semiconductors

In the case of homogeneous, isotropic turbulence⁴⁻⁶ caused in the electron-hole plasma of an infinite sample of a symmetric intrinsic semiconductor by dynamical instabilities of any kind, we start from the equations

$$\mathbf{v}^+ = (e/2c)\mathbf{v}^- \times \mathbf{B} - (1/n)\nabla P, \quad (15)$$

$$\mathbf{v}^- = 2e[\mathbf{E} + \mathbf{v}^+ \times \mathbf{B}/c] - (2/n)\nabla(P_p - P_n), \quad (16)$$

$$\nabla \cdot \mathbf{v}^+ = 0 \quad (n = \text{const}), \quad (17)$$

$$\nabla \times \mathbf{E} = -(1/c)\partial \mathbf{B}/\partial t, \quad (18)$$

$$\nabla \times \mathbf{B} = 2\pi en\mathbf{v}^-/c, \quad (19)$$

$$\nabla \cdot \mathbf{B} = 0. \quad (20)$$

Here n is the total carrier concentration including an equal number of electrons and holes, v/e their reciprocal mobility assumed to be the same for electrons and holes, P_n and P_p the partial pressures of electrons and holes, P the total carrier pressure, $2\mathbf{v}^+$, $\mathbf{v}^-$ the sum and the difference of the carrier drift velocities. Inertial terms proportional to the effective masses of the carriers, as well as electrostatic terms and compressibility terms have been neglected here in a consistent way⁴⁻⁷, because we are interested in the low-frequency domain only. Although we do not work this out here, this system of equations can be shown to admit an energy theorem. Performing a Fourier expansion, we obtain

$$\mathbf{v}\mathbf{v}^+(\mathbf{k}) = (e/2c)\sum_{\mathbf{k}'} \mathbf{v}^-(\mathbf{k}') \times \mathbf{B}(\mathbf{k}-\mathbf{k}') - (i/n)\mathbf{k} \cdot \mathbf{P}(\mathbf{k}), \quad (21)$$

$$\mathbf{v}\mathbf{v}^-(\mathbf{k}) = 2e[\mathbf{E}(\mathbf{k}) + \sum_{\mathbf{k}'} \mathbf{v}^+(\mathbf{k}') \times \mathbf{B}(\mathbf{k}-\mathbf{k}')/c] - (2i/n)\mathbf{k}(P_p - P_n), \quad (22)$$

$$\mathbf{k} \cdot \mathbf{v}^+(\mathbf{k}) = 0. \quad (23)$$

$$i\mathbf{k} \times \mathbf{E}(\mathbf{k}) = -(1/c)\partial \mathbf{B}(\mathbf{k})/\partial t, \quad (24)$$

$$i\mathbf{k} \times \mathbf{B}(\mathbf{k}) = 2\pi en \mathbf{v}^-(\mathbf{k})/c, \quad (25)$$

$$\mathbf{k} \cdot \mathbf{B}(\mathbf{k}) = 0, \quad (26)$$

Substituting $\mathbf{E}$ from Eq. (22) into Eq. (24), we obtain with Eq. (25)

$$\partial \mathbf{B}(\mathbf{k})/\partial t + \mu k^2 \mathbf{B}(\mathbf{k}) = i\mathbf{k} \times \sum_{\mathbf{k}'} \mathbf{v}^+(\mathbf{k}') \times \mathbf{B}(\mathbf{k}-\mathbf{k}'), \quad (27)$$

where $\mu = c^2 v / 4\pi n e^2$. Eqs. (21) and (25) yield

$$\begin{aligned} \mathbf{v}^+(\mathbf{k}) = (i/4\pi v n) \sum_{\mathbf{k}''} \{ & \mathbf{B}(\mathbf{k}'') [\mathbf{k}'' \cdot \mathbf{B}(\mathbf{k}-\mathbf{k}'')] - \mathbf{k}'' [\mathbf{B}(\mathbf{k}'') \cdot \mathbf{B}(\mathbf{k}-\mathbf{k}'')]] \\ & - (\mathbf{k}/k^2)(1-\delta_{\mathbf{k},0}) [\mathbf{k}'' \cdot \mathbf{B}(\mathbf{k}-\mathbf{k}'') \mathbf{k} \cdot \mathbf{B}(\mathbf{k}'') - \mathbf{B}(\mathbf{k}'') \cdot \mathbf{B}(\mathbf{k}-\mathbf{k}'') (\mathbf{k} \cdot \mathbf{k}'')]] \}. \end{aligned} \quad (28)$$

Substituting this into Eq. (27), we obtain the fundamental dynamical field-equation of turbulence in the electron-hole plasma of a symmetric intrinsic semiconductor

$$\begin{aligned} \partial b_{\beta}(\mathbf{k},t)/\partial t + \mu k^2 b_{\beta}(\mathbf{k},t) = \sum_{\mathbf{k}'} \mathbf{k}'' b_j(\mathbf{k}-\mathbf{k}',t) b_l(\mathbf{k}'',t) b_m(\mathbf{k}'-\mathbf{k}'',t) \\ \cdot (k_j \delta_{\beta s} - k_s \delta_{\beta j}) [k_s \delta_{lm} - k_m'' \delta_{ls} + (k_s'/k'^2)(1-\delta_{\mathbf{k}',0})(k_m'' k_l' - \mathbf{k}' \cdot \mathbf{k}'' \delta_{lm})], \end{aligned} \quad (29)$$

in terms of $\mathbf{b} \equiv \mathbf{B}/\sqrt{2\pi v n}$. This dynamical equation has the form of Eq. (3), with $p=2$ in Eq. (4), and with G defined as the r.h.s. minus the term in k^2 on the l.h.s.. Our sufficient criterion thus tells us that this nonlinear system will yield a $1/f$ spectrum. We present below the direct derivation for this example.

Multiplying Eq. (29) with $b_\alpha^*(\mathbf{k}, t-\tau)$ and taking the average over a statistical ensemble which represents our notion of stationary turbulence, we obtain in quasi-stationary conditions

$$\begin{aligned} & \partial w_{\alpha\beta}(\mathbf{k}, \tau) / \partial \tau + \mu k^2 w_{\alpha\beta}(\mathbf{k}, \tau) \\ &= \sum_{\mathbf{k}' \mathbf{k}''} \langle b_\alpha^*(\mathbf{k}, t-\tau) b_j(\mathbf{k}-\mathbf{k}', t) b_l(\mathbf{k}'', t) b_m(\mathbf{k}'-\mathbf{k}'', t) \rangle R_{jlm\beta}, \end{aligned} \quad (30)$$

with $w_{\alpha\beta}(\mathbf{k}, \tau) \equiv (L/2\pi)^3 \langle b_\alpha^*(\mathbf{k}, t-\tau) b_\beta(\mathbf{k}, t) \rangle$, where L is the edge of the cubic normalization box, and

$$R_{jlm\beta} \equiv (k_j \delta_{\beta s} - k_s \delta_{\beta j}) [k_s \delta_{lm} - k_m'' \delta_{ls} + (k_s'/k'^2)(1 - \delta_{\mathbf{k}', 0})(k_m'' k_l' - \mathbf{k}' \cdot \mathbf{k}'' \delta_{lm})]. \quad (31)$$

Multiplying Eq. (29) with more magnetic field components and averaging, we obtain equations connecting the fourth-order correlation tensor to the sixth-order tensor, and so on⁴⁻⁷. To end this infinite chain of equations for the correlation functions, we make a quasinormality assumption which expresses the fourth-order moment appearing in Eq. (30) according to the scheme

$$\langle ABCD \rangle = \langle AB \rangle \langle CD \rangle + \langle AC \rangle \langle BD \rangle + \langle AD \rangle \langle BC \rangle, \quad (32)$$

valid if the four field components would approximate a joint normal distribution. This approximation does not alter the homogeneity of the system, which ultimately causes the $1/f$ spectrum. This approximation yields the closed equation

$$\begin{aligned} & \partial w_{\alpha\beta}(\mathbf{k}, \tau) / \partial \tau + \mu k^2 w_{\alpha\beta}(\mathbf{k}, \tau) \\ &= (2\pi/L)^3 w_{\alpha j}(\mathbf{k}, \tau) \sum_{\mathbf{k}'} w_{lm}(\mathbf{k}', 0) R_{jlm\beta}(\mathbf{k}, \mathbf{k}'). \end{aligned} \quad (33)$$

Isotropic turbulence requires $w_{\alpha\beta} = A_1(k) \delta_{\alpha\beta} + A_2(k) k_\alpha k_\beta$, with coefficients A_1 and A_2 related through Eq. (26), yielding

$$w_{\alpha\beta}(\mathbf{k}, \tau) = (1/2) [\delta_{\alpha\beta} - k_\alpha k_\beta / k^2] u(k, \tau), \quad (34)$$

where $u(k, \tau) = \sum_{\alpha} w_{\alpha\alpha}(k, \tau)$. Therefore, the scalar correlation function $u(k, \tau)$ satisfies the dynamical equation of homogeneous, isotropic, stationary turbulence

$$\frac{\partial v(k, x)}{\partial |x|} + v(k, x) = -\frac{1}{2}v(k, x) \int \frac{d^3 k'}{k'^3} \frac{k^2 + k \cdot k'}{(k + k')^2} \left[1 - \left(\frac{k \cdot k'}{kk'} \right)^2 \right] v(k', 0), \quad (35)$$

where $v(k, x) \equiv k^{-3}u(k, \tau)$, and $x = \mu\tau k^2$ is a dimensionless variable replacing τ . We convince ourselves that the integral is independent of k , provided $v(k, x)$ does not depend on its first argument, by setting $k'/k \equiv \kappa$. This yields a solution. However, with $v = e^{-m|x|}$ we get a logarithmic divergence at $\kappa=0$. We look for an exact solution of the form⁴⁻⁷

$$v(k, x) = h k^{\epsilon} e^{-|x|m(k)}, \quad \text{or} \quad u(k, x) = (h/k^{3-\epsilon}) e^{-|x|m(k)}, \quad (36)$$

where $m(k)$ is very close to a constant, almost independent of k , and h is a constant proportional to the intensity of the turbulence, or the turbulence level. Substituting this into Eq. (35) and performing the integration, we obtain a finite result only for $0 < \epsilon < 2$:

$$m(k) = 1 + h r(\epsilon) k^{\epsilon}, \quad \text{with } r(\epsilon) = [2\pi^2 \cotan(\epsilon\pi/2)] / [(1-\epsilon^2)(3-\epsilon^2)]. \quad (37)$$

We notice that $m(k)$ is indeed practically constant when $0 < \epsilon \ll 1$ is very small, arbitrarily small. The value $\epsilon=0$ leads to a logarithmic divergence, but we can set $\epsilon=0$ for practical purposes.

The spectral density corresponding to Eq. (36) with $\epsilon=0$ is

$$\begin{aligned} w_{\alpha\beta}(\omega) &= (1/\pi) \int_0^{\infty} \cos \omega \tau d\tau \int w_{\alpha\beta}(k, \tau) d^3 k \\ &= \frac{4}{3} \delta_{\alpha\beta} \int_0^{\infty} k^2 dk \int_0^{\infty} d\tau u(k, \tau) \cos \omega \tau = \frac{4}{3} h \delta_{\alpha\beta} \int_0^{\infty} \frac{m k dk}{\omega^2 + m^2 k^2} = \frac{\pi}{3} \frac{h}{\omega} \delta_{\alpha\beta}. \end{aligned} \quad (38)$$

This is a $1/f$ spectrum. At the low frequency end we do not get a divergent spectral integral, because the more exact form of the spectrum with a finite small $\varepsilon \ll 1$ is⁴⁻⁷

$$\int_0^{\infty} \frac{mk^{1+\varepsilon} dk}{\omega^2 + m^2 k^4} = \frac{1}{\omega^{1-\varepsilon/2} m^{\varepsilon/2}} \int_0^{\infty} \frac{x^{1+\varepsilon} dx}{1+x^4}, \quad (39)$$

which is proportional to $f^{\varepsilon/2-1}$. It is interesting to note that for $\varepsilon \ll 1$ $\cotan \varepsilon\pi/2 \approx 2/\varepsilon\pi$ in Eq. (37), and that the value of ε calculated from Eq. (37) is therefore proportional to $\hbar$, or to the intensity of the turbulence. This feature of the classical theory⁴⁻⁷ is expressed with fascinating clarity in the quantum form of the theory, where ε is replaced by $2\alpha A$ which also appears as a intensity factor multiplying the quantum $1/f$ noise.

The essential element which led to the $1/f$ spectrum in the classical turbulence theory is the *nonlinearity* of the equations of motion, caused by the reaction of the electric currents back on themselves via the generated electromagnetic field. The same feedback reaction, via the electromagnetic field, also caused the nonlinearity in the quantum $1/f$ theory, and in QED in general, leading in the same way to an identical $1/f$ spectrum, this time with a physically more meaningful $\varepsilon=2\alpha A$. This *nonlinearity* induces the coupling between various scales of turbulence and leads to the dynamical equilibrium between eddies of all sizes, expressed by the $1/f$ spectrum. In the $\varepsilon=0$, or $\alpha A=0$, limit, this dynamical equilibrium assumes both for the quantum case and for homogeneous, isotropic, turbulence in the unbounded semiconductor sample the simplest form, characterized by scale-homogeneity, or scale invariance. Indeed, replacing for $\varepsilon=0$ in Eqs. (35) and (36) k and k' by λk and $\lambda k'$, while also replacing τ by τ/λ^2 , (or ω by $\lambda^2\omega$), Eq. (35) is not affected, and λ drops out. We conclude that *in the weak turbulence limit ($\varepsilon=0$) we obtain perfect self-similarity of the turbulence process at all scales in space and time, classically and quantum-mechanically*. The implied scale invariance is caused by the absence of any characteristic length or time scale, or by the presence of a sliding scale. Indeed, the frequency scale μk^2 is a function

of the size of the eddies, given by the wave number k which can have any value. The actual frequency and wave-number spectra are closely related fractals, but in the weak-turbulence limit they approach an exact $1/f$ and $1/k^3$ spectrum respectively. In fact, we are here understanding the nonlinear dynamics which shapes this fractal for the first time.

III.2 Turbulence Theory for Drude Electrons in Metals

Our classical turbulence theory can be extended to the case of metals or degenerate extrinsic semiconductors⁷ in the Drude model. The system of integro-differential equations is quite different,

$$\mathbf{v}\mathbf{v}^+ = -e\mathbf{E} - (e/c)\mathbf{v}\times\mathbf{B} - (1/n)\nabla P \quad (40)$$

$$\nabla\times\mathbf{E} = -(1/c)\partial\mathbf{B}/\partial t \quad (41)$$

$$\nabla\times\mathbf{B} = -(4\pi en/c)\mathbf{v} \quad (42)$$

$$\nabla\cdot\mathbf{B} = 0, \quad (43)$$

and leads to a third-order nonlinearity⁷ in the resulting closed equation of motion, or nonlinear field-equation, which replaces Eq. (28):

$$\partial\mathbf{B}(\mathbf{k},t)/\partial t + \nu k^2\mathbf{B}(\mathbf{k},t) = -(c/4\pi ne)\mathbf{k}\times\int d^3k'\mathbf{B}(\mathbf{k}-\mathbf{k}',t)\times[\mathbf{k}'\times\mathbf{B}(\mathbf{k}',t)]. \quad (44)$$

This is again in the form of Eq. (3), with $p=2$ in Eq. (4). We thus expect a $1/f$ spectrum in this system as well. This time we only sketch the derivation. The corresponding infinite chain of equations for the correlation tensors now goes in steps of one. As was shown above, it went in steps of two for semiconductors. The third-order correlation can be eliminated between the first and second equations in the chain. The resulting dynamical equation⁷ for homogeneous, isotropic, stationary turbulence, which replaces Eq. (35), with the same notations, using $\mathbf{e}_3$ as the unit vector of the third axis, is

$$\begin{aligned}
& - \frac{\partial^2 v(k, x)}{\partial x^2} + v(k, x) \\
& = - \frac{1}{2} \int \frac{d^3 \kappa}{\kappa^3} \frac{1 + \kappa \cdot \mathbf{e}_3}{|\mathbf{e}_3 + \kappa|^3} \left[1 - \frac{(\kappa \cdot \mathbf{e}_3)^2}{\kappa^2} \right] v(\kappa, \kappa^2 x) v(k | \mathbf{e}_3 + \kappa |, x | \mathbf{e}_3 + \kappa |^2). \quad (45)
\end{aligned}$$

This also admits, in the $\varepsilon=0$ limit of weak turbulence, a solution $v(k, x)$ which does not depend on the first argument, and $u(k, x) = k^{-3} e^{-x m(x)}$, this time with an x -dependent m . With the change of variables $t = \omega \tau$ and $k' = k/\sqrt{\omega}$ in the second (middle, involving u) form of Eq. (38), x remains invariant, and a factor $1/\omega$ will appear in front of the integrals which themselves will just yield a constant factor independent of ω , τ or k . We thus obtain again a universal $1/f$ spectrum. As is shown in detail elsewhere⁷, this $1/f$ spectrum is expressed in the corresponding current and voltage fluctuations which can be observed in the semiconductor or metallic medium. We conclude that the $1/f$ spectrum is a general property of electrically conducting systems in interaction with the electromagnetic field, a property which is caused by the nonlinearity of the system of carriers and field in mutual interaction due to the absence of a characteristic scale in the nonlinear equation of motion, and which finds its clearest expression in the Quantum $1/f$ Effect.

III.3 Theory of Highway Traffic Fluctuations

Musha and Higuchi^{8,9} discovered the $1/f$ spectrum of highway traffic fluctuations empirically in 1977, also developing a model based on a postulated linear dependence of the average traffic speed v on the linear concentration of cars $n(x)$ on the road, $v = v_0(1 - n/n_s)$. The model was recognized to be similar to Burger's model of turbulence, and was simulated numerically leading to a $1/f$ -like spectrum at low frequencies.

The present paper develops a statistical turbulence theory for the Musha model, showing how in the low wave number and low frequency limit a universal $1/f$ spectrum emerges. In this limit, this is a particular case of the author's sliding-scale-invariant class of nonlinear systems, all characterized by the presence of a universal $1/f$ spectrum. The author's classical^{10,11} and quantum¹² $1/f$ theory is another example in the same class¹³.

Musha writes the traffic current J as a sum of drift and diffusion currents

$$J = nv - D\partial n/\partial x = nv_0 - (v_0/n_s)n^2 - D\partial n/\partial x, \quad (46)$$

where D is a "diffusion coefficient". The equation of continuity is^{8,9}

$$0 = \partial n/\partial t + \partial J/\partial x \equiv (\partial/\partial t + v_0\partial/\partial x)n - 2(v_0/n_s)n\partial n/\partial x - D\partial^2 n/\partial x^2. \quad (47)$$

This is Musha's fundamental equation of traffic dynamics, which also was written⁸ in a system of reference defined by

$$x' = -x + v_0 t, \quad t' = t \quad (48)$$

in the final form⁸

$$\partial n/\partial t' + a\partial n/\partial x' = D\partial^2 n/\partial x'^2, \quad (49)$$

where $a \equiv 2v_0/n_s$.

We normalize the concentration to $n_s/2$, the coordinate along the road x to D/v_0 , and the time to D/v_0^2 , thereby obtaining the dimensionless form of the fundamental traffic-dynamical equation

$$\partial n(x,t)/\partial t + n(x,t)\partial n(x,t)/\partial x = \partial^2 n(x,t)/\partial x^2, \quad (50)$$

where we did not bother to change the notation, and returned to the original unprimed notation. Expanding in a Fourier series over the interval L , we obtain

$$\partial n/\partial t + i\sum_k k' n(k')n(k-k') = -k^2 n(k,t). \quad (51)$$

Comparing Eq. (50) with Eqs. (1),(2), or Eq. (51) with Eqs. (3),(4), we notice that this time our criterion is not satisfied, due to the r.h.s. term. However, in the limit of small k that term becomes negligible, and thus, our criterion becomes applicable, and we should get a $1/f$ spectrum in the

low frequency limit. This would correspond to $p=1$ in Eqs. (2) and (3). We derive this $1/f$ spectrum below.

Defining the autocorrelation function

$$A(\xi, \tau) \equiv \langle n^*(x, t) n(x + \xi, t + \tau) \rangle = \sum_k \langle n^*(k, t) n(k, t + \tau) \rangle e^{ik\xi} = \sum_k U(k, \tau) e^{ik\xi}, \quad (52)$$

as a turbulent ensemble average $\langle \dots \rangle$, in quasistationary homogeneous conditions we obtain by multiplication of Eq. (51) with $n^*(k, t - \tau)$, after ensemble averaging,

$$\partial U / \partial \tau + k^2 U(k, \tau) + i \sum_{k'} k' \langle n^*(k, t - \tau) n(k', t) n(k - k', t) \rangle = 0. \quad (53)$$

Linking the complex function $U(k, \tau)$ to a third-order correlation function, this is the first equation of an infinite chain of equations connecting the N^{th} order to the order $N+1$ correlation function. Applying the operator $-\partial/\partial\tau + k^2$ to Eq. (53), and using the complex conjugate of Eq. (51) to define the action of this operator on the first factor inside the averaging brackets in Eq. (53), we obtain

$$\begin{aligned} -\partial^2 U / \partial \tau^2 + k^4 U &= -i \sum_{k'} k' \langle [i \sum_{k''} k'' n^*(k'', t - \tau) n^*(k - k'', t - \tau)] n(k', t) n(k - k', t) \rangle \\ &\approx \sum_{k', k''} k' k'' [U(k'', 0) U(k', 0) \delta_{k, 0} + U(k', \tau) U(k - k', \tau) \delta_{k'' k'} + U(k', \tau) U(k - k', \tau) \delta_{k'' k - k'}]. \end{aligned} \quad (54)$$

The last form was obtained by approximating the fourth-order correlation function with its expression in terms of the second-order correlation applicable for Gaussian processes:

$$\langle ABCD \rangle = \langle AB \rangle \langle CD \rangle + \langle AC \rangle \langle BD \rangle + \langle AD \rangle \langle BC \rangle. \quad (55)$$

This approximation was used by Heisenberg¹⁴ in his turbulence theory, and was successfully verified in its practical applicability by Uberoi¹⁵ and Batchelor¹⁶.

In the limit $L \rightarrow \infty$, setting $U(k, \tau) L / 2\pi = u(k\tau)$, we write for $k \neq 0$ Eq. (54) in the form

$$-\partial^2 u / \partial \tau^2 + k^4 u = \int [k'^2 u(k', \tau) u(k - k', \tau) + k'(k - k') u(k', \tau) u(k - k', \tau)] dk'$$

or

$$-\partial^2 u(k, \tau) / \partial \tau^2 + k^4 u(k, \tau) = k \int k' u(k', \tau) u(k-k', \tau) dk'. \quad (56)$$

This is our fundamental dynamical equation of traffic turbulence. All unspecified limits on integrals are from $-\infty$ to ∞ , as we mentioned earlier. From the symmetry $A(\xi, \tau) = A(-\xi, -\tau) = A^*(\xi, \tau)$ we see that a physically acceptable solution of this equation must satisfy the conditions

$$u(k, \tau) = u(-k, -\tau) = u^*(-k, -\tau) = u^*(k, -\tau). \quad (57)$$

A solution of the form

$$u(k, \tau) = V(k) e^{-imk\tau}, \text{ with } V(k) = V(-k) = V^*(k) \quad (58)$$

where m is a real constant, substituted into Eq. (56), yields

$$k(m^2 + k^2)V(k) = \int k' V(k') V(k-k') dk'. \quad (59)$$

In the low wave number region $k \ll 1$ (i.e., $k \ll v_0/D$) we neglect the k^2 term which arises from diffusion, and get

$$m^2 k V(k) = \int k' V(k') V(k-k') dk'. \quad (60)$$

A solution $V(k) = C|k|^{\epsilon-1}$, with arbitrarily small $\epsilon > 0$, yields the value of C , independent of k only in the limit of $\epsilon \rightarrow 0$:

$$\begin{aligned} m^2/C &= \int_{-\infty}^{\infty} k' |k'|^{\epsilon-1} |1-k'/k|^{\epsilon-1} dk'/k = |k|^{\epsilon} \int_{-\infty}^{\infty} \kappa |\kappa|^{\epsilon-1} |1-\kappa|^{\epsilon-1} d\kappa \\ &= |k|^{\epsilon} \int_0^2 |\kappa|^{\epsilon} |1-\kappa|^{\epsilon-1} d\kappa \approx 2/\epsilon = 1 \approx \text{const}, \end{aligned} \quad (61)$$

where we used the substitution $k'/k=\kappa$. The divergence at $\varepsilon=0$ disappears when we return to a finite value of the maximal road length L , which corresponds to a minimal k (or k') value $k_0=2\pi/L$, and transforms the integrals back into sums.

Eq. (61) establishes a proportionality between the level of the turbulence, described by C , and the magnitude of the small parameter ε as in earlier turbulence calculations^{10,11}. The same fundamental feature is more clearly expressed, without the pseudo-singularities present here, in the quantum $1/f$ theory¹², where ε becomes the infrared exponent αA known from quantum electrodynamics. Indeed, αA is present there, just as we see it come in here, both as a factor in front of the final result, and as a small defect in the exponent of the frequency. We also mention that the apparent absolute determination of C by Eq. (61) is just an artifact which reminds us that we omitted a source term in Eqs. (47), (49-51), (53-54), (56), which comes in as a δ function of time, $h(k)\delta(t)$ on the r.h.s. of Eq. (53), only if we assume the excitation in Eq. (47) to depend on time like white noise. Once that source term is written explicitly, it will allow us to determine C as this was done earlier¹¹ for a different equation, and it does not affect our equations for $\tau \neq 0$.

We can rewrite Eq. (52) in the form

$$\begin{aligned} A(\xi, \tau) &\equiv \langle n^*(x, t) n(x + \xi, t + \tau) \rangle = \sum_k U(k, \tau) e^{ik\xi} \equiv \int dk u(k, \tau) e^{ik\xi} \\ &= C \int e^{ik(\xi - m\tau)} |k|^{\varepsilon-1} dk = |\xi - m\tau|^{-\varepsilon} (m^2/l) \int e^{i\kappa} |\kappa|^{\varepsilon-1} d\kappa \approx m^2 |\xi - m\tau|^{-\varepsilon}. \end{aligned} \quad (62)$$

Here we have used the substitution $k|\xi - m\tau| = \kappa$, and we have taken the limit $\varepsilon \rightarrow 0$ in the integral and in l , noting that they exhibit the same divergence, and therefore can be simplified in the limit. The cancellation of the divergences in the expression of the autocorrelation function shows that this important function is finite even in the continuum limit. It is only the spectral distribution of turbulence which exhibits a singularity at low wave numbers and frequencies.

Since only the limit $\varepsilon=0$ satisfies the fundamental dynamical equation of traffic turbulence, Eq. (62) means that the autocorrelation function is a constant. It also indicates that the constant has to be interpreted as the limit of a slowly decreasing power law which depends

only on $|\xi-\tau|$; therefore the spectrum in wave numbers is the same as the spectrum in frequencies. The Fourier transform with respect to τ is the spectral density

$$S_n'(\xi, \omega) = \int \langle n^*(x, t) n(x + \xi, t + \tau) \rangle e^{i\omega\tau} d\tau = C \iint (dk/|k|^{1-\varepsilon}) e^{ik(\xi - m\tau) + i\omega\tau} d\tau. \quad (63)$$

To leave the moving (primed) frame and return to the system of reference at rest, we replace ω by $\omega - kv_0$ in the last integrand, actually just by $\omega - k$ in our ($v_0=1$) normalization:

$$\begin{aligned} S_n(\xi, \omega) &= \int \langle n^*(x, t) n(x + \xi, t + \tau) \rangle e^{i(\omega - kv_0)\tau} d\tau \\ &= C \iint (dk/k^{1-\varepsilon}) e^{ik(\xi - m\tau) + i(\omega - k)\tau} d\tau. \end{aligned} \quad (64)$$

The spectral density of concentration fluctuations in a given point is obtained by setting $\xi=0$. The integration with respect to τ yields a delta function $2\pi\delta[\omega - (m+1)k]$, and we finally obtain the spectrum

$$S_n(0, \omega) = C[(m+1)/\omega]^{1-\varepsilon} \quad (65)$$

where again the constant will turn out to be finite when we coarse grain the integrals. As mentioned above, the constant will actually be determined by the excitation term omitted in Eq. (56).

According to Eq. (2) we can write $J(k, \omega) = (\omega/k)n(k, \omega)$ in the system at rest. Therefore, for J we include a factor $(\omega/k)^2$ into the integrand of Eq. (64), and we get again the spectrum

$$\begin{aligned} S_J(\xi, \omega) &= \int \langle J^*(x, t) J(x + \xi, t + \tau) \rangle e^{i(\omega - kv_0)\tau} d\tau \\ &= C \iint (\omega^2 dk/k^{3-\varepsilon}) e^{ik(\xi - m\tau) + i(\omega - k)\tau} d\tau; \end{aligned} \quad (66)$$

$$S_J(0, \omega) = C(m+1)^2 [(m+1)/\omega]^{1-\varepsilon} \approx \text{Const}/\omega. \quad (67)$$

Due to the neglect of the k^2 term in Eq. (59), the universal $1/f$ spectrum will be limited towards high frequencies by $\omega < v_0^2/D$, and the $1/k$ -spectrum by $k < v_0/D$. This limitation occurs because only Eq. (60) satisfies the condition of being free of any characteristic scale, thus

exhibiting our sliding scale invariance¹³, while Eq. (59) does not have this property. We have thus constructed a statistical dynamic theory of traffic turbulence, proving analytically Musha's earlier result, without any pretension of mathematical rigor. Traffic turbulence arising from instabilities of the laminar traffic flow can be considered as a form of classical fluid-dynamical chaos.

III.4 Quantum 1/f Noise (QED)

The nonlinearity causing the 1/f spectrum of turbulence in both semiconductors and metals is the reaction of the field generated by charged particles and their currents back on themselves. The same nonlinearity is present in quantum electrodynamics (QED), causes the infrared divergence, infrared radiative corrections for cross sections and process rates, and causes the quantum 1/f effect. The basic equations of QED are

$$\partial_\mu \partial^\mu A^\nu = J^\nu, \quad J^\nu = -ie\psi\gamma^\nu\psi, \quad (68)$$

$$(\partial_\mu \gamma^\mu + m)\psi = -ieA^\nu \gamma_\nu \psi \quad (69)$$

Here ∂_μ is a shorthand for $\partial/\partial x_\mu$, γ^μ are the Dirac matrices, the Greek indices run from 0 to 3, and ψ is the Dirac spinor field.

We can formally solve Eq. (68) for the potential A^ν in momentum space (i.e. by Fourier transforming)

$$A^\nu = (1/\partial^\mu \partial_\mu) J^\nu, \quad (70)$$

which can be substituted into Eq. (70), yielding with the expression (68) of the current J^ν ,

$$(\partial_\mu \gamma^\mu + mc/\hbar)\psi = -\alpha[(1/\partial^\mu \partial_\mu)\psi\gamma^\nu\psi]\gamma_\nu\psi. \quad (71)$$

The integral operator $(1/\partial^\mu \partial_\mu)$ has a kernel $1/q^2$, where q is the Fourier four-vector corresponding to x . Eq. (71) contains a third-order nonlinearity and is therefore similar to the dynamical equation (29) describing turbulence in semiconductors. In the spinless non-relativistic limit, Schrödinger's equation yields

$$\partial\psi/\partial t = [-i\hbar\nabla + A]^2\psi, \quad (72)$$

or, with Eq. (68),

$$2mi\hbar\partial\psi/\partial t = [-i\hbar\nabla - i(e^2\hbar/mc^2)(1/\partial\mu\partial_\mu)\psi^*\nabla\psi]^2\psi \quad (73)$$

At very low frequencies the last term in rectangular brackets is dominant on the r.h.s., leading to

$$2i\partial\psi/\partial t = -\hbar[(e^2/mc^2)(1/\partial\mu\partial_\mu)\psi^*\nabla\psi]^2\psi \quad (74)$$

Both Eq. (71), in which we neglect at low wave-numbers the terms in $\partial/\partial x_j$ ($j=1,2,3$) and eliminate the term with the rest mass m through a substitution $\psi=\phi e^{im\gamma t}$, and right away Eq. (74), satisfy our criterion with $p=2$ in Eq. (2). Therefore, we expect a $1/f$ spectrum of current fluctuations, i.e., of cross sections and process rates in physics. This is in agreement with the well-known, and experimentally verified, results of the conventional Quantum $1/f$ Theory.

In conclusion, we realize that, both in classical and quantum mechanical nonlinear systems, the limiting behaviour at low wave numbers is usually expressed by homogeneous functional dependences, (as shown in Eq. 2), leading to fundamental $1/f$ spectra on the basis of our criterion.

IV. ANALYTICAL CALCULATION OF MOBILITY FLUCTUATIONS IN SEMICONDUCTORS, BASED ON THE QUANTUM $1/f$ CROSS-CORRELATION FORMULA

Together with the graduate student Thomas H. Chung, the author has performed an analytical calculation of mobility fluctuations in silicon and gallium arsenide, using the new quantum $1/f$ cross-correlations formula derived by the author in the previous AFOSR Grant period, and included in the July 1989 Final Technical Report. This calculation is of major importance for the $1/f$ noise-related optimization both of the two types

of materials, and of the many devices constructed with them for military and civilian applications in the electronic and opto-electronic industry.

The new cross-correlation formula gives the cross-spectral density which describes the way in which simultaneous quantum 1/f scattering rate fluctuations ΔW observed in the direction of the outgoing scattered wave-vector $\mathbf{K}'$ are correlated with those in the $\mathbf{K}''$ direction, when the two corresponding incoming current carriers have the wave vectors $\mathbf{K}_1$ and $\mathbf{K}_2$:

$$S_{\Delta W}(\mathbf{K}_1, \mathbf{K}'; \mathbf{K}_2, \mathbf{K}''; f) = (2\alpha/3\pi f)(\hbar/m^*c)^2 W_{\mathbf{K}_1, \mathbf{K}'} W_{\mathbf{K}_2, \mathbf{K}''} [(\mathbf{K}' - \mathbf{K}_1)^2 + (\mathbf{K}'' - \mathbf{K}_2)^2] \delta_{\mathbf{K}_1, \mathbf{K}_2}. \quad (75)$$

The form conjectured by us earlier had $2(\mathbf{K}' - \mathbf{K}_1)(\mathbf{K}'' - \mathbf{K}_2)$ in place of the rectangular bracket.

IV.1 Impurity Scattering

For impurity scattering of electrons in solids, fluctuations $\Delta\tau$ of the collision times τ will cause mobility fluctuations

$$\Delta\mu_{\text{band}}(t) = [e/m^* \langle\langle v^2 \rangle\rangle] \sum_{\mathbf{K}} v_{\mathbf{K}}^2 \Delta\tau(t) n_{\mathbf{K}}, \quad (76)$$

where $\langle\langle v^2 \rangle\rangle$ is both the average over all states of wave-vectors $\mathbf{K}$, with occupation numbers $n_{\mathbf{K}}$, in the conduction band, and the thermal equilibrium average of the quadratic carrier velocities. With the help of the relation

$$1/\tau(\mathbf{K}) = (V/8\pi^3) \int (1 - \cos\theta'/\cos\theta) W_{\mathbf{K}, \mathbf{K}'} d^3K', \quad (77)$$

the mobility fluctuations are reduced to fluctuations of the elementary scattering rates $W_{\mathbf{K}, \mathbf{K}'}$, governed by Eq. (75). Here V is the volume of the normalization box which disappears in the final result, θ and θ' respectively the angles $\mathbf{K}$ and $\mathbf{K}'$ form with the direction of the applied field. One finally obtains after tedious multiple integrations

$$\mu^{-2} S_{\Delta\mu}(f) = [256\pi\alpha\kappa^2\epsilon^4\hbar^{12}/3m^{*8}Z^4e^8N_i^2] (1/f) \sum_{\mathbf{K}} K^{10} [\ln(1+a^2) - a^2/(1+a^2)]^{-3} [(2a^2+a^4)/(1+a^2) - 2\ln(1+a^2)] F(E_{\mathbf{K}}) [\sum_{\mathbf{K}} v_{\mathbf{K}}^2 \tau(\mathbf{K}) F(E_{\mathbf{K}})]^{-2}, \quad (78)$$

where $a=2K/\kappa$, $\kappa^2=e^2n(T)/\epsilon k_B T$, $n(T)$ is the electron concentration, $F(E_K)=\exp(E_F-E_K)$ for non-degenerate semiconductors, N_i the concentration of impurities of charge Ze and ϵ the dielectric constant. The corresponding partial Hooke parameter for impurity scattering is thus

$$\alpha_i = [4\sqrt{2}\pi\alpha\kappa\hbar^5 N_c / 3m^{*7/2}(k_B T)^{3/2}c^2] \int_0^\infty dx x^{11/2} e^{-x} [\ln(bx+1) - bx/(bx+1)]^{-3} [(2bx+b^2x^2)/(bx+1) - 2\ln(bx+1)] \left\{ \int_0^\infty dx x^3 e^{-x} [\ln(bx+1) - bx/(bx+1)]^{-1} \right\}^{-2}. \quad (79)$$

IV.2 Acoustic Electron-Phonon Scattering

In this case the calculation is similar, and leads to the result

$$\alpha_{ac} = [32\pi\alpha N_c m^* C_1^2 \hbar^3 / 3c^2 k_B T]^4 \left\{ \left(\frac{1}{R^2} \right) \int_1^\infty dx x^{-4} \left[\frac{(x-1)^{7/7} + (R+1)(x-1)^{6/6} + R(x-1)^{5/5}}{(x-1)^{5/5} + (R+1)(x-1)^{4/4} + R(x-1)^{3/3}} \right] \exp(-x^2/4R) \right. \\ \left. + \int_0^1 dx x^{-4} \left[\frac{(x+1)^{5/5} - (x+1)^{6/6} + (x-1)^{5/5} + (x-1)^{6/6}}{(x+1)^{3/3} + (x-1)^{4/4} + (x-1)^{3/3} - (x+1)^{4/4}} \right] \exp(-x^2/4R) \right. \\ \left. + \int_1^\infty dx x^{-4} [(x+1)^{5/5} - (x+1)^{6/6}] [(x+1)^{3/3} - (x+1)^{4/4}] \exp(-x^2/4R) \right\}, \quad (80)$$

where $R=k_B T/2m^* C_1^2$, C_1 is the deformation potential, and N_c is the effective density of states for the conduction band.

IV.3 Non-Polar Optical Phonon Scattering

This time one obtains

$$\alpha_{n.o.ph} = [8\pi\sqrt{2\hbar\omega_0}\alpha N_c\hbar^2/3m^{*5/2}c^2\omega_0]\left\{\int_0^\infty dx x^{5/2} [(F+1)(x-1)^{1/2}\theta(x-1)+F(x+1)^{1/2}]^{-4} [(F+1)^2(x-1)(2x-1)\theta(x-1)+F^2(x+1)(2x+1)]\exp(-\hbar\omega_0 x/k_B T)\right\} \\ \int_0^\infty dx x^{3/2} [(F+1)(x-1)^{1/2}\theta(x-1)+F(x+1)^{1/2}]^{-1}\exp(-\hbar\omega_0 x/k_B T)\}^{-2}, \quad (81)$$

where $F=[\exp(\hbar\omega_0/k_B T)-1]^{-1}$, and ω_0 is the optical phonon frequency.

V. CALCULATION OF COLLECTOR 1/f NOISE IN BJTs

Based on a consequent application of the conventional quantum 1/f approach, we show that for the calculation of conventional quantum 1/f noise in the collector current of BJTs the effective lifetime τ of minority carriers in the base must be used instead of their diffusion time τ_D through the base. This allows us to represent the effective number of carriers in the denominator of our quantum 1/f formula as $l\tau/e$ for noise in the collector current, and the theory of Van der Ziel and Kleinpenning remains valid with τ_D replaced by τ . A long-standing difficulty present in the application of bulk noise sources to the collector current is thus removed in a natural way, and the agreement of the quantum 1/f theory with the experiment is substantially improved, particularly for narrow base BJTs.

1/f noise in bipolar junction transistors (BJTs) was elegantly treated by van der Ziel¹⁷⁻¹⁹ who applied a Hooge-type approach similar to Kleinpenning's treatment²⁰ of pn junctions, and used experimental data to determine the Hooge constant which was in turn compared with the quantum 1/f theory. However, since the BJT is a minority carrier device, it requires the application of the quantum 1/f (Handel) equation^{19,1-3,21}

from the beginning, for the correct interpretation of the number of carriers in the denominator of the Langevin noise source.

In the most elementary model²² of a BJT, the collector current I_C arises from minority carriers injected from the emitter into the base, which diffuse across the width X_B base and are then all swept across the reverse-biased collector junction by the built-in field of the junction. If we neglect the usually small leakage current of the collector junction and the small fraction of the carriers recombining in the base, we get for a n^+pn BJT

$$I_C = AqD_n[n_{0B}\exp(qV_{BE}/kT)/X_B], \quad (82)$$

where A is the cross sectional area of the base, $q=-e$ is the charge of the minority carriers in the base, D_n their diffusion coefficient in the base, $n_B(0)=n_{0B}\exp(qV_{BE}/kT)$ is the electron concentration at the limit of the emitter space charge region, V_{BE} is the applied base - emitter voltage, and X_B is the width of the base. The expression in rectangular brackets is the electron concentration gradient calculated with the boundary condition of a vanishing electron concentration at the limit of the collector space charge region. We assume the base to be much narrower than the electron diffusion length $L_n=(D_n\tau)$, $X_B \ll L_n$, but sufficiently wide to avoid ballistic electron transport across the base. Usually X_B is a fraction of a micron.

Quantum $1/f$ fluctuations of the collisional cross sections of the electrons in the base will yield fluctuations of the diffusion constant, and of the mobility ($\delta D_n/D_n = \delta\mu/\mu$)

$$\delta I_C = Aq(\delta D_n)[n_{0B}\exp(qV_{BE}/kT)/X_B]. \quad (83)$$

The corresponding spectral density of fractional fluctuations $I^{-2}S_{I_C}$ is

$$I_C^{-2} \langle (\delta I_C)^2 \rangle_f = D_n^{-2} \langle (\delta D_n)^2 \rangle = \mu^{-2} \langle (\delta\mu)^2 \rangle = \alpha_n/fN. \quad (84)$$

In the last step our quantum $1/f$ equation^{19,1-3} was used, where N is the number of carriers which define the scattered, or diffused, current leaving the base and emerging in the collector, while $\alpha_n = \alpha A_n$ is the effective quantum $1/f$ noise coefficient, or Hooge constant. The number of

electrons N is thus determined by the effective lifetime τ of the electrons, which will be slightly lower than the lifetime in the unbounded collector material, due to the collector lead contact processes, and due to lateral surface recombination. Indeed, we can write $N = \tau I_C / q$. Thus we finally obtain the spectral density of the collector current fluctuations

$$S_{I_C} = \alpha_n I_C / f \tau, \quad (85)$$

in which τ is the effective lifetime of the majority carriers in the collector. This expression is simpler, but similar to the expression derived earlier, with the important difference that now we have a lifetime of the carriers in the denominator, while before it was the usually much smaller diffusion time $\tau_D = X_B^2 / D_n$ of the electrons in the base. Eq. (85) also implies that in narrow-base BJTs of various base-widths α_n will be constant, as in other devices, rather than α_n / τ_D .

VI. REFERENCES

1. Handel, P.H.: 1/f Noise - an 'Infrared' Phenomenon. Phys. Rev. Letters **34**, 1492-1494 (1975).
2. P.H. Handel, Phys. Rev. **A22**, 745 (1980).
3. P.H. Handel: "Starting Points of the Quantum 1/f Noise Approach", p.1-26, Submitted to Physical Review B.
4. Handel, P.H.: Instabilitäten, Turbulenz und Funkelrauschen in Halbleitern III; Turbulenz im Halbleiterplasma und Funkelrauschen. Z. Naturforschg. **21a**, 579-593 (1966).
5. Handel, P.H.: Instabilities and Turbulence in Semiconductors. Phys. Stat. Sol. **29**, 299-306 (1968).
6. Handel, P.H.: Turbulence Theory for Solid State Plasmas. Proc. XVIIIth P.L.B. - M.R.I. Internatl. Symp. on Turbulence of Fluids and Plasmas, New York (1968). Brooklyn Polytechnic Inst. Press, New York, p. 381-395 (1969).
7. Handel, P.H.: Turbulence Theory for the Current Carriers in Solids and a Theory of 1/f Noise.: Phys. Rev. **3**, 2066-2073 (1971).

8. T. Musha and H. Higuchi, Jap. J. Appl. Phys. 15 1271 (1976); Jap. J. Appl. Phys. 17, 811-816 (1978).
9. T. Musha and H. Higuchi, Proc. I. Int. Conf. on 1/f Noise, T. Musha Ed., Tokyo Inst. of Technology Press, Tokyo 1977, pp. 187-191.
10. P.H. Handel, "Turbulence Theory for the Current Carriers in Solids and a Theory of 1/f Noise", Phys. Rev. A3, 2066 (1971).
11. P.H. Handel, "Instabilitäten, Turbulenz und Funkelrauschen in Halbleitern III. Turbulenz im Halbleiterplasma und Funkelrauschen" Z. Naturforschung 21a, 579-593 (1966).
12. P.H. Handel, "1/f Noise - an 'Infrared' Phenomenon", Phys. Rev. Letters 34, p.1492 - 1494 (1975); P.H. Handel, "Quantum Approach to 1/f Noise", Phys. Rev. 22A, p. 745 (1980).
13. P.H. Handel, "Quantum and Classical Nonlinear Dynamics, Quantum Chaos and 1/f Fluctuations of Physical Cross Sections" submitted to the Physical Review.
14. W. Heisenberg, Z. Physik 124, 628 (1948); Proc. Roy. Soc. London A 195, 1042 (1948).
15. M.S. Uberoi, J. Aeronaut. Sci. 20, 197 (1953).
16. G.K. Batchelor, The Theory of Homogeneous Turbulence, Cambridge Univ. Press, New York, 1953.
17. A. van der Ziel, Solid St. Electron. 25, 141 (1982).
18. A. Van der Ziel, *Noise in Solid State Devices and Circuits*. New York, NY: Wiley, 1986.
19. A. van der Ziel, Proc. IEEE 76, 233 (1988).
20. T.G.M. Kleinpenning, Physica 98B, 289 (1980).
21. P.H. Handel, Archiv für Elektronik u. Übertr. 43, 261 (1989).
22. R.M. Warner, Jr., and B.L. Grung: *Transistors/Fundamentals for the Integrated-Circuit Engineer*, New York, NY: Wiley, 1983, Eq. (7-6).

VII. PAPERS PUBLISHED UNDER THE PRESENT GRANT

1. P.H. Handel: "The Quantum 1/f Effect and the General Nature of 1/f Noise", Archiv für Elektronik und Übertragungstechnik (AEÜ) 43, 261-270 (1989).
2. A. van der Ziel, P. Fang, L. He, X.L. Wu, A.D. van Rheeën and P.H. Handel: "1/f Noise Characterization of n⁺-p and n-i-p Hg_{1-x}Cd_xTe Detectors" J. Vac. Sci. Technol. A 7, 550-554 (1989).
3. P.H. Handel: "General Derivation of the Quantum 1/f Noise Effect in Physical Cross Sections and the 1/N Factor", Proc. of the X. Int. Conf. on Noise in Physical Systems, Budapest, Aug. 20-25, 1989, A. Ambrozy, Ed., Akademiai Kiado, Budapest 1990, pp. 155-158.
4. P.H. Handel: " Quantum 1/f Cross-Correlations and Spectra", Ibid., pp. 167-170.
5. D. Wolf, P.H. Handel and M. Sekine: "Characteristic Functional of Physical Thermal Noise which includes Equilibrium 1/f Noise", Ibid., pp. 365-368.
6. P.H. Handel: "1/f Noise and Quantum 1/f Approach in Ferroelectrics and Ferromagnetics", Ibid., pp. 433-435.
7. B. Weber, D. Wolf and P.H. Handel: "Analytical and Numerical Study of Fluctuations in Active Nonlinear Systems", Ibid., pp. 351-355.
8. P.H. Handel: " The Nonlinearity causing Quantum 1/f Noise; Sliding Scale Invariance and Quantum Chaos Definition", Ibid.,pp. 179-186.

Papers Submitted for Publication

1. P.H. Handel: "Quantum and Classical Nonlinear Dynamics, Quantum Chaos and 1/f Fluctuations of Physical Cross Sections" submitted to the Physical Review.
2. P.H. Handel: "Spectrum of Musha's Turbulence Model of Highway Traffic Fluctuations", submitted to Phys. Rev. Lett..

GENERAL QUANTUM 1/f NOISE BIBLIOGRAPHY

-P.H. Handel, June, 1990-

1. P.H. Handel: "1/f Noise - an 'Infrared' Phenomenon", Phys. Rev. Letters 34, p.1492 - 1494 (1975).
2. P.H. Handel: "Nature of 1/f Phase Noise", Phys. Rev. Letters 34, p.1495 - 1497 (1975).
3. P.H. Handel: "Quantum Theory of 1/f Noise", Physics Letters 53A, p.438 (1975).
4. P.H. Handel: "1/f Macroscopic Quantum Fluctuations of Electric Currents Due to Bremsstrahlung with Infrared Radiative Corrections", Zeitschrift fuer Naturforschung 30a, p.1201 (1975).
5. P.H. Handel: "Low Frequency Fluctuations in Electronic Transport Phenomena", in *Linear and Nonlinear Electron Transport in Solids*, Proceedings of the NATO Advanced Study Institute on 'Linear and Nonlinear Electron Transport in Solids', p. 515-47, Plenum Press (1976). Editors: J.T. Devreese and V. van Doren.
6. P.H. Handel: "Progress in the Quantum Theory of 1/f Noise", Proc. of the Symposium on 1/f Fluctuations, (I. Int. Conf. on 1/f Noise); T. Musha Editor, Tokyo (Japan), 1977, Tokyo Institute of Technology Press (1977), p.12.
7. P.H. Handel: "Carrier Energy Loss Spectrum and 1/f Noise at Finite Temperature", *ibid.* Tokyo 1977, p.216.
8. P.H. Handel: "Generalized 1/f Noise and the Principles of Infra-Quantum Physics", *ibid.*, Tokyo 1977, p.26.
9. P.H. Handel and C. Eftimiu: "Survival of the Long Time Correlations in 1/f Noise", Tokyo 1977, *ibid.*, p.183.
10. T. Dodo: "The 1/f fluctuation and Particle - Wave Interaction", *ibid.*, Tokyo 1977, p.29-35.
11. P.H. Handel and D. Wolf: "Amplitude Distribution of 1/f Noise", Proc. of the 5th Int. Conf. on 'Noise in Physical Systems', p.125. Also in Springer Series in Electro - Physics Vol. II, p.169 (Springer Verlag 1978).
12. A.M. Tremblay: Thesis, MIT 1978.

13. P.H. Handel: "Keldysh - Schwinger Method Calculations of $1/f$ Low Frequency Current Fluctuations", unpublished manuscript, available contra cost \$3 from the author, Physics Department, Univ. of MO, St. Louis, MO 63121, USA (1979).
14. P.H. Handel: "Nature of $1/f$ Frequency Fluctuation in Quartz Crystal Resonators", Solid State Electronics 22, p. 875 (1979).
15. P.H. Handel: "Quantum Approach to $1/f$ Noise", Phys. Rev. 22A, p. 745 (1980).
16. P.H. Handel: "Review of Progress in the Theory of $1/f$ Noise", Proc. of the 2nd Int. Symposium on $1/f$ Noise, Orlando 1980, C.M. Van Vliet Editor, University of Florida - Gainesville Press, p.42.
17. P.H. Handel and D. Wolf: "Characteristic Functional of Quantum $1/f$ Noise, *ibid.* Orlando, 1980.
18. P.H. Handel: "Quantum $1/f$ Noise in the Presence of a Thermal Radiation Background", *ibid.*, Orlando, 1980, p.96.
19. T. Sherif and P.H. Handel: "Diffraction and $1/f$ Noise", *ibid.*, Orlando, 1980. p.525.
20. J.J. Gagnepain, P.H. Handel and J. Uebersfeld: "How Do Fluctuations in the Dissipation Cause $1/f$ Frequency Noise in Quartz?", *ibid.*, Orlando, 1980, p.550.
21. K.L. Ngai: "Unified Theory of $1/f$ Noise and Dielectric Response in Condensed Matter", Phys. Rev. B22, p. 2066-2077 (1980).
22. C.M.van Vliet: "Classification of Noise Phenomena", Proc. of the 6th Int. Conf. on Noise in Physical Systems, P.H.E. Meijer, R.D. Mountain and R.J. Soulen Jr. Editors, NBS Special Publication 614, U.S. Government Printing Office, Washington D.C. 1981, p.3-10.
23. C.M. Van Vliet, P.H. Handel and A. van der Ziel: "Superstatistical Emission Noise", Physica 108A, p.511-530 (1981).
24. J. Uebersfeld, P.H. Handel and J.J. Gagnepain: "Fluctuations of the Relaxation Time as a Source of $1/f$ Noise in Macroscopic Physical Systems", Proc. of the 6th International Conference on Noise in Physical Systems, P.H.E. Meijer, R.D. Mountain and R.J. Soulen Editors, National Bureau of Standards Special publication 614 (1981), p.189.

25. P.H. Handel, D. Wolf and C.M. van Vliet: "Non-Gaussian Amplitude Distribution of Thermal Noise in Resistors with $1/f$ Noise", *Ibid.*, p.196.
26. J. Kilmer, C.M. van Vliet, E.R. Chenette and P.H. Handel: "Temperature Response and Correlation of $1/f$ Noise in Transistors", *Ibid.*, p.151.
27. P.H. Handel and A. van der Ziel: "Comment on Noise in Transferred Electron Amplifiers", *Solid State Electronics*, 25, 541-542 (1981).
28. J.J. Gagnepain, J. Uebersfeld, G. Goujon and P.H. Handel: "Relation between $1/f$ Noise and Q-factor in Quartz Resonators at Room and Low Temperatures", *Proc. 35 Annual Symposium on Frequency Control*, Philadelphia 1981, p.476-483.
29. P.H. Handel and D. Wolf: "Characteristic Functional of Quantum $1/f$ Noise", *Phys. Rev.* A26, 3727-30 (1982).
30. J. Kilmer, C.M. van Vliet, E.R. Chenette and P.H. Handel: "Absence of Temperature Fluctuations in $1/f$ Noise Correlation Experiments in Silicon", *Phys. Stat. Sol.* a 70, 287-294 (1982).
31. C.M. Van Vliet and P.H. Handel: "A New Transform Theorem for Stochastic Processes with Special Application to Counting Statistics", *Physica* 113A, 261-276, (1982).
32. T.S. Sherif and P.H. Handel: "Unified Treatment of Diffraction and $1/f$ Noise", *Phys. Rev.* A26, p.596-602, (1982).
33. T.S. Sherif: "*Contributions to the Theory of Quantum $1/f$ Noise*", Thesis, Department of Physics, St. Louis University, St. Louis, (1982).
34. A. Widom, G. Pancheri, Y. Srivastava, G. Megaloudis, T.D. Clark, H. Prance and R. Prance: "Soft Photon Emission from Electron-Pair Tunneling in Small Josephson Junctions", *Phys. Rev.* B26, p.1475-1476 (1982).
35. Y. Srivastava: "Radiation and Noise", Lectures delivered at Escuela Latino Americana de Fisica, Cali, Colombia; Laboratori Nazionali di Frascati, INFN Press, Rome 1982, p.1-28.
36. P.H. Handel: "Any Particle Represented by a Coherent State Exhibits $1/f$ Noise", *Noise in Physical Systems and $1/f$ Noise*. Proc. of the 7th Int. Conf. on Noise in Phys. Syst. and 3rd Int. Conf. on $1/f$ Noise, Montpellier, M. Savalli, G. Lecoy and P. Nougier Editors, Elsevier Science Publ. BV, p 79-100, 1983.

37. P.H. Handel and T. Musha: "Quantum $1/f$ Noise from Piezoelectric Coupling, Ibid., p.101-104.
38. P.H. Handel and T. Sherif: "Direct Calculation of the Schroedinger Field which Generates Quantum $1/f$ Noise", Ibid., p.109-112.
39. J. Gong, C.M. van Vliet, W.H. Ellis, G. Bosman and P.H. Handel: " $1/f$ Noise Fluctuations in Alpha -Particle Radioactive Decay of $^{95}\text{Americium241}$ ", Ibid., p.381-384.
40. P.H. Handel, C.M. Van Vliet and A. van der Ziel: "Derivation of the Nyquist- $1/f$ Noise Theorem", Ibid., p.93-96.
41. A. Widom, G. Megaloudis, G. Pancheri, Y. Srivastava, T.D. Clark, R.J. Prance, H. Prance and J.E. Mutton: "Soft Photon Noise in Electrical Circuits", Ibid, p 105-107.
42. J. Kilmer, C.M. van Vliet, G. Bosman and A. van der Ziel: " $1/f$ Noise in Metal Films of Submicron Dimensions", Ibid, 205-208.
43. J. Gong, W.H. Ellis, C.M. van Vliet, G. Bosman and P.H. Handel: "Observation of $1/f$ Noise Fluctuations in Radioactive Decay Rates", Trans. Amer. Nucl. Soc. 45, p.221-222, (1983).
44. A. Widom, G. Pancheri, Y. Srivastava, G. Megaloudis, T.D. Clark, H. Prance and R.J. Prance: "Quantum Electrodynamic Circuit Soft-Photon Renormalization of the Conductance in Electronic Shot-Noise Devices", Phys. Rev. B27, p.3412-3417, (1983).
45. A. van der Ziel, C.J. Hsieh, P.H. Handel, C.M. van Vliet, and G. Bosman: "Partition $1/f$ Noise in Vacuum Pentodes", Physica 124B, p.299-304, (1984).
46. P.H. Handel: "Infrared Divergences, Radiative Corrections, and Bremsstrahlung in the Presence of a Thermal Equilibrium Radiation Background", Phys. Rev. A38, 3082 (1988).
47. P.H. Handel, T. Sherif, A. van der Ziel, C.M. van Vliet and E.R. Chenette: "Towards a More General Understanding of $1/f$ Noise", Phys. Letters (submitted).
48. J. Kilmer, C.M. van Vliet, G. Bosman, A. van der Ziel and P.H. Handel: "Evidence of Electromagnetic Quantum $1/f$ Noise Found in Gold Films", Phys. Status Solidi 121B, p.429-432, (1984).

49. A. Widom, G. Megaloudis, J.E. Mutton, T.D. Clark, and R.J. Prance: "Quantum Electrodynamic Noise in a Circuit Model Field Effect Transistor", unpublished manuscript, (1984).
50. W.A. Radford and C.E. Jones: "1/f Noise in Ion-Implanted and Double-Layer Epitaxial HgCdTe Photodiodes", J. Vac. Sci. Technol. A3, p.183-188, (1984).
51. M. Mihaila: "Phonon Observations from 1/f Noise Measurements", Physics Letters 104A, p.157-158, (1984).
52. H.R. Bilger: "Low Frequency Noise in Ring Laser Gyros", Proc. of the Society of Photo-Optical Engineers (SPIE) 487, p.42-48, (1984).
53. R.L. Baer, D.M. Hoover, D. Molinari and E.C. Herleikson: "Phase Noise in SAW Filters", Proc. of the 1984 Ultrasonics Symposium.
54. A. van der Ziel and P.H. Handel: "Quantum Partition 1/f Noise in Pentodes", Physica 125B, p.286-292, (1985).
55. A. van der Ziel, X.C. Zhu K.H. Duh and P.H. Handel: "A Theory of the Hooge Parameters of Solid State Devices", IEEE Transactions on Electron Devices, Ed.32, p.667-671, (1985).
56. A. van der Ziel and P.H. Handel: "1/f Noise in N⁺ -P Diodes", IEEE Transactions on Electron Devices, Ed.32, p.1802-1805, (1985).
57. A. van der Ziel and P.H. Handel: "Quantum 1/f Phenomena in Semiconductor Noise", Physica 129B, p.578-579, (1985).
58. A. van der Ziel and P.H. Handel: "Discussion of a Generalized Quantum 1/f Noise Process with Applications", Physica 132B, p.367-369, (1985).
59. T.E. Parker: "1/f Frequency Fluctuations in Quartz Acoustic Resonators", Appl. Phys. Letters, (1985).
60. X.C. Zhu and A. van der Ziel: "The Hooge Parameters of n⁺ -p-n and p⁺ -n-p Silicon Bipolar Transistors", IEEE Transactions, Ed.32, p.658-661, (1985).
61. K.H. Duh and A. van der Ziel: "Hooge Parameters for Various FET Structures", IEEE Transactions, Ed.32, p.662-666, (1985).

62. X.C. Zhu, X. Wu, A. van der Ziel, and E.G. Kelso: "The Hooge Parameters for n- and p-type $\text{Hg}_{1-x}\text{Cd}_x\text{Te}$ ", IEEE Transactions, Ed.32, p.1353-1354, (1985).
63. A. Pawlikiewicz and A. van der Ziel: "Temperature Dependence of the Hooge Parameter in n-Channel Silicon JFETs", IEEE Electron Device Letters, EDL-6, p. 500-501 (1985).
64. A.D. van Rheenen and G. Bosman: "Calculation of Hot Electron Quantum 1/f Noise in GaAs", Physica 1985.
65. G.S. Kousik: "*Quantum 1/f Noise in Non-Degenerate Semiconductors and Emission Statistics of Alpha Particles*", Thesis, Department of Electrical Engineering, University of Florida, Gainesville, (1985).
66. M.R. Sayeh and H.R. Bilger: "Flicker Noise in Frequency Fluctuations of Lasers", Phys. Rev. Letters 55, p. 700-702, (1985).
67. A. van der Ziel and P.H. Handel: "1/f Noise in n+ -p Junctions Calculated with Quantum 1/f Theory", *Noise in Physical Systems and 1/f Noise* .Proc. of the 8th Int. Conf. on Noise in Physical Systems and 4th Int. Conf. on 1/f Noise, (Rome 1985), A. D'Amico and P. Mazzetti Editors, North-Holland Publ. Co., 1986, p.481-484.
68. P.H. Handel and C.M. van Vliet: "Quantum 1/f Noise in Solid State Scattering, Recombination, Trapping and Injection Processes", Ibid., p.473-475.
69. P.H. Handel: "Quantum 1/f Noise in Squids", Ibid., p.489-490.
70. P.H. Handel: "Coherent States Quantum 1/f Noise and the Quantum 1/f Effect", Ibid., p.465-468.
71. P.H. Handel: "Gravidynamic Quantum 1/f Noise", Ibid., p.477-480.
72. A. van der Ziel: "Theory of and Experiments on Quantum 1/f Noise", Ibid., p.11-17, (1986).
73. X.L. Wu and A. van der Ziel: "Experiments on High-Frequency and 1/f Noise in Long n+p $\text{Hg}_{1-x}\text{Cd}_x\text{Te}$ Diodes", Ibid., p.491-494.
74. X.N. Zhang and A. van der Ziel: "Test for the Presence of Injection-Extraction and of Umklapp Quantum 1/f Noise in the Collector of Silicon Transistors", Ibid., p.485-487.

75. C.M. van Vliet and G. Kousik: "Quantum 1/f Noise in Semiconductors Involving Ionized Impurity Scattering and Various Types of Electron-Phonon Scattering", *Ibid.*, p.3-10.
76. H.R. Bilger and M.R. Sayeh: "White Noise and 1/f Noise in Optical Oscillators: State-of-the-Art in Ring Lasers", *Ibid.*, p.293-296.
77. G.S. Kousik, C.M. van Vliet, G. Bosman, W.H. Ellis and E.E. Carroll: "1/f Noise in Alpha-Particle Radioactive Decay of ^{239}Pu , ^{241}Am and ^{244}Cm ", *Ibid.*, p.469-472.
78. M. Planat and J.J. Gagnepain: "Temperature Dependence of 1/f Noise in Quartz Resonators in Relation with Acoustic Attenuation", *Ibid.*, p.323-326.
79. P.H. Handel and A. van der Ziel: "Relativistic Correction of the Hooge Parameter for Umklapp 1/f Noise", *Physica* 141B, p. 145 -147 (1986).
80. G.S. Kousik, C.M. van Vliet, G. Bosman and P.H. Handel: "Quantum 1/f Noise associated with Ionized Impurity Scattering and Electron-phonon Scattering in Condensed Matter", *Advances in Physics* 34, p.663-702, (1985).
81. A. van der Ziel, P.H. Handel, X.L. Wu, and J.B. Anderson: "Review of the Status of Quantum 1/f Noise in n+-p HgCdTe Photodetectors and Other Devices", (Proc. of the 1985 Workshop on the Physics and Chemistry of Mercury Cadmium Telluride, San Diego, Oct.8-10, 1985), *J. Vac. Sci. Technol.* A4, 2205-2216 (1986).
82. A. van der Ziel: "Interpretation of Schwates's Experimental Data on Secondary Emission 1/f Noise", *Physica* 144B, 205(1986).
83. A. van der Ziel and X. Wu: "Hooge's Formula for the Relative Noise in $\text{Hg}_{1-x}\text{Cd}_x\text{Te}$ Resistors When Both Electrons and Holes Contribute to the Noise", (1986).
84. A. van der Ziel: "*Noise in Solid State Devices and Circuits*", Wiley-Interscience, New York, 1986, Ch. 11.
85. A. van der Ziel: "1/f Noise in Secondary Emission Tubes and in Space-Charge-Limited Vacuum Diodes", (1986).
86. C.M. van Vliet and A. van der Ziel: "Summary of the Second Quantum 1/f Noise Conference held at Minneapolis, October 24, 1986", *Solid State Electronics*, 30, 777 (1987).

87. L.B. Kiss and P. Heszler: "An Exact Proof of the Invalidity of 'Handel's Quantum 1/f Noise Model', Based on Quantum Electrodynamics", J. Phys. C 19, L 631 (1986); See also the rebuttal in #102 below.

88. X.L. Wu, J.B. Anderson, and A. van der Ziel: "Diffusion and Recombination 1/f Noise in Long n+ -p Hg_{1-x}Cd_xTe Diodes", IEEE Transactions on Electron Devices ED-34, 1971-1977 (1987).

89. G.S. Kousik, J. Gong, C.M. van Vliet, G. Bosman, W.H. Ellis, E.E. Carrol and P.H. Handel: "Flicker Noise Fluctuations in Alpha-Radioactive Decay", Canadian J. of Physics 65, 365-375 (1987).

90. A. van der Ziel, C.J. Hsieh, P.H. Handel, C.M. van Vliet and G. Bosman: "Partition 1/f Noise in Pentodes and its Quantum Interpretation", Physica 145B, 195-204 (1987).

91. P. Fang and A. van der Ziel: "Collector 1/f Noise in a Silicon n-p-n Transistor on a (100) Substrate", Solid State Electronics, (1987).

92. A. van der Ziel: "Unified Presentation of 1/f Noise in Electronic Devices; Fundamental 1/f Noise Sources", Proc. of the IEEE, 76, 233-258 (1988).

93. C.M. Van Vliet: "Further Comments on Handel's Theories of Quantum 1/f Noise", Physica A150, 244-260 (1988).

94. P.H. Handel: "Answer to Objections against the Quantum 1/f Theory", p.1-39, Submitted to Physical Review.

95. P.H. Handel: "Fundamental Quantum 1/f Fluctuation of Physical Cross Sections and Process Rates", p.1-9, Submitted to Physical Review Letters.

96. P. Fang, H. Kang, L. He, Q. Peng and A. van der Ziel: "1/f Noise Study in Vacuum Photodiodes". 1987.

97. P.H. Handel: "Quantum Approach to 1/f Noise II: Fluctuations of Physical Cross Sections - An Infrared Divergence Phenomenon", p.1-9, Submitted to Physical Review.

98. P.H. Handel: "Quantum 1/f Effect with a Finite Mean Free Path of the Current Carriers", Submitted to Physical Review.

99. P.H. Handel and T. Musha: "Coherent Quantum 1/f Noise from Electron-Phonon Interactions", Zeitschrift für Physik B 70, 515-516 (1988).

100. P.H. Handel: "Derivation of Quantum 1/f Fluctuations in Physical Cross Sections", p.1-14, Submitted to Physical Review Letters.
101. P.H. Handel: "Quantum 1/f Cross Section Fluctuations in Condensed Matter Conditions", p.1-6, Submitted to Physical Review Letters.
102. P.H. Handel: "On the Invalidity of the Kiss-Heszler 'exact proof' and correctness of the quantum 1/f noise theory", Journal of Physics C: Solid State Physics 21 2435-2438..
103. Heinrich Hora and P.H. Handel: "New Experiments and Theoretical Development of the Quantum Modulation of Electrons (Schwarz-Hora Effect)", Advances in Electronics and Electron Physics 69, p.55-113 (1987).
104. P.H. Handel: "Starting Points of the Quantum 1/f Noise Approach", p.1-26, Submitted to Physical Review B.
105. P.H. Handel: "Characteristic Functionals of Quantum 1/f Noise and Thermal Noise", Proc. of the Conf. on Information Theory, Jap. Inst. of Electronics Information and Communication Engineers, (IEICE), Osaka, Japan (1987).
106. R.D. Black: "Comments on 'A Theory of the Hooge Parameters of Solid-State Devices'", IEEE Transactions on Electron Devices", ED-33, 532 (1986).
107. A. van der Ziel: "Reply to 'Comments on A Theory of the Hooge Parameters of Solid State Devices'", IEEE Transactions on Electron Devices ED-33, 533 (1986).
108. P.H. Handel: "Rebuttal to 'Comments on a Theory of the Hooge Parameters of Solid-State Devices'", IEEE Transactions on Electron Devices ED-33, 534-536 (1986).
109. J. Gong: "Noise Associated with Electron Statistics in Avalanche Photodiodes and Emission Statistics of Alpha-Particles",. PhD Thesis, Electr. Eng. Dept., University of Florida - Gainesville, 1983.
110. P.H. Handel: "Second-Quantized Formulation of the Quantum 1/f Effect", *Noise in Physical Systems*, Proc. IX Int. Conf. on Noise in Physical Systems, Montreal (Canada), May 1987; C.M. Van Vliet Editor, World Scientific Publ. Co. (Singapore 1987), p. 365-372.

111. P.H. Handel, E. Kelso and M. Belasco: "Theory of Quantum 1/f Noise in n+p Junctions and MIS Diodes", Ibid. 423-426.
112. P.H. Handel: "Effect of a Finite Mean Free Path on Quantum 1/f Noise", Ibid. p.419-422.
113. P.H. Handel and Musha: "Coherent State Piezoelectric Quantum 1/f Noise", Ibid. p. 413-414.
114. P.H. Handel and Q. Peng, "Quantum 1/f Fluctuations of Alpha Particle Scattering Cross Sections", Ibid. p. 415-418.
115. G.S. Kousik, C.M. Van Vliet, G. Bosman, W.H. Ellis, E.E. Carrol and P.H. Handel: " A More Complete Interpretation of Flicker Noise in Alpha Radioactive Decay". Ibid., pp. 121-128.
116. Q. Peng, A. Birbas and A. van der Ziel: "A Note on Experimental Results for the Hooe's Parameter in p-Mosfet's", Ibid. p. 400-404.
117. A. van der Ziel: "Experimental Results Possibly Involving Quantum 1/f Noise", ibid., p 383-92.
118. A.N. Birbas, A. Pawlikiewicz and A. van der Ziel: "Noise in Silicon JFETs", Ibid., p. 405-409.
119. P. Fang and A. van der Ziel: "Coherent State Quantum 1/f Noise in Long Silicon PIN Diodes at elevated Temperatures", Ibid., p. 410-412.
120. C.E. Jones and W.A. Radford: "Comparison of 1/f Noise in HgCdTe Diodes with 1/f Noise Theory", Idem, p. 393-396.
121. T.M. Nieuwenhuizen, D. Frenkel and N.G. van Kampen: "Objections to Handel's Quantum Theory of 1/f Noise", Phys. Rev. A 35, 2750 (1987).
122. A. van der Ziel: "Semiclassical Derivation of Handel's Expression for the Hooe Parameter", J. Appl. Phys. 63, 2456-2457 (1988).
123. Adam Henry Marcin Pawlikiewicz: (PhD Thesis) "*Flicker Noise in Solid State Devices*". University of Minnesota , August 1986.
124. W.V. Prestwich, T.J. Kenneth and G.T. Pepper: "Search for 1/f Fluctuations in alpha Decay". Phys. Review A 34, 5132-5134 (1986).
125. A. van der Ziel: "The Experimental Verification of Handel's Expressions for the Hooe Parameter", Solid State Electronics, 31, 1205-1209 (1988).

126. A. van der Ziel: "Generalized Semiclassical quantum 1/f Noise Theory, I: Acceleration 1/f Noise in Semiconductors", J. Appl. Phys. 64, 903-906 (1988).
127. H Hora: "Laser and Particle Beams", in *Encycl. of Phys. Science and Technology* Vol.7, pp. 99-129 (Academic Press, 1987); see p. 126.
128. A.N. Birbas, Q. Peng, A. van der Ziel, A.D. van Rheeën and K. Amberiadis: "Channel-Length Dependence of the 1/f Noise in Silicon Metal-Oxide-Semiconductor Field Effect Transistors, Verification of the Acceleration 1/f Noise Process", J. Appl. Phys. 64, 907-912 (1988).
129. A.H. Pawlikiewicz, A. van der Ziel, G.S. Kousik and C.M. Van Vliet: "Fundamental 1/f Noise in Silicon Bipolar Transistors". Solid-State Electronics 31, 831-834 (1988).
130. A. van der Ziel, P. Fang, L. He and X.L. Wu: "1/f Noise Characterization in n+-p Hg_{1-x}Cd_xTe Detector Diodes". Proc. of the Mercury-Cadmium-Telluride Workshop, Orlando, Oct. 1988.
131. M. Athiba Azhar and K. Gopala: "1/f Noise in the Radioactive β Decay of Ti²⁰⁴", Phys. Rev. A 39, 4137-4139 (1989).
132. P. Fang, L He, A.D. Van Rheeën, A. van der Ziel and Q. Peng: "Noise and Lifetime Measurements in Si p+ Power Diodes" Solid-State Electronics 32, 345-348 (1989). Obtains $\alpha_H = 4 \cdot 10^{-3}$, in agreement with the coherent state quantum 1/f theory.
133. A. van der Ziel, P. Fang, L. He, X.L. Wu, A.D. van Rheeën and P.H. Handel: "1/f Noise Characterization of n+-p and n-i-p Hg_{1-x}Cd_xTe Detectors" J. Vac. Sci. Technol. A7, 550-554 (1989).
134. A. van der Ziel: "1/f Noise Performance of Hg_{1-x}Cd_xTe Photoresistors and n+-p Photodiodes", 1985.
- 135.. C.M. Van Vliet: "Quantum Electrodynamical treatment (QED) of the Interaction of Electrical Current with the Electromagnetic field", Quantum 1/f Noise Conference, Minneapolis, Minn., April 28, 1988.
136. A. van der Ziel, C.M. Van Vliet, R.J.J. Zijlstra, R.R. Jindal: "1/f Noise in Mobility Fluctuations and the Boltzman Equation", Physica 121B, 420-422, (1983).

137. P.H. Handel: "The Quantum $1/f$ Effect and the General Nature of $1/f$ Noise", Archiv für Elektronik und Übertragungstechnik (AEÜ) 43, 261-270 (1989).
138. A. van der Ziel, A.D. van Rheenen and A.N. Birbas: "Extensions of Handel's $1/f$ Noise Equations and their Semiclassical Theory", Phys. Rev. B 40, 1806-1809 (1989).
139. Xiaolan Wu: "Noise in Semiconductor Devices, Particularly in $\text{Cd}_x\text{Hg}_{1-x}\text{Te}$ Photo Diodes", (PhD Thesis) ,University of Minnesota, Jan.1987.
140. A.H. Pawlikiewicz, A. van der Ziel, G.S. Kousik and C.M. Van Vliet: "On the Temperature Dependence of the Hooge Parameter α_H in n and p-channel Silicon JFETs", Solid State Electr. 31 (2) 233-236 (1988).
141. R.Z. Fang, A.C Young, A. van der Ziel and A.D. van Rheenen: "A new $1/f$ Noise Parameter in Bipolar Transistors", 1989.
142. A. van der Ziel and A.D. van Rheenen: " Extension of the Hooge Equation and of the Hooge Parameter Concept", 1989.
143. A. van der Ziel: " Formulation of Surface $1/f$ Noise Processes in Bipolar Junction Transistors and in p-n Diodes in Hooge-Type Form", Solid State Electr. 32 (1), pp. 91-93, (1989).
144. P. Fang and A. van der Ziel: " Study of Secondary Emission Noise", Physica 147B, 311-315, (1987).
145. P.H. Handel: "Quantum and Classical Nonlinear Dynamics, Quantum Chaos, and $1/f$ Fluctuations of Physical Cross Sections", submitted to Phys. Rev.
146. P.H. Handel: ' Spectrum of Musha's Turbulence Model of Highway Traffic Fluctuations", submitted to Phys. Rev. Lett., July 1989.
147. P.H. Handel: " General Derivation of the Quantum $1/f$ Noise Effect in Physical Cross Sections and the $1/N$ Factor", Proc. of the X. Int. Conf. on Noise in Physical Systems, Budapest, Aug. 20-25, 1989, A. Ambrozy, Ed., Akademiai Kiado, Budapest 1990, pp. 155-158.
148. P.H. Handel: "Quantum $1/f$ Cross-Correlations and Spectra", Ibid. pp. 167-170.
149. D. Wolf, P.H. Handel and M. Sekine: "Characteristic Functional of Physical Thermal Noise which Includes Equilibrium $1/f$ Noise", Ibid., pp. 365-368.

150. P.H. Handel: " 1/f Noise and Quantum 1/f Approach in Ferroelectrics and Ferromagnetics", Ibid., pp. 433-435.

151. B. Weber, D. Wolf and P.H. Handel: "Analytical and Numerical Study of Fluctuations in Active Nonlinear Systems", Ibid., pp. 351-355.

152. P.H. Handel: "The Nonlinearity causing Quantum 1/f Noise; Sliding Scale Invariance and Quantum Chaos Definition", Ibid., pp. 179-186.

153. B.K. Jones, M.G. Berry and G. Hughes: "A Test of Quantum 1/f Noise using α -Decay", to be published, Can. J. Phys., 1989.

154. A. van der Ziel: "Experiments on 1/f Noise Agreements with Handel's Predictions", Invited Paper, X. Int. Conf. on Noise in Physical Systems, Budapest, Aug. 20-25, 1989, A. Ambrozy, Ed., Akademiai Kiado, Budapest 1990, pp. 143-153.

155. Horng-Jye Luo: '*Low Frequency Noise Studies in Silicon and Silicon Devices with Emphasis on Quantum 1/f Noise.*' MS Thesis, University of Florida, 1989.

156. G.S. Kousik, C.M. Van Vliet, G. Bosman, and Horng-Jye Luo: "Quantum 1/f Noise Associated with Intervalley Scattering in Nondegenerate Semiconductors", Phys. stat. sol. 154, 713-726, (1989).

157. C.M. Van Vliet: "A Quantum Electrodynamical Theory of Quantum 1/f Noise in Condensed Matter." Conf. Proc., Iguazu, Argentina, Aug. 1989.

158. C.M. Van Vliet: "An Alternative Theory for Quantum 1/f Noise Based on Quantum Electrodynamics", Abstract, X. Int. Conf. on Noise in Physical Systems, Budapest, Aug. 21-25, 1989.

159. C.M. Van Vliet: " An Alternative Theory for Quantum 1/f Noise Based on Quantum Electrodynamics", Proc. X. Int. Conf. on Noise in Physical Systems, Budapest, Aug. 21-25, 1989, A. Ambrozy, Ed., Akademiai Kiado, Budapest 1990, pp. 357-363.

160. C.M. Van Vliet: "Quantum Electrodynamical Theory of Infrared Effects in Condensed Matter. I.: Radiation Damping of Cross Sections and Mobility." Physica, 1990.

161. C.M. Van Vliet: "Quantum Electrodynamical Theory of Infrared Effects in Condensed Matter. II.: Radiation Corrections of Cross Sections and Scattering Rates and Quantum 1/f Noise." Physica, 1990.

162. C.M. Van Vliet: "A Survey of Results and Future Prospects on Quantum $1/f$ Noise and $1/f$ Noise in General." Solid St. Electronics, 1990.

163. G.S. Kousik, S.M. Van Vliet, G. Bosman, and Horng-Jye Luo: "Quantum $1/f$ Noise Associated with Intervalley Scattering in Nondegenerate Semiconductors." Phys. stat. sol. (b) **154**, (713-726) (1989).

164. A. Young: "*Quantum $1/f$ Noise in Bipolar Junction Transistors*" PhD Thesis, Electrical Engrg. Dept., Univ. of Minnesota, Minneapolis, MN 55455, June 1990

Note: Papers with no page and volume numbers listed are submitted for publication, and are still in the reviewing process or in process of publication, but may not have been published yet by the respective authors.