

REPORT DOCUMENTATION PAGE

Form Approved
OMB NO. 0704-0188

Public Reporting burden for this collection of information is estimated to average 1 hour per response, including the time for reviewing instructions, searching existing data sources, gathering and maintaining the data needed, and completing and reviewing the collection of information. Send comment regarding this burden estimates or any other aspect of this collection of information, including suggestions for reducing this burden, to Washington Headquarters Services, Directorate for Information Operations and Reports, 1215 Jefferson Davis Highway, Suite 1204, Arlington, VA 22202-4302, and to the Office of Management and Budget, Paperwork Reduction Project (0704-0188,) Washington, DC 20503.

1. AGENCY USE ONLY (Leave Blank)

2. REPORT DATE
09/22/99

3. REPORT TYPE AND DATES COVERED
Final Progress Report 03/01/98-08/31/99

4. TITLE AND SUBTITLE
Synthetic Aperture Radar for Mine Detection and Identification

5. FUNDING NUMBERS
DAAG55-98-1-0148

6. AUTHOR(S)
Lawrence Carin

7. PERFORMING ORGANIZATION NAME(S) AND ADDRESS(ES)
Duke University
Department of Electrical and Computer Engineering
Durham, NC 27708-0291

8. PERFORMING ORGANIZATION
REPORT NUMBER

9. SPONSORING / MONITORING AGENCY NAME(S) AND ADDRESS(ES)

U. S. Army Research Office
P.O. Box 12211
Research Triangle Park, NC 27709-2211

10. SPONSORING / MONITORING
AGENCY REPORT NUMBER

ARO 35791.1-EL

11. SUPPLEMENTARY NOTES

The views, opinions and/or findings contained in this report are those of the author(s) and should not be construed as an official Department of the Army position, policy or decision, unless so designated by other documentation.

12 a. DISTRIBUTION / AVAILABILITY STATEMENT

Approved for public release; distribution unlimited.

12 b. DISTRIBUTION CODE

13. ABSTRACT (Maximum 200 words)

This project has focused on modeling and signal processing for the detection and identification of buried and surface land mines, both metal and plastic. The modeling has been performed through development of a method of moments (MoM) for general conducting/dielectric targets in an arbitrary multi-layered environment. The model accounts for all loss and dispersion associated with real soils. Using the MoM models, we have generated computed synthetic-aperture radar (SAR) imagery for buried and surface mines, with this model data compared very favorably to data measured by the Army Research Laboratory (ARL). Moreover, the models have been employed in an optimal Bayesian processor, in which the real-world uncertainties have been accounted for, including variability in the soil properties and the target depth. For the case of anti-tank mines, the results of the Bayesian processor are very encouraging, demonstrating a dramatic decrease in the false alarm rate, via-a-vis traditional approaches. This suggests that SAR may be a viable technology for mine field detection.

14. SUBJECT TERMS

mines, method of moments, Bayesian

19991102 144

15. NUMBER OF PAGES

6

16. PRICE CODE

17. SECURITY
CLASSIFICATION
OR REPORT

UNCLASSIFIED

18. SECURITY
CLASSIFICATION
ON THIS PAGE

UNCLASSIFIED

19. SECURITY
CLASSIFICATION
OF ABSTRACT

UNCLASSIFIED

20. LIMITATION OF
ABSTRACT

UL

NSN 7540-01-280-5500

(Rev.2-89)

DTIC QUALITY INSPECTED 4

Standard Form 298

A. Statement of the Problem Studied

Ground-penetrating radar (GPR) constitutes one of the oldest technologies for subsurface sensing. Most such systems are placed in direct or near-direct contact with the earth surface. A significant drawback of this approach is the lack of "standoff", a particular problem for the detection of buried ordnance (*e.g.*, mines). Moreover, it is time consuming to use such hand-held systems for large-area interrogation over variable terrain and foliage. The US Army Research Laboratory (ARL) has therefore undertaken the development of a synthetic aperture radar (SAR) system, with which significant standoff can be achieved. This system provides surveillance of large areas, the results from which can dictate the smaller regions over which conventional hand-held systems (*e.g.*, electromagnetic induction, conventional GPR, and magnetometers) should be deployed. Therefore, while ideally we would like to use the SAR system to detect and distinguish *each* mine, we are particularly interested in mine *field* detection, over very large areas. Consequently, we need not detect each mine, but rather mine *clusters*. This simplified problem statement still constitutes a significant technological challenge, particularly in highly cluttered (natural and anthropic) environments.

To enhance discrimination between targets and clutter, the excitation should be as wideband as possible. However, it is also essential to operate at frequencies for which adequate soil (and foliage) penetration can be effected, particularly for deeply buried targets or regions in which there has been significant foliage growth (for humanitarian demining, one often must deal with mine fields that have been in the ground for decades). The ARL ultra-wideband (UWB) SAR therefore transmits and receives waveforms with usable bandwidth from 50-1200 MHz. Moreover, this system is fully polarimetric, providing access to HH, HV, VH, and VV imagery.

While radar-based subsurface sensing is an old technology, until recently there has been very little modeling done to characterize expected system performance as a function of mine type and environment. In practice there can be wide variability in the mines deployed and in environmental (background) conditions. Therefore, system performance has historically been anecdotal, with excellent performance under certain conditions and unsatisfactory performance elsewhere. Recently, however, we have developed rigorous electromagnetic scattering models for conducting and plastic mines buried in lossy, layered soil (including, potentially, a top layer of snow). Our models are based on a full-wave formulation of Maxwell's equations, with solution via the method of moments (MoM). The principal challenge to making such an analysis tractable is computation of the halfspace or layered-medium Green's function, which we have performed efficiently via the method of complex images. Moreover, we have restricted ourselves to targets that can be simulated as a body of revolution (BOR), simplifying computational complexity significantly. While not all mines can be modeled as a BOR, the vast majority of land mines (both conducting and plastic) are accurately so modeled.

The phenomenological insight garnered from such models can guide system design and automatic target detection and discrimination. In particular, we examine the potential of radar-based sensing as a function of mine type and environment, in the

context of target RCS and possible target resonances. These results quantify the dramatic variability in radar performance that can be achieved, depending on the detailed mine and soil characteristics. We also document that system performance for plastic mines can be enhanced significantly by modifying the properties of the surrounding environment (*e.g.*, enhancement of the dielectric mismatch between a plastic mine and soil, induced by increasing the soil water content). Other issues that we explore include system performance as a function of bandwidth, in which the benefits of enhanced bandwidth (resolution) are examined in the context of the attendant loss in soil penetration. Finally, we address the potential of polarimetric sensing of buried and surface land mines. It is demonstrated theoretically and experimentally that the special symmetry properties of land mines (and the lack of such for clutter) make polarimetric imaging attractive.

In addition to using wave modeling to elucidate phenomenology and guide system design, the target models play an important role in detection and identification algorithms. In particular, optimal detectors require an accurate model for the signature of the target in question. For the case of buried mines, until recently one was required to use *measured* signatures for such applications. However, empirical target models for buried mines are of limited value due to the strong dependence of the target signature on the mine type, target depth, and soil properties. We have therefore utilized our simulated target models as integral parts of a detector, with results presented here for data measured by the BoomSAR at Yuma Proving Ground (Yuma, AZ, USA). Results are presented in the form of receiver operating characteristic (ROC) curves. We also address wavelet-based compression techniques which reduce algorithm complexity.

B. Summary of Most Important Results

Although radar is one of the oldest tools for subsurface sensing, until very recently there has been little rigorous modeling of the fields scattered from or the resonances supported by buried targets. This is in large part due to the complexity of such analyses, which have been aided greatly of late by revolutionary increases in computational power. Therefore, for much of its existence, the efficacy of radar-based subsurface sensing has been assessed based on a limited set of measured data, yielding results in some cases that suggested radar is a panacea and, at the other extreme, cases in which radar failed entirely. It is now understood that the utility of radar-based sensing for buried targets is largely dictated by the details of the problem (target and soil) in question, with the advances in modeling providing the key to appropriate radar deployment.

In demining applications, one generally must interrogate a large swath of terrain. Moreover, standoff is of obvious benefit when attempting to locate these insidious targets. Therefore, ARL has focused on development of a SAR-based system that affords both of these desired attributes. Moreover, the ARL BoomSAR operates over ultra-wideband frequencies (50-1200 MHz), simultaneously providing soil penetration and resolution. Synthetic-aperture radar results have been presented for data measured at Yuma Proving Ground, Yuma, AZ. These data were used to confirm our MoM-based scattering models as well as predictions with regard to the polarimetric properties of most

land mines. In particular, we confirmed that mines that approximate a body of revolution (BOR) excite no cross-polarized backscattered fields.

After substantiating the model accuracy, we used the computed target signatures to effect a detector. This detector accounted for the real-world situation in which the expected mines are generally known, but the exact (spatially varying) soil properties and target depths are often not known exactly. Therefore, these latter properties have been treated within a statistical framework, in which the soil properties and target depth are characterized via statistical distributions. Results have been presented in the form of the receiver operating characteristic (ROC) and indicate that such an approach has promise. We accurately detected a large percentage of the mines, at a relatively low false alarm rate. Moreover, the false alarms tended to be spread sporadically throughout the SAR image (based on *a posteriori* ground-truth knowledge), while the correct mine detections tended to be clustered, as expected of a mine field. Hence, SAR appears to be an attractive option for mine-field detection. Finally, a wavelet-based optimization scheme was investigated to improve detector efficiency. Results from this preliminary multi-resolution study appear attractive, but significantly greater computational savings can be achieved by exploiting a multi-resolution scheme that is shift invariant (unlike the spatial wavelet transform).

While the SAR detector results are encouraging, there were some disconcerting issues learned as a consequence of the measurements. In particular, the buried *plastic* mines were virtually invisible to the radar and were *not* detected. Since many mines have only trace metal content, this failure is particularly troubling. The near-invisibility of the plastic mines to radar may be traced to the fact that the electrical contrast between the plastic target and soil was insignificant for the examples considered here. However, while the properties of the plastic mine cannot be changed, the electrical characteristics of the soil can. In particular, we have examined the utility of applying water to a suspected mine field, thereby increasing the electrical contrast between the target and soil. This issue was addressed in the context of the scattered-field amplitude as well as with regard to the natural resonances of such targets. For the soil and (representative) plastic target considered, it was demonstrated that this technique potentially has significant utility. This matter is aided by the fact that most anti-personnel mines are buried near the surface, mitigating the increased soil attenuation.

In addition to the weak target-background contrast, making difficult the detection of plastic mines, the SAR image is contaminated by artifacts due to imperfections in the imaging itself (*e.g.*, angle-dependent effects in the transmitted waveform and in the polarization, which do not currently allow image calibration) as well as radio frequency interference (RFI). It is felt that significant improvements can still be accrued in these areas (for example, through better understanding of the antennas), and that the subsequently improved SAR imagery will play an important role in detecting low-contrast (plastic) targets. Hence, while soil modification will play an important role in detecting such targets, it is felt that significant systems-level improvements are also important. While the current manifestation of the BoomSAR represents a notable engineering achievement, it is felt that significant improvements are still possible.

The M20 mines buried to a depth of 15.24 cm were the weakest scatterers detected from measured data in this study. To quantify the complexity of the problem for plastic mines, our theoretical results indicate that the plastic mine had a scattered amplitude roughly 4% that of the buried M20 mine (with the plastic mine placed in the same soil as considered in the measurements, *buried to a depth of only 2 cm*). This scattered amplitude is well beneath the noise (random system noise, imaging artifacts, and RFI) and clutter floor, and explains why the plastic mines were invisible in the imagery. After increasing the water content to 20%, the plastic mine had a scattered amplitude approximately 20% that of the 15.24 cm deep M20. This is still a very stressing target, but with better imaging techniques and better removal of radio-frequency interference (RFI), it may yet be possible to detect plastic mines.

Finally, the matched-filter-like detector, which was so effective for the measured data considered here, implicitly assumes that the air-soil interface is flat. In humanitarian demining, for which the mines may have been in the ground for decades, this interface may be rough (or foliated by randomizing overgrowth). In this case, electromagnetic transmission through and scattering from the interface must be parametrized as a random process. While this has not been a concern for the data considered here, there are many applications for which such a formulation is essential. We have addressed this issue in detail, and future SAR-based investigations will investigate the utility of such a framework, through consideration of measured data.

C. Refereed Publications

- [1] S. Vitebskiy and L. Carin, "Late-time resonant frequencies of buried bodies of revolution," *IEEE Trans. Antennas Prop.*, vol. 44, pp. 1575-1583, Dec. 1996.
- [2] S. Vitebskiy, L. Carin, M. Ressler and F. Le, "Ultra-wideband, short-pulse ground-penetrating radar: theory and measurement," *IEEE Trans. Geoscience and Remote Sensing*, vol. 35, pp. 762-772, May 1997.
- [3] T. Dogaru and L. Carin, "Time-Domain Sensing of Targets Buried Under a Rough Air-Ground Interface", *IEEE Trans. Antennas Prop.*, vol. 46, pp. 360-372, March 1998.
- [4] N. Geng, C.E. Baum, and L. Carin, "On the low-frequency natural response of conducting and permeable targets," *IEEE Trans. Geoscience and Remote Sensing*, vol. 37, pp. 347-359, Jan. 1999.
- [5] L. Carin, R. Kapoor, C.E. Baum, "Polarimetric SAR imaging of buried landmines," *IEEE Trans. Geoscience and Remote Sensing*, vol. 36, pp. 1985-1988, Nov. 1998.
- [6] D. Wong and L. Carin, "Analysis and processing of ultra-wideband SAR imagery for buried landmine detection," *IEEE Trans. Antennas Propagat.*, vol. 46, pp. 1747-1748, Nov. 1998.

[7] T. Dogaru, L. Collins, and L. Carin, "Optimal detection of a deterministic target buried under a randomly rough interface," submitted to *IEEE Trans. Antennas Propagat.*

[8] L. Carin, N. Geng, M. McClure, J. Sichina, and L. Nguyen, "Ultra-wideband synthetic aperture radar for mine field detection," *IEEE Antennas and Propagation Magazine* (invited), vol. 41, pp. 18-33, Feb. 1999.

[9] N. Geng and L. Carin, "Ultrawideband, short-pulse scattering from a dielectric body of revolution buried in a lossy, dispersive layered medium," *IEEE Trans. Antennas Propagat.*, vol. 47, pp. 610-619, April 1999.

[10] N. Geng, D. Jackson, and L. Carin, "On the resonances of dielectric bodies of revolution buried in a lossy, dispersive layered medium," to appear in the *IEEE Trans. Antennas Propagat.*

[11] N. Geng and L. Carin, "Short-pulse electromagnetic scattering from arbitrarily oriented subsurface ordnance," *IEEE Trans. Geoscience and Remote Sensing*, vol. 37, pp. 2111-2113, July 1999.

[12] N. Geng, M. Ressler, and L. Carin, "Wideband VHF scattering from a trihedral reflector situated above a lossy dispersive halfspace," *IEEE Trans. Geoscience and Remote Sensing*, vol. 37, pp. 2609-2617, Sept. 1999.

[13] N. Dasgupta, N. Geng, T. Dogaru and L. Carin, "On the extended-Born technique for scattering from buried dielectric targets," accepted for publication in the *IEEE Trans. Antennas Propagation*

[14] T. Dogaru and L. Carin, "Application of multiresolution time-domain schemes to two-dimensional electromagnetic scattering problems," submitted to the *IEEE Trans. Antennas Propagat.*

D. Participating personnel

Dr. Norbert Geng (post doc)
Dr. Anders Sullivan (post doc)
Traian Dogaru (PhD earned June 1999)
Mark McClure (PhD earned June 1998)
Bimba Rao (PhD earned May 1999)

E. Report of Inventions

None

A. Statement of the Problem Studied

Ground-penetrating radar (GPR) constitutes one of the oldest technologies for subsurface sensing. Most such systems are placed in direct or near-direct contact with the earth surface. A significant drawback of this approach is the lack of "standoff", a particular problem for the detection of buried ordnance (*e.g.*, mines). Moreover, it is time consuming to use such hand-held systems for large-area interrogation over variable terrain and foliage. The US Army Research Laboratory (ARL) has therefore undertaken the development of a synthetic aperture radar (SAR) system, with which significant standoff can be achieved. This system provides surveillance of large areas, the results from which can dictate the smaller regions over which conventional hand-held systems (*e.g.*, electromagnetic induction, conventional GPR, and magnetometers) should be deployed. Therefore, while ideally we would like to use the SAR system to detect and distinguish *each* mine, we are particularly interested in mine *field* detection, over very large areas. Consequently, we need not detect each mine, but rather mine *clusters*. This simplified problem statement still constitutes a significant technological challenge, particularly in highly cluttered (natural and anthropic) environments.

To enhance discrimination between targets and clutter, the excitation should be as wideband as possible. However, it is also essential to operate at frequencies for which adequate soil (and foliage) penetration can be effected, particularly for deeply buried targets or regions in which there has been significant foliage growth (for humanitarian demining, one often must deal with mine fields that have been in the ground for decades). The ARL ultra-wideband (UWB) SAR therefore transmits and receives waveforms with usable bandwidth from 50-1200 MHz. Moreover, this system is fully polarimetric, providing access to HH, HV, VH, and VV imagery.

While radar-based subsurface sensing is an old technology, until recently there has been very little modeling done to characterize expected system performance as a function of mine type and environment. In practice there can be wide variability in the mines deployed and in environmental (background) conditions. Therefore, system performance has historically been anecdotal, with excellent performance under certain conditions and unsatisfactory performance elsewhere. Recently, however, we have developed rigorous electromagnetic scattering models for conducting and plastic mines buried in lossy, layered soil (including, potentially, a top layer of snow). Our models are based on a full-wave formulation of Maxwell's equations, with solution via the method of moments (MoM). The principal challenge to making such an analysis tractable is computation of the halfspace or layered-medium Green's function, which we have performed efficiently via the method of complex images. Moreover, we have restricted ourselves to targets that can be simulated as a body of revolution (BOR), simplifying computational complexity significantly. While not all mines can be modeled as a BOR, the vast majority of land mines (both conducting and plastic) are accurately so modeled.

The phenomenological insight garnered from such models can guide system design and automatic target detection and discrimination. In particular, we examine the potential of radar-based sensing as a function of mine type and environment, in the

context of target RCS and possible target resonances. These results quantify the dramatic variability in radar performance that can be achieved, depending on the detailed mine and soil characteristics. We also document that system performance for plastic mines can be enhanced significantly by modifying the properties of the surrounding environment (*e.g.*, enhancement of the dielectric mismatch between a plastic mine and soil, induced by increasing the soil water content). Other issues that we explore include system performance as a function of bandwidth, in which the benefits of enhanced bandwidth (resolution) are examined in the context of the attendant loss in soil penetration. Finally, we address the potential of polarimetric sensing of buried and surface land mines. It is demonstrated theoretically and experimentally that the special symmetry properties of land mines (and the lack of such for clutter) make polarimetric imaging attractive.

In addition to using wave modeling to elucidate phenomenology and guide system design, the target models play an important role in detection and identification algorithms. In particular, optimal detectors require an accurate model for the signature of the target in question. For the case of buried mines, until recently one was required to use *measured* signatures for such applications. However, empirical target models for buried mines are of limited value due to the strong dependence of the target signature on the mine type, target depth, and soil properties. We have therefore utilized our simulated target models as integral parts of a detector, with results presented here for data measured by the BoomSAR at Yuma Proving Ground (Yuma, AZ, USA). Results are presented in the form of receiver operating characteristic (ROC) curves. We also address wavelet-based compression techniques which reduce algorithm complexity.

B. Summary of Most Important Results

Although radar is one of the oldest tools for subsurface sensing, until very recently there has been little rigorous modeling of the fields scattered from or the resonances supported by buried targets. This is in large part due to the complexity of such analyses, which have been aided greatly of late by revolutionary increases in computational power. Therefore, for much of its existence, the efficacy of radar-based subsurface sensing has been assessed based on a limited set of measured data, yielding results in some cases that suggested radar is a panacea and, at the other extreme, cases in which radar failed entirely. It is now understood that the utility of radar-based sensing for buried targets is largely dictated by the details of the problem (target and soil) in question, with the advances in modeling providing the key to appropriate radar deployment.

In demining applications, one generally must interrogate a large swath of terrain. Moreover, standoff is of obvious benefit when attempting to locate these insidious targets. Therefore, ARL has focused on development of a SAR-based system that affords both of these desired attributes. Moreover, the ARL BoomSAR operates over ultra-wideband frequencies (50-1200 MHz), simultaneously providing soil penetration and resolution. Synthetic-aperture radar results have been presented for data measured at Yuma Proving Ground, Yuma, AZ. These data were used to confirm our MoM-based scattering models as well as predictions with regard to the polarimetric properties of most

land mines. In particular, we confirmed that mines that approximate a body of revolution (BOR) excite no cross-polarized backscattered fields.

After substantiating the model accuracy, we used the computed target signatures to effect a detector. This detector accounted for the real-world situation in which the expected mines are generally known, but the exact (spatially varying) soil properties and target depths are often not known exactly. Therefore, these latter properties have been treated within a statistical framework, in which the soil properties and target depth are characterized via statistical distributions. Results have been presented in the form of the receiver operating characteristic (ROC) and indicate that such an approach has promise. We accurately detected a large percentage of the mines, at a relatively low false alarm rate. Moreover, the false alarms tended to be spread sporadically throughout the SAR image (based on *a posteriori* ground-truth knowledge), while the correct mine detections tended to be clustered, as expected of a mine field. Hence, SAR appears to be an attractive option for mine-*field* detection. Finally, a wavelet-based optimization scheme was investigated to improve detector efficiency. Results from this preliminary multi-resolution study appear attractive, but significantly greater computational savings can be achieved by exploiting a multi-resolution scheme that is shift invariant (unlike the spatial wavelet transform).

While the SAR detector results are encouraging, there were some disconcerting issues learned as a consequence of the measurements. In particular, the buried *plastic* mines were virtually invisible to the radar and were *not* detected. Since many mines have only trace metal content, this failure is particularly troubling. The near-invisibility of the plastic mines to radar may be traced to the fact that the electrical contrast between the plastic target and soil was insignificant for the examples considered here. However, while the properties of the plastic mine cannot be changed, the electrical characteristics of the soil can. In particular, we have examined the utility of applying water to a suspected mine field, thereby increasing the electrical contrast between the target and soil. This issue was addressed in the context of the scattered-field amplitude as well as with regard to the natural resonances of such targets. For the soil and (representative) plastic target considered, it was demonstrated that this technique potentially has significant utility. This matter is aided by the fact that most anti-personnel mines are buried near the surface, mitigating the increased soil attenuation.

In addition to the weak target-background contrast, making difficult the detection of plastic mines, the SAR image is contaminated by artifacts due to imperfections in the imaging itself (*e.g.*, angle-dependent effects in the transmitted waveform and in the polarization, which do not currently allow image calibration) as well as radio frequency interference (RFI). It is felt that significant improvements can still be accrued in these areas (for example, through better understanding of the antennas), and that the subsequently improved SAR imagery will play an important role in detecting low-contrast (plastic) targets. Hence, while soil modification will play an important role in detecting such targets, it is felt that significant systems-level improvements are also important. While the current manifestation of the BoomSAR represents a notable engineering achievement, it is felt that significant improvements are still possible.

The M20 mines buried to a depth of 15.24 cm were the weakest scatterers detected from measured data in this study. To quantify the complexity of the problem for plastic mines, our theoretical results indicate that the plastic mine had a scattered amplitude roughly 4% that of the buried M20 mine (with the plastic mine placed in the same soil as considered in the measurements, *buried to a depth of only 2 cm*). This scattered amplitude is well beneath the noise (random system noise, imaging artifacts, and RFI) and clutter floor, and explains why the plastic mines were invisible in the imagery. After increasing the water content to 20%, the plastic mine had a scattered amplitude approximately 20% that of the 15.24 cm deep M20. This is still a very stressing target, but with better imaging techniques and better removal of radio-frequency interference (RFI), it may yet be possible to detect plastic mines.

Finally, the matched-filter-like detector, which was so effective for the measured data considered here, implicitly assumes that the air-soil interface is flat. In humanitarian demining, for which the mines may have been in the ground for decades, this interface may be rough (or foliated by randomizing overgrowth). In this case, electromagnetic transmission through and scattering from the interface must be parametrized as a random process. While this has not been a concern for the data considered here, there are many applications for which such a formulation is essential. We have addressed this issue in detail, and future SAR-based investigations will investigate the utility of such a framework, through consideration of measured data.

C. Refereed Publications

- [1] S. Vitebskiy and L. Carin, "Late-time resonant frequencies of buried bodies of revolution," *IEEE Trans. Antennas Prop.*, vol. 44, pp. 1575-1583, Dec. 1996.
- [2] S. Vitebskiy, L. Carin, M. Ressler and F. Le, "Ultra-wideband, short-pulse ground-penetrating radar: theory and measurement," *IEEE Trans. Geoscience and Remote Sensing*, vol. 35, pp. 762-772, May 1997.
- [3] T. Dogaru and L. Carin, "Time-Domain Sensing of Targets Buried Under a Rough Air-Ground Interface", *IEEE Trans. Antennas Prop.*, vol. 46, pp. 360-372, March 1998.
- [4] N. Geng, C.E. Baum, and L. Carin, "On the low-frequency natural response of conducting and permeable targets," *IEEE Trans. Geoscience and Remote Sensing*, vol. 37, pp. 347-359, Jan. 1999.
- [5] L. Carin, R. Kapoor, C.E. Baum, "Polarimetric SAR imaging of buried landmines," *IEEE Trans. Geoscience and Remote Sensing*, vol. 36, pp. 1985-1988, Nov. 1998.
- [6] D. Wong and L. Carin, "Analysis and processing of ultra-wideband SAR imagery for buried landmine detection," *IEEE Trans. Antennas Propagat.*, vol. 46, pp. 1747-1748, Nov. 1998.

[7] T. Dogaru, L. Collins, and L. Carin, "Optimal detection of a deterministic target buried under a randomly rough interface," submitted to *IEEE Trans. Antennas Propagat.*

[8] L. Carin, N. Geng, M. McClure, J. Sichina, and L. Nguyen, "Ultra-wideband synthetic aperture radar for mine field detection," *IEEE Antennas and Propagation Magazine* (invited), vol. 41, pp. 18-33, Feb. 1999.

[9] N. Geng and L. Carin, "Ultrawideband, short-pulse scattering from a dielectric body of revolution buried in a lossy, dispersive layered medium," *IEEE Trans. Antennas Propagat.*, vol. 47, pp. 610-619, April 1999.

[10] N. Geng, D. Jackson, and L. Carin, "On the resonances of dielectric bodies of revolution buried in a lossy, dispersive layered medium," to appear in the *IEEE Trans. Antennas Propagat.*

[11] N. Geng and L. Carin, "Short-pulse electromagnetic scattering from arbitrarily oriented subsurface ordnance," *IEEE Trans. Geoscience and Remote Sensing*, vol. 37, pp. 2111-2113, July 1999.

[12] N. Geng, M. Ressler, and L. Carin, "Wideband VHF scattering from a trihedral reflector situated above a lossy dispersive halfspace," *IEEE Trans. Geoscience and Remote Sensing*, vol. 37, pp. 2609-2617, Sept. 1999.

[13] N. Dasgupta, N. Geng, T. Dogaru and L. Carin, "On the extended-Born technique for scattering from buried dielectric targets," accepted for publication in the *IEEE Trans. Antennas Propagation*

[14] T. Dogaru and L. Carin, "Application of multiresolution time-domain schemes to two-dimensional electromagnetic scattering problems," submitted to the *IEEE Trans. Antennas Propagat.*

D. Participating personnel

Dr. Norbert Geng (post doc)
Dr. Anders Sullivan (post doc)
Traian Dogaru (PhD earned June 1999)
Mark McClure (PhD earned June 1998)
Bimba Rao (PhD earned May 1999)

E. Report of Inventions

None