

REPORT DOCUMENTATION PAGE

Form Approved
OMB NO. 0704-0188

Public Reporting burden for this collection of information is estimated to average 1 hour per response, including the time for reviewing instructions, searching existing data sources, gathering and maintaining the data needed, and completing and reviewing the collection of information. Send comment regarding this burden estimates or any other aspect of this collection of information, including suggestions for reducing this burden, to Washington Headquarters Services, Directorate for Information Operations and Reports, 1215 Jefferson Davis Highway, Suite 1204, Arlington, VA 22202-4302, and to the Office of Management and Budget, Paperwork Reduction Project (0704-0188,) Washington, DC 20503.

1. AGENCY USE ONLY (Leave Blank)

2. REPORT DATE 05/03/2005

3. REPORT TYPE AND DATES COVERED
Final

4. TITLE AND SUBTITLE

WBGS Epitaxial Materials Development and Scale up for RF/Microwave-Millimeter Wave Devices

5. FUNDING NUMBERS

DAAD190210236

6. AUTHOR(S)

M. Asif Khan, G. Simin, M. Shur, R. Gaska

7. PERFORMING ORGANIZATION NAME(S) AND ADDRESS(ES)

1) Lead: Dept. of EE. Univ. of South Carolina, Columbia, SC 29208.
2) CIE and ECSE Department, RPI, Troy, 12180,
3) Sensor Electronic Technology Inc., 1195 Atlas Road Columbia, SC 29209

8. PERFORMING ORGANIZATION
REPORT NUMBER
15530 FA16

9. SPONSORING / MONITORING AGENCY NAME(S) AND ADDRESS(ES)

U. S. Army Research Office
P.O. Box 12211
Research Triangle Park, NC 27709-2211

10. SPONSORING / MONITORING
AGENCY REPORT NUMBER

11. SUPPLEMENTARY NOTES

The views, opinions and/or findings contained in this report are those of the author(s) and should not be construed as an official Department of the Army position, policy or decision, unless so designated by other documentation.

12 a. DISTRIBUTION / AVAILABILITY STATEMENT

Approved for public release; distribution unlimited.

12 b. DISTRIBUTION CODE

13. ABSTRACT (Maximum 200 words)

The project aimed at significant improvement of the III-nitride based epitaxial materials and device design and fabrication for high-power heterostructure field-effect transistors (HFETs). The key innovative approaches implemented in this program include novel pulsed atomic layer epitaxy (PALE) technique to grow the buffer layer with low defect density, improved epitaxial uniformity in multi-wafer MOCVD reactor, growing HFET wafers with the sheet resistance below 300 Ohm/square. Design improvements include double-heterostructure devices (DHFET) with InGaN electron confinement layer, insulated gate design using SiO₂ gate insulator (MOSDHFETs) and innovative field-plate design. These new devices demonstrated high RF powers 15-20 W/mm at a drain bias of 50-65 V, and good parameter stability at 19 W/mm CW powers as confirmed by 100+ hours testing.

14. SUBJECT TERMS

Nitride materials, MOCVD, FETs, HEMTs, HFETs, Insulating gate FETs, MOSHFETs

15. NUMBER OF PAGES
9

16. PRICE CODE

17. SECURITY CLASSIFICATION
OR REPORT
UNCLASSIFIED

18. SECURITY CLASSIFICATION
ON THIS PAGE
UNCLASSIFIED

19. SECURITY CLASSIFICATION
OF ABSTRACT
UNCLASSIFIED

20. LIMITATION OF ABSTRACT
UL

NSN 7540-01-280-5500

Standard Form 298 (Rev.2-89)
Prescribed by ANSI Std. Z39-18
298-102

GENERAL INSTRUCTIONS FOR COMPLETING SF 298

The Report Documentation Page (RDP) is used for announcing and cataloging reports. It is important that this information be consistent with the rest of the report, particularly the cover and title page. Instructions for filling in each block of the form follow. It is important to **stay within the lines** to meet **optical scanning requirements**.

Block 1. Agency Use Only (Leave blank)

Block 2. Report Date. Full publication date including day, month, and year, if available (e.g. 1 Jan 88). Must cite at least year.

Block 3. Type of Report and Dates Covered. State whether report is interim, final, etc. If applicable enter inclusive report dates (e.g. 10 Jun 87 - 30 Jun 88).

Block 4. Title and Subtitle. A title is taken from the part of the report that provides the most meaningful and complete information. When a report is prepared in more than one volume, repeat the primary title, and volume number, and include subtitle for the specific volume. On classified documents enter the title classification in parentheses.

Block 5. Funding Numbers. To include contract and grant numbers; may include program element number(s) project number(s), task number(s), and work unit number(s). Use the following labels:

C - Contract	PR - Project
G - Grant	TA - Task
PE - Program Element	WU - Work Unit Accession No.

Block 6. Author(s). Name(s) of person(s) responsible for writing the report, performing the research, or credited with the content of the report. If editor or compiler, this should follow the name(s).

Block 7. Performing Organization Name(s) and Address(es). Self-explanatory.

Block 8. Performing Organization Report Number. Enter the unique alphanumeric report number(s) assigned by the organization performing the report.

Block 9. Sponsoring/Monitoring Agency Name(s) and Address(es). Self-explanatory.

Block 10. Sponsoring/Monitoring Agency Report Number. (if known)

Block 11. Supplementary Notes. Enter information not included elsewhere such as; prepared in cooperation with....; Trans. of....; To be published in.... When a report is revised, include a statement whether the new report supersedes or supplements the older report.

Block 12a. Distribution/Availability Statement.

Denotes public availability or limitations. Cite any availability to the public. Enter additional limitations or special markings in all capitals (e.g. NORFON, REL, ITAR).

DOD - See DoDD 4230.25, "Distribution Statements on Technical Documents."

DOE - See authorities.

NASA - See Handbook NHB 2200.2.

NTIS - Leave blank.

Block 12b. Distribution Code.

DOD - Leave Blank

DOE - Enter DOE distribution categories from the Standard Distribution for unclassified Scientific and Technical Reports

NASA - Leave Blank.

NTIS - Leave Blank.

Block 13. Abstract. Include a brief (*Maximum 200 words*) factual summary of the most significant information contained in the report.

Block 14. Subject Terms. Keywords or phrases identifying major subject in the report.

Block 15. Number of Pages. Enter the total number of pages.

Block 16. Price Code. Enter appropriate price code (NTIS only).

Block 17. - 19. Security Classifications. Self-explanatory. Enter U.S. Security Regulations (i.e., UNCLASSIFIED). If form contains classified information, stamp classification on the top and bottom of the page.

Block 20. Limitation of Abstract. This block must be completed to assign a limitation to the abstract. Enter either UL (Unlimited) or SAR (same as report). An entry in this block is necessary if the abstract is to be limited. If blank, the abstract is assumed to be unlimited.

REPORT DOCUMENTATION PAGE (SF298)
(Continuation Sheet)

Statement of the problem studied

The program focused on the most important unresolved problems that impede the incorporation of high-power nitride based heterostructure field-effect transistors (HFETs) technology into defense and commercial systems.

These problems include:

1. Poor doping, thickness and composition uniformity of the HFET epitaxial layers over (2") substrates.
2. Poor reproducibility of epitaxial growths from run to run.
3. Lack of availability and epitaxial growth optimization over 4" substrates.
4. Aging effects and parameter degradation in AlGa_N/Ga_N HFETs.
5. RF dispersion and current collapse in AlGa_N/Ga_N HFETs high-power devices.

To overcome the above problems several innovative research approaches has been undertaken in the course of the program. The major research efforts have been aimed to:

- Develop innovative buffer-layer technology to mitigate substrate surface and bulk quality.
- Improve epitaxial uniformity in multi-wafer reactor to meet program goals.
- Scale-up growth process to 4-inch substrates.
- Incorporate double heterostructure epilayer designs for improved carrier confinement (*DHFET*)
- Improve the performance and stability via insulating gate (MOSDHFET) device design.
- Correlate material and device characteristics to study and optimize:

Current collapse

Long-term DC and RF power stability

Summary of the key achievements.

I. Uniformity and quality of epitaxial materials for HFET devices

Epitaxial barrier/ buffer layers quality is a key parameter controlling the DC and RF performance of the nitride based HFETs. The problem of growing the high quality materials arises mainly from significant lattice mismatch between the SiC substrate and Ga_N epitaxial layer as well as from the strain induced at the Ga_N - AlGa_N interface.

A novel approach to radically improve the Ga_N buffer layer quality based on pulsed atomic layer epitaxy (PALE) further developed into more advanced Migration Enhanced MOCVD (MEMOCVD) technology was used. These new techniques resulted in significant improvement in the Ga_N crystalline quality.

GaN buffer layers grown by conventional MOCVD technique demonstrated the X-ray diffraction ω -scan with the HWFM of typically 550 sec. Novel pulsed epitaxial growth technique resulted in 330 sec line-width (PALE growth), which was further improved to obtain 230 sec line-width (MEMOCVD growth) in the course of the program. Excellent run-to-run uniformity of the XRD ω -scan line-width was achieved. For 15 sequential runs, the line-width deviation does not exceed 50 sec.

The pictures below illustrate the quality of MEMOCVD grown 2", 3" and 4" HFET structures.




Figure 1. XRD omega scan of MEMOCVD grown AlN buffer




Figure 2. Resistivity map of the HFET structure on a 2" SiC wafer





Figure 3. Resistivity map of the HFET structure on a 3" SiC wafer



II. Insulated Gate MOSDHFET Device design

Gate leakage current in conventional HFETs is a major contributor to device instability and failure. The development of Metal-Oxide-Semiconductor Insulated gate HFETs (MOSHFETs) leads to the gate leakage currents four to six orders of magnitude lower than those of the HFETs (see Figure 5). The MOSHFETs has demonstrated a significant performance improvement as compared to conventional HFETs resulting in higher channel currents and RF powers. In the course of this study, we have carried out a comparative experimental evaluation of the HFET and MOSHFET lifetime at room and elevated temperatures. The room temperature MOSHFET stability lifetime as high in excess of 21,000 hours is estimated. The pronounced similarity of the mechanisms of device degradation and current collapse has been observed.




Figure 5. Comparative I-V characteristics of the sub-micron gate HFET and MOSHFET




Figure 6. The effect of high input RF powers on the HFET gate leakage currents.

Figure 6 illustrates an increase in the DC components of the HFET gate current with the input RF powers. Note that the gate current direction corresponds to the forward currents in spite of the negative DC bias. When a Schottky gate FET operates under large input signal, the maximum peak gate voltage may cause forward currents through the gate leading to different degradation mechanisms, including tunnel and avalanche breakdown. Dynamic forward gate biasing becomes even more important in high-power high-voltage devices such as AlGaIn/GaN HFETs.




Figure 7. Aim-Spice simulations for the HFET gate voltage, drain voltage and gate current at 40 V drain bias and -2V gate bias. For the simulations, the model parameters were fitted to the experimental HFET data. The capacitive component of the gate current is not shown to simplify the waveforms.

As seen from Figure 7, the dynamic forward biasing coming from a large amplitude of the input signal causes up to 25 mA peak forward gate currents. We have found a strong correlation between RF power stability and an increases in the dynamic forward gate currents, as illustrated in Figure 8.




Figure 8. RF stability of the HFET and MOSHFET devices fabricated on the same SiC wafer.

III. Stable High-Power Field-Plated MOSDHFET.

Using a field-plate (FP) device design that was previously applied to GaAs HEMTs, several groups (NEC, UCSB, Cornell Univ., TriQuint et. al.) recently reported on HFETs with significantly improved RF-power performance, which they attributed to an increase in the breakdown voltage and a decrease in the current-collapse by the channel field reduction. They demonstrated microwave powers ranging from 10-W/mm at $V_{ds} = 65$ V to 30 W/mm at $V_{ds} = 120$ V. However, all the reported FP devices suffered from degradation at high RF power levels. As confirmed by several research groups including ours, the degradation mainly comes from the excessive gate current.

The MOSHFET design approach allows the application of high positive gate voltages thereby increasing the device peak currents. It also suppresses the gate leakage current. In the course of current work, combining the MOSHFET design with a field-plate, we for the first time achieved a stable operation at 2 GHz for times in excess of 100 hours and at power densities as high as 19-W-mm ($V_{ds} = 55$ V). The extremely low leakage currents for our insulating gate device configuration enable us to achieve the long term stability in spite of the high power densities.




Figure 9. (a): Drain bias dependence of output RF power at 2 GHz for a MOSDHFET with and without field plate. (b): Power sweep at 2 GHz for 200 μm wide device. The device dimensions are: $L_{\text{sd}} = 6 \mu\text{m}$, $L_g = 1.1 \mu\text{m}$, $L_{\text{FP}} = 2.1 \mu\text{m}$ with a 1.1 μm overlap with the gate.




Figure 10. Output power at 2GHz for identical geometry field-plated MOSHFET and HFET as a function of time. The drain bias for both FP device types was 55 V. The right axis shows the time dependence of DC component of the HFET gate current. The current under the MOSHFET gate is too low to be shown and does not show any significant increase over the time.

IV. Conclusion.

By combining the innovative growth, device design and fabrication technique, in the course of this project we demonstrated the highest RF powers (close to 20 W/mm) at 55V drain bias, the highest Power-Voltage efficiency (0.36 W/V) and the first high-power stable performance at the power levels as high as $\sim 20\text{W/mm}$. We have also successfully demonstrated the technology scale-up to grow high-quality 3" and 4" HFET epitaxial structures..

MASTER COPY: PLEASE KEEP THIS "MEMORANDUM OF TRANSMITTAL" BLANK FOR REPRODUCTION PURPOSES. WHEN REPORTS ARE GENERATED UNDER THE ARO SPONSORSHIP, FORWARD A COMPLETED COPY OF THIS FORM WITH EACH REPORT SHIPMENT TO THE ARO. THIS WILL ASSURE PROPER IDENTIFICATION. NOT TO BE USED FOR INTERIM PROGRESS REPORTS; SEE PAGE 2 FOR INTERIM PROGRESS REPORT INSTRUCTIONS.

MEMORANDUM OF TRANSMITTAL

U.S. Army Research Office
ATTN: AMSRL-RO-BI (TR)
P.O. Box 12211
Research Triangle Park, NC 27709-2211

- | | |
|--|---|
| ☐ Reprint (Orig + 2 copies) | ☐ Technical Report (Orig + 2 copies) |
| ☐ Manuscript (1 copy) | ☒ Final Progress Report (Orig + 2 copies) |
| | ☐ Related Materials, Abstracts, Theses (1 copy) |

CONTRACT/GRANT NUMBER:

REPORT TITLE: **WBGS Epitaxial Materials Development and Scale up for RF/Microwave-Millimeter Wave Devices**

is forwarded for your information.

SUBMITTED FOR PUBLICATION TO (applicable only if report is manuscript):

Sincerely,



M. Asif Khan



G. Simin