

Delay Time Enhanced Flat Band Photonic Crystal Waveguides with Capsule-shaped Holes on Silicon Nanomembrane

Yun-Sheng Chen, Yang Zhao, Amir Hosseini, David Kwong, Wei Jiang, *Member, IEEE*, Seth R. Bank, *Member, IEEE*, Emanuel Tutuc, *Member, IEEE*, Ray T. Chen, *Fellow, IEEE*

Abstract—A slow group velocity and low group velocity dispersion photonic crystal slab waveguide is designed by using capsule shaped air holes in hexagonal lattice. The theoretical study shows that adjusting the aspect ratio of holes in the innermost rows can fine tune the dispersion tail. The presented design can achieve nearly flat band photonic crystal waveguides with group index of 21-36 over the normalized bandwidth ($\Delta\omega/\omega$) of 1.38%~0.4%. We also discuss the effects of the change in the holes' aspect ratio combined with a slight size adjustment. The group index in the range of 21~43 for normalized bandwidth of about 1.5%~0.3% is obtained with the combination effect. The optimized designed exhibits a nearly constant group index of 21 over 22.7 nanometer bandwidth at $\lambda=1.55\mu\text{m}$.

Index Terms—photonic crystal waveguide, slow group velocity, group velocity dispersion.

I. INTRODUCTION

THE interest in manipulating the speed of propagating light has increased dramatically in recent years for applications such as optical delay lines [1], optical buffers [2, 3], and all optical switches [4, 5]. The possibility to compress the energy and signal provides the opportunity for reducing the footprint of the devices. In addition, the strong light-matter interaction due to the small group velocity enhances the absorptions, non-linearity, and gains per unit length which benefits numerous of optical devices, such as detectors, amplifiers, and lasers [6, 7]. In recent years, the engineered slow light photonic crystals have drawn a great deal of attention by researchers because of the flexibility in design and compatibility for on-chip applications. Slow light three dimensional semiconductor photonic crystals with a complete band gap are ideal candidates, however their fabrication is challenging. Planar photonic crystal slabs fabricated on semiconductor membrane, such as silicon on insulator (SOI) wafers, where light is confined in-plane by the

band gap of two-dimensional (2-D) photonic crystals [8-10] or by 2-D negative refractive index photonic crystals [11] and vertically by total internal reflection of index contrast are alternative solutions because of their relative ease of fabrication. However, the narrow bandwidth due to the highly dispersive group velocity of the photonic crystal slabs in the slow light regime restricts their applications [12]. Several research groups have achieved low group velocity dispersion (GVD) by adjusting the waveguide width [13-15], the size of the first two innermost rows of holes [16, 17], the displacement of the first two rows [18], or by chirping the property of photonic crystals [19]. In this paper, a design of photonic crystal slab waveguide with a nearly constant group index of 21




Fig. 1. (a) The geometry of the capsule shaped hole photonic crystal waveguide with hexagonal lattice. Two half circles with diameter of $2r$ at both terminals and a rectangle with a width of $2r$ and length of l in the middle assemble the capsule. (b) A typical band diagram of the capsule shaped photonic crystal. The red dot line indicates the index guided regime and blue dot curve shows the gap guided regime. The inset illustrates the 1×6 supercell in plane, which has 6 periods in the vertical direction to ensure that the defect is sufficiently isolated.

Manuscript received Jan 3, 2009; revised Jan 28, Mar 5 and Mar 29, 2009; accepted Apr 3, 2009. This work was supported by the multi-disciplinary university research initiative (MURI) program through the AFOSR.

Y.-S. Chen, Y. Zhao, A. Hosseini, D. Kwong, S. R. Bank, E. Tutuc and R. T. Chen are with Microelectronic Research Center, Department of Electrical and Computer Engineering, University of Texas at Austin, Austin, TX 78758 USA (corresponding author e-mail: chen@ece.utexas.edu). W. Jiang is with the Department of Electrical and Computer Engineering and Institute for Advanced Materials, Devices and Nanotechnology, Rutgers University, Piscataway, NJ 08854, USA

Report Documentation Page				Form Approved OMB No. 0704-0188	
Public reporting burden for the collection of information is estimated to average 1 hour per response, including the time for reviewing instructions, searching existing data sources, gathering and maintaining the data needed, and completing and reviewing the collection of information. Send comments regarding this burden estimate or any other aspect of this collection of information, including suggestions for reducing this burden, to Washington Headquarters Services, Directorate for Information Operations and Reports, 1215 Jefferson Davis Highway, Suite 1204, Arlington VA 22202-4302. Respondents should be aware that notwithstanding any other provision of law, no person shall be subject to a penalty for failing to comply with a collection of information if it does not display a currently valid OMB control number.					
1. REPORT DATE 2009		2. REPORT TYPE N/A		3. DATES COVERED -	
4. TITLE AND SUBTITLE Delay Time Enhanced Flat Band Photonic Crystal Waveguides with Capsule-shaped Holes on Silicon Nanomembrane				5a. CONTRACT NUMBER	
				5b. GRANT NUMBER	
				5c. PROGRAM ELEMENT NUMBER	
6. AUTHOR(S)				5d. PROJECT NUMBER	
				5e. TASK NUMBER	
				5f. WORK UNIT NUMBER	
7. PERFORMING ORGANIZATION NAME(S) AND ADDRESS(ES) Microelectronic Research Center, Department of Electrical and Computer Engineering, University of Texas, Austin, TX 78758 USA				8. PERFORMING ORGANIZATION REPORT NUMBER	
9. SPONSORING/MONITORING AGENCY NAME(S) AND ADDRESS(ES)				10. SPONSOR/MONITOR'S ACRONYM(S)	
				11. SPONSOR/MONITOR'S REPORT NUMBER(S)	
12. DISTRIBUTION/AVAILABILITY STATEMENT Approved for public release, distribution unlimited					
13. SUPPLEMENTARY NOTES The original document contains color images.					
14. ABSTRACT					
15. SUBJECT TERMS					
16. SECURITY CLASSIFICATION OF:			17. LIMITATION OF ABSTRACT UU	18. NUMBER OF PAGES 5	19a. NAME OF RESPONSIBLE PERSON
a. REPORT unclassified	b. ABSTRACT unclassified	c. THIS PAGE unclassified			




Fig. 2. (a) The waveguide mode dispersion with various aspect ratios which are larger than one, with fixed area ratio R equal to one. The guiding modes move towards higher frequency as the aspect ratio is increased. (b) The corresponding group velocities of the guided modes. The gray bar marked the regime that the group velocity fluctuation is within $\pm 10\%$. (c) The corresponding GVD of the guided modes indicate that in the flat band regime the GVD fluctuation is smaller than ± 0.07 nsec/nm/cm for the case of $A=2.3$, and is smaller than ± 0.05 nsec/nm/cm for the rest cases.

over 22.7nm centered at $\lambda=1.55\mu\text{m}$ is reported, which could provide an alternative path to approach the flat band photonic crystal waveguides.

II. DESIGN OF PHOTONIC CRYSTAL SLAB WAVEGUIDE

An air-bridged silicon photonic crystal slab waveguide with a hexagonal lattice and “capsule” shaped air holes is considered in the calculations. As shown in Fig. 1 (a), a , t , $2r+l$ and $2r$ denotes the periodicity, the slab thickness, the total length of capsule, and the width of the capsule, respectively. The refractive index of the slab, n , is 3.46 at $\lambda=1.55\mu\text{m}$ and t is $0.6a$. The slab is laid on the x - z plane and a line waveguide is formed by removing a single row of holes along x direction in real space which is corresponding to the ΓK direction of the reciprocal lattice. Due to the introduction of the line defect, the Brillouin Zone edge is shifted from K to K' instead [20]. The band structure of the photonic crystal, as illustrated in Fig. 1 (b), is calculated using BandSOLVETM of the Rsoft Photonics CAD Design Suite based on three dimensional plane-wave-expansion (PWE) method and projected from the ΓM direction onto the $\Gamma K'$ direction, which gives the boundary of the first Brillouin zone. The defect modes inside the band gap are studied by replacing a 1×1 unit cell with a supercell which is 1 unit in the x direction and 6 units in the z direction in the PWE calculation, as shown in the inset of Fig. 1 (b). The figure also shows a lateral even guided mode and a lateral odd guided mode, and both of them are vertical even modes. The vertical even mode is defined as the mode symmetric with respect to the x - z plane. The lateral even guided mode is defined as the mode

symmetric with respect to the x - y plane, which is a fundamental mode, while the lateral odd guided mode is a higher order mode. The group velocity of a guided mode is calculated from its definition as the derivative of the angular frequency over the wavevector.

$$v_g \equiv \frac{\partial \omega}{\partial k} \quad (1)$$

The derivative of the reciprocal group velocity over the frequency gives the GVD.

$$GVD = \frac{\partial(1/v_g)}{\partial \lambda} \quad (2)$$

In photonic crystal slab waveguide modes, there coexist gap guided modes and index guided modes. A high GVD happens at the anticrossing point where gap guided modes and index guided modes couple with each other [12]. One can tailor the dispersion curve and shift the anticrossing point by engineering the parameters of the line defect. Frandsen *et al.* have proposed an approach to “flatten” the dispersion curve by perturbing the size of the periodic holes of the two innermost rows close to the defect [16]. An alternative new approach that this paper presents, aims to control the shift of gap guided mode, thus flattening the dispersion curve by manipulating the aspect ratio of the capsule shaped air holes.

The aspect ratio of the capsule shaped holes is defined as

$$A = \begin{cases} \frac{2r'+l'}{2r'}, & A > 1 \\ \frac{2r'}{2r'+l'}, & A < 1 \end{cases} \quad (3)$$




Fig. 3. (a) The waveguide mode dispersion with various aspect ratios which are smaller than one, with fixed area ratio R equal to one. The guided modes move towards higher frequency as the aspect ratio is decreased. (b) The corresponding group velocities of the guided modes. The gray bar marked the regime that the group velocity fluctuation is within $\pm 10\%$. (c) The corresponding GVD of the guiding modes which indicate that in the flat band regime the GVD fluctuation is smaller than ± 0.1 nsec/nm/cm.




Fig. 4. Systematic calculation of product $ng(\Delta\omega/\omega)$ as a function of area ratio R and aspect ratio A . The color bar indicates the product which is calculated to be within 0.03 to 0.3, when R is in the range of 0.92 to 1.08 and A is from 0.6 to 2.0.

where r is the radius of curvature at the two terminals of the capsule, and l is the length of the straight portion of the capsule as shown in Fig. 1 (a). r' especially denotes that of the inner most rows, and so does l' . The dispersion relations of the calculated fundamental modes with various values of A are illustrated respectively in Fig. 2 (a) and Fig. 3 (a) under two different conditions. Corresponding schematic structures of the photonic crystal waveguide with aspect ratio of the holes bigger than 1 and smaller than 1 are shown in the insets of Fig. 2 (a) and Fig. 3 (a) accordingly. Aspect ratios of outside holes except for the innermost rows are fixed during the calculation, where the radius r is $0.162a$, the length l is $0.35a$, which corresponds to an aspect ratio of 2.08, and area of the hole of $0.196a^2$. The area ratio which is defined as R below denotes the relative area ratio of innermost holes over outside holes.

$$R = \frac{\pi r'^2 + 2r' \cdot l'}{\pi r^2 + 2r \cdot l} \quad (4)$$

In the calculations of Fig. 2 and Fig. 3, R is kept as 1, which indicates that all the capsule holes have the same size no matter of their locations in the waveguide. Under this condition, the designed photonic crystal waveguide can provide a sufficient bandgap width for operation wavelength at $1.55\mu\text{m}$ with corresponding periodicity within $400\sim 450\text{nm}$.

III. RESULTS AND DISCUSSIONS

To observe the effect of tuning the aspect ratio of holes at the inner most rows on the dispersion relation, group velocity as well as the GVD, aspect ratios of the innermost holes are changed with a fixed area equal to the outside holes. Aspect ratios of 1.4, 1.6, 1.9, 2.1 and 2.3 are chosen as an example. The trend is clear as A increases, both the index guided mode and gap guided mode move towards higher frequency, but with the tendency that the gap guided modes moving faster than the index guided mode, a sharper GVD happens at a lower wavevector when A increases. Fig. 2 (b) and (c) show two sets

of comparison of group velocity and GVD respectively at the above mentioned aspect ratios. The GVD tends to vanish as A decreases, but increase after $A=1.6$.

An aspect ratio smaller than 1 is realized by rotating the holes of the inner most rows close to the line defect 90 degree around the center of the hole, which is shown as the inset of Fig. 3 (a), and A is defined as in (3). When $A < 1$, the trend of dispersion relation is opposite. It is when A decreases, that the gap guided regime will move towards a higher frequency and form a sharp dispersion. Corresponding dispersion relation, group velocity and GVD with aspect ratios of 0.6, 0.7, 0.8 and 0.9 are shown in Fig. 3 (b) and (c) to illustrate such phenomenon. These aspect ratios are reciprocals of 1.67, 1.43, 1.25 and 1.11. For instance, if A changes from 0.6 to 0.7, it can be considered to change an amount of 16.67%, which is similar to the degree of change when A changes from 1.6 to 1.9 in $A > 1$ case. However, with the same amount of change in aspect ratio, when $A < 1$, Fig. 3 (a) shows that gap guided regime moves much faster than under the $A > 1$ case, which indicates that with a small aspect ratio (< 1) of the inner most holes, the gap guided modes are more sensitive to the change of the aspect ratio. Furthermore, one can observe that in the case of $A > 1$, the designed structure can control the GVD within 0.05nsec/nm/cm with properly chosen aspect ratio with group index around 30.

The effect of the manipulation of aspect ratio as well as the size of the innermost holes is also studied to show the influence of holes' size in combination with A on pursuing a nearly constant group index and to further investigate the tolerance of the design. Fig. 4 illustrates the systematic calculation of the product of group index (n_g) and normalized bandwidth ($\Delta\omega/\omega$) [17] covering a range of A from 0.6 to 2.0 and R from 0.92 to 1.08. The bandwidth $\Delta\omega$ is defined as the frequency range which is corresponding to the change of group index within $\pm 10\%$, where the group index is considered constant [18]. The relative area ratio R is slightly tailored to represent a possible deviation of the area ratio causing by fabrication process. Fig. 4 indicates that a flat band slow light region can be traced at the




Fig. 5. An approaching constant group index with change of the relative area ratio R . When R is around 1.0, a nearly constant group index of 36 can be achieved with aspect ratio of 2.0.

maroon area where the product $n_g(\Delta\omega/\omega)$ [16] reaches its highest value above 0.3 and the group index keeps almost constant when A is around 1.6. The calculation shows under the condition that A is fixed at 1.6, when the increment of R is less than 4%, the product $n_g(\Delta\omega/\omega)$ remains almost constant, and when the R is slightly decreased to the range of 0.92~0.94, the product $n_g(\Delta\omega/\omega)$ slightly increases to 0.304. In other words, with slight R change within 10%, the product of $n_g(\Delta\omega/\omega)$ remains nearly constant at 0.3. This result reveals one of the advantages of such design, the robustness against the change of holes sizes, if a proper aspect ratio is chosen. This advantage can release the stringent requirement of controlling precise hole sizes during the fabrication process. Fig. 5 further explains the effect of aspect ratio combined with area change to achieve a nearly constant group index. When the hole area is fixed, in the flat band region, the average group index increases and the fluctuation is reduced as aspect ratio increases; while under the same aspect ratio, a higher area ratio R can reduce the fluctuation. In a previously reported method by changing positions of first two rows of holes, the group index fluctuation in the flat band region increases as the group index increases [18], which indicates the GVD increases at a higher group index. In comparison, in the proposed design the fluctuation of group index in the flat band region remains almost to the same extent when the group index increases as shown in Fig. 5. With proper choice of aspect ratio, a vanishing GVD within $\pm 0.05\text{nsec/nm/cm}$ is achieved which is twice smaller than the data reported as in [14] under similar group index. Under such circumstances, an almost optimized flat band which is marked correspondingly as the gray region in Fig. 2 (b) and as the black solid curve in Fig. 5 with normalized bandwidth ($\Delta\omega/\omega$) of 1.38% can be achieved, and the maximum group index-bandwidth product $n_g(\Delta\omega/\omega)$ is 0.304.

IV. CONCLUSION

Slow group velocity photonic crystal waveguide with vanishing GVD by using capsule shaped air holes on hexagonal lattice is proposed. Theoretical study on the effect of fine tuning the aspect ratio of the innermost holes on flattening the group velocity dispersion is briefly introduced. A nearly flat band photonic crystal waveguides with group index of 21-36 over the normalized bandwidth ($\Delta\omega/\omega$) of 1.38%~0.4% can be achieved with this design. In combination with the size tuning effect, group index in the range of 21~43 for normalized bandwidth about 1.5%~0.3% is obtained. The optimized design exhibits a nearly constant group index of 21 over 22.7 nm and 32 over 8 nm at $\lambda=1.55\mu\text{m}$, which corresponds to a 700 ps and 1.1 nsec delay time with bandwidth of 2.8 THz and 1 THz for a centimeter long device, respectively. The proposed idea can lead to an alternative route to achieve flat band, and the studied effect can contribute an extra degree of freedom to the design and fabrication of slow light photonic crystal slab waveguides with vanishing group velocity dispersion.

REFERENCES

- [1] M. S. Moreolo, V. Morra, and G. Cincotti, "Design of photonic crystal delay lines based on enhanced coupled-cavity waveguides," *Journal of Optics a-Pure and Applied Optics*, vol. 10, p. 064002, Jun 2008.
- [2] C. J. Chang-Hasnain, P. C. Ku, J. Kim, and S. L. Chuang, "Variable optical buffer using slow light in semiconductor nanostructures," *Proceedings of the IEEE*, vol. 91, pp. 1884-1897, Nov 2003.
- [3] J. B. Khurgin, "Optical buffers based on slow light in electromagnetically induced transparent media and coupled resonator structures: comparative analysis," *Journal of the Optical Society of America B-Optical Physics*, vol. 22, pp. 1062-1074, May 2005.
- [4] S. F. Mingaleev, A. E. Miroshnichenko, Y. S. Kivshar, and K. Busch, "All-optical switching, bistability, and slow-light transmission in photonic crystal waveguide-resonator structures," *Physical Review E*, vol. 74, p. 046603, Oct 2006.
- [5] S. F. Mingaleev, A. E. Miroshnichenko, Y. S. Kivshar, and K. Busch, "All-optical switching, bistability, and slow-light transmission in photonic crystal waveguide-resonator structures," *Physical Review E*, vol. 74, p. 15, Oct 2006.
- [6] M. Soljacic, S. G. Johnson, S. H. Fan, M. Ibanescu, E. Ippen, and J. D. Joannopoulos, "Photonic-crystal slow-light enhancement of nonlinear phase sensitivity," *Journal of the Optical Society of America B-Optical Physics*, vol. 19, pp. 2052-2059, Sep 2002.
- [7] R. Iliew, C. Etrich, T. Pertsch, and F. Lederer, "Slow-light enhanced collinear second-harmonic generation in two-dimensional photonic crystals," *Physical Review B*, vol. 77, p. 115124, Mar 2008.
- [8] T. Baba, "Slow light in photonic crystals," *Nature Photonics*, vol. 2, pp. 465-473, Aug 2008.
- [9] E. Chow, S. Y. Lin, S. G. Johnson, P. R. Villeneuve, J. D. Joannopoulos, J. R. Wendt, G. A. Vawter, W. Zubrzycki, H. Hou, and A. Alleman, "Three-dimensional control of light in a two-dimensional photonic crystal slab," *Nature*, vol. 407, pp. 983-986, Oct 2000.
- [10] S. G. Johnson, S. H. Fan, P. R. Villeneuve, J. D. Joannopoulos, and L. A. Kolodziejski, "Guided modes in photonic crystal slabs," *Physical Review B*, vol. 60, pp. 5751-5758, Aug 1999.
- [11] J. L. He, Y. Jin, Z. Hong, and S. L. He, "Slow light in a dielectric waveguide with negative-refractive-index photonic crystal cladding," *Optics Express*, vol. 16, pp. 11077-11082, Jul 2008.
- [12] M. Notomi, K. Yamada, A. Shinya, J. Takahashi, C. Takahashi, and I. Yokohama, "Extremely large group-velocity dispersion of line-defect waveguides in photonic crystal slabs," *Physical Review Letters*, vol. 87, p. 253902, Dec 2001.
- [13] J. M. Brosi, J. Leuthold, and W. G. Freude, "Microwave-frequency experiments validate optical simulation tools and demonstrate novel dispersion-tailored photonic crystal waveguides," *Journal of Lightwave Technology*, vol. 25, pp. 2502-2510, Sep 2007.
- [14] A. Y. Petrov and M. Eich, "Zero dispersion at small group velocities in photonic crystal waveguides," *Applied Physics Letters*, vol. 85, pp. 4866-4868, Nov 2004.
- [15] M. D. Settle, R. J. P. Engelen, M. Salib, A. Michaeli, L. Kuipers, and T. F. Krauss, "Flatband slow light in photonic crystals featuring spatial pulse compression and terahertz bandwidth," *Optics Express*, vol. 15, pp. 219-226, Jan 2007.
- [16] L. H. Frandsen, A. V. Lavrinenko, J. Fage-Pedersen, and P. I. Borel, "Photonic crystal waveguides with semi-slow light and tailored dispersion properties," *Optics Express*, vol. 14, pp. 9444-9450, Oct 2006.
- [17] S. Kubo, D. Mori, and T. Baba, "Low-group-velocity and low-dispersion slow light in photonic crystal waveguides," *Optics Letters*, vol. 32, pp. 2981-2983, Oct 2007.
- [18] J. Li, T. P. White, L. O'Faolain, A. Gomez-Iglesias, and T. F. Krauss, "Systematic design of flat band slow light in photonic crystal waveguides," *Optics Express*, vol. 16, pp. 6227-6232, Apr 2008.
- [19] D. Mori and T. Baba, "Wideband and low dispersion slow light by chirped photonic crystal coupled waveguide," *Optics Express*, vol. 13, pp. 9398-9408, Nov 2005.
- [20] S. G. Johnson, P. R. Villeneuve, S. H. Fan, and J. D. Joannopoulos, "Linear waveguides in photonic-crystal slabs," *Physical Review B*, vol. 62, pp. 8212-8222, Sep 2000.

Yun-Sheng Chen (SM'08) received his M.S. degree in Optics from the College of Optics and Photonics-CREOL, the University of Central Florida. He is currently working towards his Ph.D. degree at the department of electrical and computer engineering, University of Texas at Austin. His research interest is focused on photonic crystal waveguide, optical true time delay, and nano-fabrication.

Yang Zhao (SM'08) received her M.S. degree in Optics in May 2008 from College of Optics and Photonics-CREOL, the University of Central Florida. She is currently working toward her PhD degree at the department of Electrical and Computer Engineering, the University of Texas at Austin. Her current research interest is focused on Si photonics, optical phased array and nano-fabrication.

Amir Hosseini (SM'05) received his B.Sc. degree (with honors) in electrical engineering in 2005 from Sharif University of Technology, Tehran, Iran, and the M.S. degree in electrical and computer engineering in 2007 from Rice University, Houston, TX. He is currently working toward his Ph.D. degree in Optical Interconnect Group at The University of Texas at Austin, Department of Electrical and Computer Engineering. He is engaged in research on optical phased array technology and high performance optical modulators design and optimizations. His main focus is on the design optimization for nano-scale manufacturability.

David Kwong received his BS degree in electrical engineering in 2006 from the University of Texas at Austin. He is currently pursuing his Master's Degree with the Optical Interconnect Group at UT Austin, with a focus on optical phased array technology and optical modulation. Before joining UT Austin, Kwong spent two years working at Samsung Austin Semiconductor in process integration for DRAM Back End Of Line (BEOL) processes.

Wei Jiang received the B.S. degree in physics from Nanjing University, Nanjing, China, in 1996, and the M.A. degree in physics and the Ph.D. degree in electrical and computer engineering from the University of Texas, Austin, in 2000 and 2005, respectively.

He held research positions with Omega Optics, Inc., Austin, Texas from 2004 to 2007. Since September 2007, he has been an Assistant Professor in the Department of Electrical and Computer Engineering, Rutgers University, Piscataway, NJ. His current research interests include photonic crystals, silicon photonics, optical interconnects, and beam steering.

Seth R. Bank (S'95, M'06) received the B.S. degree from the University of Illinois at Urbana-Champaign (UIUC), Urbana, IL in 1999 and the M.S. and Ph.D. degrees in 2003 and 2006 from Stanford University, Stanford, CA, all in electrical engineering. While at UIUC, he studied the fabrication of InGaP-GaAs and InGaAs-InP HBTs. His Ph.D. research focused upon the MBE growth, fabrication, and device physics of long-wavelength VCSELs and low-threshold edge-emitting lasers in the GaInNAs(Sb)-GaAs material system. In 2006, he was a post-doctoral scholar at the University of California, Santa Barbara, CA where his research centered on the growth of metal-semiconductor hetero- and nano-structures (e.g. ErAs nanoparticles in GaAs). He is currently an Assistant Professor of Electrical and Computer Engineering at the University of Texas at Austin, Austin, TX. His current research interests are the MBE growth of novel heterostructures and nanocomposites and their application to silicon-based lasers, mid-IR lasers, THz generation and sensing, and high-speed/low-power transistors. He has coauthored over 130 papers and presentations in these areas.

Dr. Bank is a recipient of a 2008 DARPA Young Faculty Award, the 2008 Young Investigator Award from the North American MBE Meeting, a Best Paper Award at the 2006 Rank Prize Minisymposium on Dilute-Nitrides, a 2005 Ross N. Tucker Award (Stanford), a Student Paper Award from the 2005 North American MBE Meeting, a 2004 Electronic Materials Conference Student Award, the Gerald L. Pearson Memorial Fellowship (Stanford), and a John Bardeen Scholarship (UIUC).

Emanuel Tutuc received the B.S. and M.S. degrees from Ecole Normale Supérieure, The University of Paris, France in 1997 and 1998, and the Ph.D. degrees in 2004 from Princeton University, all in physics. His Ph.D. research focused upon the MBE growth of ultra-high mobility electron systems, and the physics of interacting electron systems in two dimensions. Between 2004 and 2006, he was a post-doctoral research at I.B.M. T.J. Watson Research Center, Yorktown Heights, NY where his research centered on the growth and electronic properties of Si and Ge nanowires and heterostructures. He is currently an Assistant Professor of Electrical and Computer Engineering at the University of Texas at Austin, Austin, TX. His current research interests are

the growth and electronic properties of semiconductor nanowires and graphene, and their application to high-speed/low-power transistors.

Dr. Tutuc is a recipient of a 2009 NSF CAREER Award, a 2008 DARPA Young Faculty Award, and the Charlotte Elizabeth Procter Fellowship (Princeton).

Ray T. Chen (M'91-SM'98-F'04) holds the Cullen Trust for Higher Education Endowed Professorship at UT Austin and the director of nanophotonics and optical interconnects research lab within the microelectronics research center. He is also the director of a newly formed AFOSR Multi-disciplinary Research Initiative (MURI) Center for Silicon Nanomembrane involving faculty from Stanford, UIUC, Rutgers and UT Austin. He received his BS degree in Physics from National Tsing-Hua University in 1980 in Taiwan and his MS degree in physics in 1983 and his PhD degree in Electrical Engineering in 1988, both from the University of California. He joined UT Austin as a faculty to start optical interconnect research program in the ECE Department in 1992. Prior to his UT's professorship, Chen was working as a research scientist, manager and director of the Department of Electrooptic Engineering in Physical Optics Corporation in Torrance, California from 1988 to 1992.

Chen also served as the CTO/founder and chairman of the board of Radiant Research from 2000 to 2001 where he raised 18 million dollars A-Round funding to commercialize polymer-based photonic devices. He also serves as the founder and Chairman of the board of Omega Optics Inc. since its initiation in 2001. Over 5 million dollars of research funds were raised for Omega Optics. His research work has been awarded with 94 research grants and contracts from such sponsors as DOD, NSF, DOE, NASA, the State of Texas, and private industry. The research topics are focused on three main subjects: 1. Nano-photonic passive and active devices for optical interconnect applications, 2. Polymer-based guided-wave optical interconnection and packaging, and 3. True time delay (TTD) wide band phased array antenna (PAA). Experiences garnered through these programs in polymeric material processing and device integration are pivotal elements for the research work conducted by Chen's group.

Chen's group at UT Austin has reported its research findings in more than 510 published articles including over 80 invited papers. He holds 18 issued patents. He has chaired or been a program-committee member for more than 90 domestic and international conferences organized by IEEE, SPIE (The International Society of Optical Engineering), OSA, and PSC. He has served as an editor, co-editor or coauthor for 22 books. Chen has also served as a consultant for various federal agencies and private companies and delivered numerous invited talks to professional societies. Dr. Chen is a Fellow of IEEE, OSA and SPIE. He was the recipient 1987 UC Regent's dissertation fellowship and of 1999 UT Engineering Foundation Faculty Award for his contributions in research, teaching and services. He received IEEE Teaching Award in 2008. Back to his undergraduate years in National Tsing-Hua University, he led a university debate team in 1979 which received the national championship of national debate contest in Taiwan.

There are 32 students who received the EE PhD degree in Chen's research group at UT Austin.