

Robot Battery Rundown Test Plan

PackBot Modernization Project

Ty Valascho, Dan Ryan

10/5/2012



A test plan to measure run down time of a battery-powered robot under several repeatable conditions.

Report Documentation Page				Form Approved OMB No. 0704-0188	
Public reporting burden for the collection of information is estimated to average 1 hour per response, including the time for reviewing instructions, searching existing data sources, gathering and maintaining the data needed, and completing and reviewing the collection of information. Send comments regarding this burden estimate or any other aspect of this collection of information, including suggestions for reducing this burden, to Washington Headquarters Services, Directorate for Information Operations and Reports, 1215 Jefferson Davis Highway, Suite 1204, Arlington VA 22202-4302. Respondents should be aware that notwithstanding any other provision of law, no person shall be subject to a penalty for failing to comply with a collection of information if it does not display a currently valid OMB control number.					
1. REPORT DATE 05 OCT 2012		2. REPORT TYPE Technical Report		3. DATES COVERED 29-09-2012 to 05-10-2010	
4. TITLE AND SUBTITLE Robot Battery Rundown Test Plan PackBot Modernization Project				5a. CONTRACT NUMBER	
				5b. GRANT NUMBER	
				5c. PROGRAM ELEMENT NUMBER	
6. AUTHOR(S) Ty Valascho; Daniel Ryan				5d. PROJECT NUMBER	
				5e. TASK NUMBER	
				5f. WORK UNIT NUMBER	
7. PERFORMING ORGANIZATION NAME(S) AND ADDRESS(ES) U.S. Army TARDEC, 6501 East Eleven Mile Rd, Warren, Mi, 48397-5000				8. PERFORMING ORGANIZATION REPORT NUMBER #23399	
9. SPONSORING/MONITORING AGENCY NAME(S) AND ADDRESS(ES) U.S. Army TARDEC, 6501 East Eleven Mile Rd, Warren, Mi, 48397-5000				10. SPONSOR/MONITOR'S ACRONYM(S) TARDEC	
				11. SPONSOR/MONITOR'S REPORT NUMBER(S) #23399	
12. DISTRIBUTION/AVAILABILITY STATEMENT Approved for public release; distribution unlimited					
13. SUPPLEMENTARY NOTES The views, opinion and/or findings contained in this report are those of the authors and should not be construed as an official Department of the Army position, policy, or decision, unless so designated.					
14. ABSTRACT A test plan to measure the amount of time a small robot remains powered and functional using two standard Li-Ion batteries, under a variety of operating conditions.					
15. SUBJECT TERMS					
16. SECURITY CLASSIFICATION OF:			17. LIMITATION OF ABSTRACT Public Release	18. NUMBER OF PAGES 10	19a. NAME OF RESPONSIBLE PERSON
a. REPORT unclassified	b. ABSTRACT unclassified	c. THIS PAGE unclassified			

Objectives

This test is intended to measure the amount of time a robot remains powered and functional using two standard Li-Ion batteries, under a variety of operating conditions.

Requirements

Special equipment

- Loading device to simulate operation of the Unit Under Test (UUT) at grade while ambient temperature is kept at specific temperatures: robot dynamometer, load rig, or treadmill
- Temperature measurement device

Site requirements

- None

Procedure

3 trials of each the following tests must be performed with valid completion.

Idle Test, -20 C

1. Measure and record State of Charge (SOC) of 2 fully charged BB-2590 batteries (NSN 6140-01-490-4316, 6.8 Ah @ 28.8 V).
2. Place UUT and the 2 batteries inside the temperature chamber. The batteries are not to be installed in the UUT at this time.
3. Install ambient temperature sensor inside the chamber to measure inside air temperature
4. Monitor and log the power bus voltage of the platform. Rate of datalogging should be at least 0.1 Hz.
5. Bring temperature of chamber to -20 C and soak UUT and batteries for 2 hours.
6. Begin logging of data, monitoring power bus voltage.
7. Power on the UUT's Operator Control Unit (OCU). Verify OCU is completely powered on before proceeding to the next step.
8. Open the chamber for no more than 1-minute maximum; install batteries into the UUT and power on UUT.
9. Connect and verify communication to the UUT
10. Test is completed when robot shuts off due to loss of battery power. Any other end of test results in an invalid test.
11. If a valid test, record the amount of time from the start of the test until the robot shut off. Also record the SOC of the two batteries.
12. If an invalid test, note the error or conditions which resulted in the end of test.

Idle Test, +25 C

1. Measure and record State of Charge on 2 fully charged BB-2590 batteries (NSN 6140-01-490-4316, 6.8 Ah @ 28.8 V).
2. Place UUT and the 2 batteries inside the temperature chamber. The batteries are not to be installed in the UUT at this time.
3. Install ambient temperature sensor inside the chamber to measure inside air temperature. Rate of datalogging should be at least 0.1 Hz.
4. Monitor and log the power bus voltage of the platform.
5. Bring temperature of chamber to +25 C and soak UUT and batteries for 2 hours.
6. Begin logging of data, monitoring power bus voltage.
7. Power on the UUT's Operator Control Unit (OCU). Verify OCU is completely powered on before proceeding to the next step.
8. Open the chamber for no more than 1-minute maximum; install batteries into the UUT and power on UUT.
9. Connect and verify communication to the UUT
10. Test is completed when robot shuts off due to loss of battery power. Any other end of test results in an invalid test.
11. If a valid test, record the amount of time from the start of the test until the robot shut off. Also record the SOC of the two batteries.
12. If an invalid test, note the error or conditions which resulted in the end of test.

Idle Test, +50 C

1. Measure and record State of Charge on 2 fully charged BB-2590 batteries (NSN 6140-01-490-4316, 6.8 Ah @ 28.8 V).
2. Place UUT and the 2 batteries inside the temperature chamber. The batteries are not to be installed in the UUT at this time.
3. Install ambient temperature sensor inside the chamber to measure inside air temperature. Rate of datalogging should be at least 0.1 Hz.
4. Monitor and log the power bus voltage of the platform.
5. Bring temperature of chamber to +50 C and soak UUT and batteries for 2 hours.
6. Begin logging of data, monitoring power bus voltage.
7. Power on the UUT's Operator Control Unit (OCU). Verify OCU is completely powered on before proceeding to the next step.
8. Open the chamber for no more than 1-minute maximum; install batteries into the UUT and power on UUT.
9. Connect and verify communication to the UUT
10. Test is completed when robot shuts off due to loss of battery power. Any other end of test results in an invalid test.
11. If a valid test, record the amount of time from the start of the test until the robot shut off. Also record the SOC of the two batteries.
12. If an invalid test, note the error or conditions which resulted in the end of test.

Maximum Normal Speed Test, -20 C

1. Measure and record State of Charge on 2 fully charged BB-2590 batteries (NSN 6140-01-490-4316, 6.8 Ah @ 28.8 V).
2. Place loading device, UUT and the 2 batteries inside the temperature chamber. The batteries are not to be installed in the UUT at this time.
3. Install ambient temperature sensor inside the chamber to measure inside air temperature. Rate of datalogging should be at least 0.1 Hz.
4. Monitor and log the power bus voltage of the platform.
5. Bring temperature of chamber to -20 C and soak UUT and batteries for 2 hours.
6. Begin logging of data, monitoring power bus voltage.
7. Power on the UUT's Operator Control Unit (OCU). Verify OCU is completely powered on before proceeding to the next step.
8. Open the chamber for no more than 1-minute maximum; install batteries into the UUT and power on UUT.
9. Connect and verify communication to the UUT
10. Hold the robot speed at 100% maximum platform speed in Normal mode on level ground. This speed will be kept constant for the entire test.
11. Test is completed when robot shuts off due to loss of battery power. Any other end of test results in an invalid test.
12. If a valid test, record the amount of time from the start of the test until the robot shut off. Also record the SOC of the two batteries.
13. If an invalid test, note the error or conditions which resulted in the end of test.

Maximum Normal Speed Test, +25 C

1. Measure and record State of Charge on 2 fully charged BB-2590 batteries (NSN 6140-01-490-4316, 6.8 Ah @ 28.8 V).
2. Place loading device, UUT and the 2 batteries inside the temperature chamber. The batteries are not to be installed in the UUT at this time.
3. Install ambient temperature sensor inside the chamber to measure inside air temperature. Rate of datalogging should be at least 0.1 Hz.
4. Monitor and log the power bus voltage of the platform.
5. Bring temperature of chamber to +25 C and soak UUT and batteries for 2 hours.
6. Begin logging of data, monitoring power bus voltage.
7. Power on the UUT's Operator Control Unit (OCU). Verify OCU is completely powered on before proceeding to the next step.
8. Open the chamber for no more than 1-minute maximum; install batteries into the UUT and power on UUT.
9. Connect and verify communication to the UUT
10. Hold the robot speed at 100% maximum platform speed in Normal mode on level ground. This speed will be kept constant for the entire test.
11. Test is completed when robot shuts off due to loss of battery power. Any other end of test results in an invalid test.

12. If a valid test, record the amount of time from the start of the test until the robot shut off. Also record the SOC of the two batteries.
13. If an invalid test, note the error or conditions which resulted in the end of test.

Maximum Normal Speed Test, +50 C

1. Measure and record State of Charge on 2 fully charged BB-2590 batteries (NSN 6140-01-490-4316, 6.8 Ah @ 28.8 V).
2. Place loading device, UUT and the 2 batteries inside the temperature chamber. The batteries are not to be installed in the UUT at this time.
3. Install ambient temperature sensor inside the chamber to measure inside air temperature. Rate of datalogging should be at least 0.1 Hz.
4. Monitor and log the power bus voltage of the platform.
5. Bring temperature of chamber to +50 C and soak UUT and batteries for 2 hours.
6. Begin logging of data, monitoring power bus voltage.
7. Power on the UUT's Operator Control Unit (OCU). Verify OCU is completely powered on before proceeding to the next step.
8. Open the chamber for no more than 1-minute maximum; install batteries into the UUT and power on UUT.
9. Connect and verify communication to the UUT
10. Hold the robot speed at 100% maximum platform speed in Normal mode on level ground. This speed will be kept constant for the entire test.
11. Test is completed when robot shuts off due to loss of battery power. Any other end of test results in an invalid test.
12. If a valid test, record the amount of time from the start of the test until the robot shut off. Also record the SOC of the two batteries.
13. If an invalid test, note the error or conditions which resulted in the end of test.

Maximum Fast Speed Test, -20 C

1. Measure and record State of Charge on 2 fully charged BB-2590 batteries (NSN 6140-01-490-4316, 6.8 Ah @ 28.8 V).
2. Place loading device, UUT and the 2 batteries inside the temperature chamber. The batteries are not to be installed in the UUT at this time.
3. Install ambient temperature sensor inside the chamber to measure inside air temperature. Rate of datalogging should be at least 0.1 Hz.
4. Monitor and log the power bus voltage of the platform.
5. Bring temperature of chamber to -20 C and soak UUT and batteries for 2 hours.
6. Begin logging of data, monitoring power bus voltage.
7. Power on the UUT's Operator Control Unit (OCU). Verify OCU is completely powered on before proceeding to the next step.
8. Open the chamber for no more than 1-minute maximum; install batteries into the UUT and power on UUT.
9. Connect and verify communication to the UUT

10. Hold the robot speed at 100% maximum platform speed in Fast mode on level ground. This speed will be kept constant for the entire test.
11. Test is completed when robot shuts off due to loss of battery power. Any other end of test results in an invalid test.
12. If a valid test, record the amount of time from the start of the test until the robot shut off. Also record the SOC of the two batteries.
13. If an invalid test, note the error or conditions which resulted in the end of test.

Maximum Fast Speed Test, +25 C

1. Measure and record State of Charge on 2 fully charged BB-2590 batteries (NSN 6140-01-490-4316, 6.8 Ah @ 28.8 V).
2. Place loading device, UUT and the 2 batteries inside the temperature chamber. The batteries are not to be installed in the UUT at this time.
3. Install ambient temperature sensor inside the chamber to measure inside air temperature. Rate of datalogging should be at least 0.1 Hz.
4. Monitor and log the power bus voltage of the platform.
5. Bring temperature of chamber to +25 C and soak UUT and batteries for 2 hours.
6. Begin logging of data, monitoring power bus voltage.
7. Power on the UUT's Operator Control Unit (OCU). Verify OCU is completely powered on before proceeding to the next step.
8. Open the chamber for no more than 1-minute maximum; install batteries into the UUT and power on UUT.
9. Connect and verify communication to the UUT
10. Hold the robot speed at 100% maximum platform speed in Fast mode on level ground. This speed will be kept constant for the entire test.
11. Test is completed when robot shuts off due to loss of battery power. Any other end of test results in an invalid test.
12. If a valid test, record the amount of time from the start of the test until the robot shut off. Also record the SOC of the two batteries.
13. If an invalid test, note the error or conditions which resulted in the end of test.

Maximum Fast Speed Test, +50 C

1. Measure and record State of Charge on 2 fully charged BB-2590 batteries (NSN 6140-01-490-4316, 6.8 Ah @ 28.8 V).
2. Place loading device, UUT and the 2 batteries inside the temperature chamber. The batteries are not to be installed in the UUT at this time.
3. Install ambient temperature sensor inside the chamber to measure inside air temperature. Rate of datalogging should be at least 0.1 Hz.
4. Monitor and log the power bus voltage of the platform.
5. Bring temperature of chamber to +50 C and soak UUT and batteries for 2 hours.
6. Begin logging of data, monitoring power bus voltage.

7. Power on the UUT's Operator Control Unit (OCU). Verify OCU is completely powered on before proceeding to the next step.
8. Open the chamber for no more than 1-minute maximum; install batteries into the UUT and power on UUT.
9. Connect and verify communication to the UUT
10. Hold the robot speed at 100% maximum platform speed in Fast mode on level ground. This speed will be kept constant for the entire test.
11. Test is completed when robot shuts off due to loss of battery power. Any other end of test results in an invalid test.
12. If a valid test, record the amount of time from the start of the test until the robot shut off. Also record the SOC of the two batteries.
13. If an invalid test, note the error or conditions which resulted in the end of test.

TARDEC Battery Rundown Test Form

PackBot Performance Test

Start Date	
Start Time	
Robot Serial Number	
Tester Name	
Chamber Temperature (C)	
Test Type	
Trial Number	
Test Number	
Data File Name	
Left Front Battery S/N	
Starting SOC (%)	
Ending SOC (%)	
Left Front Battery S/N	
Starting SOC (%)	
Ending SOC (%)	
Valid Test?	
Did the UUT remain in chamber for at least 2 hours before start of test?	
Did the data logger start recording prior to powering on the UUT?	
Was the battery SOC verified before installing the batteries in the UUT?	
Did the batteries remain uninstalled for at least 2 hours before the start of test?	
Notes	