

UNCLASSIFIED

AD 295 448

*Reproduced
by the*

**ARMED SERVICES TECHNICAL INFORMATION AGENCY
ARLINGTON HALL STATION
ARLINGTON 12, VIRGINIA**



UNCLASSIFIED

NOTICE: When government or other drawings, specifications or other data are used for any purpose other than in connection with a definitely related government procurement operation, the U. S. Government thereby incurs no responsibility, nor any obligation whatsoever; and the fact that the Government may have formulated, furnished, or in any way supplied the said drawings, specifications, or other data is not to be regarded by implication or otherwise as in any manner licensing the holder or any other person or corporation, or conveying any rights or permission to manufacture, use or sell any patented invention that may in any way be related thereto.


295 448

AD No.

A REVERSIBLE DECIMAL COUNTER

By

I. M. Beskrovnyy



295 448

UNEDITED ROUGH DRAFT TRANSLATION

A REVERSIBLE DECIMAL COUNTER

BY: I. M. Beskrovn'y

English Pages: 4

SOURCE: Russian Patent Nr. 133684 (660467/26),
28 March 1960.

SOV/19-60-0-22-127-161

THIS TRANSLATION IS A RENDITION OF THE ORIGINAL FOREIGN TEXT WITHOUT ANY ANALYTICAL OR EDITORIAL COMMENT. STATEMENTS OR THEORIES ADVOCATED OR IMPLIED ARE THOSE OF THE SOURCE AND DO NOT NECESSARILY REFLECT THE POSITION OR OPINION OF THE FOREIGN TECHNOLOGY DIVISION.

PREPARED BY:

TRANSLATION SERVICES BRANCH
FOREIGN TECHNOLOGY DIVISION
WP-APB, OHIO.

FTD-TT- 62-1438/1+2+4

Date 10 Jan. 1963

A REVERSIBLE DECIMAL COUNTER

I. M. Beskrovnyy

Decimal counters consisting of series-connected binary counters, and reversible binary counters are known. A drawback to these known devices is the fact that additional feedback is used in them for reversing, which complicates the device as a whole.

In the device described here this drawback is eliminated by adding two channels to the decimal counter, which consists of four flip-flops with a pair of output channels. The connections between counter cells are made so that there is no need for additional feedback.

The counter contains four flip-flops 1, 2, 3 and 4 (see block diagram), which are connected through channels 5, 6, 7, 8, 9 and 10. At the output of the flip-flop, besides channels 11 and 12, there are additional channels 13 and 14. A subtraction sign is sent to bus 15, and an addition sign to bus 16. The voltage fed to bus 15 controls the uneven channels, and the voltage to bus 16 controls the even channels. Channels 13 and 14 are connected in opposite phase with channels 11 and 12. In addition, signals from the output of channels 11 and 12 enter the unit inputs of flip flops 2 and 3. The

outputs of flip-flop 4 are disconnected: the signal from channels 9 and 10 are sent to one of them, and the signal from channels 5 and 6 are sent to the other.

When summing pulses entering input clip 17, the device retains the ordinary binary code up to the number 7. The eighth pulse switches flip-flops 1, 2 and 3 to the "zero" position, and flip-flop 4 to the "one" position. Thus a binary code of the received number 8 (0001) is set up in the device. However, when flip-flop 4 switches to the "one" position, the current pulse generated at the output of this flip-flop returns flip-flops 2 and 3 to the "one" position through channel 14. The code 0111 is set up in the device, which is taken for the code of the number 8. Accordingly, the combination 1111 is taken as the code for 9 and the combination 0000 is taken for 10.


When subtracting pulses entering input clip 17, after the state 0000, the device takes positions 1111 and 0111 successively. These codes, as indicated above, correspond to the numbers 10, 9 and 8.

After this, the output pulse from flip-flop 1 returns flip-flop 4 to the "zero" position. The signal generated at the output of flip-flop 4, through additional channel 13, places flip-flop 2 in the "one" position. The code 1110 is generated in the device, which corresponds to the number 7 in the binary number system. Then the device continues operation as an ordinary binary counter.

Object of the Invention

The reversible decimal counter, consisting of four flip-flops with a pair of output channels, one of which is opened by a "+" signal, and the other by a "-" signal, is distinguished by the fact that, in order to obtain reversing without additional feedback, the fourth flip-flop is connected to an additional pair of gates, and the collected

outputs of the gates are connected to the "one" inputs of the flip-flops of the second and third digits; the "one" input of the fourth digit is connected to the outputs of the channels of the third digit, and the "zero" input to the outputs of the channels of the first digit.



DISTRIBUTION LIST

DEPARTMENT OF DEFENSE	Nr. Copies	MAJOR AIR COMMANDS	Nr. Copies
		AFSC	
		SCFTR	1
		AEDC (AEY)	1
HEADQUARTERS USAF		ASTIA	25
		TD-B1a	5
AF CIN-3D2	1	TD-B1b	3
ARL (ARB)	1	SSD (SSF)	2
		APGC (PGF)	1
		ESD (ESY)	1
OTHER AGENCIES		RADC (RAY)	1
CIA	1	AFMDC (MDF)	1
NSA	6	AFSWC (SWF)	1
AID	2	AFMTC (MTW)	1
OTS	2		
AEC	2		
PWS	1		
NASA	1		
RAND	1		