


600539

Office of Naval Research

Contract Nonr-1866(32)

NR-371-016

THE ADMITTANCE OF BARE CIRCULAR LOOP
ANTENNAS IN A DISSIPATIVE MEDIUM



By

R.W.P. King, C.W. Harrison, Jr.,
D.G. Tingley

August 5, 1963

Technical Report No. 419

Cruft Laboratory

Division of Engineering and Applied Physics
Harvard University • Cambridge, Massachusetts

Reproduced by
NATIONAL TECHNICAL
INFORMATION SERVICE
U.S. Department of Commerce
Springfield, VA 22151

PRICES SUBJECT TO CHANGE

AD No.

THE COPY

Office of Naval Research
Contract Nonr-1866(32)
NR - 371 - 016

THE ADMITTANCE OF BARE CIRCULAR LOOP
ANTENNAS IN A DISSIPATIVE MEDIUM

by

R. W. P. King

C. W. Harrison, Jr.

D. G. Tingley

August 5, 1963

The research reported in this document was made possible through support extended Cruft Laboratory, Harvard University, jointly by the Navy Department (Office of Naval Research), the Signal Corps of the U. S. Army, and the U. S. Air Force, under ONR Contract Nonr-1866 (32). Reproduction in whole or in part is permitted for any purpose of the United States Government.

Technical Report No. 419

Cruft Laboratory
Harvard University
Cambridge, Massachusetts

ABSTRACT

The normalized input admittance of thin bare circular loop antennas has been evaluated from the theory of T. T. Wu. Computations have been made for loops in air and in an infinite homogeneous isotropic dissipative medium. A comparison is also made with Storer's theory of the loop. Numerical results are given in the form of graphs for several wire sizes and for loops up to 2.5 wavelengths in circumference. The properties of the medium are represented by the ratio α/β in the range from zero (perfect dielectric) to one (good conductor); α and β are the imaginary and real parts of the complex propagation constant $k = \beta - j\alpha = \omega \sqrt{\mu (\epsilon - j\sigma/\omega)}$ where μ is the permeability, ϵ the dielectric constant and σ the conductivity of the medium.

TABLE OF CONTENTS

	Page
Introduction	5
Analytical Formulation	5
Evaluation of the Tables	7
Graphical Representation	8
Conclusion	8
List of References	9

LIST OF ILLUSTRATIONS

Figure

1	Normalized conductance and susceptance of circular loop in air as a function of the number of terms - Wu's theory for $\beta b = 0.5$ and 2.0 , $\Omega = 2 \ln(2\pi b/a) = 8 - 12$	10
2	Normalized susceptance of circular loop in a dissipative medium with propagation constant $k = \beta - j\alpha$ as a function of the number of terms - Wu's theory for $\beta b = 2.0$, $\Omega = 8, 12, 20$, $\alpha/\beta = 0 - 1$	11
3	Normalized admittance of circular loop antenna in a dissipative medium - Wu's theory, $\Omega = 10$	12
4	Normalized admittance of circular loop antenna in a dissipative medium - Wu's theory, $\Omega = 11$	13
5	Normalized admittance of circular loop antenna in a dissipative medium - Wu's theory, $\Omega = 12$	14
6	Normalized admittance of circular loop antenna in a dissipative medium - Wu's theory, $\Omega = 15$	15
7	Normalized admittance of circular loop antenna in a dissipative medium - Wu's theory, $\Omega = 17.5$	16
8	Normalized admittance of circular loop antenna in a dissipative medium - Wu's theory, $\Omega = 20$	17

LIST OF TABLES

TABLE I	Normalized Admittance Y/Δ of Loop Antennas in Dissipative Media	18-19
TABLE II	Normalized Admittance Y/Δ of Loop Antennas in Dissipative Media	20-21
TABLE III	Normalized Admittance Y/Δ of Loop Antennas in Dissipative Media	22-23
TABLE IV	Normalized Admittance Y/Δ of Loop Antennas in Dissipative Media	24-25
TABLE V	Normalized Admittance Y/Δ of Loop Antennas in Dissipative Media	26-27
TABLE VI	Normalized Admittance Y/Δ of Loop Antennas in Dissipative Media	28-29

THE ADMITTANCE OF BARE CIRCULAR LOOP ANTENNAS IN A DISSIPATIVE MEDIUM

Introduction

The first general analysis of the circular loop as a transmitting antenna appears to be that of Hallen¹; he used the method of expansion in Fourier series. However, owing to the occurrence of a singularity or a very large value when the number of terms in the summation is sufficiently great, Hallen concluded that the series was divergent. Storer² avoided the contribution from the large term by replacing the Fourier series by the corresponding integral and evaluating this in the sense of the Cauchy principal value. He provided extensive tables and graphs of the impedance, admittance, and distribution of current for loops up to a wavelength in circumference with a number of different wire sizes. Recently, Wu³ re-examined the problem of evaluating the Fourier series. He considered Storer's expedient to be of doubtful validity and devised an alternative and improved method with approximations that are valid over larger ranges of the parameters.

Although formulated specifically for loops in air, the solutions of both Wu and Storer are readily applied to loops in an infinite homogeneous and isotropic medium by the introduction of the constitutive parameters of the medium at the appropriate points. It is the purpose of this paper to discuss the evaluation of the admittance of a loop antenna in an arbitrary dissipative medium from Wu's formula. A comparison with Storer's results is also provided.

Since loops up to a wave length in circumference are considered, the present work is a significant extension of the earlier studies by Kraichman⁴ and by Chen and King.⁵ Kraichman's analysis is based on a postulated uniform distribution of current around the loop which is valid only for electrically extremely small loops if these are bare or covered with a very thin layer of dielectric. The work of Chen and King makes use of Storer's analysis but retains only the first two terms in the Fourier Series. Although this is a considerably better approximation than that of Kraichman, it is also limited to electrically rather small loops. Indeed, even for loops with circumferences as small as 0.1λ to 0.3λ , a surprisingly large error in the normalized conductance is made when only the first two terms in the Fourier series are retained.

Analytical Formulation

The admittance of a circular loop of radius b when made of wire of radius a has been derived by Storer² and, in a somewhat more general form, by Wu³ specifically for antennas in air. The generalized formula for the normalized admittance $Y/\Delta = G/\Delta + jB/\Delta$ of a loop in an infinite homogeneous and isotropic dissipative medium when driven by a delta-function generator is

$$\frac{Y}{\Delta} = \frac{-j(1 - j\alpha/\beta)}{\pi \zeta_0} \left[\frac{1}{a_0} + 2 \sum_{n=1}^{\infty} \frac{1}{a_n} \right] \quad (1)$$

$$\zeta_0 = (\mu_0/\epsilon_0)^{1/2} \doteq 120 \pi \text{ ohms}$$

where

$$a_n = \frac{kb}{2} (K_{n+1} + K_{n-1}) - \frac{n^2}{kb} K_n. \quad (2)$$

In this formula

$$K_0 = \frac{1}{\pi} \ln \frac{8b}{a} - \frac{1}{2} \left[\int_0^{2kb} \Omega_0(x) dx + j \int_0^{2kb} J_0(x) dx \right] \quad (3)$$

$$K_n = K_{-n} = \frac{1}{\pi} \left[\mathcal{X}_0\left(\frac{na}{b}\right) \mathcal{Y}_0\left(\frac{na}{b}\right) + C_n \right] - \frac{1}{2} \left[\int_0^{2kb} \Omega_{2n}(x) dx + j \int_0^{2kb} J_{2n}(x) dx \right] \quad (4)$$

$$C_n = \ln(4n) + 0.5772... - 2 \sum_{m=0}^{n-1} (2m+1)^{-1} \quad (5)$$

where $\mathcal{Y}_0(z)$ and $\mathcal{X}_0(z)$ are the modified Bessel functions of the first and second kinds and $\Omega(x)$ is the Lommel-Weber function defined by

$$\Omega_m(x) = \frac{1}{\pi} \int_0^\pi \sin(x \sin \theta - m\theta) d\theta. \quad (6)$$

In (2)

$$k = \beta - j\alpha = \omega \sqrt{\mu(\epsilon - j\sigma/\omega)} = \omega \sqrt{\mu\epsilon} \left[f(p) - j g(p) \right] \quad (7)$$

is the complex propagation constant. In (7)

$$p = \sigma/\omega\epsilon \quad (8)$$

is the loss tangent of the medium and the $f(p)$ and $g(p)$ functions are defined as follows:

$$f(p) \pm j g(p) = \sqrt{1 \pm jp}. \quad (9)$$

This is equivalent to

$$f(p) = \cosh\left(\frac{1}{2} \sinh^{-1} p\right), \quad g(p) = \sinh\left(\frac{1}{2} \sinh^{-1} p\right). \quad (10)$$

The functions $f(p)$ and $g(p)$ are extensively tabulated in the literature.^{6,7}

In order to provide generally useful graphs and tables of the admittance of a loop antenna when immersed in a medium characterized by arbitrary values of σ and ϵ , it is convenient to introduce the normalizing factor

$$\Delta = \sqrt{\frac{\epsilon_r}{\mu_r}} f(p) \quad (11)$$

where ϵ_r and μ_r are the relative dielectric constant and permeability. This factor appears in (1), for antennas in air, it is equal to unity.

As with a dipole antenna when center driven by a delta-function generator, the admittance Y strictly does not exist, since its susceptance must become infinite owing to the knife-edge terminals with zero separation that characterize the delta-function generator. However, as shown for the dipole,^{6,9} the representation of the current by continuous functions combined with the extreme localization of that part of the current that is associated with the knife edges of the generator, effectively omits the latter for thin wires unless a very large number of terms in the Fourier series is taken. If the infinite sum in (1) is replaced by a sum over a finite number of terms, an approximate formula is obtained that is a good measure of the admittance of the antenna for use with a practical method of driving when combined with a suitable terminal-zone network.

Evaluation of the Tables

The formula (1) was evaluated on a high-speed computer using successively 8, 9, 10, 18, 19, and 20 terms in the series. The normalized conductance G/Δ and normalized susceptance B/Δ for $\alpha/\beta = 0$ are shown in Fig. 1 as a function of the number of terms in the series. Curves are shown for $\beta b = 0.5$ and 2.0 and for $\Omega = 2 \ln(2\pi b/a) = 8, 9, 10, 11$, and 12. It is seen that the convergence is such that G/Δ does not change noticeably for both values of βb and for all values of Ω . On the other hand, B/Δ continues to increase with the number of terms. The rate of this increase is great when $\Omega < 10$ and when βb is large; it is quite small for $\Omega \geq 10$, especially when βb is small. In general, it may be concluded that when $\Omega \geq 10$, 20 terms in the Fourier series yield highly accurate values of G/Δ for $\beta b \leq 2.5$, quite good values of B/Δ for $\beta b < 1$, and fair values when $1 \leq \beta b \leq 2.5$.

The values of G/Δ and B/Δ evaluated from Storer's theory⁸ are indicated on the right in Fig. 1. It is seen that they are in excellent agreement with Wu's results using 20 terms insofar as G/Δ is concerned, but that significant differences occur in B/Δ .

In Fig. 2 values of B/Δ are shown as functions of the number of terms in the Fourier series for $\beta b = 2.0$ with $\Omega = 8, 12$, and 20, when a/β is increased from zero to one. It is seen that except for $a/\beta = 1$, the curves for the relatively thick-wire loop with $\Omega = 8$ or $2\pi b/a = 27.3$ increase significantly with the number of terms. On the other hand, the curves for the thinner loops with $\Omega = 12$ ($2\pi b/a = 259$) and $\Omega = 20$ ($2\pi b/a = 11,013$) are practically independent of the number of terms for all values of a/β .

These results indicate that a Fourier series solution in which 20 terms are retained is satisfactory for determining the admittance of thin-wire loops ($\Omega \geq 10$) that are not too large ($\beta b \leq 2.5$) when in air or an arbitrary dissipative medium. The approximation is excellent for the conductance, somewhat less accurate for the susceptance. Numerical values of the normalized admittance $Y/\Delta = G/\Delta + jB/\Delta$ for loops with $\Omega = 10, 11, 12, 15, 17.5$, and 20 are in the tables for $0 \leq \beta b \leq 2.5$ and for $0 \leq \frac{a}{\beta} \leq 1$.

Graphical Representation

Graphs of the normalized conductance and susceptance of thin-wire loops as a function of the variable $\beta b = 2\pi b/\lambda$ are shown in Fig. 3-8. The parameter a/β of the surrounding medium ranges from zero to one. Note how insensitive to the size of the loop the admittance becomes as a/β approaches unity. This is true particularly of loops near antiresonance that have a high driving point impedance. Such an insensitivity merely means that most of the current has left the loop and has entered the surrounding dissipative medium.

Conclusion

The driving-point admittance of bare thin-wire loops $\frac{1}{2}$ and $\frac{1}{4}$ wavelengths in circumference when immersed in an arbitrary dissipative medium has been determined from Wu's theory using 20 terms in the Fourier series.

LIST OF REFERENCES

1. Hallen, E., "Theoretical Investigations Into Transmitting and Receiving Qualities of Antennae," Nova Acta Regiae Soc. Sci. Upsaliensis [4] 11, 1-44 (1938).
2. Storer, J. E., "Impedance of Thin-Wire Loop Antennas," Trans. Am. Inst. Elec. Engrs. 75, Part I, p. 606 (1956); also Cruft Laboratory Technical Report No. 212, May 1, 1955.
3. Wu, T. T., "Theory of Thin Circular Loop Antenna," J. Math. Phys. 3, 1301-1304 (1962).
4. Kraichman, M. B., "Impedance of a Circular Loop in an Infinite Conducting Medium," J. Research Natl. Bur. Standards 66D, pp. 499-503, July-August 1962.
5. Chen, C. L. and King, R. W. P., "The Small Bare Loop Antenna Immersed in a Dissipative Medium," IEEE Trans. AP 11, pp. 266-268, (May 1963).
6. King, R. W. P., "Fundamental Electromagnetic Theory," Appendix II, Dover Publications (1963).
7. Gooch, D. W., Harrison, C. W., Jr., King, R. W. P., and Wu, T. T., "Impedances and Admittances of the Long Antenna in Air and in Dissipative Media With Tables of the Functions $f(p) \pm ig(p) = \sqrt{1 \pm ip}$," Cruft Laboratory Technical Report No. 352, January 15, 1962.
8. Wu, T. T. and King, R. W. P., "Driving Point and Input Admittance of Linear Antennas," J. Appl. Phys. 30, p. 76 (1959).
9. Duncan, R. H. and Hinchey, F. A., "Cylindrical Antenna Theory," J. Research Natl. Bur. Standards 64D, pp. 569-584, September-October 1960.




Fig. 1 Normalized conductance and susceptance of circular loop in air as a function of the number of terms - Wu's theory for $\beta b = 0.5$ and 2.0 ,

$$\Omega = 2 \ln \left(\frac{2\pi b}{a} \right) = 8 - 12$$




Fig. 2 Normalized susceptance of circular loop in a dissipative medium with propagation constant $k = \beta - j\alpha$ as a function of the number of terms - Wu's theory for $\beta b = 2.0$, $\Omega = 8, 12, 20$, $\alpha/\beta = 0 - 1$.




Fig. 3 Normalized admittance of circular loop antenna in a dissipative medium - Wu's theory, $\Omega = 10$




Fig. 4 Normalized admittance of circular loop antenna in a dissipative medium - Wu's theory, $\Omega \approx 11$




Fig. 5 Normalized admittance of circular loop antenna in a dissipative medium - Wu's theory, $\Omega = 12$




Fig. 6 Normalized admittance of circular loop antenna in a dissipative medium - Wu's theory, $\Omega = 15$




Fig. 7 Normalized admittance of circular loop antenna in a dissipative medium - Wu's theory, $\Omega = 17.5$




Fig. 8 Normalized admittance of circular loop antenna in a dissipative medium - Wu's theory, $\Omega = 20$

TABLE I
Normalized Admittance Y/Δ of Loop Antennas in Dissipative Media

βb	$\frac{\alpha}{\beta} = 0.00$	$\frac{\alpha}{\beta} = 0.01$	$\frac{\alpha}{\beta} = 0.03$	$\frac{\alpha}{\beta} = 0.05$	$\frac{\alpha}{\beta} = 0.07$
	Y/Δ	Y/Δ	Y/Δ	Y/Δ	Y/Δ
0.05	0.0003	-16.1742	0.0108	-16.1744	0.0248
0.10	0.0014	-7.8236	0.0225	-7.8241	-16.1751
0.15	0.0032	-4.9201	0.0353	-4.9209	0.0507
0.20	0.0061	-3.3750	0.0496	-3.3763	0.0781
0.25	0.0102	-2.3691	0.0660	-2.3711	0.1076
0.30	0.0162	-1.6283	0.0851	-1.6313	-2.3767
0.35	0.0242	-1.0333	0.1081	-1.0378	0.1401
0.40	0.0370	-0.5233	0.1364	-0.5300	0.1766
0.45	0.0546	-0.0624	0.1723	-0.0723	-1.6391
0.50	0.0801	0.3730	0.2191	0.3590	-1.0487
					0.2186
0.55	0.1174	0.8006	0.2814	0.7776	0.2680
0.60	0.1728	1.2351	0.3666	1.1997	-0.0938
0.65	0.2561	1.6908	0.4857	1.6354	0.4013
0.70	0.3837	2.1816	0.6563	2.0937	0.4947
0.75	0.5830	2.7214	0.9051	2.5796	0.6158
0.80	0.9009	3.3195	1.2738	3.0877	0.7761
0.85	1.4151	3.9671	1.8222	3.5873	0.9921
0.90	2.2513	4.5965	2.6194	3.9908	1.2868
0.95	3.5409	4.9903	3.6909	4.1131	1.6899
1.00	5.2227	4.6875	4.8814	3.6941	2.2330
					2.9313
1.05	6.6359	3.2896	5.7564	2.6416	3.7408
1.10	6.8730	1.3221	5.9058	1.3233	4.5101
1.15	6.0398	-0.1400	5.4080	0.2831	0.7335
1.20	4.9127	-0.7848	4.8271	-0.2698	1.1350
1.25	3.9355	-0.8925	3.9399	-0.4304	1.5393
1.30	3.1945	-0.7081	3.2478	-0.3531	1.9491
1.35	2.6537	-0.4132	2.7340	-0.1475	2.3599
1.40	2.2627	-0.0671	2.3595	0.0008	2.7536
1.45	1.9826	0.3014	2.0916	0.3479	3.0870
1.50	1.7878	0.6819	1.9076	0.7098	3.2790
					3.2122
1.55	1.6637	1.0722	1.7942	1.0822	4.5101
1.60	1.6039	1.4734	1.7457	1.4359	0.7335
1.65	1.6093	1.8871	1.7628	1.8558	1.1350
1.70	1.6877	2.3137	1.8524	2.2545	1.5393
1.75	1.8540	2.7491	2.0269	2.6535	1.9491
1.80	2.1306	3.1797	2.3038	3.0368	2.3599
1.85	2.5444	3.5744	2.7011	3.3725	2.7536
1.90	3.1165	3.8733	3.2271	3.6068	3.0870
1.95	3.8359	3.9815	3.8587	3.6637	3.2790
2.00	4.6171	3.7906	4.5146	3.4690	3.7408
					4.5101
2.05	5.2801	3.2530	5.0531	3.0048	0.7335
2.10	5.6233	2.4710	5.3316	2.3600	1.1350
2.15	5.5686	1.6718	5.2987	1.7030	1.5393
2.20	5.2098	1.0560	5.0200	1.1830	1.9491
2.25	4.7102	0.6964	4.6144	0.8631	2.3599
2.30	4.1983	0.5656	4.1341	0.7327	2.7536
2.35	3.7412	0.6027	3.7886	0.7500	3.0870
2.40	3.3624	0.7520	3.4543	0.8714	3.2790
2.45	3.0648	0.9739	3.1888	1.0632	3.7408
2.50	2.8436	1.2429	2.9916	1.3016	4.5101
					0.7335
2.55					1.1350
2.60					1.5393
2.65					1.9491
2.70					2.3599
2.75					2.7536
2.80					3.0870
2.85					3.2790
2.90					3.7408
2.95					4.5101
3.00					0.7335
3.05					1.1350
3.10					1.5393
3.15					1.9491
3.20					2.3599
3.25					2.7536
3.30					3.0870
3.35					3.2790
3.40					3.7408
3.45					4.5101
3.50					0.7335
3.55					1.1350
3.60					1.5393
3.65					1.9491
3.70					2.3599
3.75					2.7536
3.80					3.0870
3.85					3.2790
3.90					3.7408
3.95					4.5101
4.00					0.7335
4.05					1.1350
4.10					1.5393
4.15					1.9491
4.20					2.3599
4.25					2.7536
4.30					3.0870
4.35					3.2790
4.40					3.7408
4.45					4.5101
4.50					0.7335
4.55					1.1350
4.60					1.5393
4.65					1.9491
4.70					2.3599
4.75					2.7536
4.80					3.0870
4.85					3.2790
4.90					3.7408
4.95					4.5101
5.00					0.7335
5.05					1.1350
5.10					1.5393
5.15					1.9491
5.20					2.3599
5.25					2.7536
5.30					3.0870
5.35					3.2790
5.40					3.7408
5.45					4.5101
5.50					0.7335
5.55					1.1350
5.60					1.5393
5.65					1.9491
5.70					2.3599
5.75					2.7536
5.80					3.0870
5.85					3.2790
5.90					3.7408
5.95					4.5101
6.00					0.7335
6.05					1.1350
6.10					1.5393
6.15					1.9491
6.20					2.3599
6.25					2.7536
6.30					3.0870
6.35					3.2790
6.40					3.7408
6.45					4.5101
6.50					0.7335
6.55					1.1350
6.60					1.5393
6.65					1.9491
6.70					2.3599
6.75					2.7536
6.80					3.0870
6.85					3.2790
6.90					3.7408
6.95					4.5101
7.00					0.7335
7.05					1.1350
7.10					1.5393
7.15					1.9491
7.20					2.3599
7.25					2.7536
7.30					3.0870
7.35					3.2790
7.40					3.7408
7.45					4.5101
7.50					0.7335
7.55					1.1350
7.60					1.5393
7.65					1.9491
7.70					2.3599
7.75					2.7536
7.80					3.0870
7.85					3.2790
7.90					3.7408
7.95					4.5101
8.00					0.7335
8.05					1.1350
8.10					1.5393
8.15					1.9491
8.20					2.3599
8.25					2.7536
8.30					3.0870
8.35					3.2790
8.40					3.7408
8.45					4.5101
8.50					0.7335
8.55					1.1350
8.60					1.5393
8.65					1.9491
8.70					2.3599
8.75					2.7536
8.80					3.0870
8.85					3.2790
8.90					3.7408
8.95					4.5101
9.00					0.7335
9.05					1.1350
9.10					1.5393
9.15					1.9491
9.20					2.3599
9.25					2.7536
9.30					3.0870
9.35					3.2790
9.40					3.7408
9.45					4.5101
9.50					0.7335
9.55					1.1350
9.60					1.5393
9.65					1.9491
9.70					2.3599
9.75					2.7536
9.80					3.0870
9.85					3.2790
9.90					3.7408
9.95					4.5101
10.00					0.7335

TABLE II
Normalized Admittance Y/Δ of Loop Antennas in Dissipative Media

$\beta\lambda$	$\frac{\alpha}{\beta} = 0.00$	$\frac{\alpha}{\beta} = 0.01$	$\frac{\alpha}{\beta} = 0.03$	$\frac{\alpha}{\beta} = 0.05$	$\frac{\alpha}{\beta} = 0.07$
	Y/Δ	Y/Δ	Y/Δ	Y/Δ	Y/Δ
0.05	0.0002	-14.0300	0.0089	-14.0304	0.0204
0.10	0.0010	-6.7985	0.0184	-6.7988	0.0416
0.15	0.0024	-4.2391	0.0288	-4.2397	0.0641
0.20	0.0046	-2.9573	0.0405	-2.9584	0.0883
0.25	0.0077	-2.0031	0.0537	-2.0047	0.1149
0.30	0.0122	-1.4585	0.0692	-1.4609	0.1449
0.35	0.0187	-0.9503	0.0877	-0.9538	0.1793
0.40	0.0279	-0.5154	0.1106	-0.5207	0.2200
0.45	0.0413	-0.1228	0.1395	-0.1306	0.2691
0.50	0.0606	0.2483	0.1771	0.2365	0.3300
0.55	0.0890	0.6135	0.2274	0.5955	0.4075
0.60	0.1314	0.9867	0.2963	0.9344	0.5086
0.65	0.1958	1.3913	0.3934	1.3372	0.6437
0.70	0.2957	1.8124	0.5341	1.7413	0.8283
0.75	0.4550	2.2969	0.7434	2.1746	1.0953
0.80	0.7169	2.9520	1.0628	2.6537	1.4469
0.85	1.1622	3.4865	1.5590	3.1444	1.9532
0.90	1.9374	4.1612	2.3258	3.5737	2.6350
0.95	3.2622	4.6662	3.4364	3.7337	3.4625
1.00	5.1922	4.5834	4.7489	3.2605	4.2623
1.05	6.8232	2.5879	5.6666	1.9755	4.7312
1.10	6.7120	0.1691	5.6112	0.4414	4.6867
1.15	5.3779	-1.2319	4.8322	-0.5849	4.2556
1.20	4.0411	-1.5838	3.9190	-0.9827	3.6936
1.25	3.0663	-1.4420	3.1599	-0.9966	3.1707
1.30	2.4031	-1.1269	2.5967	-0.8039	2.7473
1.35	1.9519	-0.7638	2.1941	-0.5346	2.4275
1.40	1.6438	-0.3945	1.9114	-0.2367	2.1975
1.45	1.4256	-0.0293	1.7179	0.0725	2.0422
1.50	1.2804	0.3306	1.5941	0.3860	1.9497
1.55	1.1914	0.6913	1.5289	0.7021	1.9125
1.60	1.1531	1.0561	1.5178	1.0211	1.9270
1.65	1.1669	1.4370	1.5618	1.3432	1.9924
1.70	1.2412	1.8330	1.6671	1.6663	2.1102
1.75	1.3928	2.2484	1.8446	1.9837	2.2824
1.80	1.6496	2.6778	2.1085	2.2904	2.5094
1.85	2.0527	3.0985	2.4729	2.5267	2.7859
1.90	2.6507	3.4504	2.9409	2.6739	3.0959
1.95	3.4702	3.6083	3.4849	2.6559	3.4087
2.00	4.4330	3.3816	4.0239	2.4743	3.6804
2.05	5.2599	2.6373	4.4283	1.9503	3.8656
2.10	5.5806	1.5399	4.5934	1.2631	3.9357
2.15	5.2983	0.5189	4.4680	0.6572	3.8917
2.20	4.6658	-0.1268	4.4801	0.1015	3.7609
2.25	3.9731	-0.3895	3.9146	-0.1562	3.5819
2.30	3.3679	-0.3895	3.3961	-0.1989	3.3899
2.35	2.8872	-0.2379	2.9690	-0.0792	3.2101
2.40	2.5221	-0.0053	2.5370	0.1138	3.0575
2.45	2.2533	0.2702	2.3898	0.3544	2.9397
2.50	2.0636	0.5696	2.2157	0.6228	2.8597

TABLE III
Normalized Admittance Y/Δ of Loop Antennas in Dissipative Media

βb	$\frac{\sigma}{\beta} = 0.00$	$\frac{\sigma}{\beta} = 0.01$	$\frac{\sigma}{\beta} = 0.03$	$\frac{\sigma}{\beta} = 0.05$	$\frac{\sigma}{\beta} = 0.07$
	Y/Δ	Y/Δ	Y/Δ	Y/Δ	Y/Δ
0.05	0.0002 -12.3838	0.0026 -12.3839	0.0075 -12.3840	0.0124 -12.3842	0.0173 -12.3845
0.10	0.0008 -6.0079	0.0057 -6.0079	0.0156 -6.0082	0.0254 -6.0086	0.0353 -6.0093
0.15	0.0019 -3.7985	0.0094 -3.7986	0.0244 -3.7991	0.0393 -3.7998	0.0543 -3.8009
0.20	0.0036 -2.6282	0.0137 -2.6284	0.0341 -2.6291	0.0545 -2.6302	0.0748 -2.6317
0.25	0.0060 -1.8703	0.0191 -1.8706	0.0452 -1.8713	0.0713 -1.8732	0.0973 -1.8754
0.30	0.0095 -1.3150	0.0258 -1.3154	0.0581 -1.3169	0.0905 -1.3192	0.1227 -1.3222
0.35	0.0146 -0.8711	0.0343 -0.8717	0.0736 -0.8739	0.1128 -0.8771	0.1519 -0.8813
0.40	0.0213 -0.4917	0.0455 -0.4928	0.0926 -0.4960	0.1396 -0.5005	0.1864 -0.5063
0.45	0.0323 -0.1495	0.0605 -0.1511	0.1167 -0.1558	0.1726 -0.1622	0.2281 -0.1704
0.50	0.0474 0.1742	0.0811 0.1716	0.1479 0.1646	0.2142 0.1554	0.2799 0.1438
0.55	0.0698 0.4934	0.1100 0.4893	0.1896 0.4788	0.2683 0.4652	0.3459 0.4486
0.60	0.1033 0.8207	0.1516 0.8142	0.2479 0.7980	0.3407 0.7777	0.4324 0.7534
0.65	0.1544 1.1592	0.2131 1.1587	0.3283 1.1332	0.4403 1.1020	0.5489 1.0657
0.70	0.2347 1.5538	0.3065 1.5363	0.4470 1.4951	0.5814 1.4463	0.7096 1.3909
0.75	0.3646 1.9931	0.4544 1.9631	0.6262 1.8945	0.7871 1.8161	0.9369 1.7297
0.80	0.5833 2.5099	0.6961 2.4564	0.9060 2.3385	1.0952 2.2094	1.2640 2.0727
0.85	0.9693 3.1257	1.1088 3.0265	1.3561 2.8175	1.5659 2.6016	1.7363 2.3854
0.90	1.6821 3.8294	1.8378 3.6393	2.0877 3.2657	2.2692 2.9111	2.3977 2.5925
0.95	3.0140 4.4372	3.1124 4.0862	3.2198 3.4637	3.2489 2.9404	3.2328 2.5022
1.00	5.1747 4.1923	4.9896 3.7064	4.6349 2.9477	4.3203 2.3893	4.0503 1.9646
1.05	6.9797 1.9691	6.4182 1.7662	5.5604 1.4470	4.9408 1.2056	4.4768 1.0151
1.10	6.3872 -0.7830	5.9627 -0.5402	5.2650 -0.2246	4.7283 -0.0478	4.3118 0.0497
1.15	4.6500 -1.9270	4.5259 -1.6197	4.2584 -1.1427	3.9992 -0.8072	3.7666 -0.5726
1.20	3.2716 -1.9702	3.2919 -1.7477	3.2807 -1.3632	3.2274 -1.0562	3.1547 -0.8170
1.25	2.3829 -1.6551	2.4583 -1.5089	2.5554 -1.2396	2.6099 -1.0065	2.6355 -0.8115
1.30	1.8314 -1.2655	1.9157 -1.1693	2.0552 -0.9858	2.1616 -0.8194	2.2416 -0.6740
1.35	1.4688 -0.8811	1.5575 -0.8168	1.7149 -0.6922	1.8473 -0.5770	1.9579 -0.4744
1.40	1.2260 -0.5180	1.3170 -0.4750	1.4842 -0.3920	1.6321 -0.3156	1.7618 -0.2482
1.45	1.0616 -0.1741	1.1555 -0.1464	1.3314 -0.0948	1.4009 -0.0495	1.6344 -0.0119
1.50	0.9530 0.1578	1.0514 0.1730	1.2373 0.1983	1.4079 0.2164	1.5630 0.2270
1.55	0.8886 0.4858	0.9936 0.4894	1.1921 0.4896	1.3745 0.4812	1.5403 0.4650
1.60	0.8642 0.8179	0.9780 0.8090	1.1922 0.7821	1.3873 0.7450	1.5630 0.6997
1.65	0.8814 1.1624	1.0067 1.1381	1.2395 1.0783	1.4476 1.0071	1.6315 0.9283
1.70	0.9487 1.5270	1.0880 1.4918	1.3411 1.3786	1.5605 1.2645	1.7485 1.1455
1.75	1.0832 1.9184	1.2381 1.8427	1.5097 1.6793	1.7343 1.5096	1.9179 1.3419
1.80	1.3152 2.3383	1.4838 2.2166	1.7638 1.9683	1.9788 1.7271	2.1428 1.5025
1.85	1.6044 2.7739	1.8656 2.5923	2.1251 2.2172	2.3013 1.8899	2.4208 1.6049
1.90	2.2933 3.1723	2.4329 2.9810	2.6079 2.3718	2.6959 1.9569	2.7374 1.6218
1.95	3.1836 3.3899	3.2132 2.9853	3.1923 2.3471	3.1289 1.8794	3.0591 1.5283
2.00	4.3153 3.1453	4.1192 2.6969	3.7835 2.0555	3.5260 1.6252	3.3335 1.3182
2.05	5.2921 2.1830	4.8422 1.8938	4.2051 1.4992	3.7880 1.2175	3.5046 1.0191
2.10	5.5121 0.7726	5.0070 0.8014	4.3002 0.7930	3.8443 0.7482	3.5399 0.6908
2.15	4.9312 -0.3661	4.5938 -0.1131	4.0706 0.1875	3.7043 0.3340	3.4480 0.3999
2.20	4.0586 -0.9108	3.9217 -0.6096	3.6575 -0.1953	3.4383 0.0500	3.2701 0.1915
2.25	3.2688 -1.0093	3.2661 -0.7494	3.2090 -0.3536	3.1297 -0.0900	3.0553 0.0786
2.30	2.6622 -0.8742	2.7322 -0.6745	2.8088 -0.3473	2.8363 -0.1105	2.8422 0.0514
2.35	2.2212 -0.6356	2.3283 -0.4892	2.4846 -0.2378	2.5863 -0.0458	2.6541 0.0908
2.40	1.9063 -0.3555	2.0330 -0.2514	2.2373 -0.0685	2.3889 0.0746	2.5021 0.1774
2.45	1.6846 -0.0599	1.8233 0.0107	2.0584 0.1342	2.2442 0.2295	2.3899 0.2952
2.50	1.5338 0.2419	1.6816 0.2847	1.9391 0.3555	2.1489 0.4047	2.3176 0.4320

$$\Omega = 12$$

$\beta\delta$	$\frac{\alpha}{\beta} = 0.10$		$\frac{\alpha}{\beta} = 0.30$		$\frac{\alpha}{\beta} = 0.50$		$\frac{\alpha}{\beta} = 0.70$		$\frac{\alpha}{\beta} = 1.00$	
	Y/Δ	Y/Δ	Y/Δ	Y/Δ	Y/Δ	Y/Δ	Y/Δ	Y/Δ	Y/Δ	Y/Δ
0.05	0.0246	-12.3651	0.0734	-12.3951	0.1221	-12.4148	0.1707	-12.4443	0.2433	-12.5069
0.10	0.0500	-6.0107	0.1482	-6.0312	0.2458	-6.0718	0.3426	-6.1323	0.4857	-6.2596
0.15	0.0767	-3.8031	0.2256	-3.8356	0.3725	-3.8991	0.5168	-3.9930	0.7265	-4.1891
0.20	0.1053	-2.6349	0.3066	-2.6914	0.5035	-2.7739	0.6940	-2.9021	0.9644	-3.1724
0.25	0.1364	-1.8799	0.3929	-1.9431	0.6403	-2.0632	0.8749	-2.2365	1.1973	-2.5867
0.30	0.1710	-1.3283	0.4860	-1.4125	0.7840	-1.5689	1.0591	-1.7901	1.4220	-2.2256
0.35	0.2103	-0.8895	0.5877	-1.0305	0.9356	-1.2067	1.2458	-1.4763	1.6350	-2.0003
0.40	0.2561	-0.5175	0.7003	-0.6632	1.0958	-0.9165	1.4331	-1.2528	1.8323	-1.8652
0.45	0.3105	-0.1858	0.8262	-0.3774	1.2544	-0.6944	1.6182	-1.0966	2.0105	-1.7931
0.50	0.3770	0.1224	0.9680	-0.1304	1.4405	-0.5232	1.7973	-0.9940	2.1670	-1.7552
0.55	0.4599	0.4184	1.1283	0.0835	1.6215	-0.3969	1.9661	-0.9351	2.3008	-1.7675
0.60	0.5660	0.7100	1.3092	0.2652	1.8035	-0.3123	2.1203	-0.9117	2.4126	-1.7890
0.65	0.7047	1.0025	1.5114	0.4119	1.9810	-0.2670	2.2562	-0.9161	2.5043	-1.8214
0.70	0.8897	1.2971	1.7328	0.5174	2.1471	-0.2578	2.3715	-0.9402	2.5789	-1.8585
0.75	1.1403	1.5888	1.9670	0.5739	2.2951	-0.2796	2.4657	-0.9767	2.6398	-1.8962
0.80	1.4814	1.8602	2.2021	0.5746	2.4191	-0.3251	2.5400	-1.0187	2.6903	-1.9322
0.85	1.9387	2.0703	2.4203	0.5172	2.5159	-0.3855	2.5972	-1.0612	2.7332	-1.9653
0.90	2.5192	2.1430	2.6016	0.4083	2.5856	-0.4514	2.6408	-1.1064	2.7709	-1.9953
0.95	3.1671	1.9724	2.7293	0.2644	2.6309	-0.5149	2.6744	-1.1343	2.8051	-2.0225
1.00	3.7210	1.4915	2.7960	0.1090	2.6570	-0.5700	2.7015	-1.1622	2.8369	-2.0471
1.05	3.9720	0.7912	2.8065	-0.0341	2.6699	-0.6135	2.7248	-1.1845	2.8671	-2.0699
1.10	3.8479	0.1131	2.7747	-0.1480	2.6752	-0.6445	2.7463	-1.2019	2.8961	-2.0913
1.15	3.4768	-0.3481	2.7184	-0.2245	2.6776	-0.6640	2.7673	-1.2155	2.9242	-2.1117
1.20	3.0383	-0.5602	2.6537	-0.2641	2.6806	-0.6740	2.7887	-1.2264	2.9514	-2.1313
1.25	2.6421	-0.5859	2.5928	-0.2721	2.6864	-0.6768	2.8107	-1.2356	2.9779	-2.1505
1.30	2.3258	-0.4980	2.5435	-0.2559	2.6960	-0.6749	2.8334	-1.2439	3.0035	-2.1693
1.35	2.0906	-0.3481	2.5095	-0.2232	2.7098	-0.6703	2.8567	-1.2519	3.0283	-2.1878
1.40	1.9261	-0.1669	2.4921	-0.1809	2.7275	-0.6649	2.8803	-1.2600	3.0523	-2.2060
1.45	1.8213	0.0286	2.4909	-0.1347	2.7484	-0.6599	2.9039	-1.2684	3.0755	-2.2241
1.50	1.7673	0.2287	2.5043	-0.0892	2.7717	-0.6563	2.9273	-1.2772	3.0979	-2.2419
1.55	1.7583	0.4277	2.5300	-0.0479	2.7966	-0.6545	2.9503	-1.2865	3.1195	-2.2595
1.60	1.7913	0.6207	2.5653	-0.0133	2.8222	-0.6548	2.9728	-1.2961	3.1403	-2.2769
1.65	1.8649	0.8028	2.6074	0.0129	2.8477	-0.6570	2.9946	-1.3061	3.1604	-2.2941
1.70	1.9786	0.9673	2.6532	0.0297	2.8728	-0.6610	3.0157	-1.3162	3.1798	-2.3110
1.75	2.1314	1.1049	2.6999	0.0375	2.8968	-0.6665	3.0361	-1.3265	3.1986	-2.3277
1.80	2.3197	1.2040	2.7450	0.0369	2.9197	-0.6729	3.0559	-1.3368	3.2167	-2.3442
1.85	2.5346	1.2506	2.7862	0.0291	2.9413	-0.6800	3.0749	-1.3472	3.2343	-2.3604
1.90	2.7594	1.2325	2.8223	0.0160	2.9616	-0.6875	3.0934	-1.3574	3.2513	-2.3765
1.95	2.9691	1.1438	2.8522	-0.0002	2.9808	-0.6950	3.1113	-1.3676	3.2677	-2.3923
2.00	3.1348	0.9918	2.8760	-0.0175	2.9990	-0.7024	3.1287	-1.3778	3.2836	-2.4079
2.05	3.2323	0.7986	2.8943	-0.0343	3.0143	-0.7095	3.1457	-1.3878	3.2990	-2.4234
2.10	3.2512	0.5972	2.9019	-0.0490	3.0330	-0.7164	3.1622	-1.3977	3.3139	-2.4386
2.15	3.1994	0.4199	2.9181	-0.0608	3.0492	-0.7229	3.1783	-1.4076	3.3284	-2.4537
2.20	3.0976	0.2890	2.9263	-0.0692	3.0651	-0.7291	3.1940	-1.4174	3.3424	-2.4686
2.25	2.9705	0.2132	2.9336	-0.0743	3.0807	-0.7352	3.2094	-1.4272	3.3560	-2.4833
2.30	2.8399	0.1900	2.9410	-0.0765	3.0961	-0.7410	3.2244	-1.4369	3.3692	-2.4979
2.35	2.7212	0.2109	2.9491	-0.0762	3.1113	-0.7468	3.2390	-1.4465	3.3820	-2.5123
2.40	2.6238	0.2655	2.9594	-0.0742	3.1264	-0.7525	3.2534	-1.4561	3.3944	-2.5265
2.45	2.5523	0.3436	2.9711	-0.0712	3.1413	-0.7583	3.2674	-1.4657	3.4064	-2.5406
2.50	2.5088	0.4362	2.9845	-0.0679	3.1561	-0.7641	3.2811	-1.4753	3.4180	-2.5545

TABLE IV
Normalized Admittance Y/Δ of Loop Antennas in Dissipative Media
 $\Omega = 15$

βb	$\frac{\alpha}{\beta} = 0.00$	$\frac{\alpha}{\beta} = 0.01$	$\frac{\alpha}{\beta} = 0.03$	$\frac{\alpha}{\beta} = 0.05$	$\frac{\alpha}{\beta} = 0.07$
	Y/Δ	Y/Δ	Y/Δ	Y/Δ	Y/Δ
0.05	0.0001	-9.1554	0.0018	-9.1554	0.0052
0.10	0.0004	-4.4503	0.0038	-4.4503	0.0107
0.15	0.0010	-2.8236	0.0062	-2.8236	0.0166
0.20	0.0019	-1.9645	0.0090	-1.9646	0.0232
0.25	0.0033	-1.4101	0.0124	-1.4103	0.0306
0.30	0.0052	-1.0053	0.0165	-1.0056	0.0391
0.35	0.0080	-0.6827	0.0218	-0.6831	0.0493
0.40	0.0120	-0.4077	0.0286	-0.4083	0.0618
0.45	0.0178	-0.1597	0.0377	-0.1606	0.0775
0.50	0.0262	0.0751	0.0501	0.0736	0.0977
0.55	0.0386	0.3076	0.0674	0.3052	0.1247
0.60	0.0574	0.5477	0.0925	0.5439	0.1619
0.65	0.0865	0.8065	0.1298	0.8003	0.2150
0.70	0.1330	1.0977	0.1874	1.0872	0.2937
0.75	0.2105	1.4408	0.2807	1.4221	0.4158
0.80	0.3471	1.8645	0.4403	1.8295	0.6149
0.85	0.6069	2.4125	0.7334	2.3416	0.9588
0.90	1.1506	3.1369	1.3176	2.9793	1.5834
0.95	2.4073	3.9786	2.5577	3.6081	2.7152
1.00	5.1475	3.9093	4.8714	3.2605	4.3462
1.05	7.1521	0.2902	6.3132	0.3242	5.1358
1.10	4.8807	-2.5090	4.6364	-2.0294	4.1444
1.15	2.8139	-2.5757	2.8608	-2.2910	2.8541
1.20	1.7662	-2.0714	1.8597	-1.9144	1.9844
1.25	1.2225	-1.5815	1.3131	-1.4928	1.4598
1.30	0.9134	-1.1718	0.9954	-1.1182	1.1394
1.35	0.7239	-0.8280	0.7994	-0.7940	0.9380
1.40	0.6016	-0.5295	0.6738	-0.5077	0.8094
1.45	0.5214	-0.2599	0.5930	-0.2466	0.7293
1.50	0.4702	-0.0366	0.5439	-0.0001	0.6848
1.55	0.4422	0.2409	0.5203	0.2409	0.6699
1.60	0.4354	0.4918	0.5209	0.4946	0.6835
1.65	0.4520	0.7555	0.5481	0.7390	0.7283
1.70	0.4988	1.0428	0.6095	1.0125	0.8123
1.75	0.5901	1.3663	0.7201	1.3135	0.9497
1.80	0.7540	1.7408	0.9083	1.6506	1.1639
1.85	1.0470	2.1790	1.2257	2.0204	1.4899
1.90	1.5822	2.6677	1.7624	2.3840	1.9692
1.95	2.5642	3.0700	2.6377	2.5848	2.6124
2.00	4.1394	2.8425	3.8244	2.2215	3.2960
2.05	5.4573	1.1474	4.6704	0.9285	3.6910
2.10	4.9449	-0.9671	4.3613	-0.5962	3.5472
2.15	3.5420	-1.8088	3.3844	-1.3482	3.0341
2.20	2.4554	-1.7836	2.5010	-1.4552	2.4674
2.25	1.7788	-1.4964	1.8880	-1.2847	2.0019
2.30	1.3627	-1.1686	1.4859	-1.0324	1.6593
2.35	1.0987	-0.8571	1.2218	-0.7680	1.4175
2.40	0.9260	-0.5702	1.0466	-0.5119	1.2515
2.45	0.8119	-0.3036	0.9312	-0.2667	1.1417
2.50	0.7387	-0.0499	0.8592	-0.0298	1.0759
					0.0053
					0.6556
					-0.2063
					-0.7565
					-0.9489
					-0.9170
					-0.7778
					-0.5948
					-0.3969
					-0.1956
					0.0053
					0.6556
					-0.2063
					-0.7565
					-0.9489
					-0.9170
					-0.7778
					-0.5948
					-0.3969
					-0.1956
					0.0053
					0.6556
					-0.2063
					-0.7565
					-0.9489
					-0.9170
					-0.7778
					-0.5948
					-0.3969
					-0.1956
					0.0053
					0.6556
					-0.2063
					-0.7565
					-0.9489
					-0.9170
					-0.7778
					-0.5948
					-0.3969
					-0.1956
					0.0053
					0.6556
					-0.2063
					-0.7565
					-0.9489
					-0.9170
					-0.7778
					-0.5948
					-0.3969
					-0.1956
					0.0053
					0.6556
					-0.2063
					-0.7565
					-0.9489
					-0.9170
					-0.7778
					-0.5948
					-0.3969
					-0.1956
					0.0053
					0.6556
					-0.2063
					-0.7565
					-0.9489
					-0.9170
					-0.7778
					-0.5948
					-0.3969
					-0.1956
					0.0053
					0.6556
					-0.2063
					-0.7565
					-0.9489
					-0.9170
					-0.7778
					-0.5948
					-0.3969
					-0.1956
					0.0053
					0.6556
					-0.2063
					-0.7565
					-0.9489
					-0.9170
					-0.7778
					-0.5948
					-0.3969
					-0.1956
					0.0053
					0.6556
					-0.2063
					-0.7565
					-0.9489
					-0.9170
					-0.7778
					-0.5948
					-0.3969
					-0.1956
					0.0053
					0.6556
					-0.2063
					-0.7565
					-0.9489
					-0.9170
					-0.7778
					-0.5948
					-0.3969
					-0.1956
					0.0053
					0.6556
					-0.2063
					-0.7565
					-0.9489
					-0.9170
					-0.7778
					-0.5948
					-0.3969
					-0.1956
					0.0053
					0.6556
					-0.2063
					-0.7565
					-0.9489
					-0.9170
					-0.7778
					-0.5948
					-0.3969
					-0.1956
					0.0053
					0.6556
					-0.2063
					-0.7565
					-0.9489
					-0.9170
					-0.7778
					-0.5948
					-0.3969
					-0.1956
					0.0053
					0.6556
					-0.2063
					-0.7565
					-0.9489
					-0.9170
					-0.7778
					-0.5948
					-0.3969
					-0.1956
					0.0053
					0.6556
					-0.2063
					-0.7565
					-0.9489
					-0.9170
					-0.7778
					-0.5948
					-0.3969
					-0.1956
					0.0053
					0.6556
					-0.2063
					-0.7565
					-0.9489
					-0.9170
					-0.7778
					-0.5948
					-0.3969
					-0.1956
					0.0053
					0.6556
					-0.2063
					-0.7565
					-0.9489
					-0.9170
					-0.7778
					-0.5948
					-0.3969
					-0.1956
					0.0053
					0.6556
					-0.2063
					-0.7565
					-0.9489
					-0.9170
					-0.7778
					-0.5948
					-0.3969
					-0.1956
					0.0053
					0.6556
					-0.2063
					-0.7565
					-0.9489
					-0.9170
					-0.7778
					-0.5948
					-0.3969
					-0.1956
					0.0053
					0.6556
					-0.2063
					-0.7565
					-0.9489
					-0.9170
					-0.7778
					-0.5948
					-0.3969
					-0.1956
					0.0053
					0.6556
					-0.2063
					-0.7565
					-0.9489
					-0.9170
					-0.7778
					-0.5948
					-0.3969
					-0.1956
					0.0053
					0.6556
					-0.2063
					-0.7565
					-0.9489
					-0.9170
					-0.7778
					-0.5948
					-0.3969
					-0.1956
					0.0053
					0.6556
					-0.2063
					-0.7565
					-0.9489
					-0.9170
					-0.7778
					-0.5948
					-0.3969
					-0.1956

Normalized Admittance Y/Δ of Loop Antennas in Dissipative Media
 $\Omega = 15$

$\beta\Omega$	$\frac{\alpha}{\beta} = 0.10$	$\frac{\alpha}{\beta} = 0.30$	$\frac{\alpha}{\beta} = 0.50$	$\frac{\alpha}{\beta} = 0.70$	$\frac{\alpha}{\beta} = 1.00$
0.05	0.0170	0.0508	0.0845	0.1182	0.1685
0.10	0.0346	0.1026	0.1702	0.2573	0.3364
0.15	0.0529	0.1562	0.2581	0.3582	0.5033
0.20	0.0726	0.2126	0.3494	0.4815	0.6684
0.25	0.0940	0.2728	0.4449	0.6077	0.8298
0.30	0.1179	0.3380	0.5458	0.7367	0.9854
0.35	0.1451	0.4098	0.6529	0.8678	1.1322
0.40	0.1769	0.4898	0.7669	0.9997	1.2671
0.45	0.2145	0.5801	0.8876	1.1302	1.3871
0.50	0.2612	0.6829	1.0146	1.2562	1.4903
0.55	0.3195	0.8006	1.1460	1.3742	1.5756
0.60	0.3949	0.9352	1.2785	1.4804	1.6436
0.65	0.4949	1.0912	1.4076	1.5718	1.6965
0.70	0.6314	1.2580	1.5273	1.6464	1.7362
0.75	0.8221	1.4537	1.6316	1.7035	1.7659
0.80	1.0933	1.7800	1.7154	1.7453	1.7882
0.85	1.4784	1.5656	1.7758	1.7734	1.8056
0.90	2.0007	1.6315	1.8133	1.7913	1.8197
0.95	2.6147	1.4445	1.8308	1.8022	1.8319
1.00	3.1199	0.9046	1.8335	1.8090	1.8431
1.05	3.2410	0.1506	1.8268	1.8130	1.8536
1.10	2.9489	-0.4763	1.8159	1.8184	1.8637
1.15	2.4815	-0.7973	1.8046	1.8235	1.8736
1.20	2.0429	-0.8667	1.7956	1.8296	1.8832
1.25	1.7024	-0.7948	1.7904	1.8368	1.8925
1.30	1.4588	-0.6578	1.7894	1.8450	1.9015
1.35	1.2923	-0.4951	1.7926	1.8540	1.9100
1.40	1.1848	-0.3251	1.7995	1.8634	1.9182
1.45	1.1229	-0.1554	1.8092	1.8730	1.9259
1.50	1.0953	0.0107	1.8210	1.8826	1.9332
1.55	1.1065	0.1716	1.8340	1.8919	1.9400
1.60	1.1458	0.3258	1.8473	1.9009	1.9465
1.65	1.2166	0.4707	1.8605	1.9094	1.9525
1.70	1.3203	0.6016	1.8731	1.9175	1.9582
1.75	1.4586	0.7104	1.8847	1.9251	1.9636
1.80	1.6306	0.7851	1.8952	1.9322	1.9685
1.85	1.8298	0.8097	1.9046	1.9389	1.9733
1.90	2.0394	0.7681	1.9130	1.9453	1.9778
1.95	2.2303	0.6512	1.9204	1.9514	1.9819
2.00	2.3663	0.4680	1.9272	1.9572	1.9858
2.05	2.4487	0.2503	1.9333	1.9627	1.9894
2.10	2.3825	0.0418	1.9391	1.9680	1.9928
2.15	2.2778	-0.1205	1.9447	1.9731	1.9960
2.20	2.1369	-0.2198	1.9501	1.9780	1.9989
2.25	1.9897	-0.2578	1.9555	1.9827	2.0016
2.30	1.8558	-0.2461	1.9609	1.9873	2.0041
2.35	1.7454	-0.1988	1.9663	1.9917	2.0064
2.40	1.6623	-0.1280	1.9716	1.9950	2.0086
2.45	1.6070	-0.0433	1.9770	2.0000	2.0105
2.50	1.5782	0.0482	1.9823	2.0039	2.0123
2.55					
2.60					
2.65					
2.70					
2.75					
2.80					
2.85					
2.90					
2.95					
3.00					

TABLE V
Normalized Admittance Y/Δ of Loop Antennas in Dissipative Media
 $\Omega = 17$

βb	$\frac{\alpha}{\beta} = 0.00$	$\frac{\alpha}{\beta} = 0.01$	$\frac{\alpha}{\beta} = 0.03$	$\frac{\alpha}{\beta} = 0.05$	$\frac{\alpha}{\beta} = 0.07$
0.05	0.0001	0.0014	0.0041	0.0068	0.0095
0.10	0.0003	0.0030	0.0085	0.0139	0.0194
0.15	0.0007	0.0048	0.0131	0.0214	0.0297
0.20	0.0013	0.0070	0.0183	0.0296	0.0409
0.25	0.0022	0.0095	0.0241	0.0386	0.0531
0.30	0.0035	0.0126	0.0307	0.0488	0.0668
0.35	0.0054	0.0165	0.0386	0.0606	0.0826
0.40	0.0081	0.0215	0.0482	0.0748	0.1013
0.45	0.0120	0.0281	0.0602	0.0921	0.1238
0.50	0.0177	0.0371	0.0756	0.1139	0.1518
0.55	0.0262	0.0496	0.0942	0.1422	0.1877
0.60	0.0391	0.0677	0.1245	0.1804	0.2352
0.65	0.0591	0.0947	0.1649	0.2336	0.3003
0.70	0.0913	0.1366	0.2253	0.3108	0.3928
0.75	0.1459	0.2053	0.3200	0.4284	0.5296
0.80	0.2444	0.3254	0.4781	0.6167	0.7405
0.85	0.4389	0.5542	0.7611	1.0351	1.2878
0.90	0.8742	1.0412	1.3092	1.4950	1.7490
0.95	2.0206	3.6945	2.4020	2.4446	2.4077
1.00	5.1373	3.8032	4.1369	3.6118	3.2029
1.05	6.9020	-0.9520	4.7075	3.8984	3.3449
1.10	3.6382	-2.9701	3.3293	3.0334	2.7606
1.15	1.8759	-2.4507	2.0919	2.1019	2.0591
1.20	1.1348	-1.8366	1.3914	1.4866	1.5375
1.25	0.7756	-1.3653	1.0036	1.1141	1.1957
1.30	0.5773	-1.0030	0.7775	0.8868	0.9773
1.35	0.4575	-0.7109	0.6396	0.7455	0.8380
1.40	0.3810	-0.4625	0.5539	0.6582	0.7528
1.45	0.3313	-0.2407	0.5025	0.6077	0.7047
1.50	0.3002	-0.0334	0.4761	0.5850	0.6860
1.55	0.2840	0.1691	0.4709	0.5863	0.6929
1.60	0.2917	0.3752	0.4866	0.6114	0.7250
1.65	0.2953	0.5939	0.5263	0.6632	0.7848
1.70	0.3201	0.8357	0.5972	0.7486	0.8776
1.75	0.3976	1.1146	0.7129	0.8790	1.0112
1.80	0.5216	1.4501	0.8971	1.0715	1.1952
1.85	0.7542	1.8676	1.1849	1.3475	1.4365
1.90	1.2167	2.3958	1.6440	1.7225	1.7285
1.95	2.1930	2.9150	2.2976	2.1705	2.0322
2.00	4.0749	2.7502	3.0131	2.5679	2.2652
2.05	5.5169	0.3773	3.3397	2.7168	2.3382
2.10	4.1584	-1.8453	3.0115	2.5427	2.2308
2.15	2.5313	-2.1189	2.3870	2.1843	2.0087
2.20	1.6193	-1.7831	1.7409	1.8125	1.7590
2.25	1.1521	-1.3982	1.2637	1.5070	1.5525
2.30	0.8541	-1.0616	0.9759	1.2798	1.3525
2.35	0.6447	-0.7746	0.9810	1.1199	1.2181
2.40	0.5766	-0.5244	0.6806	1.0096	1.1243
2.45	0.5066	-0.2986	0.6070	0.9405	1.0548
2.50	0.4627	-0.0871	0.5630	0.9040	1.0351

βb	$\frac{\alpha}{\beta} = 0.10$	$\frac{\alpha}{\beta} = 0.30$	$\frac{\alpha}{\beta} = 0.50$	$\frac{\alpha}{\beta} = 0.70$	$\frac{\alpha}{\beta} = 1.00$
	Y/Δ	Y/Δ	Y/Δ	Y/Δ	Y/Δ
C.05	0.0136	0.0405	0.0675	0.0943	0.1345
C.10	0.0275	0.0819	0.1359	0.1894	0.2686
C.15	0.0422	0.1247	0.2061	0.2860	0.4019
C.20	0.0578	0.1697	0.2791	0.3647	0.5338
C.25	0.0749	0.2179	0.3557	0.4859	0.6629
C.30	0.0939	0.2703	0.4358	0.5894	0.7971
C.35	0.1155	0.3281	0.5232	0.6948	0.9041
C.40	0.1408	0.3927	0.6153	0.8010	1.0111
C.45	0.1709	0.4660	0.7133	0.9062	1.1057
C.50	0.2080	0.5498	0.8167	1.0076	1.1860
C.55	0.2547	0.6464	0.9240	1.1022	1.2513
C.60	0.3153	0.7577	1.0325	1.1867	1.3021
C.65	0.3904	0.8850	1.1380	1.2585	1.3399
C.70	0.5082	1.0276	1.2354	1.3157	1.3715
C.75	0.6670	1.1819	1.3192	1.3582	1.3859
C.80	0.8980	1.3378	1.3848	1.3671	1.3990
C.85	1.2355	1.4601	1.4297	1.4047	1.4082
C.90	1.7134	1.3777	1.4545	1.4140	1.4152
C.95	2.2912	1.1906	1.4622	1.4178	1.4209
1.00	2.7504	0.6387	1.4576	1.4186	1.4260
1.05	2.7882	-0.1033	1.4458	1.4183	1.4308
1.10	2.4265	-0.6519	1.4312	1.4181	1.4356
1.15	1.9561	-0.8737	1.4172	1.4187	1.4403
1.20	1.5609	-0.8741	1.4059	1.4206	1.4449
1.25	1.2759	-0.7706	1.3984	1.4236	1.4494
1.30	1.0821	-0.6282	1.3951	1.4275	1.4537
1.35	0.9550	-0.4755	1.3956	1.4323	1.4577
1.40	0.8763	-0.3237	1.3994	1.4376	1.4615
1.45	0.8341	-0.1764	1.4057	1.4430	1.4650
1.50	0.8213	-0.0345	1.4137	1.4484	1.4682
1.55	0.8347	0.1019	1.4227	1.4537	1.4712
1.60	0.8733	0.2323	1.4319	1.4586	1.4738
1.65	0.9381	0.3550	1.4409	1.4632	1.4762
1.70	1.0315	0.4662	1.4493	1.4675	1.4784
1.75	1.1559	0.5586	1.4567	1.4714	1.4803
1.80	1.3119	0.6208	1.4632	1.4749	1.4820
1.85	1.4943	0.6363	1.4687	1.4782	1.4836
1.90	1.6870	0.5676	1.4733	1.4812	1.4849
1.95	1.8595	0.4646	1.4772	1.4839	1.4861
2.00	1.9729	0.2780	1.4805	1.4865	1.4871
2.05	1.9987	0.0641	1.4834	1.4889	1.4879
2.10	1.9374	-0.1293	1.4860	1.4912	1.4886
2.15	1.8164	-0.2673	1.4885	1.4934	1.4891
2.20	1.6716	-0.3397	1.4910	1.4954	1.4895
2.25	1.5312	-0.3549	1.4934	1.4973	1.4897
2.30	1.4106	-0.3277	1.4959	1.4991	1.4896
2.35	1.3159	-0.2728	1.4985	1.5009	1.4898
2.40	1.2478	-0.2012	1.5011	1.5025	1.4897
2.45	1.2051	-0.1207	1.5037	1.5040	1.4895
2.50	1.1857	-0.0369	1.5064	1.5054	1.4891

TABLE VI
Normalized Admittance Y/Δ of Loop Antennas in Dissipative Media
 $\alpha = 20$

$\beta\lambda$	$\frac{\alpha}{\beta} = 0.00$	$\frac{\alpha}{\beta} = 0.01$	$\frac{\alpha}{\beta} = 0.03$	$\frac{\alpha}{\beta} = 0.05$	$\frac{\alpha}{\beta} = 0.07$
0.05	0.0001	0.0012	0.0034	0.0057	0.0079
0.10	0.0002	0.0025	0.0070	0.0116	0.0161
0.15	0.0005	0.0040	0.0109	0.0178	0.0247
0.20	0.0009	0.0057	0.0151	0.0245	0.0339
0.25	0.0016	0.0077	0.0198	0.0319	0.0441
0.30	0.0026	0.0101	0.0252	0.0403	0.0554
0.35	0.0039	0.0132	0.0316	0.0501	0.0685
0.40	0.0059	0.0170	0.0394	0.0616	0.0838
0.45	0.0087	0.0222	0.0490	0.0758	0.1024
0.50	0.129	0.0291	0.0614	0.0936	0.1255
0.55	0.0190	0.0387	0.0779	0.1168	0.1552
0.60	0.0283	0.0526	0.1005	0.1479	0.1944
0.65	0.0429	0.0731	0.1329	0.1914	0.2484
0.70	0.0646	0.1054	0.1814	0.2550	0.3256
0.75	0.1070	0.1585	0.2581	0.3526	0.4409
0.80	0.1812	0.2527	0.3879	0.5113	0.6216
0.85	0.3315	0.4367	0.6265	0.7868	0.9175
0.90	0.6446	0.9473	1.1092	1.2922	1.4103
0.95	1.7134	3.4487	2.1525	2.2026	2.1640
1.00	5.1313	3.7410	3.9455	3.3597	2.9227
1.05	0.3542	-1.9606	4.2674	3.4577	2.9593
1.10	2.6497	-2.9449	2.6900	2.5089	2.3089
1.15	1.3056	-2.2037	1.5893	1.6491	1.6490
1.20	0.7795	-1.5977	0.8759	1.1363	1.2011
1.25	0.5302	-1.1739	0.6054	0.8419	0.9227
1.30	0.3442	-0.8597	0.4565	0.6677	0.7506
1.35	0.3135	-0.6105	0.3676	0.5619	0.6441
1.40	0.2614	-0.4004	0.3122	0.4981	0.5801
1.45	0.2285	-0.2136	0.2774	0.4527	0.5460
1.50	0.2078	-0.0391	0.2584	0.4289	0.5351
1.55	0.1975	0.1315	0.2514	0.4539	0.5449
1.60	0.1970	0.3059	0.2566	0.4779	0.5754
1.65	0.2079	0.4921	0.2763	0.5242	0.6293
1.70	0.2345	0.7002	0.3158	0.5901	0.7119
1.75	0.2859	0.9443	0.3862	0.7137	0.8311
1.80	0.3820	1.2453	0.5103	0.8953	0.9972
1.85	0.5625	1.6361	0.7369	1.0198	0.7298
1.90	0.9635	2.1591	1.1755	1.1375	0.7965
1.95	1.8979	2.7845	2.0572	1.4911	0.7832
2.00	4.0386	2.7033	3.5455	1.9246	0.6421
2.05	5.4567	-0.3557	4.2701	2.3015	0.3566
2.10	3.3406	-2.2772	3.0998	2.3989	2.0269
2.15	1.8152	-2.0877	1.9261	2.1653	1.8894
2.20	1.1145	-1.6269	1.2608	1.7833	1.6572
2.25	0.7683	-1.2369	0.8977	1.4371	1.4179
2.30	0.5773	-0.9277	0.6081	1.1726	1.2160
2.35	0.4628	-0.6754	0.5603	0.9841	1.0616
2.40	0.3906	-0.4603	0.4799	0.8555	0.9506
2.45	0.3442	-0.2685	0.4296	0.7710	0.8757
2.50	0.3156	-0.0895	0.4006	0.7196	0.8302
			0.5578	0.6947	0.8098
			-0.0705	-0.0627	-0.0600
			-0.0134	0.0037	-0.0050
			-0.8202	-0.4822	-0.3170
			-1.0959	-0.7240	-0.5011
			-1.0537	-0.7647	-0.5612
			-0.8998	-0.6975	-0.5378
			-0.7211	-0.5843	-0.4678
			-0.5454	-0.4551	-0.3749
			-0.3792	-0.3226	-0.2722
			-0.2217	-0.1915	-0.1661
			-0.0705	-0.0627	-0.0600

Normalized Admittance Y/Δ of Loop Antennas in Dissipative Media

$$\Omega = 20$$

β_0	$\frac{\alpha}{\beta} = 0.10$	$\frac{\alpha}{\beta} = 0.30$	$\frac{\alpha}{\beta} = 0.50$	$\frac{\alpha}{\beta} = 0.70$	$\frac{\alpha}{\beta} = 1.00$					
	Y/Δ	Y/Δ	Y/Δ	Y/Δ	Y/Δ					
0.05	0.0113	-6.3815	0.0338	-6.3861	0.0562	-6.3952	0.0786	-6.4087	0.1120	-6.4375
0.10	0.0229	-3.1070	0.0682	-3.1164	0.1132	-3.1351	0.1578	-3.1629	0.2237	-3.2217
0.15	0.0351	-1.9772	0.1038	-1.9920	0.1717	-2.0214	0.2383	-2.0648	0.3349	-2.1557
0.20	0.0480	-1.3823	0.1414	-1.4036	0.2326	-1.4452	0.3207	-1.5062	0.4448	-1.6322
0.25	0.0622	-0.9999	0.1816	-1.0290	0.2966	-1.0852	0.4051	-1.1666	0.5524	-1.3310
0.30	0.0780	-0.7220	0.2254	-0.7611	0.3645	-0.8349	0.4917	-0.9399	0.6560	-1.1458
0.35	0.0959	-0.5020	0.2738	-0.5538	0.4369	-0.6495	0.5800	-0.7817	0.7533	-1.0313
0.40	0.1169	-0.3157	0.3281	-0.3845	0.5143	-0.5072	0.6690	-0.6706	0.8421	-0.9639
0.45	0.1420	-0.1495	0.3897	-0.2410	0.5968	-0.3972	0.7571	-0.5950	0.9202	-0.9296
0.50	0.1728	0.0058	0.4606	-0.1169	0.6842	-0.3141	0.8421	-0.5481	0.9859	-0.9182
0.55	0.2117	0.1567	0.5425	-0.0093	0.7750	-0.2552	0.9211	-0.5250	1.0386	-0.9221
0.60	0.2624	0.3084	0.6375	0.0820	0.8669	-0.2197	0.9914	-0.5214	1.0788	-0.9351
0.65	0.3305	0.4651	0.7467	0.1545	0.9563	-0.2069	1.0504	-0.5326	1.1079	-0.9523
0.70	0.4251	0.6303	0.8698	0.2031	1.0384	-0.2155	1.0967	-0.5540	1.1279	-0.9706
0.75	0.5609	0.8048	1.0034	0.2209	1.1084	-0.2423	1.1300	-0.5807	1.1409	-0.9877
0.80	0.7619	0.9825	1.1388	0.2009	1.1621	-0.2824	1.1516	-0.6086	1.1492	-1.0027
0.85	1.0632	1.1375	1.2616	0.1399	1.1974	-0.3293	1.1635	-0.6345	1.1544	-1.0153
0.90	1.5000	1.1974	1.3544	0.0430	1.2149	-0.3765	1.1683	-0.6566	1.1578	-1.0256
0.95	2.0413	1.0150	1.4031	-0.0744	1.2174	-0.4185	1.1686	-0.6739	1.1604	-1.0340
1.00	2.4573	0.4673	1.4043	-0.1905	1.2096	-0.4518	1.1667	-0.6868	1.1626	-1.0410
1.05	2.4343	-0.2422	1.3669	-0.2858	1.1958	-0.4752	1.1641	-0.6956	1.1648	-1.0470
1.10	2.0421	-0.7142	1.3069	-0.3501	1.1803	-0.4893	1.1619	-0.7015	1.1670	-1.0523
1.15	1.5945	-0.8641	1.2401	-0.3927	1.1658	-0.4956	1.1606	-0.7052	1.1693	-1.0573
1.20	1.2458	-0.8260	1.1779	-0.3889	1.1542	-0.4963	1.1605	-0.7076	1.1716	-1.0620
1.25	1.0062	-0.7116	1.1267	-0.3761	1.1463	-0.4932	1.1616	-0.7093	1.1738	-1.0667
1.30	0.8488	-0.5744	1.0889	-0.3513	1.1422	-0.4882	1.1636	-0.7109	1.1759	-1.0712
1.35	0.7483	-0.4351	1.0648	-0.3201	1.1416	-0.4826	1.1663	-0.7127	1.1779	-1.0758
1.40	0.6881	-0.3003	1.0532	-0.2868	1.1439	-0.4775	1.1695	-0.7148	1.1797	-1.0803
1.45	0.6577	-0.1716	1.0526	-0.2546	1.1485	-0.4736	1.1729	-0.7174	1.1813	-1.0847
1.50	0.6514	-0.0487	1.0613	-0.2258	1.1545	-0.4712	1.1762	-0.7203	1.1827	-1.0891
1.55	0.6666	0.0690	1.0771	-0.2022	1.1613	-0.4706	1.1795	-0.7236	1.1839	-1.0935
1.60	0.7030	0.1815	1.0981	-0.1848	1.1683	-0.4715	1.1825	-0.7272	1.1849	-1.0977
1.65	0.7619	0.2876	1.1222	-0.1744	1.1749	-0.4738	1.1852	-0.7309	1.1857	-1.1019
1.70	0.8458	0.3841	1.1472	-0.1710	1.1810	-0.4772	1.1876	-0.7347	1.1863	-1.1060
1.75	0.9578	0.4645	1.1711	-0.1742	1.1863	-0.4814	1.1897	-0.7386	1.1868	-1.1100
1.80	1.0993	0.5178	1.1921	-0.1831	1.1906	-0.4861	1.1916	-0.7424	1.1871	-1.1139
1.85	1.2660	0.5280	1.2090	-0.1963	1.1941	-0.4909	1.1932	-0.7462	1.1873	-1.1177
1.90	1.4425	0.4769	1.2210	-0.2120	1.1969	-0.4956	1.1946	-0.7499	1.1873	-1.1215
1.95	1.5982	0.3543	1.2279	-0.2284	1.1990	-0.5002	1.1959	-0.7535	1.1873	-1.1252
2.00	1.6933	0.1719	1.2301	-0.2441	1.2006	-0.5044	1.1970	-0.7571	1.1871	-1.1288
2.05	1.7011	-0.0310	1.2286	-0.2577	1.2020	-0.5083	1.1981	-0.7605	1.1868	-1.1324
2.10	1.6264	-0.2059	1.2244	-0.2686	1.2031	-0.5118	1.1990	-0.7639	1.1864	-1.1358
2.15	1.5014	-0.3217	1.2188	-0.2762	1.2042	-0.5150	1.1998	-0.7672	1.1859	-1.1392
2.20	1.3621	-0.3741	1.2128	-0.2808	1.2053	-0.5180	1.2006	-0.7705	1.1853	-1.1426
2.25	1.2334	-0.3749	1.2074	-0.2827	1.2064	-0.5208	1.2013	-0.7739	1.1846	-1.1459
2.30	1.1271	-0.3404	1.2033	-0.2825	1.2076	-0.5235	1.2019	-0.7770	1.1838	-1.1491
2.35	1.0463	-0.2841	1.2007	-0.2809	1.2089	-0.5261	1.2025	-0.7802	1.1829	-1.1523
2.40	0.9902	-0.2157	1.1999	-0.2784	1.2102	-0.5287	1.2029	-0.7834	1.1820	-1.1554
2.45	0.9565	-0.1415	1.2008	-0.2758	1.2116	-0.5314	1.2033	-0.7865	1.1809	-1.1585
2.50	0.9433	-0.0659	1.2033	-0.2736	1.2129	-0.5341	1.2037	-0.7897	1.1798	-1.1615

Defense Documentation Center [20]
100A-1
Camden Station
Alexandria, Virginia 22304

Activity Supply Office [10]
Building 2504
Charles Wood Area
Fort Monmouth, New Jersey
Attn: Director of Research

Commanding Officer [10]
Office of Naval Research
Navy 100, Box 19
Fleet Post Office
New York, New York

Chief of Naval Research [2]
Department of the Navy
Washington 25, D.C.
Attn: Code 427, Dr. Shostak

Commanding Officer [2]
Office of Naval Research
495 Summer Street
Boston, Massachusetts

Chief of Naval Research
Department of the Navy
Washington 25, D.C.
Attn: Code 421

Commanding Officer
Office of Naval Research
John Crerar Library Building
56 East Randolph Street
Chicago 1, Illinois

Commanding Officer
Office of Naval Research
46 Broadway
New York 13, New York

Commanding Officer
Office of Naval Research
1010 East Green Street
Pasadena, California

Commanding Officer
Office of Naval Research
1000 Geary Street
San Francisco 9, California

The Director [4]
Naval Research Laboratory
Washington 25, D.C.
Attn: Technical Information
Office

Head, Document Section
Technical Information Division
Naval Research Laboratory
Washington 25, D.C.

Martin A. Garstens
Magnetism Branch, Code 6450
Solid State Division
Naval Research Laboratory
Washington 25, D.C.

Assistant Secretary of Defense
(Research and Development)
Research and Development Board
Department of Defense
Washington 25, D.C.

Chief of Naval Operations
Department of the Navy
Washington 25, D.C.
Attn: Op-20

Chief of Naval Operations
Department of the Navy
Washington 25, D.C.
Attn: Op-12

Chief of Naval Operations
Department of the Navy
Washington 25, D.C.
Attn: Op-413

Chief, Bureau of Ships [2]
Department of the Navy
Washington 25, D.C.
Attn: Code 910

Commander [2]
U. S. Naval Electronics Lab
San Diego, California

Director
Naval Ordnance Laboratory
White Oak, Maryland

Technical Library
U. S. Naval Proving Ground
Dahlgren, Virginia

Commanding Officer
U. S. Air Development
Center
Johnsville, Pennsylvania
Attn: NADC Library

Commander
U. S. Air Development
Center
Johnsville, Pennsylvania
Attn: AAFEL

Librarian
U. S. Naval Post Graduate
School
Monterey, California

Mr. John T. Wallace
Scientific and Technical Unit
of the JCS/AFMVP
Frankfort, Kentucky 40621
U. S. Air Force
New York, N.Y.

Mr. ASCEB (CRNL) [5]
L. G. Hancock Field
Boston, Mass. 01371
[2] CRNL
[1] CRNL-Dr. Hollingsworth
[1] CRNL
[1] CRNL

Commanding General [3]
Air Research and Development
Command
P. O. Box 1395
Baltimore 3, Maryland
Attn: KDTBRP

Director, Air University [2]

Library
Maxwell Air Force Base
Alabama

Commanding General [2]
Attn: RCNW
Rome Air Development Center
Griffiss Air Force Base
Rome, New York

Commanding General
Rome Air Development Center
Griffiss Air Force Base
Rome, New York
Attn: RCREC-4C

Commanding General
Rome Air Development Center
Griffiss Air Force Base
Rome, New York
Attn: RCN

Air Force Office of Scientific
Research
Air Research and Development
Command
Washington 25, D.C.
Attn: SciV, Physics Division

Commandant
Air Force Institute of Technology
Wright Patterson Air Force Base
Ohio
Attn: Library

AF Research Division [2]
Aeronautical Research Lab.
(RWL)
Wright Patterson AF Base
OHIO

6570
AMRL (Library)
Wright-Patterson Air Force Base
Ohio

ARL (ARL/Mr. R. E. Woodard)
Building 450
Wright-Patterson AF Base
Ohio

AF Special Weapons Center
Kirtland Air Force Base
Albuquerque, New Mexico
Attn: SWOI

Headquarters
AF Missile Test Center
MU-135, ADRC
Patrick Air Force Base
Florida

Chief, European Office
ARDC Command
Shell Building
40 Rue Rayenstein
Brussels, Belgium

Headquarters
Air Research and Development
Command

United States Air Force
Andrews Air Force Base
Washington 25, D.C.

Mr. A. D. Bedrosian
Signal Corps Liaison Office
Mass. Institute of Technology
Building 26, Room 131
Cambridge 39, Massachusetts

Dr. J. Anton Hoffman
Ordnance Materials Res. Office
Watertown Arsenal
Watertown, Massachusetts

Commanding Officer [3]
U. S. Army Research Office
Attn: CRD-AA-1P
Mr. Ulah

Box CM, Duke Station
Durham, North Carolina

Commanding Officer
U. S. Army Signal Missile
Support Agency
Mr. T. S. Bellows
White Sands Missile Range
Mexico

U. S. Army Engineer
Research and Development
Laboratories
Fort Belvoir, Virginia
Attn: Technical Documents Center

National Security Agency [2]
Physical Sciences Division
Fort George Meade, Maryland
Attn: Dr. Alvin Markler

Dr. H. Campaigne
National Security Agency
Physical Sciences Division
Fort George Meade, Maryland

Senate Library
Brandeis University
Waltham, Massachusetts

Senate Corporation
Org. 1416, Senate Base
Albuquerque, New Mexico
Attn: Dr. C. W. Harrison, Jr.

Senate Corporation
Senate Base
Albuquerque, New Mexico
Attn: Library Division 1922-1

National Bureau of Standards Library
Room 101, Northwest Bldg
Washington 25, D.C.

Librarian
U. S. Department of Commerce
National Bureau of Standards
Boulder, Colorado

U. S. Coast Guard
100 E. Street, N.W.
Washington 25, D.C.
Attn: EEE

Stanford Electronics Lab
Stanford University
Stanford, California
Attn: Document Library
Appl. 4 Electronics Lab.

Director, Lincoln Laboratories
Mass. Institute of Technology
Bedford, Massachusetts

Library, Room A 229
Lincoln Laboratory
P. O. Box 13
Lexington 73, Massachusetts

Mr. John Hewitt
Document Room
Research Lab. of Electronics
Mass. Institute of Technology
Cambridge 39, Massachusetts

Professor A. Von Hippel
Mass. Institute of Technology
Lab. for Radiation Research
Cambridge 39, Massachusetts

Library, College of Engineering
University Heights Library
University Heights
New York University
New York 33, New York

E. A. Chapman, Librarian
Rensselaer Polytechnic Institute
Amos Eaton Hall
Troy, New York

Dept. of Electrical Engineering
Case Institute of Technology
University Circle
Cleveland 6, Ohio
Attn: S. Seely, Head

Robert Plonsey
Department of Engineering
Case Institute of Technology
University Circle
Cleveland 6, Ohio

Librarian
Engineering Library
Brown University
Providence, Rhode Island

Secretary, Working Group
Semiconductor Devices
346 Broadway, 8th Floor
New York 13, New York
Attn: AGET

Institute for Defense Analysis
Communications Research Div.
von Neumann Hall
Princeton
New Jersey

Ohio State University
Antenna Laboratory
2024 Neil Laboratory
Columbus 10, Ohio
Attn: Reports Library

Polytechnic Institute of Brooklyn
Graduate Center
Route 110
Farmingdale, New York

Ohio State University
Research Foundation
1314 Kinnear Road
Columbus 12, Ohio
Attn: Antenna Library

Yale University
Mason Laboratory
400 Temple Street
New Haven 10, Conn.
Attn: Library

University of New Mexico
Dept. of Electrical Engineering
Room 214
Albuquerque, New Mexico
Attn: R. K. Moore, Chairman

Carlisle Barton Laboratory [2]
John Hopkins University
Charles and 14th Street
Baltimore 18, Maryland
Attn: Librarian

Associate Prof. A. Kaprielian
Dept. of Electrical Engineering
University of Southern California
University Park
Los Angeles 7, California

Donald C. Stinson
Dept. of Electrical Engineering
University of Arizona
Tucson 25, Arizona

Professor Jerome B. Sager
Div. of Electrical Engineering
University of California
Berkeley 4, California

Professor Charles Kessel
Department of Physics
University of California
Berkeley 4, California

Dr. C. H. Pope
Dept. of Electrical Engineering
California Institute of Technology
Pasadena, California

Professor H. G. Bommer
School of Electrical Engineering
Cornell University
Ithaca, New York

Dr. C. J. Falbomark
Russett Memorial Institute
Columbus, Ohio
Attn: Electrical Engineering Div.

Professor A. W. Straton
Dept. of Electrical Engineering
University of Texas
Austin 12, Texas

Charles G. H. Tang
Bell Telephone Labs
Murray Hill, New Jersey

Space Sciences Lab
Lanchester Observatory
University of California
Berkeley 4, California
Attn: Dr. Samuel Silver

Prof. A. W. Lawson
Department of Physics
University of California
Riverside
California

Professor Joseph E. Rowe
Electron Physics Lab.
Dept. of Electrical Engineering
University of Michigan
1905 East Engineering Bldg.
Ann Arbor, Michigan

Gordon McKay Library [2]
Pierce Hall, Harvard University
Oxford St., Cambridge, Mass.

Chung Kung University
Electrical Engineering Department
Tainan, Taiwan
Republic of China
Attn: Prof. Chao-Hsi-Chou
Head, Engineering Dept.

Mr. D. J. Jones
Department of Mathematics
Univ. College of No. Staffordshire
Keels Staffordshire, England

Professor Paul Sanat Mito
Osaka City University
Dept. of Engineering Sciences
12 Nishi Ogimachi Kitaku
Osaka, Japan

Contract Nonr-1866(28) only

Dept. of Electrical Engineering
King's College
Newcastle upon Tyne
England

Contract Nonr-1866(32) only

U. S. Atomic Energy
Commission
Office of Technical Information
Extension
P. O. Box 62
Oak Ridge
Tennessee

* One copy to each address unless
otherwise specified by numbers
in brackets

END

FILMED

9-85

DTIC