

(13) LEVEL II
SC

ADA 079811

JASON

Technical Note
JSN-79-06

December 1979

IMPACT FUSION WITH A SEGMENTED RAIL GUN

By: R. L. Garwin
R. A. Muller
B. Richter

DDC FILE COPY

DDC
RECEIVED
JAN 24 1980
B

SRI International
1611 North Kent Street
Arlington, Virginia 22209

DISTRIBUTION STATEMENT A

Approved for public release;
Distribution Unlimited



80 1 23 006

JASON TECHNICAL NOTE

JSN-79-05

IMPACT FUSION WITH A SEGMENTED RAIL GUN

R.A. MULLER

R.L. GARWIN

B. RICHTER

December 1979

SRI International



UNCLASSIFIED

SECURITY CLASSIFICATION OF THIS PAGE (When Data Entered)

REPORT DOCUMENTATION PAGE		READ INSTRUCTIONS BEFORE COMPLETING FORM
1. REPORT NUMBER JSN-79-05	2. GOVT ACCESSION NO.	3. RECIPIENT'S CATALOG NUMBER
4. TITLE (and Subtitle) Impact Fusion with a Segmented Rail Gun		5. TYPE OF REPORT & PERIOD COVERED Technical Note
7. AUTHOR(s) 10 R. A. Muller, R. L. Garwin B. Richter		6. PERFORMING ORG. REPORT NUMBER
8. PERFORMING ORGANIZATION NAME AND ADDRESS SRI International 1611 N. Kent Street Arlington, VA 22209		9. CONTRACT OR GRANT NUMBER(s) 75 DOLBY-76-C-03-0115
11. CONTROLLING OFFICE NAME AND ADDRESS 11		10. PROGRAM ELEMENT, PROJECT, TASK AREA & WORK UNIT NUMBERS 1216
14. MONITORING AGENCY NAME & ADDRESS (if diff. from Controlling Office) 14 SRI-JSN-79-05		12. REPORT DATE December 1979
		13. NO. OF PAGES
		15. SECURITY CLASS. (of this report) UNCLASSIFIED
		16. DECLASSIFICATION/DOWNGRADING SCHEDULE

18. DISTRIBUTION STATEMENT (of this report)

Cleared for open publication; distribution unlimited.

DISTRIBUTION STATEMENT A

Approved for public release;
Distribution Unlimited

17. DISTRIBUTION STATEMENT

18. SUPPLEMENTARY NOTES

19. KEY WORDS (Continue on reverse side if necessary and identify by block number)

ELECTROMAGNETIC PROPULSION
RAIL GUNS
MAGNETIC ACCELERATION
IMPACT FUSION
HEAVY ION FUSION

20. ABSTRACT (Continue on reverse side if necessary and identify by block number)

The rail gun offers an attractive alternative to the traveling wave rifle for the magnetic acceleration of macroscopic (0.05 g) bullets for impact fusion. In this paper we review the basic rail gun equations and indicate how energy efficiency can be designed in. We set as our preliminary goal the delivery of 1 megajoule in 10 nanoseconds, with a specific energy of 20 MJ/g (i.e. a bullet mass of 0.05 g); these values are taken from the requirements being considered for heavy-ion fusion. Using these numbers the final particle velocity is 200 km/sec. For a delivery time of 10 nanoseconds, this velocity implies that the projectile length

DD FORM 1473

EDITION OF 1 NOV 65 IS OBSOLETE

UNCLASSIFIED

SECURITY CLASSIFICATION OF THIS PAGE (When Data Entered)

389 941

JOC

UNCLASSIFIED

SECURITY CLASSIFICATION OF THIS PAGE (When Data Entered)

19. KEY WORDS (Continued)

20. ABSTRACT (Continued)

is about 2 mm. Impact fusion is feasible because of the coincidence that a bullet with all dimensions roughly 2 mm has the required mass.

DD FORM 1473 (BACK)
1 JAN 73
EDITION OF 1 NOV 66 IS OBSOLETE

UNCLASSIFIED

SECURITY CLASSIFICATION OF THIS PAGE (When Data Entered)

CONTENTS

INTRODUCTION	.	.	.	.	.	.	.	1
I BASIC RAIL GUN EQUATIONS	.	.	.	.	.	.	.	2
II EFFICIENCY	.	.	.	.	.	.	.	4
APPENDIX	.	.	.	.	.	.	.	8
DISTRIBUTION LIST	.	.	.	.	.	.	.	10

ACCESSION for	
NTIS	White Section ☒
DDC	Buff Section ☐
UNANNOUNCED	☐
JUSTIFICATION _____	
BY _____	
DISTRIBUTION/AVAILABILITY CODES	
Dist. AVAIL. and/or SPECIAL	
A	

INTRODUCTION

The rail gun offers an attractive alternative to the traveling wave rifle for the magnetic acceleration of macroscopic (0.05 g) bullets for impact fusion. For power generation it is essential for the rail gun to be energy efficient. In this paper we review the basic rail gun equations and indicate how energy efficiency can be designed in. We set as our preliminary goal the delivery of $E = 1$ megajoule in $dt = 10$ nanoseconds, with a specific energy of 20 MJ/g (i.e. a bullet mass of 0.05 g); these values are taken from the requirements being considered for heavy-ion fusion. Using these numbers, we can solve immediately for the final particle velocity u_f from $E = 1/2 mu_f^2$ to get $u_f = 200$ km/sec. For a delivery time of 10 nanoseconds, this velocity implies that the projectile length is about 2 mm. Impact fusion is feasible because of the coincidence that a bullet with all dimensions roughly 2 mm has the required mass.

I BASIC RAIL GUN EQUATIONS

We begin by reviewing the basic equations which have been derived by J.P. Barber and others. We shall derive these equations in the simplest possible form, in order to emphasize the scaling laws and the physics contained in them. The power delivered by a current I and voltage V , ignoring losses, is:

$$P = IV = d/dt(LI^2/2) + Fu$$

where L is the inductance, F is the force on the "armature" (i.e. the bullet), and u is the bullet velocity. Setting $V = d/dt(LI)$ and simplifying, we get the basic rail gun equation:

$$F = 1/2 L'I^2$$

where L' is the inductance per unit length, and is very close to $L' = 0.6$ microhenries/meter for typical rail gun geometries. For simplicity we shall now assume constant acceleration, i.e. constant current I . The work done on the bullet is $E = Fz = LI^2/2$ where $L = L'z$. Note that the work done on the bullet is equal to the energy stored in the magnetic field of the rails; this inductive energy can be recovered, in principle. Note also that for fixed E and L' the length of the rail gun " z " is proportional to I^{-2} . The required voltage can be calculated from

$V = d(\text{flux})/dt = IL'u$. The values for the current, maximum voltage, and acceleration time t for two lengths of rail-gun are given in the table below:

length z	=	100 meters	1 km
current	=	180 kA	60 kA
maximum voltage	=	23 kV + IR	7 kV + IR
time	=	0.001 sec	0.01 sec

The IR term in the voltage refers to the drop from resistive losses, and is discussed below. The required current can be supplied by capacitors or by high-voltage homopolar generators.

II EFFICIENCY

For application to impact fusion, it is essential to keep the resistive losses to a minimum. To the extent that the resistances in the rail gun are independent of velocity u , the most difficult regime is the low velocity one where the power being transferred into bullet kinetic energy $P = Fu$ is low. On the other hand, designs which are inefficient at low velocities may be considerably more efficient at high velocities, for the same reason.

The energy lost to resistive heating of the bullet or driving plasma is $Q = I^2 R t = 2ERt/L'z = 4ER/L'u_f$. The "inefficiency factor" for the bullet $Q/E = 4R/L'u_f$ is independent of accelerator length, and depends only on the final velocity to be achieved, u_f . The resistance of a copper bullet with dimensions of 2 mm will be about 10^{-5} ohm; although resistive loss is not a problem with the bullet, the copper may be heated beyond its melting point. The resistance of a driving plasma can be calculated from Spitzer's formula, and is approximately $\rho = 65 \ln(H)/T^{3/2}$ where H depends on the temperature and density; $\ln(H) = 3$ for the densities and temperatures of interest. (Black body emission alone will prevent the temperature from rising above 10^4 K). Substituting values, and assuming that the plasma occupies a 2 mm cube, the resistance of the plasma is $R = 3 \times 10^{-3}$ ohm, and for the plasma $Q/E = 30R = 0.1$, an acceptable value. The resistive voltage drop across the plasma will be $V = IR = (60kA)(0.003) = 180$ volts.

Resistive loss in the rails is a more serious problem, especially for the longer rail guns. The DC resistance for two 1-km rails with a cross-section of 2 mm x 2 mm is $R_{DC} = 8.5$ ohms. When the bullet is at a position z the resistance is $R_{DC}(z/z_m)$ if skin-depth effects are ignored (the true resistance will be greater). The energy lost to resistive heating in the rails during constant acceleration a is

$$Q = \int I^2 R dt = \frac{I^2 R_{DC}}{E_m} \int z dt = \frac{I^2 R_{DC} a}{2 E_m} \int t^2 dt = \frac{I^2 R_{DC} t}{3}$$

From the above result, we can define an average or effective resistance $R = R_{DC}/3 = 2.8$ ohms. We find for the rails, $Q/E = 30R = 85$, and an efficiency $1/(Q + E) = 1.2\%$. One cannot arbitrarily reduce the resistance by increasing the rail cross-section, for to do so reduces L' . A smaller L' implies a smaller force on the bullet, and hence a longer rail gun to achieve the same terminal velocity.

To improve the efficiency, it is necessary to divide the rail into segments, with current flowing only in the segment carrying the bullet. A schematic diagram is shown in the figure:




Fig. 1

Schematic Diagram of a Segmented Rail with
Current Flowing only in the Segment Carrying the Bullet

The current behind the bullet will penetrate to an average depth given by

$$s = \sqrt{\frac{\rho \Delta t}{\mu_0}}$$

where Δt is the time since passage of the bullet, ρ is the resistivity, and μ_0 is the permittivity ($= 1.3 \times 10^{-6}$ in MKS units, for non-magnetic materials). For a large number of segments N , we can assume that the skin depth s is less than the thickness of the rails, and derive the following formula (see Appendix) for the effective resistance of the segmented system:

$$R = \frac{Q}{I^2 t} = \frac{8l}{3h} \sqrt{\frac{\rho \mu_0}{tN}}$$

For $s = 1000$ meters, $\rho = 1.7 \times 10^{-8}$ ohm-meters (Cu), and the height of the rails $h = 2$ mm, this gives $R = 2/\sqrt{N}$ ohms. Thus for N segments, we have

$Q/E = 65/\sqrt{N}$. For $N = 1000$, the efficiency $\epsilon = E/(Q + E) = 30\%$.

Additional gains are possible by increasing N , the limit looking like a lumped delay line with propagation velocity matching the bullet velocity and pulse length not much longer than the bullet.


For the 1000 segment, 1 km rail gun, the maximum IR voltage drop from the resistance in the rails is $60\text{kA} \times 2/\sqrt{1000}$, = 4 kV, comparable to the back EMF required of 7kV (see the table on page 3).

The segmented rail gun can be fed by power supplies along its length, represented by capacitors in the figure. No switches to close the circuit are shown, because the switching is automatically provided by the bullet. Since the resonance time of the L-C circuit is approximately equal to the transit time of the bullet, it may be possible to use the automatic switching of the bullet to open the circuit at a time of near-zero current flow.

APPENDIX

Effective Resistance of a Rail Gun Segment

Consider one elem dz of segment of length l_1 . Let resistive heating during passage of bullet = dQ . Skin depth = $s(t) = \sqrt{\frac{t\rho}{\mu_0}}$.



$$\frac{dQ}{dz} = \int_0^{t_1} I^2 \frac{dR}{dz} dt = \frac{I^2 \rho}{h} \int \frac{dt}{s} = \frac{I^2 \rho}{h} \sqrt{\frac{\mu_0}{\rho}} \int_0^{t_1} \frac{dt}{\sqrt{t}} = \frac{2I^2}{h} \sqrt{\rho \mu_0 t_1}$$

where h = height of rail.

Now integrate this over segment of length l_1 . Assume velocity u_1 = constant.

$$\Delta Q_1 = \frac{2I^2}{h} \sqrt{\rho \mu_0} \int_0^{l_1} \frac{\sqrt{l_1 - z}}{u_1} dz = \frac{4}{3} \frac{I^2}{h} \sqrt{\frac{\rho \mu_0}{u_1}} l_1^{3/2} = \frac{4}{3} \frac{I^2 l_1}{h} \sqrt{\rho \mu_0 t_1}$$

(a) Suppose lengths are chosen such that $t_1 = t/N$.

$$Q = \sum \Delta Q_1 = \frac{4}{3} \frac{I^2 l}{h} \sqrt{\frac{\rho \mu_0 t}{N}}$$

so

$$R = \frac{4}{3} \frac{l}{h} \sqrt{\frac{\rho \mu_0}{tN}}$$

For 2 rails, double this answer.

(b) Suppose lengths are chosen such that $l_1 = l/N$.

$$Q = \sum \Delta Q_1 = \frac{4}{3} \frac{I^2}{h} \sqrt{\rho \mu_0} \frac{l}{N} \sum \sqrt{t_1}$$

This sum can be done by approximating it with an integral, and the answer is the same as for (a).

DISTRIBUTION LIST

ORGANIZATION	NO. OF COPIES	ORGANIZATION	NO. OF COPIES
Dr. Arden Bement Deputy Under Secretary of Defense for R&AT Room 3E114, The Pentagon Washington, D.C. 20301	2	Dr. Edward A. Frieman Director, Office of Energy Research, U.S.DOE M.S. 6E084 Washington, D.C. 20585	1
Dr. Gregory Canavan Director, Office of Inertial Fusion, U.S. DOE M.S. C404 Washington, D.C. 20545	1	Dr. George Camota OUSDRE (R&AT) Room 3D1067, The Pentagon Washington, D.C. 20301	1
Dr. Robert Clark P.O. Box 1925 Washington, D.C. 20013	1	Dr. Richard L. Garwin IBM, TJ Watson Research Center P.O. Box 218 Yorktown Heights, NY 10598	1
Cmdr. Robert Cronin NFOIO Detachment, Suitland 4301 Suitland Road Washington, D.C. 20390	1	Dr. Raymond P. Gogolewski DARPA 1400 Wilson Boulevard Arlington, VA 22209	1
Defense Documentation Center Cameron Station Alexandria, VA 22314	12	Director National Security Agency Fort Meade, MD 20755 ATTN: Mr. Thomas Handel, A243	1
The Honorable John. M. Deutch Undersecretary, U.S.DOE M.S. 7E054 Washington, D.C. 20585	1	Dr. Robert J. Hermann Assistant Secretary of the Air Force (RD&L) Room 4E856, The Pentagon Washington, D.C. 20330	1
Dr. David D. Elliott SRI International 333 Ravenswood Avenue Menlo Park, CA 94025	1	Dr. Benjamin Huberman Associate Director, OSTP Room 476, Old Executive Office Building Washington, D.C. 20506	1
Director National Security Agency Fort Meade, MD 20755 ATTN: Mr. Richard Foss, A42	2	Mr. Eugene Kopf Principal Deputy Assistant Secretary of the Air Force (RD&L) Room 4E964, The Pentagon Washington, D.C. 20330	1
Dr. Robert Fossum, Director DARPA 1400 Wilson Boulevard Arlington, VA 22209	2	Mr. Ray Leadabrand SRI International 333 Ravenswood Avenue Menlo Park, CA 94025	1

<u>ORGANIZATION</u>	<u>NO. OF COPIES</u>	<u>ORGANIZATION</u>	<u>NO. OF COPIES</u>
Mr. Barry Leven NISC/Code 20 4301 Suitland Road Washington, D.C. 20390	1	Ms. Alma Spring DARPA/Administration 1400 Wilson Boulevard Arlington, VA 22209	1
Dr. Donald M. LeVine SRI International 1611 N. Kent Street Arlington, VA 22209	3	SRI/MP Reports Area G037 333 Ravenswood Avenue Menlo Park, CA 94025 ATTN: D. Leitner	2
Dr. Harold W. Lewis Department of Physics University of California Santa Barbara, CA 93106	1	Robert Weinraub Energy Research Advisory Board Van Guard Building, Room 548 Washington, D.C. 20585	1
Director National Security Agency Fort Meade, MD 20755 ATTN: Mr. Robert Madden, R/SA	2		
Mr. John Mason DARPA 1400 Wilson Boulevard Arlington, VA 22209	1		
Dr. Richard A. Muller 2831 Garber Street Berkeley, CA 94705	1		
The Honorable William Perry Under Secretary of Defense (R&E) Office of the Secretary of Defense Room 3E1006, The Pentagon Washington, D.C. 20301	1		
Dr. Burton Richter Stanford Linear Accelerator Center P.O. Box 4349 Stanford, CA 94305	1		
Dr. Eugene Ruane P.O. Box 1925 Washington, D.C. 20013	2		
Dr. Joel A. Snow Senior Technical Advisor Office of Energy Research, U.S. DOE, M.S. E084 Washington, D.C. 20585	1		