

NOT FOUND
J V GP

REED-SOLOMON ENCODER/DECODER

APPENDICES TO
FINAL ENGINEERING REPORT

FEBRUARY 9, 1976

NADC
Not in DTIC
Tech. Info.

Prepared under Contract N62269-75-C-0503

DATA ITEM A003

for DTIC QUALITY INSPECTED 3

DISTRIBUTION STATEMENT A
Approved for public release;
Distribution Unlimited

Department of the Navy
Naval Air Development Center

by

ITT Avionics Division
500 Washington Avenue
Nutley, N.J. 01110

8500276-1

REED-SOLOMON ENCODER/DECODER

APPENDICES TO
FINAL ENGINEERING REPORT

FEBRUARY 9, 1976

Prepared under Contract N62269-75-C-0503

DATA ITEM A003

for

Department of the Navy
Naval Air Development Center

by

ITT Avionics Division
500 Washington Avenue
Nutley, N.J. 07110

DWG QUALITY INSPECTED 3

19970603 020

SECURITY CLASSIFICATION OF THIS PAGE (When Data Entered)

DD FORM 1473 EDITION OF 1 NOV 65 IS OBSOLETE

SECURITY CLASSIFICATION OF THIS PAGE (When Data Entered)

20. ABSTRACT

ITT Avionics has built and successfully tested a RSED laboratory breadboard that was funded under contract N62269-75-C-0503 (Naval Air Development Center). A summary of the engineering tests is listed below.

Encoding Time	<150 microseconds
Round Trip Timing Detection	< 20 microseconds
Decode Time	Decode time is dependent on Errata. Refer to section 5 of report number D11801 for decode times.

APPENDIX A

RSED SPECIFICATIONS AND ENGINEERING DRAWINGS

Appendix A contains the specifications and engineering drawings generated under contract N62269-75-C-0503 (Reed-Solomon Encoder/Decoder).

<u>Specifications</u>	<u>Document Number</u>
Reed-Solomon Glossary of Notation	RS-3
Reed-Solomon Hardware	
Functional Specification	RS-9
Reed-Solomon Software Algorithms	RS-10
Requirements for RSED MicroProcessor Program Documentation	RS-14
Specification for RSED MicroProcessor (Breadboard Version)	RS-16

<u>*DRAWINGS</u>	<u>DWG. NUMBER</u>	<u>NUMBER OF SHEETS</u>
RS MCU/CPE	2618933	3
RS Memory	2618934	4
RS Encoder-Syndrome Generator	2618936	5
RS Data Steering	2618939	3
RSED Input/Output Buffer	2619235	4
RSED Control	2619236	3
RSED User Panel	2619237	13

*Drawings will be supplied as data item A008 under contract N62269-75-C-0503.

REED-SOLOMON GLOSSARY
OF NOTATION

SPECIFICATION NUMBER RS-3

REED-SOLOMON GLOSSARY OF NOTATION

$$C(x) = \text{Code Word Polynomial} = \sum_{i=0}^{30} C_i X^i$$

$$C_i = \text{Encoder Character in } i^{\text{th}} \text{ position}$$

$$C_{30} \rightarrow C_{16} = C_{30} \text{ First Transmitter Character}$$

$$C_{15} \rightarrow C_0 = \text{Parity Check Character}$$

$$r'(x) = \text{Received Code Word with Erasure indications}$$

$$r(x) = \text{Received Code Word (Same format as } c(x) \text{)} = \sum_{i=0}^{30} r_i X^i$$

$$S_X = \text{Syndrome Polynomial} = \sum_{k=1}^{16} S_k X^k$$

Define $S_0 \equiv 1$

$$S_k = k^{\text{th}} \text{ syndrome} = r(x) \big|_{x=\alpha^k}$$

$$\alpha = \text{Primitive Generator of GF (32)}$$

$$\alpha^i \quad i=0 \rightarrow 30 = \quad 31 \text{ Non-Zero Elements of GF (32)}$$

Represented by 5 bits.

$$B_{EL} = \text{Erasure Location} \quad B_{EL} = \alpha^l$$

$$E_l = \text{Erasure Location Numbers} \\ l = 1 \rightarrow s \quad \text{if } r_m = \text{erasure, } E_e = m$$

$$s = \text{Number of erasures}$$

$$B_{EL}^{-1} = (\alpha^{31-EL}) \text{ Roots of Erasure Location Polynomial, } B_{E_i} = \alpha^{E_i}$$

$$\sigma_E(x) = \text{Erasures Location Polynomial} \\ \sigma_E(x) = \sum_{i=0}^s \sigma_{E_i} x^i = \prod_{l=1}^s (1 + B_{EL} x)$$

$$T'(x) = \text{Forney's T Polynomial} \\ T'(x) = (1 + S(x)) \sigma_E(x) = \sum_{m=0}^{\infty} T'_m x^m$$

$$T_j = \text{Modified Syndromes} \\ T_j = T'_{s+j} \\ T_j = \sum_{i=0}^s S_{s+j-i} \sigma_{E_i}$$

$$\sigma_e(x) = \text{Error Location Polynomial}$$

$$\sigma_e(x) = \sum_{i=0}^t \sigma_{ei} x^i$$

$$\beta_{ei}^{-1} = \text{Roots of Error Location Polynomial}$$

$$\beta_{ei} = \alpha^{ei}$$

$$e_{ii} = \text{Error Location Number } i = 1 - t$$

if $r_n = \text{error}$, then $e_i = n$

$$\sigma(x) = \text{Errata Location Polynomial}$$

$$\sigma(x) = \sum_{i=0}^{s+t} \sigma_i x^i$$

$$= \sigma_e(x) \sigma_E(x)$$

where

$$\sigma_i = \sum_{m+n=i} \sigma_{Em} \sigma_{En}$$

$$\begin{aligned} Z(x) &= \text{Errata Evaluator Polynomial} \\ Z(x) &= \sum_{i=0}^{s+t} \gamma_i X^i \equiv \sum_{i=0}^A \gamma_i X^i \quad \begin{array}{l} A \leq s \\ \text{see note} \end{array} \end{aligned}$$

$$Z(x) = (1 + S(x)) O(x) \quad \text{Mod } X^{s+t}$$

$$\gamma_i = \sum_{\forall n+k=i} \sigma_n S_k \equiv \sum_{\forall k+l+m=i} \sigma_{El} \sigma_{em} S_k$$

(Note: it is possible for $\gamma_i = 0$ for $i \geq A$, $A \leq s+t$)

$$\begin{aligned} \tilde{Z}(x) &= \text{Modified Errata Evaluator Polynomial} \\ \tilde{Z}(x) &= \sum_{i=s+t-A}^{s+t} \tilde{\gamma}_i X^i \equiv X^{s+t} Z\left(\frac{1}{x}\right) \\ \tilde{\gamma}_i &= \gamma_{s+t-i} \end{aligned}$$

B_i $=$ Inverse Roots of $\sigma_{E(X)}$ and $\sigma_{e(x)}$

$$i = (All B_{En}, B_{em})$$

 C_i' $=$

Errata Value for Location i

$$C_i' = \frac{\tilde{Z}(B_i)}{B_i \prod_{j \neq i} (\beta_i + \beta_j)}$$

REED-SOLOMON HARDWARE
FUNCTIONAL SPECIFICATION

SPECIFICATION NUMBER RS-9

TABLE OF CONTENTS

		PAGE NO.
1.0	Galois Field - GF (32)	1
2.0	Encoder Specification	4
3.0	Syndrome Generator	8
4.0	Erase Location Process	11
5.0	Error Correction Process	12
6.0	Radio Relay Process	13
7.0	Maximum Likelihood RTT Decoder	14
8.0	Encoding of (16, 4) code	15
9.0	Decoding of (16, 4) code	16

TABLES

1.	Power to Code, Code to Power, Conversion Table	3
2.	h Constants for Encoder	7

1.0

Galois Field - GF(32)

The field consists of 32 symbols represented by 5 binary bits. There are 31 non-zero symbols and 00000. Each field element is the anti-log of the field elements expressed as the integer powers of a base symbol called α . The anti-log representation will be called the code form of a symbol and the log representation will be called the power form of the symbol. The non-zero elements are shown in Table 1:

For example:

$$\log_{\alpha} (01000) = 1$$

$$\begin{array}{c} \circ \\ \circ \circ \end{array} 01000 = \alpha^1 = \alpha$$

$$\text{and anti-log}(1) = 01000$$

$$\log_{\alpha} (11111) = 15$$

$$\begin{array}{c} \circ \\ \circ \circ \end{array} 11111 = \alpha^{15}$$

$$\text{anti-log}(15) = 11111$$

$$\log_{\alpha} (10000) = 0$$

$$\begin{array}{c} \circ \\ \circ \circ \end{array} 10000 = \alpha^0$$

$$\text{By Definition } \alpha^{31} = \alpha^0 = 10000$$

1.1

Additions in GF(32) — $A + B = C$

Modulo 2 (XOR) bit by bit

$$\text{i.e. } A_4, A_3, A_2, A_1, A_0 = A \quad A_i \in (0, 1)$$

$$B_4, B_3, B_2, B_1, B_0 = B$$

$$C = C_4, C_3, C_2, C_1, C_0$$

where

$$C_i = A_i + B_i$$

1.2

Multiplication in GF (32) — $A (B) = C$

$$C = \text{Anti-log} \left((\log_{\alpha} A + \log_{\alpha} B) \text{ Mod } 31 \right)$$

$$\text{i.e. } \alpha^{15} (\alpha^{17}) = \alpha^{32 \text{ Mod } 31} = \alpha^1 = \alpha$$

Multiplication look up table can be provided in code form as a

1024 X 5 Table.

GALOIS FIELD TABLE

POWER FORM α^c	CODE FORM			CODE FORM			POWER FORM α^c
	BINARY	DEC	OCT	BINARY	DEC	OCT	
0	⁴³²¹⁰ 00001	1	1				
1	00010	2	2	00001	1	1	0
2	00100	4	4	00010	2	2	1
3	01000	8	10	00011	3	3	18
4	10000	16	20	00100	4	4	2
5	00101	5	5	00101	5	5	5
6	01010	10	12	00110	6	6	19
7	10100	20	24	00111	7	7	11
8	01101	13	15	01000	8	10	3
9	11010	26	32	01001	9	11	29
10	10001	17	21	01010	10	12	6
11	00111	7	7	01011	11	13	27
12	01110	14	16	01100	12	14	20
13	11100	28	34	01101	13	15	8
14	11101	29	35	01110	14	16	12
15	11111	31	37	01111	15	17	23
16	11011	27	33	10000	16	20	4
17	10011	19	23	10001	17	21	10
18	00011	3	3	10010	18	22	30
19	00110	6	6	10011	19	23	17
20	01100	12	14	10100	20	24	7
21	11000	24	30	10101	21	25	22
22	10101	21	25	10110	22	26	28
23	01111	15	17	10111	23	27	26
24	11110	30	36	11000	24	30	21
25	11001	25	31	11001	25	31	25
26	10111	23	27	11010	26	32	9
27	01011	11	13	11011	27	33	16
28	10110	22	26	11100	28	34	13
29	01001	9	11	11101	29	35	14
30	10010	18	22	11110	30	36	24
31	00001	1	1	11111	31	37	15

2.0 Encoder Specification

2.1 Input - 15 five bit data characters (in code form) denoted by m_0 through m_{14}

Format - $(m_{14}, \dots, m_0)$

2.2 Output - 31 five bit transmission characters, composed of the 15 original input characters and 16 computed (by Galois field arithmetic) characters denoted by $C_0 - C_{30}$

Format - $(C_{30}, \dots, C_0)$

The input characters are $C_{30} - C_{16}$ corresponding to $m_{14} - m_0$.

The computed characters are $C_{15} - C_0$ corresponding to $P_{15} - P_0$, therefore, the output format is $(m_{14}, \dots, m_0, P_{15}, \dots, P_0)$.

2.3 Process - P_i 's or C_i 's ($i = 15 - 0$) are computed according by the

following procedure: Fifteen constants (5 bits) are denoted by $h_0 - h_{14}$

(See Table 2). The recursion equation for C_j is given by

$$C_j = \sum_{i=0}^{14} h_i C_{j+15-i} \quad \text{for } j = 0 - 15$$

where $a \cdot b =$ Galois field multiplication

$a + b =$ Galois field addition

For Example, $P_{15} = C_{15}$ is

$$P_{15} = h_0 C_{30} + h_1 C_{29} + \cdot \cdot + h_{14} C_{16}$$

or

$$P_{15} = h_0 m_{14} + h_1 m_{13} + \cdot \cdot + h_{14} m_0$$

and

$$P_{14} = h_0 C_{29} + h_1 C_{28} + \cdot \cdot + h_{14} C_{15}$$

or


$$P_{14} = h_0 m_{13} + h_1 m_{12} + \cdot \cdot + h_{14} P_{15}$$

etc.


For additional clarity consider the input data $m_0 - m_{14}$ placed in an array $X_0 - X_{14}$, and the constants $h_0 - h_{14}$ placed in an array $Y_{14} - Y_0$ as shown.

ORIGINAL ARRAYS


X ARRAY



Y ARRAY



Product
ARRAY




$$\oplus \sum x_i y_i = P_{15}$$


SECOND Computation For
 $x_i = x_{i-1}$ $x_0 = P_{15}$

P_{14}


X ARRAY



Y ARRAY



Product
ARRAY



$$\sum x_i y_i = P_{14}$$

ETC. For $P_{13} - P_0$

Table 2./ h Constants

h	POWER FORM <i>2ⁱ</i> <i>i</i>	CODE WORD		
		OCTAL	BINARY	DECIMAL
		<i>0 1 2 3 4 5 6 7</i>		
h_0	19	6	00110	6
h_1	25	31	11001	25
h_2	3	10	01000	8
h_3	21	30	11000	24
h_4	6	12	01010	10
h_5	27	13	01011	11
h_6	9	32	11010	26
h_7	9	32	11010	26
h_8	16	33	11011	27
h_9	30	22	10010	18
h_{10}	0	1	00001	1
h_{11}	24	36	11110	30
h_{12}	22	25	10101	21
h_{13}	18	3	00011	3
h_{14}	23	17	01111	15
h_{15}	0	1	00001	1

3.0 Syndrome Generator

3.1 Input - 31 five bit characters (in code form) which are the received data with any arbitrary characters substituted for erasures.

Format - $(r_{30}, \dots, r_0)$

This represents the coefficient of the polynomial $r(x)$ in code form.

$$r(x) = \sum_{i=0}^{30} r_i X^i$$

3.2 Output - 16 five bit characters called Syndromes, $S_1 - S_{16}$ (in code form).

Format - $(S_1, \dots, S_{16})$

3.3 Process

By Definition

$$S_i = r(x) \big|_{x=\alpha^i}$$

OR

$$S_1 = r_{30} \alpha^{30} + r_{29} \alpha^{29} + \dots + r_1 \alpha + r_0$$

$$S_i = r_{30} (\alpha^i)^{30} + r_{29} (\alpha^i)^{29} + \dots + r_1 \alpha^i + r_0$$

$$S_{16} = r_{30} (\alpha^{16})^{30} + \dots + r_1 \alpha^{16} + r_0$$

Each S_i can be computed sequentially by factoring the equation.

$$S_i = r(x) \int_{x=\alpha^i} = ((r_{30} \alpha^i + r_{29}) \alpha^i) + r_{28} \alpha^i + \dots$$

Let $S_i(j)$ be the j^{th} partial product of S_i

Where

$$S_i(j) = \alpha^i S_i(j-1) + r_{30-j} \text{ for } j=0-30$$

and

$$S_i(-1) \equiv 0$$

Therefore:

$$S_i = S_i(30)$$

i.e. :

$$S_i(0) = \alpha^i \cdot 0 + r_{30} = r_{30}$$

$$S_i(1) = \alpha^i S_i(0) + r_{29} = \alpha^i r_{30} + r_{29}$$

$$S_i(29) = \alpha^i S_i(28) + r_1$$

$$S_i(30) = \alpha^i S_i(29) + r_0 = (\alpha^i)^2 S_i(28) + \alpha^i r_1 + r_0$$

Compute S_i by first encoding $r_{30} - r_{16}$ as in encoder get $P_{15} - P_0$.

$$\text{Compute } S(X) = \sum_{i=0}^{15} s_i X^i$$

$$\text{Where } s_i = P_i + r_i \quad i = 0 - 15$$

and then compute

$$S_i = S(X) \Big|_{X=\alpha^i} \quad \text{as in Option 1}$$

This requires only computing $S_i(15)$

$$\text{where } S_i(j) = \alpha^i S_i(j-1) + a_{15-j}$$

$$S_{i(15)} = (\alpha^i)^2 S_{i(14)} + \alpha^i s_1 + s_0$$

$\alpha^1 - \alpha^{16}$ are given in code form by power table $\rightarrow$ code.

NOTE: Code 00000 = $\emptyset$ has no power conversion

$$\emptyset(\alpha^i) = \emptyset_j \quad \emptyset + \alpha^i = \alpha^i$$

4.0 Erasure Location Process

4.1 Input - 31 six bit characters (code form)

Format - $(r_{30}, r_{29}, \dots, r_1, r_0)$

$r_i = \text{XXXXX0 data decision}$

$r_i = \text{XXXXX1 erasure decision}$

4.2 Output - 0 - 16 five bit numbers

Format $(E_1, E_2, \dots, E_s)$

4.3 Process - E_1 is the position number of an erasure.

If r_i, r_j, r_k are erasures

then $E_1 = i$

$E_2 = j$

$E_3 = k$

This leaves code 11111 to indicate end of list.

NOTE: If more than 16 erasures are detected word is not decoded and
FLAG is to be provided.

5.0 Error Correction Process

5.1 Input - 15 five bit character (code form) from the decoder.

Format - $(c'_{30}, \dots, c'_{16})$

These are data correction characters where $c'_i = \emptyset$ if character correct.

5.2 Output - 15 five bit corrected data characters (code form)

Format - $(d_{30}, \dots, d_{16})$

5.3 Process - The d_i 's are computed by $d_i = r_i + c'_i$

where r_j ($j = 30$ to 16) are the received data characters

NOTE: See Radio Relay Process if Flag for radio relay is set.

6.0 Radio Relay Process

6.1 Function

At start of time slot, the communication processor will flag the signal processor that the incoming message is to be relayed. This must set an indicator.

6.2 Input

45 five bit corrected data characters (code form)

Format: $(d_{14}, \dots, d_0)$ $(d_{14}, \dots, d_0)$ $(d_{14}, \dots, d_0)$
 First Word Word 2 Word 3

6.3 Output

One of the bits of the three words (TBD) is set to 1 and the words are sent to the encoder.

7.0 Maximum Likelihood RTT Decoder

7.1 Input - 16 six bit characters (code form)

Format: - $(r_{15}, r_{14}, \dots, r_1, r_0)$

$r_i = \text{XXXXX}(0)$ data decision

$r_i = \text{XXXXX}(1)$ erasure

7.2 Output - 1 bit - Yes or No

i.e., Match or No Match

7.3 Process - Stored Reference - $(A_{15}, A_{14}, \dots, A_1, A_0)$

16 five bit number

Compare r_i with A_i , Result = $B_{(i)}$ a number

If r_i , an erasure, $B_{(i)} = 1$

If r_i , a data decision

Compare first 5 bits of r_i with A_i

If $r_i = A_i$, $B_{(i)} = 2$

If $r_i \neq A_i$, $B_{(i)} = 0$

Compute $\sum_{i=0}^{16} B_{(i)}$ and compare to threshold $T = 20$

If $\sum_{i=0}^{15} B_{(i)} \geq 20$; output = Match

If $\sum_{i=0}^{15} B_{(i)} < 20$; output = Mismatch

8.0 Encoding of $(16, 4)$ code.

8.1 Input

Four 5 bit data characters

Format

$(m_3, \dots, m_0)$

8.2 Output

Sixteen 5 bit transmission characters.

$(c_{15}, \dots, c_8, c_7, \dots, c_0)$

which are:

$(m_3, \dots, m_0, P_{15}, \dots, P_4)$

8.3 Process

Encode m_0, m_1, m_2, m_3 , as a 15 character word by generating

$(m_{14}, \dots, m_4, \dots, m_0)$

where $m_4, \dots, m_{14} \equiv \emptyset$

Compute $P_4 - P_{15}$, the first twelve parity check characters as in encoder specification.

9.0 Decoding 16, 4 code word.

9.1 Input

Sixteen 6 bit characters from signal processor denoted by, r_i'

with erasures = XXXXX1

$$(r_{15}', \dots, r_0') \quad 1)$$

Convert to 31 character format

$$(r_{30}', \dots, r_{15}', \dots, r_0') \quad 2)$$

$$\begin{aligned} \text{where} \quad r_i &= r_{i-4}' & i &= 4, \dots, 19 \\ r_i &= \phi & i &= 20 - 31 \\ r_i &= \text{erasure} & i &= 0 - 3 \end{aligned}$$

9.2 Output

9.2.1 Erasure Locations: $(E_1, \dots, E_s)$ as in Erasure Location

Process for 2)

$$\text{i.e., } E_i = i - 1 \quad i = 1-8, \text{ and others.}$$

9.2.2 Syndromes: $S_1 - S_{16}$ as in Syndrome Generator for 2).

9.3 Error Correction: Same as (31, 15) word using 2). Output only

$$d_{16} - d_{19}.$$

9.4 Relay Mode - Encode $d_{16} - d_{19}$ as $m_0 - m_3$ in encoder.

APPENDIX A

REED-SOLOMON SOFTWARE ALGORITHM

SPECIFICATION NUMBER RS-10

TABLE OF CONTENTS

			<u>PAGE NO.</u>
1.0 Erasure Polynomial Generator	$\sigma_E(x)$	APGEN	1
2.0 Modified Syndromes	T_j	MSYNG	2
3.0 Error Location Polynomial	$\sigma_e(x)$	EPGEN	4
4.0 Error Locations Inverse Roots of	$\beta_{e_i} \sigma_e(x)^{-1}$	EPVAL	10
5.0 Modified Errata Evaluator Polynomial	$\tilde{Z}(x)$	RPGEN	11
6.0 Errata Value Calculation	C'_i	RPVAL	13

1.0 Erasure Polynomial Generator (APGEN)

1.1 Input

$E_1, 1 = 1, \dots, s$ Erasure Location Numbers

(If $r_K \equiv$ erasure, $E_1 = K, \forall K$)

1.2 Output: $s+1$ coef. $\sigma_{E_i} \quad i = 0, \dots, s$

$\sigma_{E_0} \equiv 1$, Coef. of Erasure Polynomial

$$\begin{aligned}\sigma_E(X) &= \sum_{i=0}^s \sigma_{E_i} X^i = \prod_{l=1}^s (1 + \alpha^{E_l} X) \\ &= \prod_{l=1}^s (1 + \beta_{E_l} X) ;\end{aligned}$$

where $\beta_{E_1} =$ Inverse roots of $\sigma_E(X) = \alpha^{E_1}$

1.3 Process:

In general

$$\begin{aligned}\sigma_{E_0} &= 1 \\ \sigma_{E_1} &= \sum_{\forall E_1} \beta_{E_1} \\ \sigma_{E_2} &= \sum_{\substack{\forall E_1, E_j, i \neq j}} \beta_{E_1} \beta_{E_j} \\ \sigma_{E_{s-1}} &= \sum_{\forall E_j} \left(\prod_{i=1}^s \beta_{E_i} / \beta_{E_j} \right)\end{aligned}$$

Simplify notation $\beta_i \equiv \beta_{E_i}$

can compute σ_{E_i} by the following iterative process.

Define $A_i(s) = \sigma_{E_i}$ $i = 0, \dots, s$

where $A_i(j)$ = the j^{th} value of A_i iterate till $j = s$

$$A_i(j) = A_{i-1}(j-1) \beta_j + A_i(j-1) ; i < j$$

$$A_i(i) = A_{i-1}(i-1) \beta_i + 0 ; j=i$$

$$A_i(j) \equiv 0 ; i > j$$

$$A_0(j) = A_0(j-1) \equiv 1 ; \forall j$$

First iteration $j = 1$

$$A_0(1) = 1$$

$$A_1(1) = \beta_1$$

$j = 2$

$$A_0(2) = 1$$

$$A_1(2) = A_0(1) \beta_2 + A_1(1) = \beta_2 + \beta_1$$

$$A_2(2) = A_1(1) \beta_2 + A_2(1) = \beta_1 \beta_2 \text{ etc.}$$

2.0 Modified Syndromes T_j MSYNG

2.1 Inputs

$$S_i \quad i = 1, \dots, 16$$

$$\sigma_{E_i} \quad i = 0, \dots, s \quad \sigma_{E_0} \equiv 1$$

Simplify notation $\sigma_{E_i} = \sigma_i$

2.2 Output

$$T_j \quad j = 1, \dots, (16-s)$$

2.3 Process:

$$T_j = \sum_{i=0}^j S_{s+j-i} \sigma_i$$

i.e., $T_1 = S_{s+1} + \sigma_1 S_s + \sigma_2 S_{s-1} + \dots + \sigma_s S_1$

$$T_2 = S_{s+2} + \sigma_1 S_{s+1} + \sigma_2 S_s + \dots + \sigma_s S_2$$

$$T_{16-s} = S_{16} + \sigma_1 S_{15} + \sigma_2 S_{14} + \dots + \sigma_s S_{16-s}$$

Array: $\sigma \quad y(1) \quad y(2)$

X_0	σ_0	$Y_0(1)$	S_{s+1}	$Y_0(2)$	S_{s+2}	Push down Stack
X_1	σ_1	$Y_1(1)$	S_s	$Y_1(2)$	S_{s+1}	
X_2	σ_2	$Y_2(1)$				
$\vdots$	$\vdots$	$\vdots$	$\vdots$	$\vdots$		
$\vdots$	$\vdots$	$\vdots$	$\vdots$	$\vdots$		
X_s	σ_s	$Y_s(1)$	S_1	$Y_s(2)$	S_2	

$$T_1 = \sum_{i=0}^s X_i Y_i(1)$$

$$T_2 = \sum_{i=0}^s X_i Y_i(2)$$

2.4

Modified Syndromes Berlekamp Notation

In general case, define T_j^1 as the coefficient of X^j in the equation.

$$(1 + S(X)) \sigma_E(X) = T^1(X) = \sum_{j=0}^{s+16} T_j^1 X^j$$

$$S(X) = \sum_{i=1}^{16} S_i X^i$$

$$\sigma_E(X) = \sum_{i=0}^s \sigma_{E_i} X^i, \quad s = \# \text{ of erasures}$$

Then T_i 's on previous page are $T_i = T_{s+i}^1$

3.0

Error Location Polynomial

 $\sigma_e(X)$ EPGEN

3.1

Input

Modified Syndromes T_j (5 bits)

$$j = 1, \dots, (16-s)$$

Where s = number of Erasures

If $s = 0$; $T_j = S_j$, $j = 1, \dots, 16$

3.2 Output

$t + 1$ Coefficient of Error Location

Polynomial (5 bits) σ_{e_i} $i = 0, \dots, t$

t = number of errors

where $\sigma_{e_0} \equiv 1$

3.3 Process - Simplify notation $\sigma_{e_i} = \sigma_i$

3.3.1 Option 1 Berlekamp Algorithm

This is iterative Process $K = 0, \dots, (16-s)$

Define values of K^{th} iteration (depends only on $K-1$)

$$\sigma^{(K)}(x) = \sum_{i=0}^n \sigma_i^{(K)} x^i = \text{Error Loc. Polynomial}$$

$\sigma_i^{(K)}$ GF(32) element

$$\tau^{(K)}(x) = \sum_{i=0}^m \tau_i^{(K)}(x)^i = \text{Tau Polynomial}$$

$\tau_i^{(K)} = \text{GF}(32) \text{ element}$

$B(K)$ = Computation Number (Decimal)

$D(K)$ = Computation Number (Decimal)

$\Delta^{(K)}$ = Coefficient index - GF(32) element

0th Iteration

Define $\sigma^{(0)}(x) \equiv 1$

$\tau^{(0)}(x) \equiv 1$

$$D(o) \equiv 0$$

$$B(o) \equiv 0$$

In general

$$\Delta^{(K)} = \sum_{m+n=K+1} T_m \sigma_n^{(K)} = T_{K+1} \sigma_o^{(K)} + T_K \sigma_1^{(K)} + \dots + T_o \sigma_{K+1}^{(K)}$$

Define $T_o \equiv 1$

i.e., $\Delta^{(K)} =$ Coefficient of X^{K+1} in $(1+T(X)) \sigma^{(K)}(X)$

$$T(X) = 1 + \sum_{i=1}^{16-A} T_i X^i$$

$$\sigma^{(K+1)}(X) = \sigma^{(K)}(X) + \Delta^{(K)} \tau^{(K)}(X) X$$

$$\text{or } \sigma_i^{(K+1)} = \sigma_i^{(K)} + \Delta^{(K)} \tau_{i-1}^{(K)} \quad \forall i \leq \text{max degree} \\ (\sigma^{(K)}(X), \tau^{(K)}(X))$$

The value of $D(K+1)$, $B(K+1)$ and $\tau^{(K+1)}(X)$ are computed from the two equations A and B by the rules below.

$$A: D(K+1) = D(K)$$


$$B(K+1) = B(K)$$

$$\tau^{(K+1)}(X) = \tau^{(K)}(X) \text{ or } \tau_i^{(K+1)} = \tau_i^{(K)}$$

B: $D(K+1) = K+1-D(K)$ (decimal arithmetic)

$B(K+1) = 1-B(K)$ (decimal arithmetic)

$$\tau_i^{(K+1)} = \sigma_i^{(K)} \frac{1}{\Delta^{(K)}}$$



Continue until $K = 16-s$ and $\sigma_e(X) = \sigma^{(16-s)}(X)$.

3.3.2 Option 2 Shu Lin Algorithm (Berlekamp Modified)

Iterative process with reliance on earlier results,

th
i.e., u iteration depends on $u-1$, $u-2$, etc..

th
Define values of u iteration, $u = -1, \dots, (16-s)$.

$$\sigma^{(u)}(X) = \sum_{i=0}^n \sigma_i^{(u)} X^i = \text{error location polynomial}$$

d_u = Coef Index GF32 element $\equiv \Delta^{(K)}$

l_u = Computation number.(decimal)

$u - l_u$ = Computation Number. (decimal)

th
-1 iteration

th
0 iteration

Define:

$$\sigma^{(-1)}(X) = 1$$

$$\sigma^{(0)}(X) = 1$$

$$d_{-1} = 1$$

$$d_0 = T$$

$$l_{-1} = 0$$

$$l_0 = 0$$

$$\sigma^{(16-s)}(X) \equiv \sigma_e(X)$$

In general, compute u+1st row according to value of

d_u by (A') or (B') where:

$$d_u = \sum_{\forall m+n=u+1} T_{m,n} \sigma^{(u)} = T_{u+1,0} \sigma^{(u)}_0 + \dots + T_{0,u+1} \sigma^{(u)}_{u+1}$$

$$T_0 = 1$$

A': If $d_u = 0$ (00000)

$$\sigma^{u+1}(X) = \sigma^{(u)}(X)$$

$$l_{u+1} = l_u$$

B': If $d_u \neq 0$ find previous row, ρ , such that $d_\rho \neq 0$

$$\text{and } (\rho - l_\rho) \geq (\tau - l_\tau) \quad \forall \tau < u$$

(or $(\rho - l_\rho)$ is maximum)

$$\text{Then } \sigma^{(u+1)}(X) = \sigma^{(u)}(X) + d_u^{-1} d_\rho^{u-\rho} \sigma^{(\rho)}(X)$$

$$\text{or } \sigma_i^{(u+1)} = \sigma_i^{(u)} + d_u^{-1} d_\rho \sigma_{i-(u-\rho)}^{(\rho)}$$

$$l_{u+1} = \text{Max} [l_u, l_{\rho+u-\rho}]$$

4.0 Inverse Roots of $\sigma_e(X) = \beta_{e_i} \quad i = 1, \dots, t \quad \text{EPVAL}$

4.1 Input

$t + 1$ coefficients of $\sigma_e(X) = \sigma_{e_i} \quad i = 0, \dots, t$

$$\sigma_{e_0} \equiv 1$$

4.2 Output

t distinct inverse roots of $\sigma_e(X)$

If there are less than t roots then decoding is in error and an error will be flagged.

$$\beta_{e_i} \quad i = 1, \dots, t$$

$$\beta_{e_i} = \alpha^{e_i} \quad \text{error in location} \quad r_{e_i}$$

4.3 Process

Compute $\sigma_e(X) \quad X = \alpha^j$

If $\sigma_e(\alpha^j) \equiv \phi, (00000)$

Then $\beta_{e_i}^{-1} = \alpha^j$ and $\beta_{e_i} = \alpha^{31-j}$

$$\sigma_e(\alpha^j) = \sum_{n=0}^t \sigma_{e_n} (\alpha^j)^n$$

can be computed sequentially as S_K

$$\sigma_e(\alpha^j) = ((\sigma_{e_t} \alpha^j + \sigma_{e_{t-1}}) \alpha^j + \sigma_{e_{t-2}}) \alpha^j + \dots$$

5.0 Errata Evaluator Polynomial $\tilde{Z}(X)$ RPGEN

5.1 Input

Sixteen Syndromes $S_1 \dots S_{16}$ S_i

s = coefficients of the Erasure Polynomial $\sigma_{E_0} \dots \sigma_{E_s} \sigma_{E_i}$

t = coefficients of the Error Location Polynomial $\sigma_{e_0} \dots \sigma_{e_t} \sigma_{e_i}$

5.2 Output

Coefficients of $\tilde{\gamma}_i$ (a variable number)

5.3 Process

$$Z(X) = (1 + S(X)) \sigma_E(X) \sigma_e(X) = \sum_{i=0}^{s+t} \gamma_i X^i$$

$$= (1 + S(X)) \sigma_E(X) \sigma_e(X) \bmod Z^{s+t+1}$$

Only the coefficients of $X^0, X^1, X^2, \dots, X^{s+t}$ are required

where s = # of erasures = the degree of $\sigma_E(X)$

t = # of errors = the degree of $\sigma_e(X)$

$$\therefore \gamma_i = \sum \sigma_{E_l} \sigma_{e_m} S_K$$

$$\gamma_0 \equiv 1, \sigma_{e_0} \equiv 1, \sigma_{E_0} \equiv 1$$

for all $K + l + m = i$

Note:

It is possible for $\gamma_i = 0$ for $i > A$, $A < s + t$

$$\therefore Z(X) = \sum_{i=0}^A \gamma_i X^i \quad A \leq s+t$$

$$\text{Now } \tilde{Z}(X) = X^{s+t} Z(1/X) = \sum_{i=s+t-A}^{s+t} \tilde{\gamma}_i X^i$$

$$\text{where } \tilde{\gamma}_i = \gamma_{s+t-i} \quad i = (s+t-A), \dots, (s+t)$$

6.0 Errata Value Calculator (RPVAL)

6.1 Input

sent values β_{E_i}, β_{e_i}

all inverse roots of $\sigma_E(X)$ and $\sigma_e(X)$

where $\beta_{E_i} = \alpha^{E_i}$
 $\beta_{e_i} = \alpha^{e_i}$ } Denotes errata in received
character r_{E_i} and r_{e_i}

Let β_{E_i} and β_{e_i} be denoted by β_i

where $i = E_i$ or e_i

Then $\beta_i = \alpha^i$ $i = (E_i, e_i) = \text{errata location}$

6.2 Output

C'_i = Errata value for location i

$i = 16, \dots, 30$ (all data locations)

6.3 Process

$C'_i = 0$ (00000) $\forall i \neq E_i$ or e_i

$C'_i = \frac{\tilde{Z}(\beta_i)}{\beta_i \prod_{i \neq j} (\beta_i + \beta_j)}$ $\forall i, j = E_i$ or e_i

$$\tilde{Z}(\beta_i) = \sum_{n=s+t-A}^{s+t} \tilde{\gamma}_n(\beta_i)^n$$

can be computed sequentially as in S_k computation

$$\tilde{Z}(\beta_i) = ((\tilde{\gamma}_{s+t}\beta_i + \tilde{\gamma}_{s+t-1})\beta_i + \tilde{\gamma}_{s+t-2})\beta_i \dots$$

Option 2:

$$C'_i = \frac{Z(\beta_i)^{-1}}{\prod_{i \neq j} (1 + \beta_j \beta_i^{-1})}$$

$$\text{where } \beta_i^{-1} = \beta_{e_i}^{-1} = \alpha^{31-e_i}$$

$$\beta_i^{-1} = \beta_{E_i}^{-1} = \alpha^{31-E_i}$$

REQUIREMENTS FOR RSED MICROPROCESSOR

PROGRAM DOCUMENTATION

SPECIFICATION NUMBER RS-14

INDEX

<u>PARAGRAPH</u>		<u>PAGE NO.</u>
1.0	Introduction	1
1.1	Purpose	1
1.2	Scope	1
1.2.1	Microprocessor Program Functional Specification	1
1.2.2	Microprocessor Program Design Specification	1
1.2.3	Microprocessor Program Package	1
2.0	Applicable Documents	2
3.0	Microprocessor Program Documentation	2
3.1	Symbols for Flowcharts and Text	2
3.2	Document Preparation	2
3.2.1	Nomenclature	2
3.2.2	Sections	2
3.2.3	Figures and Tables	3
3.2.3.1	Foldouts	3
3.2.3.2	Titles	3
3.2.3.3	Placement	3
4.0	Microprocessor Program Functional Specification	4
4.1	General Requirements	4
4.2	Detailed Requirements	4
	Section 1 - Scope	4
	Paragraph 1.1 Identification	4
	Paragraph 1.2 Introduction	4
	Section 2 - Applicable Documents	4

INDEX

4.2

Continued

Section 3 - Requirements	4
Paragraph 3.1 Functional Description	4
Paragraph 3.1.1 μ P Interface Block Diagram	5
Paragraph 3.1.2 Equipment Description	5
Paragraph 3.1.3. μ P Input/Output	5
Paragraph 3.1.4 Function Description	6
Appendix A - Mathematical Analysis	6
5.0 Microprocessor Program Design Specification	7
5.1 General Requirements	7
5.2 Detailed Requirements	7
Section 1 - Scope	7
Section 2 - Applicable Documents	7
Section 3 - Requirements	7
Paragraph 3.1 Function Allocation/Description	8
Paragraph 3.2 Microprocessor Program Functional Flow Diagram	8
Paragraph 3.3 Storage & Processing Allocation	8
Paragraph 3.4 Programming Guidelines	8
Section 4 - Detailed Requirements	9
Paragraph 4.N.1 Subprogram Detailed Description	9
Paragraph 4.N.2 Subprogram Flow Diagrams	9
Paragraph 4.N.3 Microprocessor Subprogram Environment	10
Paragraph 4.N.3.1 Tables	10
Paragraph 4.N.3.2 Variables	10
Paragraph 4.N.3.3 Constants	10

INDEX

Paragraph 4.N.3.4	Flags	11
Paragraph 4.N.3.5	Indexes	11
Paragraph 4.N.3.6	Common Data Base Reference	11
Paragraph 4.N.4	Input/Output - Formats	11
Paragraph 4.N.5	Conditions for Initiation	12
Paragraph 4.N.6	Subprogram/System Subroutines	12
Paragraph 4.N.7	Interface Description	12
Section 5 - Common Data Base		12
Paragraph 5.1	Tables	13
Paragraph 5.2	Variables	14
Paragraph 5.3	Constants	15
Paragraph 5.4	Flags	15
Paragraph 5.5	Indexes	15
Paragraph 5.6	Subprogram Reference	16
Paragraph 5.7	Notes	16
Appendix B	Bulky Data	16

1.0 INTRODUCTION

1.1 PURPOSE

This specification establishes a set of requirements for the preparation of digital microprocessor program technical documentation for the RSED. The specification is a modification of NAVORD WS-8506 and has similar technical content.

1.2 SCOPE

The microprocessor program documentation consists of the following items:

1.2.1 MICROPROCESSOR PROGRAM FUNCTIONAL SPECIFICATION (MPFS)

The MPFS describes the functional requirements for the microprocessor program of the RSED. The MPFS describes the function in terms of operational, functional, and mathematical language.

1.2.2 MICROPROCESSOR PROGRAM DESIGN SPECIFICATION (MPDS)

The MPDS contains the design details for the microprocessor program. The MPDS is written in programming terminology and translates the requirements of the Functional Specification into technical programming detail. It is specifically oriented to programming logic and programmer's language. A detailed description of all data items according to their type, purpose, size, range of values and structure is provided together with appropriate cross referencing.

The MPDS presents the results of the programming efforts and provides the verification that the program fulfills the original requirements.

1.2.3 MICROPROCESSOR PROGRAM PACKAGE (MPP)

The MPP consists of the physical microprocessor program in the form of paper tape/punched cards and program listings.

2.0 APPLICABLE DOCUMENTS

American National Standards Institute Inc. X3.5-1970 Flowchart Symbols and Their Usage for Information Processing.

3.0 MICROPROCESSOR PROGRAM DOCUMENTATION

Microprocessor program documentation for the RSED shall be as specified in Sections 4 and 5.

3.1 SYMBOLS FOR FLOWCHARTS AND TEXT

Flowchart symbols and logic symbols for flowcharts and text shall be as specified in the latest American National Standards Institute Document X3.5-1970.

3.2 DOCUMENT PREPARATION

All documents shall be prepared in accordance with the requirements specified in the following paragraphs.

3.2.1 NOMENCLATURE

References to the nomenclature shall be made as follows:

1. Acronyms, elisions, and nicknames shall be spelled with all capital letters, e.g., BAMS, SINS, etc.
2. Names of microprocessor data units shall be written with all capital letters, and numbers if any, e.g., XTRAP, WSFX2, NSLR3, FXWS.
3. All of the words in the titles of program subdivisions, except articles, conjunctions, and prepositions, shall be spelled with capital first letters, e.g., Racetrack and Cloverleaf Plot, Beacon Data Dump, Write Program on Magnetic Tape for Recovery.

3.2.2 SECTIONS

Sections are used primarily to subdivide the text of complex or lengthy documents into logical categories both to aid the preparer in organizing the

3.2.2 Continued

material and to aid the user in locating material. Documents should not be over-sectionalized; the exact number and content of each section shall be determined by the nature and extent of the information presented.

Descriptive section headings shall be used, and the sections shall be arranged in an orderly and logical manner.

The section number shall precede all page numbers, paragraph numbers, and figure and table numbers.

3.2.3 FIGURES AND TABLES

As far as possible, figures and tables should be limited to single sheets.

3.2.3.1 FOLDOUTS

Foldouts shall be avoided except where required for legibility.

3.2.3.2 TITLES

If the figure or table occupies more than one page, each page shall contain the same figure or table number and title, and the title shall be followed by the page number and the total number of pages of the figure or table in parentheses, e.g., (page 1 of 3).

3.2.3.3 PLACEMENT

Figures and tables may be placed on or immediately following the page of text on which the first reference is made to the figure or table. If the first reference is accompanied by an explanation, the figure or table may appear immediately following such an explanation.

If figures and tables are numerous and their locations, as indicated above, would interfere with correct sequencing of paragraphs and cause difficulty in understanding or interpretation, they may be placed in a group following a subsection of text or they may be included in a special section after all text.

4.0 MICROPROCESSOR PROGRAM FUNCTIONAL SPECIFICATION

4.1 GENERAL REQUIREMENTS

The Microprocessor Program Functional Specification (MPFS) shall describe in detail all the operational and functional requirements necessary to design and test the microprocessor program.

4.2 DETAILED REQUIREMENTS

For convenience in describing the minimum essential content, the following paragraphs show a normal format for presentation of the material.

Section 1 - Scope.

This MPFS section shall consist of the following paragraphs:

Paragraph 1.1 - Identification .

This MPFS paragraph shall contain the identification of the microprocessor program.

Paragraph 1.2 - Introduction.

This MPFS paragraph shall contain a general discussion of the RSED system within which the program will operate. It shall show the role assigned to the microprocessor program to delineate the functions it must accomplish.

Section 2 - Applicable Documents.

This MPFS section shall list all applicable documents.

Section 3- Requirements.

This section shall define and specify all functional requirements.

Paragraph 3.1 - Functional Description.

This MPFS paragraph

shall provide a detailed description of the major functions of the microprocessor program and shall describe the functional relationships of the microprocessor program with interfacing equipments. This MPFS paragraph shall include the following:

Paragraph 3.1.1 - Microprocessor Interface Block Diagram.

This MPFS paragraph shall contain a block diagram of the equipment/microprocessor relationships to facilitate presentation of material. The diagram shall show the data flow between the microprocessor and the interfacing RSED hybrid equipment.

Paragraph 3.1.2 - Equipment Descriptions. This paragraph shall contain a description of the requirements imposed on the microprocessor program by each interfacing equipment, the purpose of the equipment, and how it is used with the microprocessor.

Paragraph 3.1.3 - Microprocessor Input/Output. This MPFS paragraph shall provide a description of input data derived from sources external to the microprocessor. It will also describe output data given to interfacing equipment by the microprocessor.

Paragraph 3.1.4 - Function Description. This MPFS paragraph shall contain a subparagraph for each function to be supported by the microprocessor program. The descriptions shall provide a brief statement of purpose for each function, as well as text and mathematical descriptions for each of the functions performed by the microprocessor program.

Appendix A - Mathematical Analysis. This MPFS section may be included as an appendix to the Microprocessor Program Functional Specification. It shall include additional mathematical analysis as required to provide a complete comprehension of the RSED system.

5.0 MICROPROCESSOR PROGRAM DESIGN SPECIFICATION

5.1 GENERAL REQUIREMENTS

The Microprocessor Program Design Specification (MPDS) shall specify the design description of the microprocessor program based upon the functional requirements defined in the Microprocessor Program Functional Specification (Section 4). This MPDS shall specify the programming approach for implementing the microprocessor program and shall define how the functions are to be performed.

5.2 DETAILED REQUIREMENTS

For convenience in describing the minimum essential content, the following MPDS paragraphs show a normal format for presentation of the material.

Section 1 - Scope

This MPDS section shall contain the microprocessor program title and provide a brief summary of the purpose and scope of the specification. It shall also contain a description of the major functions of the computer program.

Section 2 - Applicable Documents

This MPDS section shall list the Microprocessor Program Functional Specification, standards, and other documents which apply to the preparation of this specification.

Section 3 - Requirements

This MPDS section shall contain a comprehensive description of the Microprocessor program design structure and processing. The description shall reflect the translation of the microprocessor system functions defined in the Microprocessor Program Functional Specification to the design of the microprocessor program.

Paragraph 3.1 - Function Allocation/Description

This MPDS paragraph shall identify and describe the allocation of functions and tasks to be performed by the individual microprocessor subprograms.

The identification of tasks shall be derived from the requirements in the Microprocessor Program Functional Specification. A description of the design structure (e.g., modular, through-put, segmented) to be implemented for translating the MPFS functions into subprograms shall be defined. This paragraph shall include a general summary of inputs, outputs, and functions to be performed for each subprogram and common subroutine.

Paragraph 3.2 - Microprocessor Program Functional Flow Diagram

This MPDS paragraph shall show the general system flow of both data and control.

Paragraph 3.3 - Storage and Processing Allocation

This MPDS paragraph shall describe the allocation of memory storage and processing time to subprograms, and the data base. The total memory allocation and processing time for each subprogram and common data base shall be summarized.

Paragraph 3.4 - Programming Guidelines

This MPDS paragraph shall specify the programming guidelines to be observed by the system programmer when producing the microprocessor program. This MPDS paragraph shall name the programming language and its supporting system, i.e., monitor, loader, librarian, debug and utilities, that will be used to produce the microprocessor program. The appropriate users manuals and specifications for the language and system shall be referenced. This MPDS paragraph shall state in concise terms the mnemonic

Paragraph 3.4 (Continued)

labeling conventions to be observed.

Section 4 - Detailed Requirements.

This section shall contain for each subprogram and system subroutine, a paragraph 4.N, which develops and completely defines the subprogram/system subroutine. Each 4.N paragraph will contain subparagraphs as follows:

Paragraph 4.N.1 - Subprogram Detailed Description

This MPDS paragraph shall specify the design of the subprogram in detail.

It shall describe completely the processing requirements of the subprogram.

This paragraph shall contain a textual development of the operations performed by the subprogram and shall describe each section of code as it appears (or will eventually appear) in the subprogram listing. This, in essence, will describe the operations performed at each branch of the subprogram, and the results obtained by following each branch.

During the discussion of subprogram segments, if common system subroutines are used, they shall be identified by their function and mnemonic label with a reference to the paragraph where they are described in detail.

The level of detail for this portion of the MPDS amplifies the information provided in the subprogram flow diagrams described in the following MPDS paragraph 4.N.2. The same subprogram tags specified in the text description shall be shown in the appropriate blocks of the related flow diagrams.

Paragraph 4.N.2 - Subprogram Flow Diagrams

A flowchart shall be included which depicts detailed operations performed by the microprocessor subprogram.

Paragraph 4.N.3 - Microprocessor Subprogram Environment

This MPDS paragraph shall contain a general description of the subprogram environment.

Paragraph 4.N.3.1 - Tables

This MPDS paragraph shall contain the detailed description of each table used only in the subprogram/system subroutine data base. Each table shall be described individually, where the descriptions are presented according to the alphabetically ordered mnemonic table names. The minimum content of the subprogram table descriptions shall be:

- a. Table Name
- b. Purpose and Type
- c. Size and Indexing Procedure
- d. Structure and Bit Layout

Paragraph 4.N.3.2. - Variables

This MPDS paragraph shall contain the detailed description of each variable included in the subprogram/system subroutine data base. Each variable shall be described individually where the descriptions are presented according to the alphabetical ordering of the mnemonic names of the variables. The minimum content of this MPDS paragraph shall be:

- a. Variable Name
- b. Purpose
- c. Structure and Bit Layout

Paragraph 4.N.3.3 - Constants

This MPDS paragraph shall contain the detailed description of each constant included in the subprogram/system subroutine data base. Each constant shall be described individually, where the descriptions are presented according to the alphabetical ordering of the mnemonic names of the flags. The minimum

Paragraph 4.N.3.3 (Continued)

content of this MPDS paragraph shall be the following information:

- a. Constant Name
- b. Purpose and Status
- c. Structure and Bit Layout

Paragraph 4.N.3.4 - Flags

This MPDS paragraph shall contain the detailed description of each flag included only in the subprogram/system subroutine data base. Each flag shall be described individually, where the descriptions are presented according to the alphabetical ordering of the mnemonic names of the flags. The minimum content of the MPDS paragraph shall be the following information

- a. Flag Name
- b. Purpose and Status
- c. Structure and Bit Layout

Paragraph 4.N.3.5 - Indexes

This MPDS paragraph shall contain the technical description of each index included in the subprogram/system subroutine data base. Each index shall be described individually where the descriptions are presented according to the alphabetical ordering of the mnemonic names of the indexes. The minimum content for this MPDS paragraph shall be:

- a. Index Name
- b. Purpose

Paragraph 4.N.3.6 - Common Data Base Reference

This MPDS paragraph shall provide a complete list of all common data base items referenced by each subprogram/system subroutine. This list provides a cross reference to the Common Data Base section which provides the technical description of the common data base items.

Paragraph 4.N.4 - Input/Output Formats

This MPDS paragraph shall contain a description of each input and output processed by the subprogram/system subroutine.

Paragraph 4.N.5 - Conditions for Initiation

This MPDS paragraph shall identify system conditions that must be met for this subprogram/system subroutine to be initiated for processing. For those subprograms/system subroutines that are always initiated for processing regardless of system conditions, the word "UNCONDITIONAL" shall be shown. For those subprograms that are initiated due to one or more unique conditions, each possible condition or set of conditions shall be described. If the conditions are based on the settings of certain items of information, each item, its required value, and a definition (or reference) of that value shall be shown.

Paragraph 4.N.6 - Subprogram / System Subroutine Limitations

This MPDS paragraph shall summarize any known or anticipated limitations of the subprogram/system subroutine. A list of all restrictions and constraints that apply to the subprogram/system subroutine shall be provided, including timing requirements, limitations of algorithms and formulas used, and design limits of input and output data.

Paragraph 4.N.7 - Interface Description

This MPDS paragraph and an associated block diagram shall show the sequential and functional relationship of the subprogram with the other subprograms and system subroutines with which it interfaces.

Section 5 - Common Data Base.

This section shall provide a complete detailed description of all data items necessary to carry out the functions of the microprocessor program. Common data is that data required by two or more subprograms or system subroutines. Examples of common data include constants, indexes, flags, variables and tables.

Paragraph 5.1 - Tables

This MPDS paragraph shall contain the detailed description of each table used in the common data base. Each table shall be described individually where the descriptions are presented according to the alphabetical ordering of the mnemonic name of the table. The minimum content of this paragraph shall be the following information:

a. Table Name

The title of the table with the assigned mnemonic label in parenthesis, e.g., Common Track Table (CDTRK).

b. Purpose and Type

The table type (e.g., fixed or variable length, table structure) and the explicit use of the table.

c. Size and Indexing Procedure

The number of items in the table and the number of microprocessor words required by each item. It shall also define, in precise terms, the method used to index through the various items of the table and any special conditions pertaining to the referencing of an included item.

d. Field Name

The title of the field with the assigned mnemonic in parenthesis.

e. Purpose and Type

An explicit description of the use of the field, and indication of its type (e.g., alphanumeric integer, fixed point or floating point).

f. Size

The size of the field in words or bits.

g. Binary Point

This information shall be included for all numeric type fields except floating point, and shall indicate the bit position of the binary

Paragraph 5.1 (Continued)

point (scaling) of the variable.

h. Range of Values and Initial Condition

The minimum and maximum values that are valid for the field, and the initial condition of the field if it is preset. For alphanumeric types the data code (e.g., ASCII, BCD) shall also be given.

i. Static/Dynamic

The changeability nature of the field (e. g., unchanging value is static, changing field values are dynamic).

j. Structure and Bit Layout

A diagram for each microprocessor word required by the field.

Paragraph 5.2 - Variables

This MPDS paragraph shall contain the detailed description of each variable included in the common data base. Each variable shall be described individually, where the descriptions are presented according to the alphabetical ordering of the mnemonic names of the variables.

The minimum content of this paragraph shall be the following information:

- a. Variable Name
- b. Purpose and Type
- c. Size - number of bits and sign
- d. Binary Point (not applicable to floating point numeric or alphanumeric types)
- e. Range of Values and Initial Condition
- f. Static/Dynamic
- g. Structure and Bit Layout

Paragraph 5.3 - Constants

This MPDS paragraph shall contain the detailed description of each constant included in the common data base. Each constant shall be described individually, where the descriptions are presented according to the alphabetical ordering of the mnemonic names of the constants. The minimum content of this paragraph shall be the following information:

- a. Constant Name
- b. Purpose
- c. Initial Condition
- d. Structure and Bit Layout

Paragraph 5.4 - Flags

This paragraph shall contain the detailed description of each flag included in the common data base. Each flag shall be described individually, where the descriptions are presented according to the alphabetical ordering of the mnemonic names of the flags. The minimum content of this paragraph shall be the following information:

- a. Flag Name
- b. Purpose
- c. Initial Condition
- d. Structure and Bit Layout

Paragraph 5.5 - Indexes

This paragraph shall contain the detailed description of each index included in the common data base. Each index shall be described individually, where the descriptions are presented according to the alphabetical ordering of the mnemonic name of the index. The minimum content of this paragraph shall include the following information:

- a. Index Name
- b. Purpose

Paragraph 5.6 - Subprogram Reference (Set/Used)

This MPDS paragraph shall include a complete list of all common data base items with a cross reference which includes all referencing subprograms/system subroutines.

Paragraph 5.7 - Notes

This MPDS section shall include a list of all subprograms/system subroutines by text name and mnemonic. The order of the list shall be in an alphabetical arrangement based upon the identifying mnemonic labels.

Appendix B

This MPDS paragraph shall include any information which is too bulky to be placed in the body of the document.

SPECIFICATION FOR RSED MICROPROCESSOR

(BREADBOARD VERSION)

SPECIFICATION NO. RS - 16

TABLE OF CONTENTS

<u>Paragraph</u>	<u>Title</u>	<u>Page No.</u>
1.0	Introduction	1
1.1	Function	1
2.0	Applicable Documents	1
3.0	Definitions	3
4.0	Performance Requirements	3
4.1	Inputs	3
4.1.1	Power Supplies	3
4.1.2	RAM Data Block	3
4.1.3	ROM Inputs from ROM Simulator	3
4.1.4	Interface from Test Panel	3
4.1.5	Interface with PDP-11/40 Data	3
4.1.6	Software	3
4.2	Outputs	3
4.2.1	RAM Data Blocks	3
4.2.2	Interface from Test Panel	3
4.2.3	Interface with PDP-11/40 Data	3
4.3	Internal Characteristics	3
4.3.1	Microprocessor Control Unit	4
4.3.2	Central Processing Element	6
4.3.3	Look Ahead Carry Generator	6
4.3.4	ROM Memory	8
4.3.5	RAM Memory	8
4.3.6	Pipe Line Register	8

TABLE OF CONTENTS (CONT.)

<u>Paragraph</u>	<u>Title</u>	<u>Page No.</u>
4.3.7	Decode	9
4.3.8	Clock Shaping, Control and Buffering	9
4.3.9	Initialization	9
4.3.10	SX, PX Bus Inputs	10
4.3.11	External Bus Inputs (I Bus)	10
4.3.12	Programmed Stop	12
4.3.13	CPE Clock Inhibit	12
4.3.14	Load	13
4.3.15	Logic Level Definitions	14

TABLE OF ILLUSTRATIONS

<u>Figure</u>		<u>Page No.</u>
1	RSED μ P BLOCK DIAGRAM	3
2	MCU (3001) BLOCK DIAGRAM	5
3	CPE (3002) BLOCK DIAGRAM	7
4	EXTERNAL BUS INPUTS (I BUS)	11

<u>Table</u>		
1	INPUT/OUTPUT WORD FORMAT	15

1.0 Introduction

This specification describes the requirements for the Microprocessor that is part of the Reed-Solomon Encoder/Decoder.

1.1 Function

The Microprocessor shall accept a data block representing header information, data characters, parity characters, S_K syndromes, number of erasures, erasure locations (compacted) and shall compute the erasure location polynomial, modified syndromes, error location polynomial, error location calculator, errata value calculator and shall output a data block representing header (with errata number) and corrected data and parity characters. The Microprocessor shall also provide two words within the DATA RAM used per data block (A & B) for data steering and completion of the decoding process.

2.0 Applicable Documents

<u>Document Name</u>	<u>Number</u>
RS Glossary	RS-3
*RS Output/Input Blocks	RS-4
RS α (Alpha) Definition	RS-8
*RS Hardware Functional Spec	RS-9
*RS Software Functional Spec	RS-10

Data Sheets for Intel 3001, 3002, 3003

*Updated by this document.

3.0 Definitions

RSED Reed Solomon Encoder/Decoder

SLL Standard Logic Level

4.0 Performance Requirements

The electrical performance shall be met over the environmental conditions specified below.

Temperature-Operating

Commercial Parts 0°C to +70°C

Military Parts -55°C to +125°C

4.1 Inputs

4.1.1 Power Supplies

To be determined.

4.1.2 RAM Data Blocks

4.1.3 ROM Inputs from ROM Simulator

4.1.4 Interface from Test Panel

4.1.6 Software


4.2 Outputs

4.2.1 RAM Data Blocks

4.2.2 Interface from Test Panel

4.3 Internal Characteristics (Hardware)

The RSED Microprocessor section of the RSED hardware shall consist of the following elements (see Figure 1) per Microprocessor.



4.3 Internal Characteristics (Hardware) (continued)

- a. Microprogram Control Unit (MCU)
- b. Central Processing Element (CPE). Six required.
- c. Look-Ahead Carry Generator (LCG)
- d. PROM Memory 2048 x 36 using 512 x 4 building blocks.
- e. RAM Memory 2048 x 8 using 1024 x 1 building blocks.
- f. Pipe Line Register
- g. 25 MHz Oscillator
- h. Clock Shaping, Control and Buffering
- i. RAM Address Multiplexer and Buffering
- j. RAM Data Multiplexer and Buffering

The microcomputer devices shall be selected from a family of Schottky bipolar LSI circuits (3000 series). Interface devices shall be compatible with the 3000 series (speed and loading). Initially, limited temperature range (0°C to 70°C) INTEL devices may be utilized for breadboard check-out. Eventually the limited temperature range devices shall be replaced with military temperature range (-55°C to +125°C) devices. Limited and full temperature range devices must be pin for pin compatible.


4.3.1 Microprogram Control Unit (3001)

The 3001 Microprogram Control Unit (MCU) controls the sequence in which microinstructions are fetched from the microprogram memory. Its functions include the following (Reference Figure 2):

- Maintenance of the microprogram address register.

- Selection of the next microinstruction based on the contents of the microprogram address register. (Refer to Pipe Line Register for plan or addressing).

5.



4.3.1 Microprogram Control Unit (3001) (continued)

Decoding and testing of data supplied via several input busses to determine the microinstruction execution sequence. Saving and testing of carry output data from the central processor (CP) array.

Control of carry/shift input data to the CP array.

Control of microprogram interrupts.

4.3.2 Central Processing Elements (3002)

The 3002 Central Processing Element contains all of the circuits that represent a 2 bit wide slice through the data processing section of a digital computer. To construct a complete central processor for a given word width N , it is simply necessary to connect an array of $N/2$ CPE's together. When wired together in such an array, a set of CPE's provide the following capabilities. (Reference Figure 3).

2's complement arithmetic

Logical AND, OR, NOT and exclusive - OR

Incrementing and Decrementing

Shifting left or right


Bit testing and zero detection

Carry look-ahead generation

Multiple data and address busses

4.3.3 Look-Ahead Carry Generator (3003)

The 3003 Look-Ahead Carry Generator (LCG) is a high speed circuit capable of anticipating a carry across a full 16 bit 3002 Central Processing Array. The LCG accepts light pairs of active high cascade inputs (X, Y) and an active low carry input and generates active low



3002 BLOCK DIAGRAM

FIGURE 3 CPE

4.3.3 Look-Ahead Carry Generator (3003)

carries for up to eight groups of binary adders. The Look-Ahead Carry Generator shall be connected to the CPEs to provide a normal arithmetic carry.

4.3.4 ROM Memory 2048 x 36^{*}

Initial μ P checkout (software) shall be accomplished with the aid of a ROM simulator. The ROM simulator shall be organized in blocks of 512 x 4 memory sections. A total memory capacity of 2048 x 36 is required (36-512x4). The ROM simulator shall have an access time of 100 nanoseconds. The final PROM's used with the μ P shall have a maximum access time of 60 com/80 mil nanoseconds under worst conditions.

4.3.5 RAM Memory 2048 x 8^{*}

A RAM Memory (2048 x 8) shall be incorporated into the μ P design. The memory shall be made up of 1024 x 1 circuits. Maximum RAM access time shall be 45 com/70 mil. nanoseconds under worst case conditions.

4.3.6 Pipe Line Register

A pipe line register (see Figure 1) shall be provided. The output of the register contains the bit pattern of the current instruction being executed.

The following bits shall be wired into the pipe line register:

READ

WRITE

STOP

Ko thru K11

CPE Inhibit

*Complete checkout requires testing using military devices at room temperature.

4.3.6 Pipe Line Register (continued)

Load

Inter Planar Control MSB and LSB

FO through F6

FCO through FC3

4.3.7 Decode

Bits 0 and 1 of the microinstruction shall be decoded as per Figure 1 description.

4.3.8 Clock Shaping, Control and Buffering

A section of the microprocessor hardware shall provide the basic micro-computer clock and clock control circuits as well as required buffering.

A 25 MHz crystal controlled oscillator shall be utilized to obtain the various clocks required. The microcomputer clock shall be 200 nanosec. with a duty cycle as specified in Intel data sheets.

The following controls shall be incorporated into the microprocessor control section.

Run/Halt - Enables/Disables the microprocessor clock.

One Step - Every time this control is activated the program advances one step (one micro instruction).

Ignore Stop - This control overrides programmed stops.

4.3.9 Initialization

With power turn on or when an initialization control is activated, the following initialization steps take place in each microprocessor simultaneously:

- a. The ROM memory address is set to plane 0, ROW 0, Column 15.

4.3.10 Sx and Px Bus Inputs

The primary and secondary bus inputs of the MCU shall be wired as follows:

Sx_0	to	D0
Sx_1	to	D1
Sx_2	to	D2
Sx_3	to	D3
Px_4	to	D4
Px_5	to	D5
Px_6	to	D6
Px_7	to	D7

4.3.11 External Bus Inputs (I Bins)

The external bus (I) inputs shall be wired as follows in Figure 4.

The following connections shall be made to the I bus as listed below:

Microinstruction

Bits	
$\frac{1}{1}$	$\frac{0}{1}$
0	1

M bus is set to logic level "0"

I Bus bits 3, 4, 5, 6 and 7 are set logic level "0"

I Bus bits 0, 1, 2 are set to the states of the D Bus

5, 6, 7 that is

$$I_0 = D5$$


$$I_1 = D6$$

$$I_2 = D7$$

0 0
or

1 0

M Bus is enabled, the I Bus is set to logic inversion of the M Bus and the D Bus is turned off (that part that connects to the I Bus).




External Bus Inputs
(I Bus)

Figure 4

I Inverting
 NI Non Inverting

4.3.12 Programmed Stop

When an instruction is clocked into the pipeline register with bits 0, 1 set to logic level "1" and "0" respectively (see Figure 1) the stop function is enabled, the CPE is clocked and the clock is disabled after the positive to negative transition of the clock (clock will remain at logic level "0").




4.3.13 CPE Clock Inhibit

When an instruction is clocked into the pipeline register with bit 14 set to logic level "1" (see Figure 1) the clock to the CPEs shall not be allowed to transition from logic level "1" to logic level "0" for the instructions that have bit 14 (micro instruction) set to logic level 1.


The instructions not requiring the CPE clock will be executed and the registers will be left unchanged.

4.3.13 CPE Clock Inhibit (continued)



4.3.14 Load

When an instruction is clocked into the pipe line register with bit 15 set to logic level "0" a load pulse shall be generated that enables the data on the D Bus to be entered into the MCU via the S_x and P_x Bus.



4.3.15 Logic Level Definitions




Intel data sheets for 3001, 3002 and 3003 circuits have an active high and active low states for the various input and output signals.

Active Low

Refer to layouts below. An active low signal represented by $\text{---}0$

is defined as follows: Logic Level "0" is equivalent to +3V.

Logic Level "1" is equivalent to 0V.



Active High

An active high signal is defined as follows:

Logic Level "0" is equivalent to 0V.

Logic Level "1" is equivalent to +3V.

DATA RAM INPUT/OUTPUT WORD FORMAT

Table 1

RAM ADDRESS	BIT POSITION						DESCRIPTION	
	* 5	4	3	2	1	0		
0 1 2 3							UNALLOCATED	
4		Word # Bit 0	Block # MSB	Block # LSB	0-Valid 1-Invalid	Code Select	Header	
5		Word # Bit 5	Word # Bit 4	Word # Bit 3	Word # Bit 2	Word # Bit 1	Header	
6		Debug Flag	Debug Flag	Word # Bit 8	Word # Bit 7	Word # Bit 6	Header	
7		Errata MSB	Errata	Errata	Errata	Errata LSB	Header	
8		MSB				LSB	31/15 C30	16/4 "0"s
9		MSB				LSB	C29	"0"s
10		MSB				LSB	C28	"0"s
11		MSB				LSB	C27	"0"s
12		MSB				LSB	C26	"0"s
13		MSB				LSB	C25	"0"s
14		MSB				LSB	C24	"0"s
15		MSB				LSB	C23	"0"s
16		MSB				LSB	C22	"0"s
17		MSB				LSB	C21	"0"s
18		MSB				LSB	C20	"0"s
19		MSB				LSB	C19	} DATA
20		MSB				LSB	C18	
21		MSB				LSB	C17	
22		MSB				LSB	C16	
23		MSB				LSB	C15	Parity A81

* See last chart page.

DATA RAM INPUT/OUTPUT WORD FORMAT

Table 1 (contd.)

RAM ADDRESS	BIT POSITION						DESCRIPTION	
	*5	4	3	2	1	0		
24		MSB				LSB	31/15 C14	16/4
25		MSB				LSB	C13	
26		MSB				LSB	C12	
27		MSB				LSB	C11	
28		MSB				LSB	C10	
29		MSB				LSB	C09	PARITY
30		MSB				LSB	C08	
31		MSB				LSB	C07	
32		MSB				LSB	C06	
33		MSB				LSB	C05	
34		MSB				LSB	C04	
35		MSB				LSB	C03	
36		MSB				LSB	C02	4 Erasures
37		MSB				LSB	C01	
38		MSB				LSB	C00	
39		MSB				LSB	SPARE	
40		MSB				LSB	S1	
41		MSB				LSB	S2	Syndromes
42		MSB				LSB	S3	
43		MSB				LSB	S4	
44		MSB				LSB	S5	
45		MSB				LSB	S6	A82

*See last chart page.

DATA RAM INPUT/OUTPUT WORD FORMAT

Table 1 (contd.)

RAM ADDRESS	BIT POSITION						DESCRIPTION
	*5	4	3	2	1	0	
46							
		MSB				LSB	S7
47							
		MSB				LSB	S8
48							S9
49							S10
							Syndromes
50							S11
51							S12
52							S13
53							S14
54							S15
55							S16
56							
		MSB				LSB	Number of Erasures
57							31/15 16/4
58							E_L
59							1. There are as many E_L 's as there are erasures.
60							2. The E_L 's are packed
61							
62							3. The E_L 's are in descending order
63							
64							4. The maximum number of E_L 's is 31.
65							
66							
67							
68							A83

*See last chart page.

DATA RAM INPUT/OUTPUT WORD FORMAT

Table 1 (contd.)

RAM ADDRESS	BIT POSITION						DESCRIPTION
	* 5	4	3	2	1	0	
69							
70							
71							
72							
73							
74							
75							
76							
77							
78							
79							
80							
81							
82							
83							
84							
85							
86							
87							
88							Unallocated
89							
90							
	*See last chart page.						

DATA RAM INPUT/OUTPUT WORD FORMAT

Table 1 (cont'd.)

RAM ADDRESS	BIT POSITION						DESCRIPTION
	* 5	4	3	2	1	0	
91							Unallocated
92							
93							
94							
95							
96							
97							
98							
99							
100							
101							
102							
103							
104							
105							
106							
107							
108							
109							
110							
111							
112							
113	*See last chart page.						A85

DATA RAM INPUT/OUTPUT WORD FORMAT

Table 1 (contd.)

RAM ADDRESS	BIT POSITION						DESCRIPTION
	* 5	4	3	2	1	0	
114							Unallocated
115							
116							
117							
118							
119							
120							
121							
122							
123							
124							
125							
126						X	A Read
127					Z	Y	A Write
	* Words at RAM address 8 through 38 bit position. 5 is used for erasure determination. "1" = erasure 0 = valid character Address 0 through 127 - Input/Output Area A 128 through 255 - Input/Output Area B (Same format as A)						

READ/WRITE CONTROL

	<u>FLAG</u>	<u>MEANING</u>	<u>SET</u>
126	$\left\{ \begin{array}{l} X = 0 \\ X = 1 \end{array} \right.$	Data not ready Data ready	DSCU (on read completion) Microprocessor (on decode completion)
127	$\left\{ \begin{array}{l} ZY = 00 \\ ZY = 01 \\ ZY = 11 \\ ZY = 10 \end{array} \right.$	No write request made Write request made (DSCU may write) DSCU has filled input buffer Not used	Microprocessor (when processing begins) Microprocessor (write early) DSCU (on write completion)

APPENDIX B

STATISTICAL DISTRIBUTION OF CORRECTABLE ERROR/ERASURE
PATTERNS FOR A (31, 15) REED-SOLOMON CODEWORD

STATISTICAL DISTRIBUTION OF CORRECTABLE ERROR/ERASURE PATTERNS FOR A

(31, 15) REED-SOLOMON CODEWORD

I. INTRODUCTION

The JTIDS II concatenated coded data link is comprised of an M'ary error/erasure inner code channel and a (31, 15) Reed Solomon (RS) outer code channel. The utility of this scheme depends not only on its high performance capability, but also on the required decoding time for received message codewords. While a worst case decoding time can be estimated from the maximum number of correctable errors and erasures, a more realistic value for the average decoding time requires a knowledge of the relative frequency of occurrence of the different errata patterns and the time to decode each pattern. This study addresses the determination of the elemental and cumulative probabilities of various errata patterns, under optimum jamming conditions and for certain specified message reliability levels.

II. ANALYSIS AND RESULTS

An (N, K) RS code can correct up to the number of errata satisfying the relation:

$$2t + s \leq N - K \quad (1)$$

where t and s are the number of character errors and erasures, respectively. Thus, for the (31, 15) code, the probability of correctly decoding a received codeword is given by:

$$Q_w = \sum_{t=0}^8 \sum_{s=0}^{16-2t} \binom{31}{t,s} p_e^t p_E^s (1 - p_e - p_E)^{31-t-s} \quad (2)$$

Use or disclosure of this data is subject to the restriction on the Title Page of this Document.

where p_e and p_E are the inner channel error and erasure transition probabilities, respectively.

From (2), the probability of any specific errata pattern, i.e. $t = t_1$ and $s = s_j$ is:

$$P(t, s) \triangleq P(t = t_1, s = s_j) \quad (3)$$

$$= \binom{31}{t_1, s_j} p_e^{t_1} p_E^{s_j} (1 - p_e - p_E)^{31-t_1-s_j} \quad (4)$$

The normalized value of this errata pattern is defined as

$$P_n(t, s) = \frac{P(t, s)}{Q_w} \quad (5)$$

The normalized probability of receiving a correctable pattern with $t = t_1$ errors is obtained by summing (5) over all values of erasures satisfying (1), or

$$P_{qn}(t) \triangleq P_{qn}(t = t_1) \quad (6)$$

$$= \sum_{s=0}^{16-2t_1} P_n(t, s) \quad (7)$$

The normalized cumulative probability of a correctable errata pattern with $t = t_1$ or less errors is obtained by summing (6) over $t \leq t_1$, or

$$Q_n(t \leq t_1) = \sum_{t=0}^{t_1} P_{qn}(t) \quad (8)$$

In another technical memorandum*, optimum jammer strategies were derived for this data link operating at various codeword reliability levels.

These jammer strategies correspond to specific average values of erasure and error probabilities $\bar{p}_E$ and $\bar{p}_e$, for the inner channel, which are used in (4) to determine the errata pattern probabilities. Table 1 gives the correspondence between two levels of codeword loss rate, $P_W = 1 - Q_W$, and the transition probabilities.

TABLE I

P_W	$\bar{p}_E$	$\bar{p}_e$
5×10^{-4}	0.196	0.0157
10^{-3}	0.214	0.0175

Figures 1, 2, and 3 show plots of equations (5), (7) and (8), respectively, for $P_W = 5 \times 10^{-4}$. Similarly, Figures 4, 5 and 6 show these same plots for $P_W = 10^{-3}$. In addition, Figures 3 and 6 show how the cumulative probability $Q_n(t \leq t_i)$ varies with receiver normalized erasure threshold setting variations due to AGC measurement errors.

* "Optimization of Jammer and Receiver Strategies for a Concatenated Coded Data Link with an Erasure/Error Inner Channel" Advanced CNI Systems Group, CNI Engineering ITT, Avionics Division, Nutley, N.J., August 1975

In Figures 1 or 4, loci for patterns with a constant number of erasures and a variable number of errors are drawn. Only the points on the curves, corresponding to integer values of t_i , are significant. The highest probabilities are obtained for errata patterns with 5 and 6 erasures. For any value of s_j , the probabilities decrease with an increasing number of errors t_i .

Figures 2 and 5 are obtained by adding the probabilities along each vertical line (i.e. for each t_i) in Figure 1 and 4. It gives the total probability of all correctable errata patterns for each value of the number of permissible errors.

In Figures 3 and 6, at the optimum normalized threshold setting of $T_n = 3.5$, the circled points correspond to the partial sums of (8) (or figures 2 and 5) for each $t=t_i$. For example, for $P_W = 5 \times 10^{-4}$, approximately 60 percent of the correctable patterns will have zero errors and 91 percent will have no more than one error. The number of erasures in each case includes all values satisfying (1). The remaining curves in Figure 3 and 6 show how these probabilities vary with T_n .

III. CONCLUSIONS

Probability data has been determined for all correctable RS codeword errata patterns. This data may serve as weighting functions to compute the average decoding time for a received codeword by the RS decoder being built by ITT Avionics, on another contract. If $T(t, s)$ is the time to decode a particular errata pattern of t errors and s erasures, then the average time to decode a word is given by:

$$T_{AVE} = \sum_{t=0}^8 \frac{16-2t}{\sum_{s=0}^{16-2t}} P_n(t, s) T(t, s) \quad (9)$$

5.

where $P_m(t, s)$ is given in Figure 1 or 4 and $T(t, s)$ may be estimated from the RS decoding algorithm and hardware implementation. A simplified calculation may also be made using the cumulative probabilities in Figures 2 or 5 and the decoding time for the maximum tolerable number of erasures for each t_i , or

$$T_{AVE} < \sum_{t=0}^8 P_{qn}(t) T(t, s=16-2t) \quad (10)$$

gives an upper bound on the average decoding time.

Use or disclosure of this information is restricted to the
restriction on the Title Page of this Document.




Figure 1. Errata Pattern Probabilities

Use or disclosure of this data is subject to the restriction on the Title Page of this Document.




Figure 2. Probability of Correctable Patterns With $t = t_i$ Errors




Figure 3. Cumulative Probability of Correctable Errata Patterns




Figure 4. Errata Pattern Probabilities




Figure 5. Probability of Correctable Patterns with $t = t_1$ Errors




Figure 6. Cumulative Probability of Correctable Errata Patterns

APPENDIX C

PERFORMANCE TEST PROCEDURE
REED SOLOMON ENCODER/DECODER

Prepared for Naval Air Development Center
Under Contract Number N62269-75-C-0503

by

ITT Avionics Division
500 Washington Avenue
Nutley, N. J. 07110

Specification D11723

Sheet 1 of 15

Issue B Date 1/16/76

1. INTRODUCTION

The purpose of these tests is to demonstrate that the Reed-Solomon Encoder/Decoder (RSED) module will satisfy the requirements presented in the RSED Statement of Work. The test data will be presented to the RSED via the User Test Panel. This data is prepared for testing from a pre-defined list of test message patterns. These test messages will include verification of the encoding and decoding processes, RTT recognition and reply, and overall message timing. See Figure 1 for RSED Block Diagram.

2. EQUIPMENT SET-UP

No specific test equipment is required. The Reed Solomon Encoder/Decoder in conjunction with the User Test Panel are sufficient equipment for performing this test procedure. A Tektronix 454 oscilloscope or equivalent is required during those portions of the tests that involve the measurement of timing waveforms.


3. PERFORMANCE TESTS

All test data taken for the following tests are to be recorded on the test data sheets supplied. Input test fields are selected at the operator's discretion from data supplied in Appendix A.

3.1 Encoder Tests

3.1.1 Encoder Accuracy

This test will be conducted on a message basis consisting of a Header (4 Data Characters), W1 (15 Data Characters), W2 (15 Data Characters) and W3 (15 Data Characters). Six separate test runs are made using the data presented in the test data sheets 3.1.1.1 thru 3.1.1.6. The "input area" column of the test data sheets represents the input data characters for H, W1, W2 and W3. The "trans word" column represents the correct encoded data characters (data and parity) for H, W1, W2 and W3. The "encoder area" column will be used for entering the data encoded by the RSED hardware and for comparison with the correct data characters to determine encoder accuracy.



RSED BLOCK DIAGRAM

Figure 1

3.1.1.1 Encoder Test Procedure

- A. Set the User test panel switches to the following positions.

<u>Switch</u>	<u>Position</u>
Power	ON
Continuous	OFF
Data-Word	Header
Data-Area	Input
Mode	Encode
Number of Messages	0001

- B. Using data sheets 3.1.1.1 thru 3.1.1.6 (one at a time) manually enter the data characters in the Input Area column. In addition, enter the Xmit data and encoded parities from Appendix A to the "trans word" column. Data characters (in decimal format) are entered by setting the data thumbwheel switches (2) to the desired magnitude and raising the deposit switch. The deposit switch is spring loaded and rests normally in the down position. If a data character greater than 31 is entered on the thumb wheel switches, the data display flashes on and off indicating the insertion of an invalid character.

The position at which data has been entered is displayed. When the advance switch is depressed, the position is advanced to the next position.

- C. After the four Header (H) characters are entered, set the Data-Word switch to W1 and enter 15 W1 data characters.
- D. After the 15 W1 characters are entered set the Data-Word switch to W2 and enter 15 W2 data characters.
- E. After the 15 W2 characters are entered set the Data-Word switch to W3 and enter 15 W3 data characters.
- F. Press the start switch and set the Data-Area switch to Encode and Data-Word switch to Header.

- G. Depressing the advance switch, write down the characters displayed for the Header in the Encoder Area column of the test data sheet. Compare the "Encoder Area" column with the "Trans Word" column and check pass or fail.
- H. Repeat for step G for W1, W2 and W3 by placing Data-Word switch to W1, W2 and W3.

3.1.2 Encoder Timing

This test will be conducted using message blocks consisting of one Header and W1, W2, W3 code words. Enter words as described in paragraph 3.1.1.1.

3.1.2.1 Encoder Timing Test Procedure

- A. Set the User test panel switches to the following positions:

<u>Switch</u>	<u>Position</u>
Number of Messages	0001
Continuous	ON

- B. Press the start switch and observe the following timing waveforms using the Tektronix 475 or equivalent oscilloscope.

Scope Settings

Sync - External +

Mode Triggering - ALT

Vertical Inputs

Channel 1 - Test Point 1, DC

Channel 2 - Test Point 14, DC

Scope GND - Test Point G

Adjust vertical gain for approximately 3 cm. deflection for Ch. 1 and Ch. 2.

Horizontal display - "A" inten
1 ms per cm.

Delayed Sweep - .1 ms/cm

Delayed Time Multiplier - 630

Horiz Display - B Dly'd

Measure time interval between last pos transition of signal on channel 1 to first pos edge transition of signal on channel 2.

Record this measurement on test data sheet for HEADER.
Record the time between pulses on channel 2 for the
time to encode W1, W2, and W3.

3.2 Decoder Tests

3.2.1 Decoder Accuracy and Timing

This test will be conducted on a message block basis to verify the decoding process. Several test words containing the number of errors and erasures (ERRATA) shown in table 1 are presented to the RSED via the User test panel.

3.2.1.1 Decoder Test Procedure

- A. Set the User test panel switches as listed in paragraph 3.1.1.1 (A) and proceed from 3.1.1.1 (A) thru 3.1.1.1 (E) using data sheets 3.2.1.1 thru 3.2.1.5.
- B. Press the start switch and set the Data-Area switch to Errata and Data-Word switch to Header.
- C. Check the displayed characters for the Errata Area column with the Trans Word column.
- D. Repeat step C for W1, W2 and W3 by placing Data-Word switch to W1, W2 and W3.
- E. Insert errors and erasures into the Header, W1, W2 and W3 as per table 1. Errata is entered as follows:

Set Data Area switch to Errata
Set Data Word switch to Header
Set Erasure Switch to OFF

Advance the position to the desired character and insert an error by depositing a character other than the one currently being displayed and write down the new character on the test data sheet under the Inserted Errata column at the present position displayed. Indicate error by "e".

If an erasure is to be inserted, advance the position to the desired character, set character magnitude to zero (00) and insert an erasure by placing the erasure switch on and lifting up the deposit switch. At this point the Red LED labeled erasure will be lit. Indicate erasures by "E".

Enter the position of the inserted erasure in the Errata Area column.

Number of Errors	Number of Erasures (31,15) (16,4)	Number of Erasures (31,15) only
0	0, 4, 8, 12,	13, 16
1	0, 3, 6, 10,	12, 14
2	0, 1, 5, 8,	11, 12
3	0, 3, 5, 6,	7, 10
4	0, 2, 3, 4,	6, 8,
5	0, 1, 2,	4, 6,
6	0	1, 2, 4,
7	-----	0, 1, 2,
8	-----	-----

Table 1. DECODER ACCURACY TEST CASES

- F. Repeat step E for W1, W2 and W3.
- G. Set the mode switch to Decode and recheck that the Number of Messages is set to 0001 and that "Continuous" is set to Off. Press the start switch and set the Data-Area switch to Decoder and Data-Word switch to Header.
- H. Write down the displayed characters by advancing through the decoded data area, for the header in the Decoder Area column. Position 00 displays the number of errors and the decode failure lamp will be lit if a data word was not decoded properly exceeds the error correction capability of the decoder.
- I. Repeat step H for W1, W2 and W3 by placing Data-Word switch to W1, W2 and W3.
- J. The User Test Panel loads the Decoder Data Area 6.7 milliseconds after the start switch is pushed in step G. If the examination of all the decode failure positions for the Header, W1, W2 and W3 results in the decode failure LED not lit, then the decoder corrected the inserted Errata in the time allotted.

Measure the decoder turnaround time using the HP 5345 Counter as follows:

Place continuous switch to On and press the start switch.

Counter Settings

FUNCTION - time int

Gate time/display - 100ms/100ms

Sample Rate - CCW

CHANNEL A

level - preset

Slope - +

Atten - 1 m Ω , X 20

AC/DC - AC

COM/SEP - COM A

CHANNEL B

preset

-

1 m Ω , X 20

AC

Connect a BNC coax to test point 13 ground to test point G. Record the time displayed in MS on the test data sheet.

- K. Repeat steps A thru J for additional tests as required.

3.2.1.2 Decoder Failure Test Procedure

Repeat steps A thru D of paragraph 3.2.1.1. At step E enter Errata patterns that exceed the power of the decoder. Example 9 errors, 17 erasures, or 4 errors and 9 erasures.

At step H note that the decode failure LED will be lit for the Data Words that have Errata exceeding the power of the decoder.

Measure the decoder turnaround time using the procedure described in paragraph 3.2.1.1. J.

3.3 RTT Tests

3.3.1 RTT Message Recognition Accuracy and Timing

This test is conducted using an RTT Donor Address which is entered into the RTT Input area, RSED encoded, and stored as the RTT Donor Address. A test word is set in the RTT Errata Area which is compared with the RTT Donor Address as shown in table 1 for the (16,4) code.

3.3.1.1 RTT Test Procedure

- A. Set the User test panel switches to the following positions:

<u>Switch</u>	<u>Position</u>
Continuous	OFF
Data-Word	RTT
Data-Area	Input
Mode	Encode
Number of Messages	0001

- B. Using data sheets 3.3.1.1 thru 3.3.1.6 enter manually the data characters in the Input Area column.

- C. Press start switch and set the Data Area to Errata and Data Word to RTT.
- D. Fill In Donor Address column with data from Appendix A.
- E. Check the displayed characters for the Errata Area column with the Donor Address column.
- F. Insert errors and erasures into the RTT Errata Word as per table 1. Errata is entered as described in paragraph 3.2.1.1 E.
- G. Set Mode switch to RTT Trial and Continuous switch to On. Press start switch and measure the following waveforms using the Tektronix 475 oscilloscope.

Scope Setting

Sync - Internal + (Channel 1 only)

Slope - -

Vertical Inputs

Channel 1 - Test Point 5, DC

Channel 2 - Test Point 10, DC

Adjust vertical gain for approximately 3 cm. deflection for ch. 1 and ch. 2.

Mode Trigger - Chop

Sweep Setting

5 microseconds per cm.

Measure the time interval between the negative edge transition of signal on channel 1 to positive edge transition of signal on channel 2.

Note: If no pulse is present on channel 2, the RTT detector may have an Errata pattern entered taht does not exceed the RTT Trial threshold criteria.

- H. If a waveform is present on channel 2, change the scope setting to 100 microsecond per cm., move channel 2 probe to test point 14 and measure the time interval between the negative edge transition of the pulse on channel 1 to the positive transition of the pulse on channel 2.
- I. Repeat steps A thru F for two additional test runs.

3.3.1.2 RTT Address Recognition

This test will demonstrate the ability of the RTT detector to reject messages not addressed to the terminal.

- A. Insert errata from the Appendix A which is unique to the data entered in paragraph 3.3.1.1 or insert errata which exceeds the (16,4) decoder capability.
- B. Proceed to step G of paragraph 3.3.1.1.

3.4 Multifunction RSED Tests

This test will demonstrate the ability of the RSED to perform an encode for Header, W1, W2 and W3, an RTT Trial, RTT Donor Address Outputting, and a decode of a Header W1, W2 and W3 in a 7.8125 msec. time slot.

3.4.1 Test Procedure

- A. Set the User test panel switches to the following positions.

<u>Switch</u>	<u>Position</u>
Continuous	Off
Number of Messages	0001
Mode	Encode
Data-Word	Header
Data-Area	Input

- B. Using data sheets 3.4.1.1 thru 3.4.1.6 enter manually the data characters in the Input Area column for Header, W1, W2 and W3 and RTT.
- C. Press the start switch and set the Data Area switch to Errata and Data Word switch to Header. Insert Errata as per paragraph 3.2.1.1 E (include RTT Errata). Record Errata pattern on test data sheet. Set the mode switch to interleaved.

- D. Set the Continuous switch to On, press the start switch and measure the following waveforms using the Tektronix 475 oscilloscope.

Scope Settings

Sync - Internal - (Channel 1 only)

Vertical Input

Channel 1 - Test Point 12

Sweep Setting

1 millisecond per cm.

Measure the repetition rate of channel 1 waveform and record.

- E. Set Scope as follows for Decoder Input Data

Sync. Ext - Test Point 12

Vertical Input - Alt

Channel 1 - Test Point 5

Channel 2 - Test Point 6

Sweep Setting - 20 usec/cm

X10 magnifier

Measure the number of 400 nanosecond negative transitions on channel 2 for each positive gate on channel 1.

1st gate - Header

2nd gate - W1

3rd gate - W2

4th gate - W3

- F. Set Scope as follows for Decoder Output Data.

Sync. Ext - Test Point 12

Vertical Input - Alt

Channel 1 - Test Point 7

Channel 2 - Test Point 8

Sweep Setting: Main - 1 ms/cm, delayed - 2 usec/cm

Use delaying sweep set at 6.7 msec. and adjust delayed sweep as required.

Measure the number of 400 nanosecond negative transitions on channel 2 for each negative gate on channel 1.

1st gate - Header
2nd gate - W1
3rd gate - W2
4th gate - W3

G. Set Scope as follows for Encoder Input Data.

Sync Ext - Test Point 12

Vertical Input

Channel 1 - Test Point 1

Channel 2 - Test Point 2

Sweep Setting

Use delaying sweep set at approximately 6.6 msec. and adjust delayed sweep as required.

Measure the number of 400 nanosecond negative transitions on channel 2 for each negative gate on channel 1.

1st gate - Header
2nd gate - W1
3rd gate - W2
4th gate - W3

H. Set Scope as follows for Encode Output Data.

Sync Ext - Test Point 12

Vertical Input

Channel 1 - Test Point 3

Channel 2 - Test Point 4

Sweep Setting

Use delaying sweep set approximately 7.6 msec. and adjust delayed sweep as required.

Measure the number of 400 nanosecond negative transitions on channel 2 for each negative gate on channel 1.

1st gate - Header
2nd gate - W1
3rd gate - W2
4th gate - W3

I. Set Scope as follows for RTT Trial.

Sync. Ext - Test Point 12

Vertical Input

Channel 1 - Test Point 5

Channel 2 - Test Point 6

Sweep Setting

Use delaying sweep set at approximately 2 msec. and adjust delayed sweep as required.

Measure the number of 400 nanosecond negative transitions on channel 2 for the negative gate on channel 1.

J. Set Scope as follows for RTT Active.

Sync. Ext - Test Point 12

Vertical Input

Channel 1 - Test Point 5

Channel 2 - Test Point 10

Sweep Setting: main - 1 ms/cm, delayed, 5 usec/cm

Use delaying sweep set at approximately 2 msec and adjust delayed sweep as required.

Measure the time interval from the positive transition of the pulse on channel 1 to the negative transition of the pulse on channel 2.

K. Set Scope as follows for RTT Turnaround Time.

Sync. Ext - Test Point 12

Vertical Input

Channel 1 - Test Point 5

Channel 2 - Test Point 14

Sweep Setting: main - 1 ms/cm, delayed - 50 usec/cm

Use delaying sweep set at approximately 2 msec and adjust delayed sweep as required.

Measure the time interval from the positive transition of the pulse on channel 1 to the negative transition of the pulse on channel 2.

L. Set Scope as follows for Read Out RTT Donor Address.

Sync. Ext + Test Point 12

Vertical Input

Channel 1 - Test Point 3

Channel 2 - Test Point 4

Sweep Setting

Use delaying sweep set at approximately 2 msec and adjust delayed sweep as required.

Measure the number of 400 nanosecond negative transitions on channel 2 for the negative gate on channel 1.

JTIDS C.S.
REQUEST?

EERUN RESM

JTIDS O.S.
REQUEST?

RUN RESMON

S000
ENCODE

S000
XMIT DATA: . 11 12 13 14

EN PARITY: 12 25 22 05 20 01 25 09 24 08 02 00

S001
XMIT DATA: . 16 10 08 04

EN PARITY: 01 24 08 25 18 25 09 14 16 24 02 29

S002
XMIT DATA: . 19 22 13 24

EN PARITY: 28 17 04 00 03 20 16 15 26 23 27 02

S003
XMIT DATA: . 25 23 08 13

EN PARITY: 09 09 19 15 16 01 17 26 22 29 14 16

S004
XMIT DATA: . 07 23 17 23

EN PARITY: 22 19 24 15 01 05 08 25 09 13 04 31

S005
XMIT DATA: . 25 00 11 13

EN PARITY: 31 25 23 31 12 23 28 12 10 09 12 22

S006
XMIT DATA: . 26 17 06 27

EN PARITY: 01 04 28 03 28 12 30 07 25 26 19 15

Appendix A
Short Code (16,4)

S007

XMIT DATA: . 02 17 12 13

EN PARITY: 14 10 05 07 25 11 15 27 00 24 05 04

S008

XMIT DATA: . 07 03 21 24

EN PARITY: 12 31 03 02 09 26 28 29 11 18 14 16

S009

XMIT DATA: . 25 04 00 29

EN PARITY: 23 15 28 00 12 01 10 04 00 27 11 18

S010

XMIT DATA: . 12 30 10 03

EN PARITY: 12 02 26 04 20 01 00 12 05 10 03 25

S011

XMIT DATA: . 21 02 13 03

EN PARITY: 22 23 30 30 18 00 10 01 03 21 26 24

S012

XMIT DATA: . 28 30 28 04

EN PARITY: 13 18 06 11 19 14 03 11 25 18 21 21

S013

XMIT DATA: . 12 26 30 26

EN PARITY: 24 00 03 13 28 13 28 28 17 15 07 31

S014

XMIT DATA: . 03 12 08 12

EN PARITY: 22 30 23 24 01 22 13 16 20 01 15 20

S015

XMIT DATA: . 23 14 08 08

EN PARITY: 01 28 03 06 06 22 27 20 16 25 18 03

SC16

XMIT DATA: . 06 31 26 05

EN PARITY: 25 22 17 30 23 06 30 26 24 06 03 01

SC17

XMIT DATA: . 07 16 14 07

EN PARITY: 29 26 00 19 15 01 14 06 12 25 23 13

SC18

XMIT DATA: . 02 01 08 01

EN PARITY: 27 11 16 21 30 30 27 04 00 04 04 12

SC19

XMIT DATA: . 15 09 05 24

EN PARITY: 04 05 01 29 02 06 24 00 09 02 14 10

SC20

XMIT DATA: . 31 23 26 31

EN PARITY: 01 19 29 00 26 29 01 01 19 29 11 05

SC21

XMIT DATA: . 13 19 10 13

EN PARITY: 16 22 30 30 19 15 27 22 08 26 25 03

SC22

XMIT DATA: . 28 31 05 01

EN PARITY: 00 25 30 26 27 27 12 16 29 20 00 09

SC23

XMIT DATA: . 20 23 30 18

EN PARITY: 00 30 13 01 06 29 10 06 08 30 01 00

SC24

XMIT DATA: . 18 15 28 25

EN PARITY: 00 23 20 27 16 20 20 21 26 06 04 28

SC25

XMIT DATA: . 06 17 01 08

EN PARITY: 24 31 12 04 01 30 12 23 03 31 23 19

SC26

XMIT DATA: . 03 11 16 00

EN PARITY: 17 28 29 06 16 29 24 14 19 26 23 22

SC27

XMIT DATA: . 26 15 29 02

EN PARITY: 05 20 04 03 13 12 11 22 28 22 18 17

SC28

XMIT DATA: . 31 25 28 04

EN PARITY: 14 16 09 17 08 08 22 00 07 29 12 22

SC29

XMIT DATA: . 09 26 02 19

EN PARITY: 08 05 22 25 19 12 19 19 00 27 09 21

SC30

XMIT DATA: . 10 02 08 03

EN PARITY: 20 29 05 06 07 18 00 18 04 05 26 17

SC31

XMIT DATA: . 30 11 19 29

EN PARITY: 10 20 28 00 22 14 24 14 25 23 30 03

SC32

XMIT DATA: . 30 03 08 19

EN PARITY: 11 22 27 01 22 26 30 00 31 06 12 06

SC33

XMIT DATA: . 12 28 02 05

EN PARITY: 28 03 24 09 01 30 03 21 29 11 25 00

S034

XMIT DATA: . 22 18 11 23

EN PARITY: 30 29 11 03 15 03 21 05 22 29 25 20

S035

XMIT DATA: . 17 24 02 29

EN PARITY: 10 08 23 00 07 01 22 27 04 06 26 25

S036

XMIT DATA: . 03 06 11 02

EN PARITY: 21 21 17 27 22 30 08 04 24 20 05 22

S037

XMIT DATA: . 16 06 08 06

EN PARITY: 24 17 29 27 30 09 11 03 21 02 23 13

S038

XMIT DATA: . 03 00 12 02

EN PARITY: 13 03 06 13 28 06 10 28 18 21 28 24

S039

XMIT DATA: . 04 08 14 26

EN PARITY: 30 23 10 07 10 28 19 16 03 04 17 27

S040

XMIT DATA: . 25 08 28 02

EN PARITY: 05 18 09 16 03 12 27 26 00 29 09 23

S041

XMIT DATA: . 16 07 31 29

EN PARITY: 28 13 07 25 21 04 10 20 12 15 05 22

S042

XMIT DATA: . 03 23 00 20

EN PARITY: 06 27 10 00 28 30 18 23 00 26 12 15

SC43

XMIT DATA: . 28 19 18 07

EN PARITY: 28 25 04 23 01 30 00 28 09 18 07 03

SC44

XMIT DATA: . 31 25 02 07

EN PARITY: 24 06 19 19 15 00 18 30 07 31 04 29

SC45

XMIT DATA: . 10 19 10 23

EN PARITY: 02 15 14 12 17 05 07 12 03 15 31 31

SC46

XMIT DATA: . 28 04 19 04

EN PARITY: 29 00 07 02 10 02 10 10 08 27 16 13

SC47

XMIT DATA: . 07 28 11 28

EN PARITY: 24 19 06 29 30 24 02 22 01 30 27 01

SC48

XMIT DATA: . 06 05 11 11

EN PARITY: 30 10 07 14 14 24 26 01 22 03 15 07

SC49

XMIT DATA: . 14 13 04 09

EN PARITY: 03 24 08 19 06 14 19 04 29 14 07 30

SC50

XMIT DATA: . 16 22 05 16

EN PARITY: 20 04 00 17 27 30 05 14 28 03 06 02

SC51

XMIT DATA: . 25 30 11 30

EN PARITY: 26 12 22 31 19 19 26 23 00 23 23 28

S052

XMIT DATA: . 27 21 09 29

EN PARITY: 23 09 30 20 25 14 29 00 21 25 05 18

S053

XMIT DATA: . 13 06 04 13

EN PARITY: 30 17 20 00 04 20 30 30 17 20 12 09

S054

XMIT DATA: . 02 17 18 02

EN PARITY: 22 24 19 19 17 27 26 24 11 04 03 07

S055

XMIT DATA: . 10 13 09 30

EN PARITY: 00 03 19 04 26 26 28 22 20 01 00 21

S056

XMIT DATA: . 01 06 19 15

EN PARITY: 00 19 02 30 14 20 18 14 11 19 30 00

S057

XMIT DATA: . 15 27 10 03

EN PARITY: 00 06 01 26 22 01 01 31 04 14 23 10

S058

XMIT DATA: . 14 08 30 11

EN PARITY: 29 13 28 23 30 19 28 06 07 13 06 17

S059

XMIT DATA: . 07 12 22 00

EN PARITY: 08 10 20 14 22 20 29 05 17 04 06 24

S060

XMIT DATA: . 04 27 20 25

EN PARITY: 09 01 23 07 02 28 12 24 10 24 15 08

S061

XMIT DATA: . 13 03 10 23

EN PARITY: 05 22 21 08 11 11 24 00 16 20 28 24

S062

XMIT DATA: . 21 04 25 17

EN PARITY: 11 09 24 03 17 28 17 17 00 26 21 31

S063

XMIT DATA: . 18 25 11 07

EN PARITY: 01 20 09 14 16 15 00 15 23 09 04 08

S064

XMIT DATA: . 19 12 17 20

EN PARITY: 18 01 10 00 24 05 29 05 03 06 19 07

S065

XMIT DATA: . 19 07 11 17

EN PARITY: 12 24 26 30 24 04 19 00 13 14 28 14

S066

XMIT DATA: . 28 10 25 09

EN PARITY: 10 07 29 21 30 19 07 31 20 12 03 00

S067

XMIT DATA: . 24 15 12 06

EN PARITY: 19 20 12 07 27 07 31 09 24 20 03 01

S068

XMIT DATA: . 08 29 25 20

EN PARITY: 18 11 06 00 16 30 24 26 23 14 04 03

S069

XMIT DATA: . 07 14 12 25

EN PARITY: 31 31 08 26 24 19 11 23 29 01 09 24

SC70

XMIT DATA: . 22 14 11 14

EN PARITY: 29 08 20 26 19 21 12 07 31 25 06 02

SC71

XMIT DATA: . 07 00 28 25

EN PARITY: 02 07 14 02 10 14 18 10 15 31 10 29

S072

XMIT DATA: . 23 11 05 04

EN PARITY: 19 06 18 16 18 10 17 22 07 23 08 26

SC73

XMIT DATA: . 03 11 10 25

EN PARITY: 09 15 21 22 07 28 26 04 00 20 21 06

SC74

XMIT DATA: . 22 16 13 20

EN PARITY: 10 02 16 03 31 23 18 01 28 27 09 24

SC75

XMIT DATA: . 07 06 00 01

EN PARITY: 14 26 18 00 10 19 15 06 00 04 28 27

SC76

XMIT DATA: . 10 17 15 16

EN PARITY: 10 03 23 06 30 19 00 10 21 15 16 07

S077

XMIT DATA: . 13 03 25 16

EN PARITY: 29 14 17 17 27 00 15 19 16 13 23 20

S078

XMIT DATA: . 18 17 18 06

EN PARITY: 25 27 05 28 08 09 16 28 07 27 13 13

S079

XMIT DATA: . 10 23 17 23

EN PARITY: 20 00 16 25 18 25 18 18 11 26 22 02

S080

XMIT DATA: . 16 10 12 10

EN PARITY: 29 17 14 20 19 29 25 24 30 19 26 30

S081

XMIT DATA: . 14 09 12 12

EN PARITY: 19 18 16 05 05 29 04 30 24 07 27 16

S082

XMIT DATA: . 05 02 23 21

EN PARITY: 07 29 11 17 14 05 17 23 20 05 16 19

S083

XMIT DATA: . 22 24 09 22

EN PARITY: 01 23 00 08 26 19 09 05 10 07 14 25

S084

XMIT DATA: . 03 19 12 19

EN PARITY: 04 28 24 13 17 17 04 06 00 06 06 10

S085

XMIT DATA: . 26 31 21 20

EN PARITY: 06 21 19 01 03 05 20 00 31 03 09 15

S086

XMIT DATA: . 02 14 23 02

EN PARITY: 19 08 01 00 23 01 19 19 08 01 28 21

S087

XMIT DATA: . 25 08 15 25

EN PARITY: 24 29 17 17 08 26 04 29 12 23 07 16

S088

XMIT DATA: . 18 02 21 19

EN PARITY: 00 07 17 23 04 04 10 24 01 30 00 31

S089

XMIT DATA: . 30 14 17 27

EN PARITY: 00 17 25 19 05 01 15 05 12 17 19 00

S090

XMIT DATA: . 27 26 18 07

EN PARITY: 00 14 30 04 24 30 30 13 23 05 06 18

S091

XMIT DATA: . 05 11 19 12

EN PARITY: 20 02 10 06 19 17 10 14 16 02 14 08

S092

XMIT DATA: . 16 28 24 00

EN PARITY: 11 18 01 05 24 01 20 09 08 23 14 29

S093

XMIT DATA: . 23 26 01 03

EN PARITY: 21 30 06 16 25 10 28 29 18 29 27 11

S094

XMIT DATA: . 02 07 18 06

EN PARITY: 09 24 31 11 12 12 29 00 22 01 10 29

S095

XMIT DATA: . 31 23 03 08

EN PARITY: 12 21 29 02 08 10 08 08 00 04 31 13

SC96

XMIT DATA: . 15 03 12 16

EN PARITY: 30 01 21 05 22 27 00 27 06 21 23 11

SC97

XMIT DATA: . 17 28 08 01

EN PARITY: 15 30 18 00 29 09 20 09 07 14 17 16

SC98

XMIT DATA: . 17 16 12 08

EN PARITY: 28 29 04 19 29 23 17 00 02 05 10 05

SC99

XMIT DATA: . 10 18 03 21

EN PARITY: 18 16 20 31 19 17 16 13 01 28 07 00

S100

XMIT DATA: . 29 27 28 14

EN PARITY: 17 01 28 16 26 16 13 21 29 01 07 30

S101

XMIT DATA: . 11 20 03 01

EN PARITY: 15 12 14 00 22 19 29 04 06 05 23 07

S102

XMIT DATA: . 16 05 28 03

EN PARITY: 13 13 11 04 29 17 12 06 20 30 21 29

S103

XMIT DATA: . 24 05 12 05

EN PARITY: 20 11 01 04 17 31 28 16 13 03 14 25

S104

XMIT DATA: . 16 00 10 03

EN PARITY: 25 16 05 25 18 05 15 18 27 13 18 20

S105

XMIT DATA: . 06 12 09 23

EN PARITY: 17 14 15 22 15 18 08 24 16 06 11 04

S106

XMIT DATA: . 07 12 18 03

EN PARITY: 21 27 31 24 16 10 04 23 00 01 31 14

S107

XMIT DATA: . 24 22 02 01

EN PARITY: 18 25 22 07 13 06 15 30 10 26 21 29

S108

XMIT DATA: . 16 14 00 30

EN PARITY: 05 04 15 00 18 17 27 14 00 23 10 26

S109

XMIT DATA: . 18 08 27 22

EN PARITY: 18 07 06 14 19 17 00 18 31 27 22 16

S110

XMIT DATA: . 02 07 03 22

EN PARITY: 20 05 08 08 26 00 27 17 22 02 06 01

S111

XMIT DATA: . 15 08 15 14

EN PARITY: 03 26 09 10 11 21 22 10 16 26 02 02

S112

XMIT DATA: . 18 06 08 06

EN PARITY: 01 00 22 03 15 03 15 15 12 04 24 25

S113

EN PARITY: 20 08 05 01 17 20 03 29 19 17 04 19

S114

XMIT DATA: . 05 21 28 28

EN PARITY: 17 15 22 09 09 20 23 19 29 16 26 22

S115

XMIT DATA: . 09 25 06 31

EN PARITY: 16 20 12 08 05 09 08 06 01 09 22 17

S116

XMIT DATA: . 24 29 21 24

EN PARITY: 30 06 00 11 04 17 21 09 18 16 05 03

S117

XMIT DATA: . 07 17 28 17

EN PARITY: 23 10 29 02 08 08 23 14 00 14 14 18

S118

XMIT DATA: . 04 13 31 01

EN PARITY: 14 31 17 30 07 09 01 00 13 07 21 27

S119

XMIT DATA: . 25 05 06 25

EN PARITY: 17 11 30 00 06 30 17 17 11 30 10 31

S120

XMIT DATA: . 03 11 27 03

EN PARITY: 29 20 08 08 11 04 23 20 28 06 16 22

S121

XMIT DATA: . 15 25 31 17

EN PARITY: 00 16 08 06 23 23 18 29 30 19 00 13

XMIT DATA: . 19 05 08 26

EN PARITY: 00 08 03 17 09 30 27 09 28 08 17 00

S123

XMIT DATA: . 26 04 15 16

EN PARITY: 00 05 19 23 29 19 19 02 06 09 14 15

S124

XMIT DATA: . 09 12 17 28

EN PARITY: 01 25 18 14 17 08 18 05 22 25 05 11

S125

XMIT DATA: . 22 10 29 00

EN PARITY: 12 15 30 09 29 30 01 21 11 06 05 20

S126

XMIT DATA: . 06 04 30 07

EN PARITY: 31 19 14 22 03 18 10 20 15 20 26 12

S127

XMIT DATA: . 25 16 15 14

EN PARITY: 21 29 13 12 28 28 20 00 24 30 18 20

S128

XMIT DATA: . 13 06 07 11

EN PARITY: 28 31 20 16 11 18 11 11 00 23 13 02

S129

XMIT DATA: . 27 07 28 22

EN PARITY: 19 30 31 09 24 26 00 26 14 31 06 12

S130

XMIT DATA: . 08 10 11 30

EN PARITY: 27 19 15 00 20 21 01 21 16 05 08 22

S131

XMIT DATA: . 08 22 28 11

EN PARITY: 10 20 23 17 20 06 08 00 25 09 18 09

S132

XMIT DATA: . 18 15 07 31

EN PARITY: 15 22 01 13 17 08 22 02 30 10 16 00

S133

XMIT DATA: . 20 26 10 05

EN PARITY: 08 30 10 22 04 22 02 31 20 30 16 19

S134

XMIT DATA: . 12 01 07 30

EN PARITY: 27 28 05 00 24 17 20 23 14 09 06 16

S135

XMIT DATA: . 22 09 10 07

EN PARITY: 02 02 12 23 20 08 28 14 01 19 31 20

S136

XMIT DATA: . 29 09 28 09

EN PARITY: 01 12 30 23 08 13 10 22 02 07 05 03

S137

XMIT DATA: . 22 00 18 07

EN PARITY: 03 22 09 03 15 09 27 15 26 02 15 01

S138

XMIT DATA: . 14 28 21 06

EN PARITY: 08 05 27 24 27 15 11 29 22 14 12 23

S139

XMIT DATA: . 16 28 15 07

EN PARITY: 31 26 13 29 22 18 23 06 00 30 13 05

S140

XMIT DATA: . 29 24 25 30

EN PARITY: 15 03 24 16 02 14 27 19 18 04 31 20

S141

XMIT DATA: . 22 05 00 19

EN PARITY: 09 23 27 00 15 08 26 05 00 06 18 04

S142

XMIT DATA: . 15 11 26 24

EN PARITY: 15 16 14 05 17 08 00 15 13 26 24 22

S143

XMIT DATA: . 25 16 07 24

EN PARITY: 01 09 11 11 04 00 26 08 24 25 14 30

S144

XMIT DATA: . 27 11 27 05

EN PARITY: 07 04 21 18 12 31 24 18 22 04 25 25

S145

XMIT DATA: . 15 14 11 14

EN PARITY: 30 00 24 07 27 07 27 27 28 23 29 03

S146

XMIT DATA: . 24 15 10 15

EN PARITY: 01 11 09 30 08 01 07 20 17 08 23 17

S147

XMIT DATA: . 09 31 10 10

EN PARITY: 08 27 24 21 21 01 06 17 20 22 04 24

S148

XMIT DATA: . 21 03 14 13

EN PARITY: 22 01 28 11 09 21 11 14 30 21 24 08

S149

XMIT DATA: . 29 20 31 29

EN PARITY: 19 14 00 12 23 08 31 21 15 22 09 07

S150

XMIT DATA: . 16 08 10 08

EN PARITY: 06 18 20 25 11 11 06 05 00 05 05 15

S151

XMIT DATA: . 23 02 13 30

EN PARITY: 05 13 08 19 16 21 30 00 02 16 31 26

S152

XMIT DATA: . 03 09 14 03

EN PARITY: 08 12 19 00 14 19 08 08 12 19 18 13

S153

XMIT DATA: . 07 12 26 07

EN PARITY: 20 01 11 11 12 23 06 01 10 14 22 24

S154

XMIT DATA: . 27 03 13 08

EN PARITY: 00 22 11 14 06 06 15 20 19 17 00 02

S155

XMIT DATA: . 17 09 11 04

EN PARITY: 00 11 07 08 21 19 26 21 10 11 08 00

S156

XMIT DATA: . 04 23 27 22

EN PARITY: 00 09 17 06 20 17 17 25 14 21 05 27

S157

XMIT DATA: . 21 28 08 10

EN PARITY: 30 03 15 05 08 11 15 09 24 03 09 12

S158

XMIT DATA: . 24 18 20 00

EN PARITY: 28 27 19 21 20 19 30 31 12 14 09 01

S159

XMIT DATA: . 14 23 19 16

EN PARITY: 13 17 05 24 07 15 18 01 27 01 04 28

S160

XMIT DATA: . 03 22 27 05

EN PARITY: 31 20 02 28 10 10 01 00 29 19 15 01

S161

XMIT DATA: . 02 14 16 12

EN PARITY: 10 13 01 22 12 15 12 12 00 06 02 25

S162

XMIT DATA: . 26 16 10 24

EN PARITY: 17 19 13 21 29 04 00 04 05 13 14 28

S163

XMIT DATA: . 11 18 12 19

EN PARITY: 26 17 27 00 01 31 30 31 22 09 11 24

S164

XMIT DATA: . 11 24 10 12

EN PARITY: 18 01 06 08 01 14 11 00 03 21 15 21

S165

XMIT DATA: . 15 27 16 13

EN PARITY: 27 24 30 02 08 11 24 25 19 18 22 00

S166

XMIT DATA: . 01 04 18 09

EN PARITY: 11 19 18 24 23 24 25 13 01 19 22 17

S167

XMIT DATA: . 28 30 16 19

EN PARITY: 26 10 09 00 29 08 01 06 05 21 14 22

S168

XMIT DATA: . 24 21 18 16

EN PARITY: 25 25 28 06 01 11 10 05 30 17 13 01

S169

XMIT DATA: . 20 21 10 21

EN PARITY: 30 28 19 06 11 02 18 24 25 16 09 07

S170

XMIT DATA: . 24 00 15 16

EN PARITY: 07 24 21 07 27 21 26 27 04 25 27 30

S171

XMIT DATA: . 05 10 31 14

EN PARITY: 11 09 26 29 26 27 12 20 24 05 28 06

S172

XMIT DATA: . 22 10 27 16

EN PARITY: 13 04 02 20 24 15 06 14 00 19 02 09

S173

XMIT DATA: . 20 29 03 19

EN PARITY: 27 07 29 22 25 05 26 17 15 23 13 01

S174

XMIT DATA: . 24 09 00 17

EN PARITY: 21 06 26 00 27 11 04 09 00 14 15 23

S175

EN PARITY: 27 22 05 09 08 11 00 27 02 04 29 24

S176

XMIT DATA: . 03 22 16 29

EN PARITY: 30 21 12 12 23 00 04 11 29 03 05 19

S177

XMIT DATA: . 26 12 26 09

EN PARITY: 16 23 31 15 28 13 29 15 24 23 03 03

S178

XMIT DATA: . 27 05 12 05

EN PARITY: 19 00 29 16 26 16 26 26 10 06 20 07

S179

XMIT DATA: . 29 27 18 27

EN PARITY: 30 12 21 19 11 30 16 01 08 11 06 08

S180

XMIT DATA: . 21 13 18 18

EN PARITY: 11 26 29 31 31 30 14 08 01 24 23 29

S181

XMIT DATA: . 31 07 05 02

EN PARITY: 24 30 10 12 21 31 12 05 19 31 29 11

S182

XMIT DATA: . 20 01 13 20

EN PARITY: 17 05 00 28 06 11 13 31 27 24 21 16

S183

XMIT DATA: . 22 11 18 11

EN PARITY: 14 15 01 03 12 12 14 09 00 09 09 27

XMIT DATA: . 06 25 02 19

EN PARITY: 09 02 11 17 22 31 19 00 25 22 13 04

S185

XMIT DATA: . 07 21 05 07

EN PARITY: 11 28 17 00 05 17 11 11 28 17 15 02

S186

XMIT DATA: . 16 28 04 16

EN PARITY: 01 30 12 12 28 06 14 30 18 05 24 29

S187

XMIT DATA: . 26 07 02 11

EN PARITY: 00 24 12 05 14 14 27 01 17 08 00 25

S188

XMIT DATA: . 08 21 12 23

EN PARITY: 00 12 16 11 31 17 04 31 18 12 11 00

S189

XMIT DATA: . 23 06 26 24

EN PARITY: 00 21 08 14 01 08 08 03 05 31 09 26

S190

XMIT DATA: . 31 10 11 18

EN PARITY: 19 07 27 09 11 12 27 21 29 07 21 28

S191

XMIT DATA: . 29 15 01 00

EN PARITY: 10 26 17 31 01 17 19 13 28 05 21 30

S192

XMIT DATA: . 05 06 17 22

EN PARITY: 02 08 09 29 16 27 15 30 26 30 23 10

S193

XMIT DATA: . 07 24 26 09

EN PARITY: 13 01 25 10 18 18 30 00 20 17 27 30

S194

XMIT DATA: . 25 05 22 28

EN PARITY: 18 02 30 24 28 27 28 28 00 14 25 03

S195

XMIT DATA: . 04 22 18 29

EN PARITY: 08 17 02 31 20 23 00 23 09 02 05 10

S196

XMIT DATA: . 12 15 28 17

EN PARITY: 04 08 26 00 30 13 19 13 24 21 12 29

S197

XMIT DATA: . 12 29 18 28

EN PARITY: 15 30 14 11 30 05 12 00 07 31 27 31

S198

XMIT DATA: . 27 26 22 02

EN PARITY: 26 29 19 25 11 12 29 03 17 15 24 00

S199

XMIT DATA: . 30 23 15 21

EN PARITY: 12 17 15 29 06 29 03 02 30 17 24 08

S200

XMIT DATA: . 10 19 22 17

EN PARITY: 04 18 21 00 20 11 30 14 09 31 05 24

S201

XMIT DATA: . 29 31 15 22

EN PARITY: 03 03 10 14 30 12 18 09 19 08 02 30

S202

XMIT DATA: . 01 31 18 31

EN PARITY: 19 10 17 14 12 25 15 29 03 22 21 16

S203

XMIT DATA: . 29 00 27 22

EN PARITY: 16 29 31 16 26 31 04 26 23 03 26 19

S204

XMIT DATA: . 09 18 13 05

EN PARITY: 12 21 04 20 04 26 28 01 29 09 10 14

S205

XMIT DATA: . 24 18 26 22

EN PARITY: 02 23 25 01 29 27 14 05 00 17 25 21

S206

XMIT DATA: . 01 20 07 17

EN PARITY: 26 16 20 24 03 09 04 08 27 06 02 30

S207

XMIT DATA: . 29 21 00 08

EN PARITY: 31 14 04 00 26 12 23 21 00 05 27 06

S208

XMIT DATA: . 26 28 23 20

EN PARITY: 26 24 09 21 11 12 00 26 25 23 20 29

S209

XMIT DATA: . 07 24 22 20

EN PARITY: 19 31 28 28 06 00 23 12 20 07 09 17

S210

XMIT DATA: . 04 28 04 21

EN PARITY: 22 06 13 27 10 02 20 27 29 06 07 07

S211

XMIT DATA: . 26 09 28 09

EN PARITY: 17 00 20 22 04 22 04 04 18 14 01 16

S212

XMIT DATA: . 20 26 15 26

EN PARITY: 19 28 31 17 12 19 22 30 11 12 14 11

S213

XMIT DATA: . 31 02 15 15

EN PARITY: 12 04 20 13 13 19 05 11 30 29 06 20

S214

XMIT DATA: . 13 16 09 25

EN PARITY: 29 19 18 28 31 13 28 09 17 13 20 12

S215

XMIT DATA: . 01 30 02 01

EN PARITY: 08 09 00 10 14 12 02 13 26 29 31 22

S216

XMIT DATA: . 24 12 15 12

EN PARITY: 05 27 30 07 28 28 05 21 00 21 21 26

S217

XMIT DATA: . 14 03 25 17

EN PARITY: 21 25 12 08 24 13 17 00 03 24 02 23

S218

XMIT DATA: . 16 31 09 16

EN PARITY: 12 10 08 00 09 08 12 12 10 08 27 25

S219

XMIT DATA: . 22 10 23 22

EN PARITY: 30 19 28 28 10 14 05 19 15 09 29 20

S220

XMIT DATA: . 04 16 25 12

EN PARITY: 00 29 28 09 05 05 26 30 08 11 00 03

S221

XMIT DATA: . 11 31 28 06

EN PARITY: 00 28 22 12 13 08 23 13 15 28 12 00

S222

XMIT DATA: . 06 14 04 29

EN PARITY: 00 31 11 05 30 11 11 07 09 13 21 04

S223

XMIT DATA: . 13 18 12 15

EN PARITY: 17 16 26 21 12 28 26 31 20 16 31 10

S224

XMIT DATA: . 20 27 30 00

EN PARITY: 18 04 08 13 30 08 17 02 10 09 31 19

S225

XMIT DATA: . 09 14 08 24

EN PARITY: 25 11 21 20 22 26 27 19 04 19 06 18

S226

XMIT DATA: . 16 29 04 21

EN PARITY: 02 30 03 18 15 15 19 00 01 08 26 19

S227

XMIT DATA: . 03 09 24 10

EN PARITY: 15 25 19 29 10 26 10 10 00 05 03 07

S228

XMIT DATA: . 23 24 15 20

EN PARITY: 11 08 25 13 01 06 00 06 21 25 09 18

S229

XMIT DATA: . 28 27 10 08

EN PARITY: 23 11 04 00 19 02 17 02 29 31 28 20

S230

XMIT DATA: . 28 20 15 10

EN PARITY: 27 19 05 12 19 09 28 00 16 13 26 13

S231

XMIT DATA: . 26 04 24 25

EN PARITY: 04 20 17 03 12 28 20 07 08 27 29 00

S232

XMIT DATA: . 19 06 27 31

EN PARITY: 28 08 27 20 14 20 07 25 19 08 29 11

S233

XMIT DATA: . 18 17 24 08

EN PARITY: 23 15 31 00 01 12 19 05 21 13 09 29

S234

XMIT DATA: . 20 13 27 24

EN PARITY: 07 07 18 05 19 28 15 21 17 11 25 19

S235

XMIT DATA: . 30 13 15 13

EN PARITY: 17 18 08 05 28 03 27 20 07 24 31 22

S236

XMIT DATA: . 20 00 26 24

EN PARITY: 22 20 13 22 04 13 23 04 06 07 04 17

S237

EN PARITY: 28 31 23 01 23 04 10 30 20 21 18 05

S238

XMIT DATA: . 29 15 04 24

EN PARITY: 25 06 03 30 20 26 05 09 00 08 03 31

S239

XMIT DATA: . 30 01 16 08

EN PARITY: 04 22 01 29 07 21 23 11 26 14 25 19

S240

XMIT DATA: . 20 31 00 11

EN PARITY: 13 05 23 00 04 28 06 31 00 09 26 14

S241

XMIT DATA: . 04 10 06 01

EN PARITY: 04 29 21 31 12 28 00 04 03 06 01 20

S242

XMIT DATA: . 16 29 24 01

EN PARITY: 17 13 10 10 14 00 06 28 01 16 21 08

S243

XMIT DATA: . 23 10 23 31

EN PARITY: 24 14 02 26 18 25 01 26 20 14 16 16

S244

XMIT DATA: . 04 21 10 21

EN PARITY: 08 00 01 24 23 24 23 23 15 05 30 22

S245

XMIT DATA: . 01 04 27 04

EN PARITY: 17 10 13 08 28 17 24 19 12 28 05 12

XMIT DATA: . 13 25 27 27

EN PARITY: 28 23 01 02 02 17 09 12 19 20 14 01

S247

XMIT DATA: . 02 22 21 03

EN PARITY: 20 17 15 10 13 02 10 21 08 02 01 28

S248

XMIT DATA: . 30 19 25 30

EN PARITY: 11 21 00 18 05 28 25 02 04 20 13 24

S249

XMIT DATA: . 29 28 27 28

EN PARITY: 09 26 19 16 10 10 09 31 00 31 31 04

S250

XMIT DATA: . 05 07 03 08

EN PARITY: 31 03 28 11 29 02 08 00 07 29 25 06

S251

XMIT DATA: . 22 13 21 22

EN PARITY: 28 18 11 00 21 11 28 28 18 11 26 03

S252

XMIT DATA: . 24 18 06 24

EN PARITY: 19 17 10 10 18 05 09 17 27 21 20 01

S253

XMIT DATA: . 23 22 03 28

EN PARITY: 00 20 10 21 09 09 04 19 11 12 00 07

S254

XMIT DATA: . 12 13 10 14

EN PARITY: 00 10 24 28 02 11 06 02 27 10 28 00

S255

XMIT DATA: . 14 05 23 20

EN PARITY: 00 13 12 09 19 12 12 16 21 02 31 23

S256

XMIT DATA: . 02 15 28 27

EN PARITY: 08 22 04 31 28 10 04 13 01 22 13 18

S257

XMIT DATA: . 01 26 19 00

EN PARITY: 15 23 11 02 19 11 08 25 18 21 13 17

S258

XMIT DATA: . 21 05 11 29

EN PARITY: 03 12 31 01 24 04 26 17 23 17 14 15

S259

XMIT DATA: . 22 20 23 31

EN PARITY: 25 19 07 15 27 27 17 00 30 11 04 17

S260

XMIT DATA: . 07 21 29 18

EN PARITY: 27 03 17 20 18 04 18 18 00 09 07 16

S261

XMIT DATA: . 06 29 27 01

EN PARITY: 12 11 03 02 30 14 00 14 31 03 21 15

S262

XMIT DATA: . 10 26 18 11

EN PARITY: 06 12 23 00 17 25 08 25 20 13 10 01

S263

XMIT DATA: . 10 01 27 18

EN PARITY: 26 17 09 28 17 21 10 00 22 02 04 02

S264

XMIT DATA: . 04 23 29 03

EN PARITY: 23 01 08 07 28 10 01 16 11 26 20 00

S265

XMIT DATA: . 17 14 26 13

EN PARITY: 10 11 26 01 05 01 16 03 17 11 20 12

S266

XMIT DATA: . 15 08 29 11

EN PARITY: 06 27 13 00 30 28 17 09 31 02 21 20

S267

XMIT DATA: . 01 02 26 29

EN PARITY: 16 16 15 09 17 10 27 31 08 12 03 17

S268

XMIT DATA: . 19 02 27 02

EN PARITY: 08 15 11 09 10 07 26 01 16 29 13 24

S269

XMIT DATA: . 01 00 04 29

EN PARITY: 24 01 02 24 23 02 06 23 14 16 23 08

S270

XMIT DATA: . 31 27 25 21

EN PARITY: 10 13 06 30 06 23 18 19 01 31 15 09

S271

XMIT DATA: . 20 27 23 29

EN PARITY: 03 14 07 19 01 04 09 21 00 11 07 13

S272

XMIT DATA: . 19 30 22 11

EN PARITY: 23 24 30 20 16 31 06 12 04 05 03 17

S273

XMIT DATA: . 01 13 00 12

EN PARITY: 02 09 06 00 23 10 14 13 00 21 04 05

S274

XMIT DATA: . 23 18 14 30

EN PARITY: 23 20 31 13 28 10 00 23 07 14 30 01

S275

XMIT DATA: . 22 20 29 30

EN PARITY: 08 02 18 18 05 00 14 10 30 22 31 11

S276

XMIT DATA: . 06 18 06 13

EN PARITY: 29 05 25 04 15 03 30 04 01 05 22 22

S277

XMIT DATA: . 23 31 18 31

EN PARITY: 11 00 30 29 06 29 06 06 27 09 19 24

S278

XMIT DATA: . 30 23 26 23

EN PARITY: 08 18 02 11 10 08 29 17 28 10 09 28

S279

XMIT DATA: . 02 03 26 26

EN PARITY: 10 06 30 25 25 08 21 28 17 01 05 30

S280

XMIT DATA: . 25 24 31 07

EN PARITY: 01 08 27 18 02 25 18 31 11 25 30 10

S281

XMIT DATA: . 19 17 03 19

EN PARITY: 12 31 00 15 09 10 03 25 23 01 02 29

S282

XMIT DATA: . 20 10 26 10

EN PARITY: 21 04 17 22 18 18 21 13 00 13 13 23

S283

XMIT DATA: . 09 16 07 11

EN PARITY: 13 07 10 12 20 25 11 00 16 20 03 14

S284

XMIT DATA: . 24 02 31 24

EN PARITY: 10 15 12 00 31 12 10 10 15 12 04 07

S285

XMIT DATA: . 29 15 14 29

EN PARITY: 17 08 18 18 15 09 21 08 26 31 01 30

S286

XMIT DATA: . 06 24 07 10

EN PARITY: 00 01 18 31 21 21 23 17 12 28 00 16

S287

XMIT DATA: . 28 02 18 05

EN PARITY: 00 18 29 10 25 12 14 25 26 18 10 00

S288

XMIT DATA: . 05 09 06 01

EN PARITY: 00 02 28 21 17 28 28 22 31 25 13 06

S289

XMIT DATA: . 25 27 10 26

EN PARITY: 11 24 23 13 10 18 23 02 30 24 02 15

S290

XMIT DATA: . 30 04 17 00

EN PARITY: 27 06 12 25 17 12 11 03 15 31 02 08

S291

XMIT DATA: . 31 09 12 20

EN PARITY: 07 28 13 30 29 23 04 08 06 08 05 27

S292

XMIT DATA: . 24 01 06 13

EN PARITY: 03 17 16 27 26 26 08 00 19 12 23 08

S293

XMIT DATA: . 16 31 20 15

EN PARITY: 26 07 08 01 15 23 15 15 00 21 16 22

S294

XMIT DATA: . 14 20 26 30

EN PARITY: 28 12 07 25 19 05 00 05 13 07 31 27

S295

XMIT DATA: . 18 04 15 12

EN PARITY: 14 28 06 00 08 03 11 03 01 02 18 30

S296

XMIT DATA: . 18 30 26 15

EN PARITY: 04 08 21 10 08 31 18 00 24 25 23 25

S297

XMIT DATA: . 23 06 20 07

EN PARITY: 06 30 11 16 10 18 30 22 12 04 01 00

S298

XMIT DATA: . 08 05 04 02

EN PARITY: 18 12 04 30 09 30 22 07 08 12 01 28

S299

EN PARITY: 14 26 02 00 19 10 08 21 13 25 31 01

S300

XMIT DATA: . 30 25 04 20

EN PARITY: 22 22 27 21 08 18 26 13 11 28 07 08

S301

XMIT DATA: . 17 25 26 25

EN PARITY: 11 27 12 21 18 16 04 30 22 20 02 29

S302

XMIT DATA: . 30 00 23 20

EN PARITY: 29 30 25 29 06 25 14 06 05 22 06 11

S303

XMIT DATA: . 13 26 03 31

EN PARITY: 18 02 14 19 14 06 15 17 30 13 27 21

S304

XMIT DATA: . 01 26 06 20

EN PARITY: 07 05 16 17 30 23 21 31 00 12 16 02

S305

XMIT DATA: . 17 19 24 12

EN PARITY: 06 29 19 01 22 13 14 28 23 09 07 08

S306

XMIT DATA: . 30 02 00 28

EN PARITY: 25 21 14 00 06 18 05 02 00 31 23 09

S307

XMIT DATA: . 06 15 05 19

EN PARITY: 06 01 13 02 10 18 00 06 16 05 19 30

XMIT DATA: . 24 01 20 19

EN PARITY: 11 25 15 15 09 00 05 18 19 24 13 12

S309

XMIT DATA: . 14 15 14 02

EN PARITY: 20 09 03 23 27 07 19 23 30 09 24 24

S310

XMIT DATA: . 06 13 15 13

EN PARITY: 12 00 19 20 14 20 14 14 26 21 17 29

S311

XMIT DATA: . 19 06 04 06

EN PARITY: 11 15 25 12 18 11 20 08 10 18 21 10

S312

XMIT DATA: . 25 07 04 04

EN PARITY: 18 14 19 03 03 11 31 10 08 30 09 19

S313

XMIT DATA: . 03 29 13 16

EN PARITY: 30 11 26 15 25 03 15 13 12 03 19 18

S314

XMIT DATA: . 17 08 07 17

EN PARITY: 28 13 00 27 21 18 07 03 06 30 25 20

S315

XMIT DATA: . 01 18 04 18

EN PARITY: 31 23 08 24 15 15 31 02 00 02 02 06

S316

XMIT DATA: . 21 22 16 12

EN PARITY: 02 16 18 28 01 03 12 00 22 01 07 05

S317

XMIT DATA: . 29 25 13 29

EN PARITY: 18 27 28 00 13 28 18 18 27 28 23 16

S318

XMIT DATA: . 20 27 05 20

EN PARITY: 08 11 15 15 27 21 31 11 04 13 30 19

S319

XMIT DATA: . 14 29 16 18

EN PARITY: 00 30 15 13 31 31 06 08 28 10 00 22

S320

XMIT DATA: . 10 25 15 09

EN PARITY: 00 15 20 18 03 28 05 03 04 15 18 00

S321

XMIT DATA: . 09 21 14 30

EN PARITY: 00 25 10 31 08 10 10 24 13 03 02 14

S322

XMIT DATA: . 03 26 18 04

EN PARITY: 12 29 06 02 18 15 06 25 19 29 25 27

S323

XMIT DATA: . 19 23 08 00

EN PARITY: 26 14 28 03 08 28 12 07 27 13 25 11

S324

XMIT DATA: . 13 21 28 01

EN PARITY: 16 10 02 19 20 06 23 11 14 11 09 26

S325

XMIT DATA: . 29 30 14 02

EN PARITY: 07 08 22 26 04 04 11 00 17 28 06 11

S326

XMIT DATA: . 22 13 01 27

EN PARITY: 04 16 11 30 27 06 27 27 00 31 22 24

S327

XMIT DATA: . 05 01 04 19

EN PARITY: 10 28 16 03 17 09 00 09 02 16 13 26

S328

XMIT DATA: . 15 23 27 28

EN PARITY: 05 10 14 00 11 07 12 07 30 25 15 19

S329

XMIT DATA: . 15 19 04 27

EN PARITY: 23 11 31 18 11 13 15 00 29 03 06 03

S330

XMIT DATA: . 06 14 01 16

EN PARITY: 14 19 12 22 18 15 19 24 28 23 30 00

S331

XMIT DATA: . 11 09 23 25

EN PARITY: 15 28 23 19 21 19 24 16 11 28 30 10

S332

XMIT DATA: . 26 12 01 28

EN PARITY: 05 04 25 00 17 18 11 31 02 03 13 30

S333

XMIT DATA: . 19 03 23 01

EN PARITY: 24 24 26 31 11 15 04 02 12 10 16 11

S334

XMIT DATA: . 08 03 04 03

EN PARITY: 12 26 28 31 15 22 23 19 24 01 25 20

S335

XMIT DATA: . 19 00 06 01

EN PARITY: 20 19 03 20 14 03 05 14 09 24 14 12

S336

XMIT DATA: . 02 04 07 13

EN PARITY: 15 25 05 17 05 14 27 08 19 02 26 31

S337

XMIT DATA: . 30 04 14 01

EN PARITY: 16 09 22 08 19 06 31 13 00 28 22 25

S338

XMIT DATA: . 08 17 29 28

EN PARITY: 14 20 17 30 24 02 05 10 06 21 16 11

S339

XMIT DATA: . 19 25 00 10

EN PARITY: 03 31 05 00 14 15 09 25 00 13 06 21

S340

XMIT DATA: . 14 27 09 17

EN PARITY: 14 30 02 25 18 15 00 14 22 09 17 19

S341

XMIT DATA: . 29 30 01 17

EN PARITY: 12 03 27 27 21 00 09 15 17 29 02 28

S342

XMIT DATA: . 05 27 05 25

EN PARITY: 01 21 07 06 26 16 17 06 19 21 29 29

S343

XMIT DATA: . 14 02 27 02

EN PARITY: 28 00 17 01 05 01 05 05 04 31 08 20

S344

XMIT DATA: . 17 14 23 14

EN PARITY: 12 27 03 28 15 12 01 11 18 15 31 18

S345

XMIT DATA: . 03 16 23 23

EN PARITY: 15 05 17 07 07 12 13 18 11 19 21 17

S346

XMIT DATA: . 07 20 02 22

EN PARITY: 19 12 04 27 03 07 27 02 28 07 17 15

S347

XMIT DATA: . 08 11 16 08

EN PARITY: 10 02 00 26 31 15 16 07 14 19 03 01

S348

XMIT DATA: . 30 15 23 15

EN PARITY: 13 06 11 29 27 27 13 25 00 25 25 14

S349

XMIT DATA: . 31 24 22 28

EN PARITY: 25 22 15 10 30 07 28 00 24 30 16 09

S350

XMIT DATA: . 20 03 02 20

EN PARITY: 15 26 10 00 02 10 15 15 26 10 06 22

S351

XMIT DATA: . 01 26 09 01

EN PARITY: 11 12 27 27 26 31 13 12 23 02 19 17

S352

XMIT DATA: . 05 20 22 15

EN PARITY: 00 19 27 02 13 13 14 11 10 18 00 24

S353

XMIT DATA: . 18 03 27 21

EN PARITY: 00 27 01 15 07 10 09 07 23 27 15 00

S354

XMIT DATA: . 21 31 05 19

EN PARITY: 00 03 18 13 11 18 18 29 02 07 25 05

S355

XMIT DATA: . 07 04 15 23

EN PARITY: 28 20 14 25 15 27 14 03 17 20 03 26

S356

XMIT DATA: . 17 06 11 00

EN PARITY: 04 05 10 07 11 10 28 16 26 02 03 12

S357

XMIT DATA: . 02 31 10 30

EN PARITY: 22 18 25 17 01 14 06 12 05 12 21 04

S358

XMIT DATA: . 20 19 05 25

EN PARITY: 16 11 24 04 23 23 12 00 08 10 14 12

S359

XMIT DATA: . 24 02 30 26

EN PARITY: 23 22 12 19 26 14 26 26 00 13 24 29

S360

XMIT DATA: . 09 30 23 17

EN PARITY: 18 10 22 07 08 21 00 21 25 22 02 04

S361

EN PARITY: 09 18 05 00 12 16 28 16 19 03 27 17

S362

XMIT DATA: . 27 17 23 26

EN PARITY: 06 12 13 15 12 02 27 00 20 07 14 07

S363

XMIT DATA: . 14 05 30 22

EN PARITY: 05 17 28 24 15 27 17 29 10 06 19 00

S364

XMIT DATA: . 12 21 06 03

EN PARITY: 27 10 06 17 31 17 29 22 12 10 19 18

S365

XMIT DATA: . 04 28 30 10

EN PARITY: 09 23 03 00 08 15 12 13 25 07 02 19

S366

XMIT DATA: . 17 07 06 30

EN PARITY: 29 29 04 13 12 27 23 25 28 18 22 12

S367

XMIT DATA: . 11 07 23 07

EN PARITY: 28 04 10 13 27 24 06 17 29 30 03 01

S368

XMIT DATA: . 17 00 14 30

EN PARITY: 01 17 07 01 05 07 09 05 21 29 05 28

S369

XMIT DATA: . 25 23 16 02

EN PARITY: 27 03 09 08 09 05 26 11 17 25 04 13

XMIT DATA: . 19 23 05 30

EN PARITY: 22 21 24 11 17 14 13 02 00 10 24 03

S371

XMIT DATA: . 11 08 20 10

EN PARITY: 05 01 08 19 29 25 09 18 14 31 22 12

S372

XMIT DATA: . 17 03 00 18

EN PARITY: 07 13 09 00 05 27 21 03 00 02 14 31

S373

XMIT DATA: . 05 26 21 08

EN PARITY: 05 19 25 03 15 27 00 05 24 21 08 17

S374

XMIT DATA: . 20 19 30 08

EN PARITY: 28 07 26 26 31 00 21 27 08 20 25 10

S375

XMIT DATA: . 09 26 09 03

EN PARITY: 30 31 16 14 04 22 08 14 17 31 20 20

S376

XMIT DATA: . 05 25 26 25

EN PARITY: 10 00 08 30 09 30 09 09 23 13 11 01

S377

XMIT DATA: . 08 05 06 05

EN PARITY: 28 26 07 10 27 28 30 12 15 27 13 15

S378

XMIT DATA: . 07 22 06 06

EN PARITY: 27 09 08 16 16 28 02 15 12 17 31 08

S379

XMIT DATA: . 16 01 25 24

EN PARITY: 17 28 23 26 07 16 26 25 10 16 08 27

S380

XMIT DATA: . 11 12 22 11

EN PARITY: 18 25 00 04 13 27 22 16 05 17 07 30

S381

XMIT DATA: . 19 27 06 27

EN PARITY: 02 14 12 20 26 26 02 03 00 03 03 05

S382

XMIT DATA: . 13 29 24 10

EN PARITY: 03 24 27 18 19 16 10 00 29 19 22 21

S383

XMIT DATA: . 01 07 25 01

EN PARITY: 27 04 18 00 25 18 27 27 04 18 14 24

S384

XMIT DATA: . 30 04 21 30

EN PARITY: 12 28 26 26 04 13 02 28 06 25 17 08

S385

XMIT DATA: . 09 01 24 27

EN PARITY: 00 17 26 25 02 02 05 12 18 15 00 29

S386

XMIT DATA: . 15 07 26 31

EN PARITY: 00 26 30 27 16 18 21 16 06 26 27 00

S387

XMIT DATA: . 31 13 09 17

EN PARITY: 00 07 15 02 12 15 15 20 25 16 03 09

S388

XMIT DATA: . 16 23 27 06

EN PARITY: 10 01 05 03 27 26 05 07 08 01 07 04

S389

XMIT DATA: . 08 14 12 00

EN PARITY: 23 09 18 16 12 18 10 22 04 25 07 28

S390

XMIT DATA: . 25 13 18 19

EN PARITY: 24 15 03 08 30 05 14 28 09 28 31 23

S391

XMIT DATA: . 01 17 09 03

EN PARITY: 22 12 29 23 06 06 28 00 11 18 05 28

S392

XMIT DATA: . 29 25 19 04

EN PARITY: 06 24 28 17 04 05 04 04 00 02 29 20

S393

XMIT DATA: . 21 19 06 08

EN PARITY: 15 18 24 16 11 31 00 31 03 24 25 23

S394

XMIT DATA: . 26 14 04 18

EN PARITY: 21 15 09 00 28 22 10 22 17 07 26 08

S395

XMIT DATA: . 26 08 06 04

EN PARITY: 14 28 02 27 28 25 26 00 01 16 05 16

S396

XMIT DATA: . 05 09 19 24

EN PARITY: 09 08 10 29 27 26 08 20 18 14 17 00

S397

XMIT DATA: . 28 31 14 07

EN PARITY: 26 18 14 08 13 08 20 24 28 18 17 15

S398

XMIT DATA: . 23 10 19 18

EN PARITY: 21 06 07 00 11 27 28 02 03 16 25 17

S399

XMIT DATA: . 08 16 14 19

EN PARITY: 20 20 23 02 28 26 06 03 10 15 24 28

S400

XMIT DATA: . 12 16 06 16

EN PARITY: 10 23 18 02 26 29 14 08 20 19 07 30

S401

XMIT DATA: . 08 00 05 19

EN PARITY: 30 08 16 30 09 16 21 09 31 20 09 10

S402

XMIT DATA: . 03 06 22 25

EN PARITY: 26 07 21 11 21 09 04 12 08 03 23 02

S403

XMIT DATA: . 17 06 09 19

EN PARITY: 24 31 29 12 08 05 02 25 00 18 29 07

S404

XMIT DATA: . 12 11 01 18

EN PARITY: 09 30 11 17 20 03 21 15 05 13 24 28

S405

XMIT DATA: . 08 07 00 15

EN PARITY: 16 02 21 00 09 26 31 07 00 25 05 13

S406

XMIT DATA: . 09 04 31 11

EN PARITY: 09 17 03 07 27 26 00 09 29 31 11 08

S407

XMIT DATA: . 01 17 19 11

EN PARITY: 10 16 04 04 13 00 31 26 11 01 03 18

S408

XMIT DATA: . 21 04 21 07

EN PARITY: 19 13 22 05 23 24 11 05 08 13 01 01

S409

XMIT DATA: . 09 03 04 03

EN PARITY: 18 00 11 19 21 19 21 21 06 02 12 30

S410

XMIT DATA: . 11 09 14 09

EN PARITY: 10 04 16 18 26 10 19 28 27 26 02 27

S411

XMIT DATA: . 16 24 14 14

EN PARITY: 26 21 11 22 22 10 25 27 28 08 13 11

S412

XMIT DATA: . 22 30 03 29

EN PARITY: 08 10 06 04 16 22 04 03 18 22 11 26

S413

XMIT DATA: . 12 28 24 12

EN PARITY: 15 03 00 23 02 26 24 22 09 08 16 19

S414

XMIT DATA: . 17 26 14 26

EN PARITY: 25 05 28 01 04 04 25 07 00 07 07 09

S415

XMIT DATA: . 02 20 29 18

EN PARITY: 07 29 26 15 17 22 18 00 20 17 24 31

S416

XMIT DATA: . 30 16 03 30

EN PARITY: 26 23 15 00 03 15 26 26 23 15 05 29

S417

XMIT DATA: . 19 23 31 19

EN PARITY: 28 10 04 04 23 02 25 10 14 03 08 11

S418

XMIT DATA: . 21 30 29 26

EN PARITY: 00 08 04 03 25 25 09 28 15 27 00 20

S419

XMIT DATA: . 27 16 04 13

EN PARITY: 00 04 19 26 22 15 31 22 14 04 26 00

S420

XMIT DATA: . 13 02 21 08

EN PARITY: 00 16 27 25 28 27 27 01 03 22 07 21

S421

XMIT DATA: . 22 06 26 14

EN PARITY: 18 30 09 07 26 04 09 16 11 30 16 23

S422

XMIT DATA: . 11 05 28 00

EN PARITY: 06 21 15 22 28 15 18 24 23 03 16 10

S423

EN PARITY: 29 27 07 11 19 09 05 10 21 10 13 06

S424

XMIT DATA: . 30 08 21 07

EN PARITY: 24 28 20 06 14 14 10 00 12 15 09 10

S425

XMIT DATA: . 20 03 17 23

EN PARITY: 14 29 10 08 23 09 23 23 00 25 20 01

S426

XMIT DATA: . 31 17 14 11

EN PARITY: 27 15 29 22 12 13 00 13 07 29 03 06

S427

XMIT DATA: . 04 05 23 15

EN PARITY: 31 27 21 00 10 24 18 24 08 16 04 11

S428

XMIT DATA: . 04 11 14 23

EN PARITY: 05 10 25 26 10 03 04 00 30 22 09 22

S429

XMIT DATA: . 09 21 17 29

EN PARITY: 21 11 18 20 26 04 11 01 15 05 08 00

S430

XMIT DATA: . 10 13 05 16

EN PARITY: 04 15 05 11 02 11 01 29 10 15 08 27

S431

XMIT DATA: . 06 18 17 15

EN PARITY: 31 14 16 00 12 26 10 25 07 22 03 08

XMIT DATA: . 11 22 05 17

EN PARITY: 01 01 06 25 10 04 14 07 18 27 29 10

S433

XMIT DATA: . 28 22 14 22

EN PARITY: 18 06 15 25 04 20 05 11 01 17 16 19

S434

XMIT DATA: . 11 00 09 17

EN PARITY: 19 11 22 19 21 22 31 21 13 01 21 18

S435

XMIT DATA: . 07 14 24 03

EN PARITY: 04 16 31 12 31 21 23 28 11 07 06 25

S436

XMIT DATA: . 08 14 21 17

EN PARITY: 29 13 20 28 11 09 25 03 00 15 20 16

S437

XMIT DATA: . 28 12 30 15

EN PARITY: 21 19 12 08 01 07 31 27 09 02 29 10

S438

XMIT DATA: . 11 16 00 27

EN PARITY: 22 25 31 00 21 04 13 16 00 03 09 02

S439

XMIT DATA: . 21 23 13 12

EN PARITY: 21 08 07 16 26 04 00 21 20 13 12 11

S440

XMIT DATA: . 30 08 17 12

EN PARITY: 18 22 23 23 02 00 13 04 12 30 07 15

S441

XMIT DATA: . 31 23 31 16

EN PARITY: 17 02 24 09 06 29 12 09 11 02 30 30

S442

XMIT DATA: . 21 07 23 07

EN PARITY: 15 00 12 17 31 17 31 31 14 25 28 19

S443

XMIT DATA: . 12 21 05 21

EN PARITY: 18 23 22 15 04 18 17 10 26 04 25 26

S444

XMIT DATA: . 22 29 05 05

EN PARITY: 04 31 12 24 24 18 03 26 10 11 02 12

S445

XMIT DATA: . 24 19 07 20

EN PARITY: 11 18 14 23 22 24 23 07 15 24 12 04

S446

XMIT DATA: . 28 10 29 28

EN PARITY: 27 07 00 06 25 04 29 24 21 11 22 17

S447

XMIT DATA: . 08 04 05 04

EN PARITY: 03 09 10 30 23 23 03 16 00 16 16 21

S448

XMIT DATA: . 25 01 20 15

EN PARITY: 16 20 04 27 08 24 15 00 01 08 29 13

S449

XMIT DATA: . 19 22 07 19

EN PARITY: 04 06 27 00 07 27 04 04 06 27 09 20

S450

XMIT DATA: . 17 06 13 17

EN PARITY: 10 18 23 23 06 25 03 18 05 07 11 12

S451

XMIT DATA: . 31 19 20 04

EN PARITY: 00 11 23 07 03 03 21 10 27 26 00 01

S452

XMIT DATA: . 26 22 23 02

EN PARITY: 00 23 17 04 24 27 13 24 05 23 04 00

S453

XMIT DATA: . 02 25 31 11

EN PARITY: 00 22 26 03 10 26 26 30 07 24 16 31

S454

XMIT DATA: . 24 14 04 05

EN PARITY: 15 19 21 16 04 23 21 22 12 19 22 06

S455

XMIT DATA: . 12 09 10 00

EN PARITY: 14 31 27 24 10 27 15 29 06 07 22 18

S456

XMIT DATA: . 07 25 27 08

EN PARITY: 20 26 16 12 17 21 09 18 31 18 02 14

S457

XMIT DATA: . 19 11 31 16

EN PARITY: 29 10 01 14 05 05 18 00 28 27 21 18

S458

XMIT DATA: . 01 07 08 06

EN PARITY: 05 20 18 11 06 21 06 06 00 03 01 30

S459

XMIT DATA: . 13 08 05 12

EN PARITY: 26 27 20 24 28 02 00 02 16 20 07 14

S460

XMIT DATA: . 23 09 06 27

EN PARITY: 13 26 31 00 18 29 15 29 11 22 23 12

S461

XMIT DATA: . 23 12 05 06

EN PARITY: 09 18 03 04 18 07 23 00 19 24 21 24

S462

XMIT DATA: . 21 31 08 20

EN PARITY: 31 12 15 01 04 23 12 30 27 09 11 00

S463

XMIT DATA: . 18 02 09 22

EN PARITY: 23 27 09 12 25 12 30 20 18 27 11 26

S464

XMIT DATA: . 14 15 08 27

EN PARITY: 13 05 22 00 28 04 18 03 16 24 07 11

S465

XMIT DATA: . 12 24 09 08

EN PARITY: 30 30 14 03 18 23 05 16 15 26 20 18

S466

XMIT DATA: . 10 24 05 24

EN PARITY: 15 14 27 03 23 01 09 12 30 08 22 17

S467

XMIT DATA: . 12 00 21 08

EN PARITY: 17 12 24 17 31 24 13 31 02 30 31 15

S468

XMIT DATA: . 16 05 29 07

EN PARITY: 23 22 13 28 13 31 06 10 12 16 14 03

S469

XMIT DATA: . 11 05 31 08

EN PARITY: 20 02 01 10 12 21 03 07 00 27 01 22

S470

XMIT DATA: . 10 28 19 27

EN PARITY: 31 17 28 11 30 16 13 26 21 25 20 18

S471

XMIT DATA: . 12 22 00 26

EN PARITY: 24 03 13 00 31 23 02 22 00 07 21 25

S472

XMIT DATA: . 31 06 02 28

EN PARITY: 31 11 16 22 04 23 00 31 01 02 28 12

S473

XMIT DATA: . 19 11 08 28

EN PARITY: 15 24 06 06 25 00 02 23 28 19 16 27

S474

XMIT DATA: . 13 06 13 22

EN PARITY: 08 25 29 21 14 20 28 21 12 25 19 19

S475

XMIT DATA: . 31 16 06 16

EN PARITY: 27 00 28 08 13 08 13 13 05 03 10 17

S476

XMIT DATA: . 28 31 09 31

EN PARITY: 15 06 24 27 23 15 08 18 04 23 03 04

S477

XMIT DATA: . 24 20 09 09

EN PARITY: 23 13 28 29 29 15 07 04 18 12 25 28

S478

XMIT DATA: . 29 17 16 01

EN PARITY: 12 15 05 06 24 29 06 16 27 29 28 23

S479

XMIT DATA: . 10 18 20 10

EN PARITY: 26 16 00 14 03 23 20 29 31 12 24 08

S480

XMIT DATA: . 11 23 09 23

EN PARITY: 07 21 18 19 06 06 07 22 00 22 22 31

S481

XMIT DATA: . 03 30 01 27

EN PARITY: 22 01 23 26 11 29 27 00 30 11 20 02

S482

XMIT DATA: . 17 24 16 17

EN PARITY: 23 14 26 00 16 26 23 23 14 26 21 01

S483

XMIT DATA: . 08 14 02 08

EN PARITY: 18 15 06 06 14 03 07 15 09 16 12 28

S484

XMIT DATA: . 13 17 01 23

EN PARITY: 00 12 06 16 07 07 31 18 26 04 00 30

S485

EN PARITY: 00 06 08 23 29 26 02 29 09 06 23 00

S486

XMIT DATA: . 25 03 13 12

EN PARITY: 00 24 04 07 18 04 04 19 16 29 22 13

S487

XMIT DATA: . 29 05 23 09

EN PARITY: 27 17 31 22 23 06 31 24 28 17 24 14

S488

XMIT DATA: . 28 21 18 00

EN PARITY: 05 13 26 29 18 26 27 20 14 16 24 15

S489

XMIT DATA: . 16 03 26 11

EN PARITY: 01 04 22 28 08 31 21 15 13 15 25 05

S490

XMIT DATA: . 17 12 13 22

EN PARITY: 20 18 30 05 09 09 15 00 10 26 31 15

S491

XMIT DATA: . 30 16 11 14

EN PARITY: 09 01 15 12 14 31 14 14 00 07 30 19

S492

XMIT DATA: . 02 11 09 28

EN PARITY: 04 26 01 29 10 25 00 25 22 01 16 05

S493

XMIT DATA: . 06 21 14 26

EN PARITY: 02 04 13 00 15 20 27 20 12 24 06 28

XMIT DATA: . 06 28 09 14

EN PARITY: 21 15 07 23 15 16 06 00 17 29 31 29

S495

XMIT DATA: . 31 13 11 01

EN PARITY: 13 28 27 30 23 06 28 19 26 21 12 00

S496

XMIT DATA: . 15 25 21 24

EN PARITY: 06 26 21 28 03 28 19 01 15 26 12 04

S497

XMIT DATA: . 05 27 11 26

EN PARITY: 02 09 24 00 10 23 15 07 22 29 16 12

S498

XMIT DATA: . 28 29 21 11

EN PARITY: 19 19 05 07 15 06 09 22 27 04 01 15

S499

XMIT DATA: . 18 29 09 29

EN PARITY: 27 05 26 07 06 30 21 28 19 11 24 08

S500

XMIT DATA: . 28 00 31 11

EN PARITY: 08 28 29 08 13 29 02 13 25 19 13 27

S501

XMIT DATA: . 22 09 20 16

EN PARITY: 06 24 02 10 02 13 14 18 28 22 05 07

S502

XMIT DATA: . 12 09 13 11

EN PARITY: 01 25 30 18 28 31 07 16 00 26 30 24

S503

XMIT DATA: . 18 10 17 26

EN PARITY: 13 08 10 12 19 22 02 04 31 03 01 15

S504

XMIT DATA: . 28 24 00 04

EN PARITY: 29 07 02 00 13 06 25 24 00 16 31 03

S505

XMIT DATA: . 13 14 25 10

EN PARITY: 13 12 22 24 23 06 00 13 30 25 10 28

S506

XMIT DATA: . 17 12 11 10

EN PARITY: 27 29 14 14 03 00 25 06 10 17 22 26

S507

XMIT DATA: . 02 14 02 24

EN PARITY: 11 03 20 31 05 01 10 31 28 03 17 17

S508

XMIT DATA: . 13 22 14 22

EN PARITY: 26 00 10 11 02 11 02 02 09 07 18 08

S509

XMIT DATA: . 10 13 21 13

EN PARITY: 27 14 29 26 06 27 11 15 23 06 07 23

S510

XMIT DATA: . 29 01 21 21

EN PARITY: 06 02 10 20 20 27 16 23 15 28 03 10

S511

XMIT DATA: . 20 08 22 30

EN PARITY: 28 27 09 14 29 20 14 22 26 20 10 06

S512

XMIT DATA: . 18 15 01 18

EN PARITY: 04 22 00 05 07 06 01 20 13 28 29 11

S513

XMIT DATA: . 12 06 21 06

EN PARITY: 16 31 15 17 14 14 16 24 00 24 24 13

S514

XMIT DATA: . 07 19 30 26

EN PARITY: 24 30 06 04 12 20 26 00 19 12 01 25

S515

XMIT DATA: . 08 29 22 08

EN PARITY: 06 05 04 00 22 04 06 06 05 04 31 30

S516

XMIT DATA: . 11 05 25 11

EN PARITY: 15 27 14 14 05 07 16 27 21 22 28 10

S517

XMIT DATA: . 02 08 30 06

EN PARITY: 00 28 14 22 16 16 13 15 04 23 00 19

S518

XMIT DATA: . 23 29 14 03

EN PARITY: 00 14 11 06 20 04 25 20 21 14 06 00

S519

XMIT DATA: . 03 07 02 28

EN PARITY: 00 29 23 16 15 23 23 17 22 20 24 02

S520

XMIT DATA: . 20 09 06 21

EN PARITY: 26 08 13 24 06 14 13 29 10 08 29 05

S521

XMIT DATA: . 10 31 15 00

EN PARITY: 09 02 04 20 15 04 26 01 05 22 29 27

S522

XMIT DATA: . 22 07 04 12

EN PARITY: 30 23 24 10 11 13 31 27 02 27 03 09

S523

XMIT DATA: . 08 28 02 24

EN PARITY: 01 15 19 09 21 21 27 00 18 04 13 27

S524

XMIT DATA: . 19 22 12 05

EN PARITY: 21 30 27 28 05 13 05 05 00 16 19 17

S525

XMIT DATA: . 25 12 21 10

EN PARITY: 23 04 30 20 18 03 00 03 24 30 22 09

S526

XMIT DATA: . 14 31 05 04

EN PARITY: 25 23 02 00 27 01 26 01 28 29 14 10

S527

XMIT DATA: . 14 10 21 05

EN PARITY: 31 27 16 06 27 22 14 00 08 20 13 20

S528

XMIT DATA: . 13 02 12 30

EN PARITY: 02 10 26 19 06 14 10 17 04 31 28 00

S529

XMIT DATA: . 27 03 31 29

EN PARITY: 14 04 31 10 07 10 17 30 27 04 28 23

S530

XMIT DATA: . 09 26 12 04

EN PARITY: 25 21 29 00 18 06 27 16 24 20 22 28

S531

XMIT DATA: . 10 20 31 12

EN PARITY: 17 17 09 16 27 14 21 24 26 23 30 27

S532

XMIT DATA: . 15 20 21 20

EN PARITY: 26 09 04 16 14 19 31 10 17 12 29 11

S533

XMIT DATA: . 10 00 13 12

EN PARITY: 11 10 20 11 02 20 25 02 03 17 02 26

S534

XMIT DATA: . 24 21 01 22

EN PARITY: 14 29 25 18 25 02 05 15 10 24 09 16

S535

XMIT DATA: . 28 21 02 12

EN PARITY: 30 03 19 15 10 13 16 22 00 04 19 29

S536

XMIT DATA: . 15 18 08 04

EN PARITY: 02 11 18 28 17 24 25 23 13 07 30 27

S537

XMIT DATA: . 10 29 00 23

EN PARITY: 20 16 25 00 02 14 03 29 00 22 13 07

S538

XMIT DATA: . 02 05 03 18

EN PARITY: 02 28 24 29 06 14 00 02 19 03 18 10

S539

XMIT DATA: . 08 28 12 18

EN PARITY: 26 20 05 05 07 00 03 14 18 08 24 04

S540

XMIT DATA: . 25 05 25 29

EN PARITY: 12 07 01 13 09 30 18 13 10 07 08 08

S541

XMIT DATA: . 02 24 05 24

EN PARITY: 04 00 18 12 25 12 25 25 21 16 15 11

S542

XMIT DATA: . 18 02 31 02

EN PARITY: 26 05 20 04 14 26 12 27 06 14 16 06

S543

XMIT DATA: . 20 30 31 31

EN PARITY: 14 25 18 01 01 26 22 06 27 10 07 18

S544

XMIT DATA: . 01 11 24 19

EN PARITY: 10 26 21 05 20 01 05 24 04 01 18 14

S545

XMIT DATA: . 15 27 30 15

EN PARITY: 23 24 00 09 16 14 30 01 02 10 20 12

S546

XMIT DATA: . 28 14 31 14

EN PARITY: 22 13 27 08 05 05 22 29 00 29 29 02

S547

EN PARITY: 29 19 14 23 28 01 04 00 17 28 30 03

S548

XMIT DATA: . 11 20 24 11

EN PARITY: 14 09 23 00 24 23 14 14 09 23 13 19

S549

XMIT DATA: . 12 09 03 12

EN PARITY: 27 26 05 05 09 16 22 26 31 24 10 18

S550

XMIT DATA: . 25 11 19 14

EN PARITY: 00 10 05 24 22 22 02 27 23 06 00 17

S551

XMIT DATA: . 06 20 05 07

EN PARITY: 00 05 12 14 01 23 03 01 31 05 14 00

S552

XMIT DATA: . 07 16 25 10

EN PARITY: 00 20 06 22 27 06 06 08 24 01 29 25

S553

XMIT DATA: . 01 21 14 31

EN PARITY: 04 11 02 29 14 05 02 20 18 11 20 09

S554

XMIT DATA: . 18 13 27 00

EN PARITY: 21 25 23 01 27 23 04 30 09 24 20 26

S555

XMIT DATA: . 24 16 23 28

EN PARITY: 19 06 29 18 12 02 13 26 25 26 07 21

XMIT DATA: . 11 10 25 29

EN PARITY: 30 27 17 21 31 31 26 00 15 23 02 26

S557

XMIT DATA: . 17 24 28 09

EN PARITY: 31 19 26 10 09 02 09 09 00 22 17 08

S558

XMIT DATA: . 03 28 31 18

EN PARITY: 06 23 19 01 15 07 00 07 29 19 24 21

S559

XMIT DATA: . 05 13 09 23

EN PARITY: 03 06 25 00 26 30 04 30 10 20 05 18

S560

XMIT DATA: . 05 18 31 09

EN PARITY: 13 26 22 14 26 24 05 00 11 01 02 01

S561

XMIT DATA: . 02 25 28 19

EN PARITY: 25 18 04 17 14 05 18 08 23 13 10 00

S562

XMIT DATA: . 26 07 13 20

EN PARITY: 05 23 13 18 16 18 08 19 26 23 10 06

S563

XMIT DATA: . 21 04 28 23

EN PARITY: 03 31 20 00 15 14 26 22 29 01 24 10

S564

XMIT DATA: . 18 01 13 28

EN PARITY: 08 08 21 22 26 05 31 29 04 06 19 26

S565

XMIT DATA: . 27 01 31 01

EN PARITY: 04 21 23 22 05 17 13 18 08 28 20 12

S566

XMIT DATA: . 18 00 02 28

EN PARITY: 12 18 01 12 25 01 03 25 07 08 25 04

S567

XMIT DATA: . 29 31 30 24

EN PARITY: 05 20 03 15 03 25 09 27 18 29 21 22

S568

XMIT DATA: . 10 31 25 28

EN PARITY: 19 07 17 27 18 02 22 24 00 23 17 20

S569

XMIT DATA: . 27 15 11 23

EN PARITY: 25 12 15 10 08 29 03 06 02 16 19 26

S570

XMIT DATA: . 18 20 00 06

EN PARITY: 01 22 03 00 25 05 07 20 00 24 02 16

S571

XMIT DATA: . 25 09 07 15

EN PARITY: 25 10 29 20 14 05 00 25 17 07 15 18

S572

XMIT DATA: . 11 10 28 15

EN PARITY: 04 01 09 09 16 00 07 05 15 11 29 23

S573

XMIT DATA: . 03 09 03 20

EN PARITY: 28 16 30 02 21 19 15 02 18 16 11 11

S574

XMIT DATA: . 25 29 09 29

EN PARITY: 23 00 15 28 03 28 03 03 31 22 27 12

S575

XMIT DATA: . 15 25 13 25

EN PARITY: 04 09 01 23 05 04 28 26 14 05 22 14

S576

XMIT DATA: . 01 19 13 13

EN PARITY: 05 03 15 30 30 04 24 14 26 18 16 15

S577

XMIT DATA: . 30 12 29 17

EN PARITY: 18 04 31 09 01 30 09 29 23 30 15 05

S578

XMIT DATA: . 27 26 19 27

EN PARITY: 06 29 00 21 22 05 19 30 25 18 01 28

S579

XMIT DATA: . 10 05 13 05

EN PARITY: 24 02 26 11 09 09 24 20 00 20 20 25

S580

XMIT DATA: . 22 08 17 23

EN PARITY: 20 17 05 06 10 30 23 00 08 10 19 07

S581

XMIT DATA: . 12 01 29 12

EN PARITY: 05 21 06 00 29 06 05 05 21 06 02 17

S582

XMIT DATA: . 28 21 07 28

EN PARITY: 26 04 09 09 21 22 24 04 13 29 18 15

S583

XMIT DATA: . 03 12 17 05

EN PARITY: 00 18 09 29 24 24 25 26 06 14 00 08

S584

XMIT DATA: . 14 01 09 16

EN PARITY: 00 09 28 05 30 06 07 30 13 09 05 00

S585

XMIT DATA: . 16 22 03 18

EN PARITY: 00 01 14 24 26 14 14 11 29 30 20 03

S586

XMIT DATA: . 30 31 05 13

EN PARITY: 23 12 25 20 05 09 25 01 15 12 01 21

S587

XMIT DATA: . 15 02 26 00

EN PARITY: 31 03 06 30 26 06 23 19 21 29 01 04

S588

XMIT DATA: . 29 22 06 10

EN PARITY: 17 14 20 15 28 25 02 04 03 04 16 31

S589

XMIT DATA: . 12 18 03 20

EN PARITY: 19 26 08 31 13 13 04 00 27 06 25 04

S590

XMIT DATA: . 08 29 10 21

EN PARITY: 13 17 04 18 21 25 21 21 00 24 08 11

S591

XMIT DATA: . 07 10 13 15

EN PARITY: 14 06 17 30 27 16 00 16 20 17 29 31

S592

XMIT DATA: . 09 02 21 06

EN PARITY: 07 14 03 00 04 19 23 19 18 01 09 15

S593

XMIT DATA: . 09 15 13 21

EN PARITY: 02 04 24 05 04 29 09 00 12 30 25 30

S594

XMIT DATA: . 25 03 10 17

EN PARITY: 03 15 23 08 05 09 15 11 06 02 18 00

S595

XMIT DATA: . 04 16 02 01

EN PARITY: 09 06 02 15 22 15 11 17 04 06 18 14

S596

XMIT DATA: . 31 23 10 06

EN PARITY: 07 13 01 00 27 05 04 24 20 30 29 18

S597

XMIT DATA: . 15 30 02 10

EN PARITY: 11 11 31 24 04 09 13 20 23 14 17 04

S598

XMIT DATA: . 26 30 13 30

EN PARITY: 23 31 06 24 09 08 02 15 11 10 01 28

S599

XMIT DATA: . 15 00 25 10

EN PARITY: 28 15 30 28 03 30 07 03 16 11 03 23

S600

XMIT DATA: . 20 13 19 29

EN PARITY: 09 01 07 27 07 03 21 26 15 20 31 24

S601

XMIT DATA: . 18 13 03 10

EN PARITY: 17 16 08 26 15 25 24 29 00 06 08 01

S602

XMIT DATA: . 26 27 12 06

EN PARITY: 03 28 27 18 11 20 07 14 25 22 17 04

S603

XMIT DATA: . 15 01 00 14

EN PARITY: 30 24 07 00 03 09 16 01 00 29 25 22

S604

XMIT DATA: . 03 21 16 27

EN PARITY: 03 18 20 01 05 09 00 03 08 16 27 15

S605

XMIT DATA: . 12 18 10 27

EN PARITY: 23 30 21 21 22 00 16 09 27 12 20 06

S606

XMIT DATA: . 07 21 07 01

EN PARITY: 10 22 19 25 31 17 27 25 15 22 12 12

S607

XMIT DATA: . 03 20 21 20

EN PARITY: 06 00 27 10 07 10 07 07 13 24 26 28

S608

XMIT DATA: . 27 03 02 03

EN PARITY: 23 21 30 06 09 23 10 04 05 09 24 05

S609

EN PARITY: 09 07 27 19 19 23 29 05 04 15 22 27

S610

XMIT DATA: . 19 28 20 08

EN PARITY: 15 23 13 21 30 19 21 20 06 19 27 09

S611

XMIT DATA: . 26 04 17 26

EN PARITY: 14 20 00 31 24 09 17 19 03 15 30 10

S612

XMIT DATA: . 18 09 02 09

EN PARITY: 29 25 04 12 21 21 29 01 00 01 01 03

S613

XMIT DATA: . 24 11 08 06

EN PARITY: 01 08 09 14 18 19 06 00 11 18 17 16

S614

XMIT DATA: . 28 30 20 28

EN PARITY: 09 31 14 00 20 14 09 09 31 14 25 08

S615

XMIT DATA: . 10 31 16 10

EN PARITY: 04 23 21 21 31 24 29 23 02 20 15 27

S616

XMIT DATA: . 07 28 08 09

EN PARITY: 00 15 21 20 29 29 03 04 14 05 00 11

S617

XMIT DATA: . 05 30 21 22

EN PARITY: 00 21 10 09 19 14 16 19 02 21 09 00

XMIT DATA: . 22 24 07 15

EN PARITY: 00 30 05 29 04 05 05 12 20 19 01 07

S619

XMIT DATA: . 19 13 09 02

EN PARITY: 06 28 03 01 09 21 03 30 27 28 30 31

S620

XMIT DATA: . 27 25 04 00

EN PARITY: 13 07 14 19 04 14 06 17 31 20 30 23

S621

XMIT DATA: . 20 24 14 18

EN PARITY: 08 05 01 27 10 03 25 23 07 23 22 13

S622

XMIT DATA: . 28 15 07 01

EN PARITY: 17 04 11 13 02 02 23 00 26 14 03 23

S623

XMIT DATA: . 11 20 18 31

EN PARITY: 02 08 23 15 31 03 31 31 00 29 11 12

S624

XMIT DATA: . 16 18 02 27

EN PARITY: 05 14 08 19 26 22 00 22 01 08 20 13

S625

XMIT DATA: . 21 25 31 14

EN PARITY: 16 05 07 00 23 17 06 17 15 30 21 27

S626

XMIT DATA: . 21 27 02 31

EN PARITY: 25 23 29 09 23 20 21 00 28 19 03 19

S627

XMIT DATA: . 03 07 18 08

EN PARITY: 07 27 06 11 09 21 27 12 14 25 15 00

S628

XMIT DATA: . 23 22 25 30

EN PARITY: 21 14 25 27 24 27 12 08 23 14 15 05

S629

XMIT DATA: . 13 06 18 14

EN PARITY: 16 02 30 00 26 09 23 29 01 19 20 15

S630

XMIT DATA: . 27 19 25 18

EN PARITY: 12 12 13 29 23 21 02 01 06 05 08 23

S631

XMIT DATA: . 04 19 02 19

EN PARITY: 06 13 14 29 21 11 25 27 12 18 30 10

S632

XMIT DATA: . 27 00 03 18

EN PARITY: 10 27 19 10 07 19 16 07 22 12 07 06

S633

XMIT DATA: . 01 02 17 20

EN PARITY: 21 30 16 26 16 07 31 04 27 01 13 29

S634

XMIT DATA: . 15 02 07 18

EN PARITY: 08 22 11 04 27 03 29 20 00 14 11 30

S635

XMIT DATA: . 04 26 28 14

EN PARITY: 07 10 26 15 12 01 16 05 03 24 08 23

S636

XMIT DATA: . 27 30 00 05

EN PARITY: 19 29 16 00 07 21 22 30 00 20 03 24

S637

XMIT DATA: . 07 31 22 26

EN PARITY: 07 15 01 30 09 21 00 07 11 22 26 27

S638

XMIT DATA: . 28 15 18 26

EN PARITY: 06 19 31 31 24 00 22 21 26 28 01 14

S639

XMIT DATA: . 16 31 16 30

EN PARITY: 18 24 17 03 13 08 26 03 27 24 28 28

S640

XMIT DATA: . 07 01 31 01

EN PARITY: 14 00 26 18 16 18 16 16 02 29 04 10

S641

XMIT DATA: . 26 07 25 07

EN PARITY: 06 31 19 14 21 06 18 23 09 21 29 09

S642

XMIT DATA: . 19 08 25 25

EN PARITY: 21 16 26 17 17 06 20 09 23 27 24 26

S643

XMIT DATA: . 17 10 01 11

EN PARITY: 27 06 02 31 19 17 31 01 14 17 26 21

S644

XMIT DATA: . 04 23 08 04

EN PARITY: 05 01 00 13 29 21 08 17 07 27 19 18

S645

XMIT DATA: . 15 21 25 21

EN PARITY: 20 03 23 28 31 31 20 30 00 30 30 07

S646

XMIT DATA: . 29 12 11 14

EN FARITY: 30 11 21 05 15 17 14 00 12 15 08 22

S647

XMIT DATA: . 10 19 01 10

EN FARITY: 21 13 05 00 01 05 21 21 13 05 03 11

S648

XMIT DATA: . 18 13 22 18

EN FARITY: 23 06 31 31 13 29 20 06 25 01 27 26

S649

XMIT DATA: . 16 10 11 21

EN PARITY: 00 27 31 01 20 20 07 23 05 09 00 12

S650

XMIT DATA: . 09 19 31 24

EN PARITY: 00 31 18 21 17 05 22 17 25 31 21 00

S651

XMIT DATA: . 24 29 16 27

EN PARITY: 00 19 09 20 23 09 09 28 01 17 30 16

S652

XMIT DATA: . 17 02 21 25

EN FARITY: 14 10 07 30 21 31 07 19 26 10 19 13

S653

XMIT DATA: . 26 03 23 00

EN PARITY: 02 16 05 17 23 05 14 08 13 01 19 06

S654

XMIT DATA: . 01 29 05 15

EN PARITY: 11 09 30 26 18 07 03 06 16 06 24 02

S655

XMIT DATA: . 10 27 16 30

EN PARITY: 08 23 12 02 25 25 06 00 04 05 07 06

S656

XMIT DATA: . 12 01 15 13

EN PARITY: 25 11 06 27 13 07 13 13 00 20 12 28

S657

XMIT DATA: . 22 15 25 26

EN PARITY: 09 05 11 17 04 24 00 24 30 11 01 02

S658

XMIT DATA: . 31 03 13 05

EN PARITY: 22 09 16 00 06 08 14 08 27 19 31 26

S659

XMIT DATA: . 31 26 25 13

EN PARITY: 03 06 20 21 06 01 31 00 10 17 07 17

S660

XMIT DATA: . 07 16 15 11

EN PARITY: 16 26 14 12 21 31 26 28 05 03 27 00

S661

XMIT DATA: . 06 24 03 19

EN PARITY: 31 05 03 26 29 26 28 11 06 05 27 09

S662

XMIT DATA: . 02 14 15 05

EN PARITY: 22 25 19 00 04 21 06 20 30 17 01 27

S663

XMIT DATA: . 26 17 03 15

EN PARITY: 28 28 02 20 06 31 25 30 14 09 11 06

S664

XMIT DATA: . 23 17 25 17

EN PARITY: 14 02 05 20 31 12 03 26 28 15 19 18

S665

XMIT DATA: . 26 00 07 15

EN PARITY: 18 26 17 18 16 17 22 16 24 28 16 14

S666

XMIT DATA: . 30 25 08 01

EN PARITY: 31 19 22 04 22 16 13 23 26 30 02 20

S667

XMIT DATA: . 27 25 16 15

EN PARITY: 11 24 12 23 26 07 20 01 00 05 12 19

S668

XMIT DATA: . 23 04 10 05

EN PARITY: 16 18 04 27 28 30 22 09 07 29 11 06

S669

XMIT DATA: . 26 19 00 09

EN PARITY: 17 20 22 00 16 31 24 19 00 01 07 29

S670

XMIT DATA: . 16 13 24 04

EN PARITY: 16 27 30 19 21 31 00 16 12 24 04 26

S671

EN PARITY: 14 17 13 13 29 00 24 31 04 10 30 05

S672

XMIT DATA: . 22 13 22 19

EN PARITY: 15 29 08 07 02 11 04 07 26 29 10 10

S673

XMIT DATA: . 16 30 13 30

EN PARITY: 05 00 04 15 22 15 22 22 25 20 23 18

S674

XMIT DATA: . 04 16 03 16

EN PARITY: 14 13 17 05 31 14 15 06 21 31 20 21

S675

XMIT DATA: . 17 11 03 03

EN PARITY: 31 22 04 08 08 14 01 21 06 26 29 04

S676

XMIT DATA: . 08 18 30 12

EN PARITY: 26 14 25 13 17 08 13 30 05 08 04 31

S677

XMIT DATA: . 23 06 11 23

EN PARITY: 09 30 00 02 20 31 11 08 16 26 17 15

S678

XMIT DATA: . 27 31 03 31

EN PARITY: 01 07 06 10 13 13 01 19 00 19 19 16

S679

XMIT DATA: . 20 28 12 05

EN PARITY: 19 12 31 09 27 08 05 00 28 27 11 24

XMIT DATA: . 18 17 30 18

EN PARITY: 31 02 09 00 30 09 31 31 02 09 07 12

S681

XMIT DATA: . 15 02 24 15

EN PARITY: 06 14 13 13 02 20 01 14 03 30 26 04

S682

XMIT DATA: . 22 18 12 31

EN PARITY: 00 26 13 30 01 01 16 06 09 21 00 28

S683

XMIT DATA: . 21 17 13 29

EN PARITY: 00 13 15 31 08 09 24 08 03 13 31 00

S684

XMIT DATA: . 29 20 22 26

EN PARITY: 00 17 21 01 06 21 21 10 30 08 19 22

S685

XMIT DATA: . 08 25 31 03

EN PARITY: 05 18 16 19 31 13 16 17 04 18 17 02

S686

XMIT DATA: . 04 07 06 00

EN PARITY: 25 22 09 08 06 09 05 11 02 30 17 14

S687

XMIT DATA: . 30 20 09 27

EN PARITY: 12 21 19 04 15 16 07 14 22 14 29 25

S688

XMIT DATA: . 18 26 22 19

EN PARITY: 11 06 28 25 03 03 14 00 23 09 16 14

S689

XMIT DATA: . 28 30 27 02

EN PARITY: 03 12 14 26 02 16 02 02 00 01 28 10

S690

XMIT DATA: . 24 27 03 04

EN PARITY: 21 09 12 08 23 29 00 29 19 12 30 25

S691

XMIT DATA: . 13 07 02 09

EN PARITY: 24 21 22 00 14 11 05 11 26 17 13 04

S692

XMIT DATA: . 13 04 03 02

EN PARITY: 07 14 01 31 14 30 13 00 18 08 16 08

S693

XMIT DATA: . 16 22 27 12

EN PARITY: 22 04 05 28 31 13 04 10 09 07 26 00

S694

XMIT DATA: . 14 29 07 17

EN PARITY: 13 09 07 04 20 04 10 12 14 09 26 21

S695

XMIT DATA: . 25 05 27 09

EN PARITY: 24 03 17 00 23 31 14 01 19 08 30 26

S696

XMIT DATA: . 04 08 07 27

EN PARITY: 10 10 25 01 14 13 03 19 05 21 12 14

S697

XMIT DATA: . 06 08 03 08

EN PARITY: 05 25 09 01 13 28 07 04 10 27 17 15

S698

XMIT DATA: . 04 00 16 27

EN PARITY: 15 04 08 15 22 08 24 22 29 10 22 05

S699

XMIT DATA: . 19 03 11 30

EN PARITY: 13 17 24 23 24 22 02 06 04 19 25 01

S700

XMIT DATA: . 26 03 22 27

EN PARITY: 12 29 28 06 04 16 01 30 00 09 28 17

S701

XMIT DATA: . 06 23 18 09

EN PARITY: 22 15 23 26 10 19 24 21 16 20 12 14

S702

XMIT DATA: . 04 17 00 21

EN PARITY: 08 01 24 00 22 13 29 17 00 30 16 20

S703

XMIT DATA: . 22 02 29 23

EN PARITY: 22 26 19 17 31 13 00 22 28 29 23 04

S704

XMIT DATA: . 18 26 27 23

EN PARITY: 05 08 02 02 20 00 29 13 23 18 19 09

S705

XMIT DATA: . 24 02 24 17

EN PARITY: 27 20 11 16 25 12 23 16 04 20 18 18

S706

XMIT DATA: . 22 19 02 19

EN PARITY: 09 00 23 27 24 27 24 24 03 01 06 15

S707

XMIT DATA: . 23 22 07 22

EN PARITY: 05 02 08 09 13 05 27 14 31 13 01 31

S708

XMIT DATA: . 08 12 07 07

EN PARITY: 13 24 23 11 11 05 30 31 14 04 20 23

S709

XMIT DATA: . 11 15 19 28

EN PARITY: 04 05 03 02 08 11 02 19 09 11 23 13

S710

XMIT DATA: . 06 14 12 06

EN PARITY: 21 19 00 25 01 13 12 11 22 04 08 27

S711

XMIT DATA: . 26 13 07 13

EN PARITY: 30 16 14 18 02 02 30 17 00 17 17 22

S712

XMIT DATA: . 01 10 28 09

EN PARITY: 17 28 13 21 26 11 09 00 10 26 12 29

S713

XMIT DATA: . 15 08 19 15

EN PARITY: 13 25 21 00 19 21 13 13 25 21 16 28

S714

XMIT DATA: . 27 25 29 27

EN PARITY: 14 05 02 02 25 01 30 05 07 19 04 23

S715

XMIT DATA: . 24 15 28 13

EN PARITY: 00 04 02 19 30 30 22 14 21 31 00 10

S716

XMIT DATA: . 31 08 02 20

EN PARITY: 00 02 27 13 11 21 29 11 07 02 13 00

S717

XMIT DATA: . 20 01 24 04

EN PARITY: 00 08 31 30 14 31 31 18 19 11 17 24

S718

XMIT DATA: . 11 03 13 07

EN PARITY: 09 15 22 17 13 02 22 08 23 15 08 25

S719

XMIT DATA: . 23 16 14 00

EN PARITY: 03 24 21 11 14 21 09 12 25 19 08 05

S720

XMIT DATA: . 19 01 21 26

EN PARITY: 28 31 17 23 27 22 16 05 24 05 20 03

S721

XMIT DATA: . 15 04 24 17

EN PARITY: 12 14 10 03 07 07 05 00 06 21 22 05

S722

XMIT DATA: . 10 19 26 25

EN PARITY: 07 28 05 04 25 22 25 25 00 30 10 18

S723

XMIT DATA: . 29 26 07 23

EN PARITY: 31 21 28 11 06 20 00 20 17 28 19 03

S724

XMIT DATA: . 02 16 25 21

EN PARITY: 29 31 24 00 05 12 09 12 04 08 02 23

S725

XMIT DATA: . 02 23 07 25

EN PARITY: 16 05 30 13 05 19 02 00 15 11 22 11

S726

XMIT DATA: . 22 24 26 28

EN PARITY: 24 23 09 10 13 02 23 18 21 16 04 00

S727

XMIT DATA: . 05 20 16 08

EN PARITY: 02 21 16 23 01 23 18 28 05 21 04 31

S728

XMIT DATA: . 03 09 26 21

EN PARITY: 29 07 08 00 06 13 05 30 17 11 19 04

S729

XMIT DATA: . 23 11 16 26

EN PARITY: 18 18 03 30 05 02 07 17 09 31 28 05

S730

XMIT DATA: . 14 11 07 11

EN PARITY: 09 03 21 30 02 10 16 23 18 26 08 27

S731

XMIT DATA: . 23 00 22 26

EN PARITY: 27 23 11 27 24 11 29 24 20 18 24 09

S732

XMIT DATA: . 17 07 12 19

EN PARITY: 02 08 29 06 29 24 25 14 23 17 03 30

S733

EN PARITY: 28 20 10 14 23 22 30 19 00 21 10 08

S734

XMIT DATA: . 14 06 15 21

EN PARITY: 24 27 06 04 18 17 29 31 22 01 28 05

S735

XMIT DATA: . 23 08 00 31

EN PARITY: 11 30 29 00 24 02 20 08 00 19 22 01

S736

XMIT DATA: . 24 25 20 06

EN PARITY: 24 04 17 08 13 02 00 24 10 20 06 23

S737

XMIT DATA: . 15 04 26 06

EN PARITY: 09 11 25 25 01 00 20 02 06 15 17 21

S738

XMIT DATA: . 29 25 29 08

EN PARITY: 26 01 12 22 03 28 06 22 23 01 15 15

S739

XMIT DATA: . 24 17 25 17

EN PARITY: 21 00 06 26 29 26 29 29 07 30 14 27

S740

XMIT DATA: . 06 24 16 24

EN PARITY: 09 25 11 21 02 09 26 05 13 02 30 13

S741

XMIT DATA: . 11 28 16 16

EN PARITY: 02 29 06 12 12 09 19 13 05 23 01 06

XMIT DATA: . 12 27 17 10

EN PARITY: 23 09 07 25 11 12 25 17 21 12 06 02

S743

XMIT DATA: . 14 05 28 14

EN PARITY: 31 17 00 03 30 02 28 12 24 23 11 26

S744

XMIT DATA: . 04 02 16 02

EN PARITY: 19 22 05 15 25 25 19 08 00 08 08 24

S745

XMIT DATA: . 30 18 10 21

EN PARITY: 08 10 02 31 04 12 21 00 18 04 28 20

S746

XMIT DATA: . 27 11 17 27

EN PARITY: 02 03 31 00 17 31 02 02 03 31 22 10

S747

XMIT DATA: . 26 03 20 26

EN PARITY: 05 09 25 25 03 30 19 09 16 17 23 06

S748

XMIT DATA: . 29 27 10 02

EN PARITY: 00 23 25 17 19 19 24 05 31 13 00 18

S749

XMIT DATA: . 13 11 25 01

EN PARITY: 00 25 26 02 12 31 20 12 16 25 02 00

S750

XMIT DATA: . 01 30 29 23

EN PARITY: 00 11 13 19 05 13 13 15 17 12 08 29

S751

XMIT DATA: . 12 07 02 16

EN PARITY: 21 27 24 08 02 25 24 11 06 27 11 03

S752

XMIT DATA: . 06 22 05 00

EN PARITY: 07 29 31 12 05 31 21 28 03 17 11 09

S753

XMIT DATA: . 17 30 31 04

EN PARITY: 10 13 08 06 26 24 22 09 29 09 01 07

S754

XMIT DATA: . 27 23 29 08

EN PARITY: 28 05 18 07 16 16 09 00 14 31 24 09

S755

XMIT DATA: . 18 17 04 03

EN PARITY: 16 10 09 23 03 24 03 03 00 19 18 15

S756

XMIT DATA: . 20 04 16 06

EN PARITY: 13 31 10 12 14 01 00 01 08 10 17 07

S757

XMIT DATA: . 25 22 03 31

EN PARITY: 20 13 29 00 09 28 21 28 23 11 25 06

S758

XMIT DATA: . 25 06 16 03

EN PARITY: 22 09 19 02 09 17 25 00 27 12 24 12

S759

XMIT DATA: . 24 29 04 10

EN PARITY: 29 06 21 18 02 25 06 15 31 22 23 00

S760

XMIT DATA: . 09 01 22 11

EN PARITY: 25 31 22 06 30 06 15 10 09 31 23 13

S761

XMIT DATA: . 07 21 04 31

EN PARITY: 20 16 11 00 14 02 09 19 08 12 17 23

S762

XMIT DATA: . 06 12 22 04

EN PARITY: 15 15 07 19 09 25 16 08 21 13 10 09

S763

XMIT DATA: . 05 12 16 12

EN PARITY: 21 07 31 19 25 18 22 06 15 04 11 26

S764

XMIT DATA: . 06 00 24 04

EN PARITY: 26 06 12 26 29 12 20 29 01 15 29 21

S765

XMIT DATA: . 08 16 28 17

EN PARITY: 25 11 20 14 20 29 03 05 06 08 07 19

S766

XMIT DATA: . 23 16 29 04

EN PARITY: 10 01 18 05 06 24 19 17 00 31 18 11

S767

XMIT DATA: . 05 14 27 31

EN PARITY: 29 26 14 23 15 08 20 13 24 30 10 09

S768

XMIT DATA: . 06 11 00 13

EN PARITY: 12 19 20 00 29 25 01 11 00 17 24 30

S769

XMIT DATA: . 29 03 01 14

EN PARITY: 29 23 08 11 02 25 00 29 18 01 14 06

S770

XMIT DATA: . 27 23 04 14

EN PARITY: 21 12 03 03 30 00 01 25 14 27 08 31

S771

XMIT DATA: . 20 03 20 11

EN PARITY: 04 30 28 24 07 10 14 24 06 30 27 27

S772

XMIT DATA: . 29 08 03 08

EN PARITY: 31 00 14 04 20 04 20 20 16 19 05 26

S773

XMIT DATA: . 14 29 22 29

EN PARITY: 21 03 12 31 25 21 04 09 02 25 19 02

S774

XMIT DATA: . 12 10 22 22

EN PARITY: 25 20 14 28 28 21 17 02 09 06 30 14

S775

XMIT DATA: . 28 26 08 18

EN PARITY: 06 21 16 03 12 28 03 08 31 28 14 25

S776

XMIT DATA: . 05 09 10 05

EN PARITY: 13 08 00 07 19 25 10 28 29 06 12 04

S777

XMIT DATA: . 23 25 22 25

EN PARITY: 17 24 09 27 03 03 17 11 00 11 11 29

S778

XMIT DATA: . 19 15 18 31

EN PARITY: 11 18 25 13 23 28 31 00 15 23 10 01

S779

XMIT DATA: . 26 12 08 26

EN PARITY: 25 07 13 00 08 13 25 25 07 13 24 18

S780

XMIT DATA: . 04 07 01 04

EN PARITY: 09 21 03 03 07 19 17 21 22 08 06 14

S781

XMIT DATA: . 20 26 18 25

EN PARITY: 00 06 03 08 17 17 29 09 13 02 00 15

S782

XMIT DATA: . 02 12 03 30

EN PARITY: 00 03 04 25 28 13 01 28 22 03 25 00

S783

XMIT DATA: . 30 19 20 06

EN PARITY: 00 12 02 17 09 02 02 27 08 28 11 20

S784

XMIT DATA: . 28 16 25 22

EN PARITY: 31 26 29 11 25 03 29 12 14 26 12 07

S785

XMIT DATA: . 14 24 09 00

EN PARITY: 16 20 13 28 09 13 31 10 07 08 12 21

S786

XMIT DATA: . 08 19 13 23

EN PARITY: 18 02 11 14 04 29 24 21 20 21 30 16

S787

XMIT DATA: . 26 06 20 11

EN PARITY: 10 09 15 16 22 22 21 00 05 13 29 21

S788

XMIT DATA: . 15 08 23 07

EN PARITY: 22 18 21 06 07 29 07 07 00 17 15 27

S789

XMIT DATA: . 01 23 22 14

EN PARITY: 02 13 18 28 05 30 00 30 11 18 08 16

S790

XMIT DATA: . 03 24 07 13

EN PARITY: 01 02 20 00 21 10 31 10 06 12 03 14

S791

XMIT DATA: . 03 14 22 07

EN PARITY: 24 21 17 25 21 08 03 00 26 28 29 28

S792

XMIT DATA: . 29 20 23 18

EN PARITY: 20 14 31 15 25 03 14 27 13 24 06 00

S793

XMIT DATA: . 21 30 24 12

EN PARITY: 03 13 24 14 19 14 27 18 21 13 06 02

S794

XMIT DATA: . 16 31 23 13

EN PARITY: 01 22 12 00 05 25 21 17 11 28 08 06

S795

EN PARITY: 27 27 16 17 21 03 22 11 31 02 18 21

S796

XMIT DATA: . 09 28 22 28

EN PARITY: 31 16 13 17 03 15 24 14 27 23 12 04

S797

XMIT DATA: . 14 00 29 23

EN PARITY: 04 14 28 04 20 28 01 20 30 27 20 31

S798

XMIT DATA: . 11 22 10 08

EN PARITY: 03 12 01 05 01 20 07 09 14 11 16 17

S799

XMIT DATA: . 06 22 20 23

EN PARITY: 18 30 15 09 14 29 17 08 00 13 15 12

S800

XMIT DATA: . 09 05 26 13

EN PARITY: 20 04 05 06 27 11 01 02 29 19 18 21

S801

XMIT DATA: . 14 12 00 02

EN PARITY: 28 17 01 00 20 03 30 12 00 08 29 19

S802

XMIT DATA: . 20 07 30 05

EN PARITY: 20 06 11 12 25 03 00 20 15 30 05 14

S803

XMIT DATA: . 26 06 23 05

EN PARITY: 31 28 07 07 19 00 30 03 05 26 11 13

XMIT DATA: . 01 07 01 12

EN PARITY: 23 19 10 29 16 18 05 29 14 19 26 26

S805

XMIT DATA: . 20 11 07 11

EN PARITY: 13 00 05 23 01 23 01 01 22 17 09 04

S806

XMIT DATA: . 05 20 24 20

EN PARITY: 31 07 28 13 03 31 23 21 25 03 17 25

S807

XMIT DATA: . 28 18 24 24

EN PARITY: 03 01 05 10 10 31 08 25 21 14 19 05

S808

XMIT DATA: . 10 04 11 15

EN PARITY: 14 31 22 07 28 10 07 11 13 10 05 03

S809

XMIT DATA: . 09 21 18 09

EN PARITY: 02 11 00 16 17 03 18 10 20 14 28 23

S810

XMIT DATA: . 06 03 24 03

EN PARITY: 08 29 21 26 07 07 08 12 00 12 12 20

S811

XMIT DATA: . 17 27 15 13

EN PARITY: 12 15 03 02 06 10 13 00 27 06 18 30

S812

XMIT DATA: . 04 28 11 04

EN PARITY: 03 16 02 00 11 02 03 03 16 02 29 15

S813

XMIT DATA: . 23 16 30 23

EN PARITY: 21 31 07 07 16 17 08 31 24 11 14 05

S814

XMIT DATA: . 01 04 15 03

EN PARITY: 00 14 07 11 08 08 20 21 02 25 00 27

S815

XMIT DATA: . 25 28 07 19

EN PARITY: 00 07 23 03 10 02 30 10 24 07 03 00

S816

XMIT DATA: . 19 17 01 14

EN PARITY: 00 28 25 08 21 25 25 26 11 10 12 01

S817

XMIT DATA: . 10 22 03 24

EN PARITY: 13 04 20 12 03 07 20 28 05 04 28 16

S818

XMIT DATA: . 05 29 21 00

EN PARITY: 22 01 02 10 21 02 13 18 16 11 28 31

S819

XMIT DATA: . 11 17 02 06

EN PARITY: 15 25 12 05 23 20 29 31 01 31 19 22

S820

XMIT DATA: . 04 14 01 12

EN PARITY: 18 21 27 22 24 24 31 00 09 02 20 31

S821

XMIT DATA: . 27 11 06 16

EN PARITY: 24 15 31 14 16 20 16 16 00 08 27 26

S822

XMIT DATA: . 30 06 24 05

EN PARITY: 25 02 15 10 09 19 00 19 12 15 11 22

S823

XMIT DATA: . 07 29 16 02

EN PARITY: 30 25 01 00 31 18 13 18 14 28 07 05

S824

XMIT DATA: . 07 05 24 16

EN PARITY: 29 31 08 03 31 11 07 00 04 10 20 10

S825

XMIT DATA: . 20 01 06 15

EN PARITY: 01 05 13 27 03 07 05 26 02 29 14 00

S826

XMIT DATA: . 31 19 29 28

EN PARITY: 07 02 29 05 17 05 26 15 31 02 14 25

S827

XMIT DATA: . 22 13 06 02

EN PARITY: 30 24 28 00 09 03 31 08 12 10 11 14

S828

XMIT DATA: . 05 10 29 06

EN PARITY: 26 26 22 08 31 07 24 12 13 25 15 31

S829

XMIT DATA: . 21 10 24 10

EN PARITY: 13 22 02 08 07 27 29 05 26 06 28 23

S830

XMIT DATA: . 05 00 20 06

EN PARITY: 23 05 10 23 01 10 30 01 19 26 01 13

S831

XMIT DATA: . 12 24 18 11

EN PARITY: 07 28 30 09 30 01 16 21 05 12 22 08

S832

XMIT DATA: . 14 24 01 06

EN PARITY: 15 19 27 21 05 20 08 11 00 02 27 28

S833

XMIT DATA: . 21 09 04 02

EN PARITY: 01 23 09 14 26 12 30 25 20 17 15 31

S834

XMIT DATA: . 05 28 00 25

EN PARITY: 10 08 30 00 01 07 19 28 00 11 20 17

S835

XMIT DATA: . 01 16 19 09

EN PARITY: 01 14 12 28 03 07 00 01 27 19 09 05

S836

XMIT DATA: . 04 14 06 09

EN PARITY: 13 10 16 16 17 00 19 07 09 04 12 02

S837

XMIT DATA: . 30 16 30 28

EN PARITY: 06 17 18 20 22 15 09 20 05 17 04 04

S838

XMIT DATA: . 01 12 16 12

EN PARITY: 02 00 09 06 30 06 30 30 24 08 21 23

S839

XMIT DATA: . 09 01 29 01

EN PARITY: 13 16 10 02 07 13 06 31 03 07 08 03

S840

XMIT DATA: . 10 15 29 29

EN PARITY: 07 30 09 18 18 13 11 03 31 05 17 09

S841

XMIT DATA: . 18 23 12 27

EN PARITY: 05 13 24 16 10 18 16 12 02 18 09 07

S842

XMIT DATA: . 21 31 15 21

EN PARITY: 25 12 00 22 08 07 15 18 01 05 10 06

S843

XMIT DATA: . 14 07 29 07

EN PARITY: 11 20 31 04 16 16 11 28 00 28 28 01

S844

XMIT DATA: . 08 26 27 02

EN PARITY: 28 27 07 25 14 18 02 00 26 14 15 19

S845

XMIT DATA: . 23 10 12 23

EN PARITY: 07 22 25 00 12 25 07 07 22 25 20 27

S846

XMIT DATA: . 06 22 19 06

EN PARITY: 31 13 16 16 22 08 11 13 29 12 05 09

S847

XMIT DATA: . 30 23 27 07

EN PARITY: 00 05 16 12 11 11 01 31 25 03 00 26

S848

XMIT DATA: . 03 10 16 17

EN PARITY: 00 16 06 07 18 25 19 18 29 16 07 00

S849

XMIT DATA: . 17 08 30 05

EN PARITY: 00 10 03 11 31 03 03 04 12 18 28 30

S850

XMIT DATA: . 18 24 07 29

EN PARITY: 02 23 01 28 07 16 01 10 09 23 10 22

S851

XMIT DATA: . 09 20 31 00

EN PARITY: 24 30 25 18 31 25 02 15 22 12 10 13

S852

XMIT DATA: . 12 08 25 14

EN PARITY: 27 03 28 09 06 01 20 13 30 13 17 24

S853

XMIT DATA: . 23 05 30 28

EN PARITY: 15 31 26 24 29 29 13 00 21 25 01 13

S854

XMIT DATA: . 26 12 14 22

EN PARITY: 29 27 13 05 22 01 22 22 00 11 26 04

S855

XMIT DATA: . 19 14 29 09

EN PARITY: 03 25 27 18 21 17 00 17 28 27 12 24

S856

XMIT DATA: . 16 20 22 25

EN PARITY: 19 03 30 00 13 15 02 15 05 10 16 09

S857

EN PARITY: 20 13 11 07 13 12 16 00 23 18 01 18

S858

XMIT DATA: . 01 30 14 27

EN PARITY: 30 09 02 26 07 16 09 04 25 20 05 00

S859

XMIT DATA: . 13 17 20 10

EN PARITY: 16 25 20 09 08 09 04 27 13 25 05 03

S860

XMIT DATA: . 24 02 14 25

EN PARITY: 19 29 10 00 21 07 13 11 28 18 12 05

S861

XMIT DATA: . 09 18 20 14

EN PARITY: 04 04 24 11 13 16 29 28 02 03 27 13

S862

XMIT DATA: . 31 18 29 18

EN PARITY: 02 24 25 11 16 26 20 09 04 14 10 06

S863

XMIT DATA: . 09 00 01 14

EN PARITY: 06 09 18 06 30 18 19 30 17 04 30 02

S864

XMIT DATA: . 28 29 15 12

EN PARITY: 16 10 19 21 19 30 22 31 09 28 24 11

S865

XMIT DATA: . 05 29 30 14

EN PARITY: 27 17 26 31 09 01 11 12 00 25 26 10

XMIT DATA: . 31 21 23 25

EN PARITY: 30 06 21 05 04 28 19 03 01 08 27 13

S867

XMIT DATA: . 09 10 00 03

EN PARITY: 18 11 19 00 30 16 17 10 00 12 01 08

S868

XMIT DATA: . 30 22 17 21

EN PARITY: 30 05 28 10 07 16 00 30 26 17 21 09

S869

XMIT DATA: . 23 05 14 21

EN PARITY: 02 18 22 22 08 00 17 16 21 23 28 25

S870

XMIT DATA: . 19 22 19 10

EN PARITY: 14 08 15 01 24 27 21 01 09 08 23 23

S871

XMIT DATA: . 30 28 22 28

EN PARITY: 25 00 21 14 19 14 19 19 29 11 31 06

S872

XMIT DATA: . 21 30 20 30

EN PARITY: 02 22 18 25 16 02 14 13 07 16 11 07

S873

XMIT DATA: . 18 27 20 20

EN PARITY: 16 19 21 15 15 02 12 07 13 09 08 21

S874

XMIT DATA: . 15 06 28 26

EN PARITY: 09 02 29 22 18 15 22 28 25 15 21 16

S875

XMIT DATA: . 31 13 27 31

EN PARITY: 03 28 00 24 11 16 27 15 30 09 18 14

S876

XMIT DATA: . 05 16 20 16

EN PARITY: 12 01 13 23 22 22 12 10 00 10 10 30

S877

XMIT DATA: . 11 04 26 25

EN PARITY: 10 26 16 03 05 15 25 00 04 05 27 17

S878

XMIT DATA: . 06 18 28 06

EN PARITY: 16 24 03 00 28 03 16 16 24 03 01 26

S879

XMIT DATA: . 14 24 17 14

EN PARITY: 13 02 22 22 24 11 12 02 20 28 09 21

S880

XMIT DATA: . 19 06 26 16

EN PARITY: 00 09 22 28 12 12 30 13 03 07 00 04

S881

XMIT DATA: . 07 18 22 08

EN PARITY: 00 22 14 16 15 03 17 15 20 22 16 00

S882

XMIT DATA: . 08 11 19 09

EN PARITY: 00 18 07 12 13 07 07 23 28 15 10 19

S883

XMIT DATA: . 15 29 16 20

EN PARITY: 25 06 30 10 16 22 30 18 21 06 18 24

S884

XMIT DATA: . 21 01 13 00

EN PARITY: 29 19 03 15 13 03 25 27 24 28 18 02

S885

XMIT DATA: . 28 11 03 05

EN PARITY: 26 07 10 21 14 30 01 02 19 02 08 29

S886

XMIT DATA: . 06 09 19 10

EN PARITY: 27 13 04 29 20 20 02 00 31 03 30 02

S887

XMIT DATA: . 04 28 05 24

EN PARITY: 20 26 02 09 24 30 24 24 00 12 04 23

S888

XMIT DATA: . 17 05 20 21

EN PARITY: 07 03 26 15 31 08 00 08 10 26 28 29

S889

XMIT DATA: . 22 01 24 03

EN PARITY: 17 07 19 00 02 27 25 27 09 18 22 21

S890

XMIT DATA: . 22 21 20 24

EN PARITY: 01 02 12 16 02 28 22 00 06 15 30 15

S891

XMIT DATA: . 30 19 05 26

EN PARITY: 19 21 25 04 16 22 21 23 03 01 09 00

S892

XMIT DATA: . 02 08 01 18

EN PARITY: 22 03 01 21 11 21 23 26 02 03 09 07

S893

XMIT DATA: . 29 25 05 03

EN PARITY: 17 20 18 00 31 16 02 12 10 15 28 09

S894

XMIT DATA: . 21 15 01 05

EN PARITY: 23 23 29 12 02 22 20 10 25 07 26 02

S895

XMIT DATA: . 13 15 20 15

EN PARITY: 25 29 03 12 22 04 01 21 23 05 18 14

S896

XMIT DATA: . 21 00 30 05

EN PARITY: 14 21 15 14 19 15 17 19 08 23 19 25

S897

XMIT DATA: . 10 20 27 28

EN PARITY: 22 18 17 31 17 19 24 13 21 10 29 12

S898

XMIT DATA: . 09 20 19 05

EN PARITY: 26 08 04 13 21 30 12 28 00 03 04 18

S899

XMIT DATA: . 13 31 06 03

EN PARITY: 19 14 31 09 23 10 17 07 30 11 26 02

S900

XMIT DATA: . 21 18 00 07

EN PARITY: 15 12 17 00 19 22 08 18 00 28 30 11

S901

XMIT DATA: . 19 24 08 31

EN PARITY: 10 00 10 18 14 22 00 10 04 08 31 21

S902

XMIT DATA: . 06 09 05 31

EN PARITY: 25 15 24 24 11 00 08 22 31 06 10 03

S903

XMIT DATA: . 17 24 17 18

EN PARITY: 05 11 27 30 29 26 31 30 21 11 06 06

S904

XMIT DATA: . 19 10 24 10

EN PARITY: 03 00 31 05 17 05 17 17 20 12 13 14

S905

XMIT DATA: . 31 19 01 19

EN PARITY: 25 24 15 03 22 25 05 02 16 22 12 16

S906

XMIT DATA: . 15 26 01 01

EN PARITY: 22 17 31 27 27 25 28 16 02 21 11 31

S907

XMIT DATA: . 27 14 10 04

EN PARITY: 21 25 20 24 15 27 24 10 03 27 31 22

S908

XMIT DATA: . 13 02 26 13

EN PARITY: 07 10 00 29 12 22 26 27 19 21 15 05

S909

XMIT DATA: . 09 22 01 22

EN PARITY: 28 30 02 06 24 24 28 18 00 18 18 19

S910

XMIT DATA: . 12 23 04 03

EN PARITY: 18 04 22 07 09 27 03 00 23 09 26 08

S911

XMIT DATA: . 14 15 10 14

EN PARITY: 22 29 07 00 10 07 22 22 29 07 30 04

S912

XMIT DATA: . 05 29 08 05

EN PARITY: 02 25 24 24 29 12 28 25 01 10 21 31

S913

XMIT DATA: . 17 14 04 22

EN PARITY: 00 21 24 10 28 28 19 02 07 16 00 23

S914

XMIT DATA: . 16 15 24 11

EN PARITY: 00 24 05 22 27 07 08 27 01 24 22 00

S915

XMIT DATA: . 11 12 17 21

EN PARITY: 00 15 16 28 02 16 16 06 10 27 18 17

S916

XMIT DATA: . 27 20 22 01

EN PARITY: 03 14 19 18 22 24 19 15 31 14 15 29

S917

XMIT DATA: . 31 30 02 00

EN PARITY: 20 17 07 27 02 07 03 26 29 10 15 25

S918

XMIT DATA: . 10 12 07 09

EN PARITY: 04 16 18 31 05 19 30 25 17 25 11 20

S919

EN PARITY: 26 02 23 20 01 01 25 00 13 07 19 25

S920

XMIT DATA: . 23 10 09 29

EN PARITY: 01 04 25 21 29 19 29 29 00 28 23 06

S921

XMIT DATA: . 08 09 01 31

EN PARITY: 16 07 04 27 13 11 00 11 18 04 10 20

S922

XMIT DATA: . 24 30 29 07

EN PARITY: 08 16 17 00 25 26 03 26 21 15 24 31

S923

XMIT DATA: . 24 31 01 29

EN PARITY: 30 25 28 22 25 10 24 00 14 27 19 27

S924

XMIT DATA: . 19 17 09 04

EN PARITY: 17 31 03 23 22 24 31 06 07 30 21 00

S925

XMIT DATA: . 25 11 30 15

EN PARITY: 24 07 30 31 12 31 06 04 25 07 21 16

S926

XMIT DATA: . 20 03 09 07

EN PARITY: 08 01 15 00 13 22 25 28 18 27 10 21

S927

XMIT DATA: . 31 27 30 09

EN PARITY: 06 06 20 28 25 24 01 18 03 16 04 25

XMIT DATA: . 02 27 01 27

EN PARITY: 03 20 07 28 24 23 30 31 06 09 15 05

S929

XMIT DATA: . 31 00 19 09

EN PARITY: 05 31 27 05 17 27 08 17 11 06 17 03

S930

XMIT DATA: . 18 01 26 10

EN PARITY: 24 15 08 13 08 17 29 02 31 18 20 28

S931

XMIT DATA: . 21 01 17 09

EN PARITY: 04 11 23 02 31 19 28 10 00 07 23 15

S932

XMIT DATA: . 02 13 14 07

EN PARITY: 17 05 13 21 06 18 08 16 19 12 04 25

S933

XMIT DATA: . 31 15 00 16

EN PARITY: 27 28 08 00 17 24 11 15 00 10 19 12

S934

XMIT DATA: . 17 29 11 13

EN PARITY: 17 21 18 15 22 24 00 17 23 11 13 31

S935

XMIT DATA: . 14 21 09 13

EN PARITY: 03 27 29 29 12 00 11 24 13 14 18 07

S936

XMIT DATA: . 08 29 08 15

EN PARITY: 09 12 26 19 20 04 13 19 31 12 14 14

S937

XMIT DATA: . 17 18 29 18

EN PARITY: 07 00 13 09 08 09 08 08 01 28 02 05

S938

XMIT DATA: . 13 17 30 17

EN PARITY: 03 29 27 07 24 03 09 25 22 24 28 22

S939

XMIT DATA: . 27 04 30 30

EN PARITY: 24 08 13 26 26 03 10 22 25 31 12 13

S940

XMIT DATA: . 26 05 18 23

EN PARITY: 31 03 01 29 27 26 29 18 07 26 13 24

S941

XMIT DATA: . 02 25 04 02

EN PARITY: 16 18 00 20 28 24 04 26 17 31 27 09

S942

XMIT DATA: . 21 24 30 24

EN PARITY: 10 19 25 14 29 29 10 15 00 15 15 17

S943

XMIT DATA: . 28 06 23 07

EN PARITY: 15 23 24 16 21 26 07 00 06 21 04 11

S944

XMIT DATA: . 05 27 18 05

EN PARITY: 24 20 16 00 18 16 24 24 20 16 19 23

S945

XMIT DATA: . 09 20 11 09

EN PARITY: 25 03 29 29 20 28 10 03 30 18 31 13

S946

XMIT DATA: . 08 05 23 24

EN PARITY: 00 31 29 18 10 10 17 25 16 22 00 06

S947

XMIT DATA: . 22 27 29 12

EN PARITY: 00 29 09 24 26 16 11 26 30 29 24 00

S948

XMIT DATA: . 12 28 08 31

EN PARITY: 00 27 22 10 25 22 22 14 18 26 15 08

S949

XMIT DATA: . 26 01 24 30

EN PARITY: 07 05 17 15 24 29 17 27 13 05 27 20

S950

XMIT DATA: . 13 19 25 00

EN PARITY: 01 08 16 26 25 16 07 04 20 18 27 03

S951

XMIT DATA: . 18 28 16 21

EN PARITY: 23 22 15 13 09 17 19 03 08 03 12 01

S952

XMIT DATA: . 05 31 08 15

EN PARITY: 04 25 06 01 30 30 03 00 02 16 17 03

S953

XMIT DATA: . 06 18 21 20

EN PARITY: 30 23 03 31 20 17 20 20 00 10 06 14

S954

XMIT DATA: . 11 21 30 13

EN PARITY: 22 16 23 26 02 12 00 12 15 23 18 01

S955

XMIT DATA: . 29 19 20 16

EN PARITY: 11 22 08 00 03 04 07 04 31 27 29 13

S956

XMIT DATA: . 29 13 30 20

EN PARITY: 19 03 10 24 03 18 29 00 05 26 17 26

S957

XMIT DATA: . 17 08 21 23

EN PARITY: 08 13 07 06 24 29 13 14 16 19 31 00

S958

XMIT DATA: . 03 12 19 27

EN PARITY: 29 16 19 13 28 13 14 23 03 16 31 22

S959

XMIT DATA: . 01 07 21 16

EN PARITY: 11 30 27 00 02 24 03 10 15 26 18 31

S960

XMIT DATA: . 13 26 19 21

EN PARITY: 14 14 01 10 03 29 30 15 07 22 23 03

S961

XMIT DATA: . 25 26 30 26

EN PARITY: 07 01 16 10 29 06 19 13 14 21 27 09

S962

XMIT DATA: . 13 00 17 21

EN PARITY: 09 13 26 09 08 26 11 08 12 14 08 07

S963

XMIT DATA: . 15 30 04 18

S964

XMIT DATA: . 31 30 08 21

EN PARITY: 23 12 06 25 13 17 10 18 00 16 06 27

S965

XMIT DATA: . 25 02 05 16

EN PARITY: 08 09 02 31 14 15 11 22 17 28 23 03

S966

XMIT DATA: . 13 27 00 22

EN PARITY: 26 10 11 00 08 29 12 27 00 18 17 28

S967

XMIT DATA: . 08 20 12 02

EN PARITY: 08 31 15 27 24 29 00 08 06 12 02 13

S968

XMIT DATA: . 05 31 21 02

EN PARITY: 07 26 20 20 28 00 12 29 02 05 15 16

S969

XMIT DATA: . 11 20 11 27

EN PARITY: 21 28 04 17 01 23 02 17 13 28 05 05

S970

XMIT DATA: . 08 15 20 15

EN PARITY: 16 00 02 21 11 21 11 11 30 10 25 09

S971

XMIT DATA: . 02 08 19 08

EN PARITY: 07 20 26 16 29 07 21 03 24 29 10 24

S972

XMIT DATA: . 26 23 19 19

EN PARITY: 29 11 02 04 04 07 18 24 03 13 28 02

S973

XMIT DATA: . 04 09 15 06

EN PARITY: 13 07 30 20 26 04 20 15 16 04 02 29

S974

XMIT DATA: . 25 03 23 25

EN PARITY: 22 15 00 01 10 29 23 04 08 13 26 21

S975

XMIT DATA: . 31 29 19 29

EN PARITY: 18 17 03 05 20 20 18 27 00 27 27 08

S976

XMIT DATA: . 10 14 06 16

EN PARITY: 27 06 29 22 31 04 16 00 14 31 23 12

S977

XMIT DATA: . 09 26 15 09

EN PARITY: 29 01 22 00 15 22 29 29 01 22 17 06

S978

XMIT DATA: . 21 01 12 21

EN PARITY: 03 07 20 20 01 10 18 07 19 15 13 02

S979

XMIT DATA: . 11 09 06 29

EN PARITY: 00 13 20 15 18 18 08 03 22 24 00 14

S980

XMIT DATA: . 24 26 20 28

EN PARITY: 00 20 21 29 04 22 12 04 19 20 29 00

S981

EN PARITY: 00 26 24 18 03 24 24 05 15 04 27 11

S982

XMIT DATA: . 04 30 29 19

EN PARITY: 16 09 08 27 29 20 08 26 02 09 26 01

S983

XMIT DATA: . 02 17 03 00

EN PARITY: 30 11 22 04 03 22 16 23 01 15 26 07

S984

XMIT DATA: . 15 10 22 31

EN PARITY: 06 24 27 02 21 08 17 07 11 07 28 30

S985

XMIT DATA: . 09 13 11 27

EN PARITY: 23 03 14 30 19 19 07 00 25 22 08 07

S986

XMIT DATA: . 14 15 31 01

EN PARITY: 19 06 07 13 01 08 01 01 00 18 14 05

S987

XMIT DATA: . 12 31 19 02

EN PARITY: 24 22 06 04 25 28 00 28 27 06 15 30

S988

XMIT DATA: . 20 17 01 22

EN PARITY: 12 24 11 00 07 23 16 23 13 26 20 02

S989

XMIT DATA: . 20 02 19 01

EN PARITY: 17 07 18 29 07 15 20 00 09 04 08 04

XMIT DATA: . 08 11 31 06

EN PARITY: 11 02 16 14 29 20 02 05 22 17 13 00

S991

XMIT DATA: . 07 28 17 26

EN PARITY: 20 22 17 02 10 02 05 06 07 22 13 24

S992

XMIT DATA: . 30 16 31 22

EN PARITY: 12 19 26 00 25 29 07 18 27 04 15 13

S993

XMIT DATA: . 02 04 17 31

EN PARITY: 05 05 30 18 07 20 19 27 16 24 06 07

S994

XMIT DATA: . 03 04 19 04

EN PARITY: 16 30 22 18 20 14 17 02 05 31 26 21

S995

XMIT DATA: . 02 00 08 31

EN PARITY: 21 02 04 21 11 04 12 11 28 05 11 16

S996

XMIT DATA: . 27 19 23 15

EN PARITY: 20 26 12 25 12 11 01 03 02 27 30 18

S997

XMIT DATA: . 13 19 11 31

EN PARITY: 06 28 14 03 02 08 18 15 00 22 14 26

S998

XMIT DATA: . 03 25 09 22

EN PARITY: 11 21 25 13 05 27 12 24 08 10 06 07

JTIDS O.S.
REQUEST?

FILE NAME A

LONG CODE (31/15)

L000

L000 XMIT DATA: . 02 01 00 05 04 03 08 07 06 11 10 09 14 13 12
EN PARITY: 25 00 01 26 15 23 28 00 03 08 22 17 19 22 18 26

L001 XMIT DATA: . 26 01 00 28 23 15 08 03 00 19 17 22 26 18 22
EN PARITY: 10 20 18 09 15 06 28 07 09 16 20 02 03 11 18 28

L002 XMIT DATA: . 09 18 20 28 06 15 16 09 07 03 02 20 28 18 11
EN PARITY: 29 08 25 31 13 08 07 21 09 03 17 19 16 09 04 24

L003 XMIT DATA: . 31 25 08 07 08 13 03 09 21 16 19 17 24 04 09
EN PARITY: 14 18 19 29 15 20 10 06 09 00 08 01 13 07 00 27

L004 XMIT DATA: . 29 19 18 10 20 15 00 09 06 13 01 08 27 00 07
EN PARITY: 16 00 06 19 28 27 30 16 01 18 17 10 13 25 31 07

L005 XMIT DATA: . 19 06 00 30 27 28 18 01 16 13 10 17 07 31 25
EN PARITY: 21 01 07 02 18 29 31 12 05 11 01 09 00 08 04 25

L006 XMIT DATA: . 02 07 01 31 29 18 11 05 12 00 09 01 25 04 08
EN PARITY: 21 09 22 27 28 00 12 14 19 02 02 18 20 04 07 07

L007 XMIT DATA: . 27 22 09 12 00 28 02 19 14 20 18 02 07 07 04
EN PARITY: 09 00 01 06 08 03 02 09 29 28 00 01 12 20 16 20

L008 XMIT DATA: . 06 01 00 02 03 08 28 29 09 12 01 00 20 16 20
EN PARITY: 26 26 02 09 14 15 17 13 29 20 26 17 16 05 14 26

L009 XMIT DATA: . 09 02 26 17 15 14 20 29 13 16 17 26 26 14 05
EN PARITY: 29 22 23 31 20 04 31 24 17 29 23 06 09 19 27 07

L010 XMIT DATA: . 31 23 22 31 04 20 29 17 24 09 06 23 07 27 19
EN PARITY: 06 07 09 20 24 20 22 04 28 22 27 11 20 16 12 12

L011 XMIT DATA: . 20 09 07 22 20 24 22 28 04 20 11 27 12 12 16
EN PARITY: 22 07 30 31 04 17 07 14 15 10 05 19 17 29 16 20

L012 XMIT DATA: . 31 30 07 07 17 04 10 15 14 17 19 05 20 16 29
EN PARITY: 27 20 27 15 25 23 13 23 26 19 27 01 21 31 04 25

L013 XMIT DATA: . 15 27 20 13 23 25 19 26 23 21 01 27 25 04 31
EN PARITY: 07 12 25 02 12 20 23 31 26 22 09 20 03 23 25 18

L014 XMIT DATA: . 02 25 12 23 20 12 22 26 31 03 20 09 18 25 23
EN PARITY: 22 05 11 31 31 24 10 25 08 27 31 16 01 00 19 29

L015 XMIT DATA: . 31 11 05 10 24 31 27 08 25 01 16 31 29 19 00
EN PARITY: 06 18 19 29 21 09 01 10 18 14 31 16 03 16 11 04

L016 XMIT DATA: . 29 19 18 01 09 21 14 18 10 03 16 31 04 11 16
EN PARITY: 10 11 00 23 28 11 10 11 15 13 16 00 02 28 29 04

L017 XMIT DATA: . 23 00 11 10 11 28 13 15 11 02 00 16 04 29 28
EN PARITY: 11 22 18 20 22 15 24 16 31 25 04 09 00 31 02 12

L018 XMIT DATA: . 20 18 22 24 15 22 25 31 16 00 09 04 12 02 31
EN PARITY: 09 27 28 17 28 14 06 13 29 03 23 20 27 06 07 23

L019 XMIT DATA: . 17 28 27 06 14 28 03 29 13 27 20 23 23 07 06
EN PARITY: 18 07 05 06 22 12 08 29 13 06 06 21 20 19 17 26

L020 XMIT DATA: . 06 05 07 08 12 22 06 13 29 20 21 06 26 17 19
EN PARITY: 07 04 13 17 26 00 03 08 27 22 13 00 00 21 09 03

L021 XMIT DATA: . 17 13 04 03 00 26 22 27 08 00 00 13 03 09 21
EN PARITY: 11 20 29 11 00 20 29 21 17 24 15 23 21 14 12 09

L022 XMIT DATA: . 11 29 20 29 20 00 24 17 21 21 23 15 09 12 14
EN PARITY: 19 15 10 15 23 22 25 14 02 27 29 10 16 27 18 21

L023 XMIT DATA: . 15 10 15 25 22 23 27 02 14 16 10 29 21 18 27

EN PARITY: 25 18 00 26 09 06 01 23 19 04 12 18 31 09 24 29

L024 XMIT DATA: . 26 00 18 01 06 09 04 19 23 31 18 12 29 24 09
EN PARITY: 30 12 10 08 01 25 21 29 00 27 26 14 24 28 01 11

L025 XMIT DATA: . 08 10 12 21 25 01 27 00 29 24 14 26 11 01 28
EN PARITY: 23 05 04 14 22 12 06 11 27 31 10 24 05 19 09 05

L026 XMIT DATA: . 14 04 05 06 12 22 31 27 11 05 24 10 05 09 19
EN PARITY: 13 23 06 12 18 31 19 22 19 02 03 25 09 16 18 21

L027 XMIT DATA: . 12 06 23 19 31 18 02 19 22 09 25 03 21 18 16
EN PARITY: 21 16 29 20 21 12 17 13 24 02 20 20 04 13 21 15

L028 XMIT DATA: . 20 29 16 17 12 21 02 24 13 04 20 20 15 21 13
EN PARITY: 23 15 09 08 26 23 00 08 29 20 07 21 27 26 17 13

L029 XMIT DATA: . 08 09 15 00 23 26 20 29 08 27 21 07 13 17 26
EN PARITY: 04 02 21 29 27 04 31 19 00 09 05 14 05 08 12 24

L030 XMIT DATA: . 29 21 02 31 04 27 09 00 19 05 14 05 24 12 08
EN PARITY: 03 24 01 17 09 10 17 06 17 20 05 11 19 07 10 01

L031 XMIT DATA: . 17 01 24 17 10 09 20 17 06 19 11 05 01 10 07
EN PARITY: 15 14 09 13 11 03 30 09 18 28 20 01 13 30 21 28

L032 XMIT DATA: . 13 09 14 30 03 11 28 18 09 13 01 20 28 21 30
EN PARITY: 23 18 27 05 11 15 03 15 22 09 31 28 30 09 00 02

L033 XMIT DATA: . 05 27 18 03 15 11 09 22 15 30 28 31 02 00 09
EN PARITY: 26 20 02 01 14 27 11 24 06 17 28 24 08 15 31 17

L034 XMIT DATA: . 01 02 20 11 27 14 17 06 24 08 24 28 17 31 15
EN PARITY: 30 05 01 14 12 19 03 30 11 13 18 16 11 27 29 11

L035 XMIT DATA: . 14 01 05 03 19 12 13 11 30 11 16 18 11 29 27
EN PARITY: 04 18 09 00 29 11 04 09 15 31 31 21 05 23 00 19

L036 XMIT DATA: . 00 09 18 04 11 29 31 15 09 05 21 31 19 00 23
EN PARITY: 22 24 23 14 09 09 17 14 10 26 12 11 21 28 12 21

L037 XMIT DATA: . 14 23 24 17 09 09 26 10 14 21 11 12 21 12 28
EN PARITY: 19 06 10 04 28 29 02 07 06 26 28 01 25 18 04 08

L038 XMIT DATA: . 04 10 06 02 29 28 26 06 07 25 01 28 08 04 18
EN PARITY: 04 28 07 06 31 18 00 28 03 00 08 31 07 12 30 23

L039 XMIT DATA: . 06 07 28 00 18 31 00 03 28 07 31 08 23 30 12
EN PARITY: 21 02 05 26 15 29 05 25 07 03 09 19 24 22 00 05

L040 XMIT DATA: . 26 05 02 05 29 15 03 07 25 24 19 09 05 00 22
EN PARITY: 18 31 23 13 10 12 27 30 26 17 11 09 21 10 01 01

L041 XMIT DATA: . 13 23 31 27 12 10 17 26 30 21 09 11 01 01 10
EN PARITY: 00 15 26 12 25 09 20 01 15 30 24 02 09 18 16 02

L042 XMIT DATA: . 12 26 15 20 09 25 30 15 01 09 02 24 02 16 18
EN PARITY: 23 29 07 25 02 07 07 20 10 05 15 00 29 11 25 04

L043 XMIT DATA: . 25 07 29 07 07 02 05 10 20 29 00 15 04 25 11
EN PARITY: 17 26 27 07 19 15 08 31 17 21 08 25 14 12 10 13

L044 XMIT DATA: . 07 27 26 08 15 19 21 17 31 14 25 08 13 10 12
EN PARITY: 23 25 27 28 12 29 08 21 04 07 20 07 12 31 21 20

L045 XMIT DATA: . 28 27 25 08 29 12 07 04 21 12 07 20 20 21 31
EN PARITY: 20 02 29 06 18 30 20 21 00 23 24 01 19 19 26 26

L046 XMIT DATA: . 06 29 02 20 30 18 23 00 21 19 01 24 26 26 19
EN PARITY: 09 13 03 03 15 29 16 12 11 17 03 17 04 08 22 26

L047 XMIT DATA: . 03 03 13 16 29 15 17 11 12 04 17 03 26 22 08
EN PARITY: 11 03 04 13 10 15 08 18 24 06 30 08 06 11 28 03

L048 XMIT DATA: . 13 04 03 08 15 10 06 24 18 06 08 30 03 28 11
EN PARITY: 21 19 18 02 22 27 10 19 15 16 29 04 02 23 06 18

L049 XMIT DATA: . 02 18 19 10 27 22 16 15 19 02 04 29 18 06 23
EN PARITY: 04 31 24 14 23 17 21 25 04 20 08 15 21 18 29 06

L050 XMIT DATA: . 14 24 31 21 17 23 20 04 25 21 15 08 06 29 18
EN PARITY: 10 05 03 23 20 01 27 27 25 31 27 15 06 22 09 05

L051 XMIT DATA: . 23 03 05 27 01 20 31 25 27 06 15 27 05 09 22
EN PARITY: 08 31 22 20 29 12 06 23 15 13 01 30 28 28 05 05

L052 XMIT DATA: . 20 22 31 06 12 29 13 15 23 28 30 01 05 05 28
EN PARITY: 04 22 01 20 09 31 05 27 10 17 19 06 25 21 19 09

L053 XMIT DATA: . 20 01 22 05 31 09 17 10 27 25 06 19 09 19 21
EN PARITY: 10 13 18 19 06 21 30 22 24 11 05 07 25 23 21 11

L054 XMIT DATA: . 19 18 13 30 21 06 11 24 22 25 07 05 11 21 23
EN PARITY: 09 29 19 10 17 27 27 05 21 19 26 25 16 09 16 25

L055 XMIT DATA: . 10 19 29 27 27 17 19 21 05 16 25 26 25 16 09
EN PARITY: 21 05 12 22 19 06 23 19 08 11 08 07 26 12 07 12

L056 XMIT DATA: . 22 12 05 23 06 19 11 08 19 26 07 08 12 07 12
EN PARITY: 27 20 31 21 05 30 24 02 31 17 29 06 20 28 12 25

L057 XMIT DATA: . 21 31 20 24 30 05 17 31 02 20 06 29 25 12 28
EN PARITY: 20 13 03 19 07 03 00 20 25 27 20 13 04 10 06 21

L058 XMIT DATA: . 19 03 13 00 03 07 27 25 20 04 13 20 21 06 10
EN PARITY: 09 06 05 23 30 26 16 06 24 06 09 05 08 21 04 23

L059 XMIT DATA: . 23 05 06 16 26 30 06 24 06 08 05 09 23 04 21
EN PARITY: 18 05 11 31 24 17 30 18 19 21 20 12 23 06 20 17

L060 XMIT DATA: . 31 11 05 30 17 24 21 19 18 23 12 20 17 20 06
EN PARITY: 09 19 30 07 21 26 17 03 18 24 02 12 31 29 22 10

L061 XMIT DATA: . 07 30 19 17 26 21 24 18 03 31 12 02 10 22 29
EN PARITY: 28 18 27 10 14 03 12 00 01 09 23 15 04 09 11 04

L062 XMIT DATA: . 10 27 18 12 03 14 09 01 00 04 15 23 04 11 09
EN PARITY: 16 09 03 19 25 30 24 13 00 24 04 06 23 24 20 10

L063 XMIT DATA: . 19 03 09 24 30 25 24 00 13 23 06 04 10 20 24
EN PARITY: 19 11 17 05 26 28 05 10 29 26 17 30 10 16 21 18

L064 XMIT DATA: . 05 17 11 05 28 26 26 29 10 10 30 17 18 21 16
EN PARITY: 11 21 16 10 07 06 30 18 08 02 24 09 07 20 12 07

L065 XMIT DATA: . 10 16 21 30 06 07 02 08 18 07 09 24 07 12 20
EN PARITY: 30 19 28 19 20 05 01 24 24 06 03 28 04 15 20 13

L066 XMIT DATA: . 19 28 19 01 05 20 06 24 24 04 28 03 13 20 15
EN PARITY: 09 21 21 13 27 23 01 10 06 03 08 09 12 20 18 08

L067 XMIT DATA: . 13 21 21 01 23 27 03 06 10 12 09 08 08 18 20
EN PARITY: 09 17 20 24 08 09 27 03 01 09 07 08 30 21 06 07

L068 XMIT DATA: . 24 20 17 27 09 08 09 01 03 30 08 07 07 06 21
EN PARITY: 14 07 08 27 06 31 14 29 28 20 03 03 17 02 09 22

L069 XMIT DATA: . 27 08 07 14 31 06 20 28 29 17 03 03 22 09 02
EN PARITY: 25 07 31 23 03 08 10 09 16 08 29 05 05 28 20 02

L070 XMIT DATA: . 23 31 07 10 08 03 08 16 09 05 05 29 02 20 28
EN PARITY: 11 15 19 04 21 24 13 01 11 18 21 30 31 31 24 16

L071 XMIT DATA: . 04 19 15 13 24 21 18 11 01 31 30 21 16 24 31
EN PARITY: 08 24 28 12 11 12 10 23 21 20 28 18 05 17 20 18

L072 XMIT DATA: . 12 28 24 10 12 11 20 21 23 05 18 28 18 20 17
EN PARITY: 04 15 06 07 30 30 23 11 16 13 08 04 01 11 31 12

L073 XMIT DATA: . 07 06 15 23 30 30 13 16 11 01 04 08 12 31 11
EN PARITY: 05 04 13 10 15 30 04 12 14 06 13 03 20 13 14 03

L074 XMIT DATA: . 10 13 04 04 30 15 06 14 12 20 03 13 03 14 13
EN PARITY: 10 31 00 13 16 21 04 21 22 18 23 16 15 12 16 08

L075 XMIT DATA: . 13 00 31 04 21 16 18 22 21 15 16 23 08 16 12
EN PARITY: 02 24 13 02 31 29 26 10 24 07 20 11 01 16 06 16

L076 XMIT DATA: . 02 13 24 26 29 31 07 24 10 01 11 20 16 06 16
EN PARITY: 10 08 05 05 18 18 12 15 06 27 16 29 23 06 26 28

L077 XMIT DATA: . 05 05 08 12 18 18 27 06 15 23 29 16 28 26 06
EN PARITY: 09 06 23 14 04 04 00 30 21 07 31 27 05 03 26 14

L078 XMIT DATA: . 14 23 06 00 04 04 07 21 30 05 27 31 14 26 03
EN PARITY: 31 31 08 16 27 15 29 05 10 07 27 29 27 29 24 01

L079 XMIT DATA: . 16 08 31 29 15 27 07 10 05 27 29 27 01 24 29
EN PARITY: 12 26 09 01 28 11 23 15 13 15 23 09 17 09 06 19

L080 XMIT DATA: . 01 09 26 23 11 28 15 13 15 17 09 23 19 06 09
EN PARITY: 20 15 14 12 28 31 30 25 03 03 03 05 12 30 23 21

L081 XMIT DATA: . 12 14 15 30 31 28 03 03 25 12 05 03 21 23 30
EN PARITY: 01 22 05 24 29 09 11 13 12 17 13 03 06 20 03 22

L082 XMIT DATA: . 24 05 22 11 09 29 17 12 13 06 03 13 22 03 20
EN PARITY: 25 05 08 12 12 30 17 19 31 04 16 19 01 09 17 23

L083 XMIT DATA: . 12 08 05 17 30 12 04 31 19 01 19 16 23 17 09
EN PARITY: 09 06 16 31 13 31 28 21 18 00 08 27 28 18 05 08

L084 XMIT DATA: . 31 16 06 28 31 13 00 18 21 28 27 08 08 05 18
EN PARITY: 16 26 01 14 27 06 15 21 22 10 24 01 19 08 31 28

L085 XMIT DATA: . 14 01 26 15 06 27 10 22 21 19 01 24 28 31 08

EN PARITY: 24 19 20 12 05 26 01 03 28 24 20 10 26 17 26 24

L086 XMIT DATA: . 12 20 19 01 26 05 24 28 03 26 10 20 24 26 17
EN PARITY: 14 18 26 11 11 29 01 04 20 27 31 04 06 25 19 23

L087 XMIT DATA: . 11 26 18 01 29 11 27 20 04 06 04 31 23 19 25
EN PARITY: 19 20 23 08 17 09 15 00 14 22 25 04 05 01 27 06

L088 XMIT DATA: . 08 23 20 15 09 17 22 14 00 05 04 25 06 27 01
EN PARITY: 29 03 24 05 16 19 01 06 20 21 11 13 00 18 27 02

L089 XMIT DATA: . 05 24 03 01 19 16 21 20 06 00 13 11 02 27 18
EN PARITY: 22 26 26 31 20 21 24 13 07 22 06 03 29 00 06 05

L090 XMIT DATA: . 31 26 26 24 21 20 22 07 13 29 03 06 05 06 00
EN PARITY: 31 24 30 14 14 03 30 05 07 17 23 07 04 26 12 18

L091 XMIT DATA: . 14 30 24 30 03 14 17 07 05 04 07 23 18 12 26
EN PARITY: 13 08 13 09 27 21 18 01 28 05 03 14 22 28 06 02

L092 XMIT DATA: . 09 13 08 18 21 27 05 28 01 22 14 03 02 06 28
EN PARITY: 24 02 31 15 07 18 19 23 23 18 26 20 05 31 21 22

L093 XMIT DATA: . 15 31 02 19 18 07 18 23 23 05 20 26 22 21 31
EN PARITY: 26 17 30 29 17 26 28 17 19 10 12 18 15 27 15 24

L094 XMIT DATA: . 29 30 17 28 26 17 10 19 17 15 18 12 24 15 27
EN PARITY: 16 18 10 06 02 15 18 27 01 23 31 19 28 20 02 12

L095 XMIT DATA: . 06 10 18 18 15 02 23 01 27 28 19 31 12 02 20
EN PARITY: 09 02 26 17 02 15 30 26 13 01 01 18 18 08 31 08

L096 XMIT DATA: . 17 26 02 30 15 02 01 13 26 18 18 01 08 31 08
EN PARITY: 12 25 15 16 00 04 18 24 11 01 05 07 03 20 31 13

L097 XMIT DATA: . 16 15 25 18 04 00 01 11 24 03 07 05 13 31 20
EN PARITY: 07 19 26 04 28 29 13 06 01 04 07 03 02 27 00 24

L098 XMIT DATA: . 04 26 19 13 29 28 04 01 06 02 03 07 24 00 27
EN PARITY: 31 03 27 02 21 04 19 04 08 20 27 21 18 14 09 00

L099 XMIT DATA: . 02 27 03 19 04 21 20 08 04 18 21 27 00 09 14
EN PARITY: 04 17 28 29 08 26 20 28 01 28 04 19 08 20 15 13

L100 XMIT DATA: . 29 28 17 20 26 08 28 01 28 08 19 04 13 15 20
EN PARITY: 00 01 27 03 20 09 06 19 13 21 08 21 11 06 09 22

L101 XMIT DATA: . 03 27 01 06 09 20 21 13 19 11 21 08 22 09 06
EN PARITY: 20 19 27 31 18 02 04 19 20 06 17 19 27 25 31 18

L102 XMIT DATA: . 31 27 19 04 02 18 06 20 19 27 19 17 18 31 25
EN PARITY: 27 31 11 11 17 11 08 08 19 31 09 11 21 21 11 03

L103 XMIT DATA: . 11 11 31 08 11 17 31 19 08 21 11 09 03 11 21
EN PARITY: 07 05 18 09 10 21 24 28 24 31 16 23 23 21 12 14

L104 XMIT DATA: . 09 18 05 24 21 10 31 24 28 23 23 16 14 12 21
EN PARITY: 09 01 08 15 09 28 14 09 12 22 23 00 12 24 22 05

L105 XMIT DATA: . 15 08 01 14 28 09 22 12 09 12 00 23 05 22 24
EN PARITY: 20 10 05 14 05 12 29 10 11 23 21 07 20 29 15 21

L106 XMIT DATA: . 14 05 10 29 12 05 23 11 10 20 07 21 21 15 29
EN PARITY: 25 13 18 22 28 11 21 10 04 25 09 10 25 09 04 23

L107 XMIT DATA: . 22 18 13 21 11 28 25 04 10 25 10 09 23 04 09
EN PARITY: 14 05 30 26 08 26 05 10 05 13 02 04 17 24 31 21

L108 XMIT DATA: . 26 30 05 05 26 08 13 05 10 17 04 02 21 31 24
EN PARITY: 26 06 02 11 06 25 04 05 12 28 03 19 30 02 23 17

L109 XMIT DATA: . 11 02 06 04 25 06 28 12 05 30 19 03 17 23 02
EN PARITY: 19 24 20 11 17 03 30 25 25 13 29 27 01 02 29 09

L110 XMIT DATA: . 11 20 24 30 03 17 13 25 25 01 27 29 09 29 02
EN PARITY: 13 11 10 09 26 06 02 16 10 10 30 09 10 11 07 26

L111 XMIT DATA: . 09 10 11 02 06 26 10 10 16 10 09 30 26 07 11
EN PARITY: 20 01 11 01 13 19 05 14 25 24 00 19 22 15 11 29

L112 XMIT DATA: . 01 11 01 05 19 13 24 25 14 22 19 00 29 11 15
EN PARITY: 13 01 00 21 10 06 24 06 13 30 17 05 17 07 26 09

L113 XMIT DATA: . 21 00 01 24 06 10 30 13 06 17 05 17 09 26 07
EN PARITY: 28 20 13 27 17 07 29 04 19 23 25 00 02 07 00 08

L114 XMIT DATA: . 27 13 20 29 07 17 23 19 04 02 00 25 08 00 07
EN PARITY: 27 03 05 19 24 30 25 30 03 07 00 22 14 01 09 30

L115 XMIT DATA: . 19 05 03 25 30 24 07 03 30 14 22 00 30 09 01
EN PARITY: 22 06 08 00 08 26 12 28 17 06 25 22 23 21 17 22

L116 XMIT DATA: . 00 08 06 12 26 08 06 17 28 23 22 25 22 17 21
EN PARITY: 07 31 18 15 00 15 15 30 15 03 10 24 24 06 08 10

L117 XMIT DATA: . 15 18 31 15 15 00 03 15 30 24 24 10 10 08 06
EN PARITY: 19 30 22 12 07 03 25 28 05 20 13 16 17 20 07 31

L118 XMIT DATA: . 12 22 30 25 03 07 20 05 28 17 16 13 31 07 20
EN PARITY: 16 25 07 10 03 27 28 18 09 01 08 28 07 25 28 21

L119 XMIT DATA: . 10 07 25 28 27 03 01 09 18 07 28 08 21 28 25
EN PARITY: 19 31 28 00 03 19 15 12 10 14 01 28 15 24 21 25

L120 XMIT DATA: . 00 28 31 15 19 03 14 10 12 15 28 01 25 21 24
EN PARITY: 17 10 26 13 04 30 12 07 10 05 12 22 29 16 03 27

L121 XMIT DATA: . 13 26 10 12 30 04 05 10 07 29 22 12 27 03 16
EN PARITY: 22 21 19 10 30 17 05 24 22 29 13 03 28 01 04 16

L122 XMIT DATA: . 10 19 21 05 17 30 29 22 24 28 03 13 16 04 01
EN PARITY: 19 15 22 12 01 21 28 02 29 25 29 18 28 28 03 21

L123 XMIT DATA: . 12 22 15 28 21 01 25 29 02 28 18 29 21 03 28
EN PARITY: 26 10 05 06 03 07 12 31 17 22 19 00 11 30 28 19

L124 XMIT DATA: . 06 05 10 12 07 03 22 17 31 11 00 19 19 28 30
EN PARITY: 31 05 02 01 07 22 14 05 01 24 23 09 18 11 13 11

L125 XMIT DATA: . 01 02 05 14 22 07 24 01 05 18 09 23 11 13 11
EN PARITY: 00 24 21 30 18 01 27 17 18 22 06 25 13 21 30 08

L126 XMIT DATA: . 30 21 24 27 01 18 22 18 17 13 25 06 08 30 21
EN PARITY: 12 06 03 19 14 20 26 02 22 31 16 05 04 03 09 31

L127 XMIT DATA: . 19 03 06 26 20 14 31 22 02 04 05 16 31 09 03
EN PARITY: 11 16 15 28 26 15 30 31 19 12 17 10 25 03 08 02

L128 XMIT DATA: . 28 15 16 30 15 26 12 19 31 25 10 17 02 08 03
EN PARITY: 17 16 21 14 12 02 18 17 00 01 30 28 28 29 26 01

L129 XMIT DATA: . 14 21 16 18 02 12 01 00 17 28 28 30 01 26 29
EN PARITY: 21 10 28 08 29 23 19 19 04 07 11 24 27 10 03 19

L130 XMIT DATA: . 08 28 10 19 23 29 07 04 19 27 24 11 19 03 10
EN PARITY: 25 31 22 21 02 31 05 10 22 23 08 18 05 13 08 17

L131 XMIT DATA: . 21 22 31 05 31 02 23 22 10 05 18 08 17 08 13
EN PARITY: 03 19 30 20 27 25 05 22 29 11 06 05 08 29 15 04

L132 XMIT DATA: . 20 30 19 05 25 27 11 29 22 08 05 06 04 15 29
EN PARITY: 28 25 09 03 14 06 15 21 23 18 22 16 01 28 17 10

L133 XMIT DATA: . 03 09 25 15 06 14 18 23 21 01 16 22 10 17 28
EN PARITY: 13 08 00 07 10 25 04 03 08 13 26 09 08 16 14 04

L134 XMIT DATA: . 07 00 08 04 25 10 13 08 03 08 09 26 04 14 16
EN PARITY: 09 15 11 08 09 18 31 06 24 31 18 28 25 04 31 15

L135 XMIT DATA: . 08 11 15 31 18 09 31 24 06 25 28 18 15 31 04
EN PARITY: 18 21 24 04 02 11 12 22 31 07 24 00 29 26 20 05

L136 XMIT DATA: . 04 24 21 12 11 02 07 31 22 29 00 24 05 20 26
EN PARITY: 02 22 25 07 10 09 03 18 07 17 26 26 03 07 00 00

L137 XMIT DATA: . 07 25 22 03 09 10 17 07 18 03 26 26 00 00 07
EN PARITY: 28 01 11 14 01 13 29 08 19 26 30 00 15 07 04 12

L138 XMIT DATA: . 14 11 01 29 13 01 26 19 08 15 00 30 12 04 07
EN PARITY: 00 18 30 05 25 06 13 08 14 14 00 20 20 05 24 11

L139 XMIT DATA: . 05 30 18 13 06 25 14 14 08 20 20 00 11 24 05
EN PARITY: 17 27 31 12 17 13 24 18 27 20 05 28 08 12 10 29

L140 XMIT DATA: . 12 31 27 24 13 17 20 27 18 08 28 05 29 10 12
EN PARITY: 24 14 20 17 12 12 22 02 29 12 09 06 10 27 12 20

L141 XMIT DATA: . 17 20 14 22 12 12 12 29 02 10 06 09 20 12 27
EN PARITY: 08 25 19 07 07 21 23 29 25 01 14 21 06 22 00 14

L142 XMIT DATA: . 07 19 25 23 21 07 01 25 29 06 21 14 14 00 22
EN PARITY: 13 06 11 19 29 06 00 06 09 27 22 15 16 05 10 10

L143 XMIT DATA: . 19 11 06 00 06 29 27 09 06 16 15 22 10 10 05
EN PARITY: 28 24 31 07 20 26 24 29 28 20 02 09 19 06 17 15

L144 XMIT DATA: . 07 31 24 24 26 20 20 28 29 19 09 02 15 17 06
EN PARITY: 29 28 14 12 17 00 02 21 31 24 21 14 11 17 21 00

L145 XMIT DATA: . 12 14 28 02 00 17 24 31 21 11 14 21 00 21 17
EN PARITY: 03 21 23 27 08 13 17 03 30 20 15 00 18 21 17 12

L146 XMIT DATA: . 27 23 21 17 13 08 20 30 03 18 00 15 12 17 21
EN PARITY: 02 04 28 16 29 10 14 01 07 06 11 19 00 04 24 13

L147 XMIT DATA: . 16 28 04 14 10 29 06 07 01 00 19 11 13 24 04

EN PARITY: 29 02 14 00 04 10 05 21 24 13 25 30 21 23 26 15

L148 XMIT DATA: . 00 14 02 05 10 04 13 24 21 21 30 25 15 26 23
EN PARITY: 15 05 30 15 20 06 15 21 04 06 29 21 01 12 30 26

L149 XMIT DATA: . 15 30 05 15 06 20 06 04 21 01 21 29 26 30 12
EN PARITY: 26 07 00 16 14 22 24 20 31 07 20 20 25 00 15 31

L150 XMIT DATA: . 16 00 07 24 22 14 07 31 20 25 20 20 31 15 00
EN PARITY: 29 31 24 17 14 08 23 31 15 15 13 00 15 05 31 13

L151 XMIT DATA: . 17 24 31 23 08 14 15 15 31 15 00 13 13 31 05
EN PARITY: 15 22 27 23 09 31 11 17 05 07 19 30 03 30 22 03

L152 XMIT DATA: . 23 27 22 11 31 09 07 05 17 03 30 19 03 22 30
EN PARITY: 27 18 02 12 15 23 05 21 13 20 05 30 27 02 06 24

L153 XMIT DATA: . 12 02 18 05 23 15 20 13 21 27 30 05 24 06 02
EN PARITY: 03 04 31 25 18 14 05 18 08 29 29 03 29 06 28 15

L154 XMIT DATA: . 25 31 04 05 14 18 29 08 18 29 03 29 15 28 06
EN PARITY: 14 16 28 04 13 27 23 16 28 07 17 27 03 05 28 00

L155 XMIT DATA: . 04 28 16 23 27 13 07 28 16 03 27 17 00 28 05
EN PARITY: 04 08 16 19 24 23 18 11 00 06 00 22 16 22 16 00

L156 XMIT DATA: . 19 16 08 18 23 24 06 00 11 16 22 00 00 16 22
EN PARITY: 04 01 10 14 10 10 25 28 04 01 15 23 09 24 06 22

L157 XMIT DATA: . 14 10 01 25 10 10 01 04 28 09 23 15 22 06 24
EN PARITY: 03 20 00 18 14 29 05 23 07 29 04 13 16 21 25 20

L158 XMIT DATA: . 18 00 20 05 29 14 29 07 23 16 13 04 20 25 21
EN PARITY: 08 26 11 14 11 05 19 28 05 06 01 09 07 09 00 31

L159 XMIT DATA: . 14 11 26 19 05 11 06 05 28 07 09 01 31 00 09
EN PARITY: 29 31 07 00 07 02 03 19 14 23 18 04 21 05 24 31

L160 XMIT DATA: . 00 07 31 03 02 07 23 14 19 21 04 18 31 24 05
EN PARITY: 05 18 20 27 15 23 30 24 01 06 08 29 22 07 30 01

L161 XMIT DATA: . 27 20 18 30 23 15 06 01 24 22 29 08 01 30 07
EN PARITY: 14 23 14 13 01 10 22 21 23 04 22 28 19 00 07 02

L162 XMIT DATA: . 13 14 23 22 10 01 04 23 21 19 28 22 02 07 00
EN PARITY: 20 06 10 14 23 18 03 02 11 11 10 22 25 19 03 11

L163 XMIT DATA: . 14 10 06 03 18 23 11 11 02 25 22 10 11 03 19
EN PARITY: 29 20 31 06 07 00 19 23 22 14 18 30 24 14 09 21

L164 XMIT DATA: . 06 31 20 19 00 07 14 22 23 24 30 18 21 09 14
EN PARITY: 00 20 04 28 13 12 22 16 18 15 02 11 30 22 17 31

L165 XMIT DATA: . 28 04 20 22 12 13 15 18 16 30 11 02 31 17 22
EN PARITY: 18 10 06 30 30 06 20 05 27 16 06 24 00 26 03 10

L166 XMIT DATA: . 30 06 10 20 06 30 16 27 05 00 24 06 10 03 26
EN PARITY: 17 04 27 13 09 20 21 20 09 24 23 06 31 28 00 12

L167 XMIT DATA: . 13 27 04 21 20 09 24 09 20 31 06 23 12 00 28
EN PARITY: 02 14 00 16 30 01 29 16 25 20 02 18 22 13 27 31

L168 XMIT DATA: . 16 00 14 29 01 30 20 25 16 22 18 02 31 27 13
EN PARITY: 26 20 27 05 24 25 26 02 11 05 10 24 10 09 28 05

L169 XMIT DATA: . 05 27 20 26 25 24 05 11 02 10 24 10 05 28 09
EN PARITY: 08 24 00 30 01 18 18 18 11 04 07 19 06 02 07 15

L170 XMIT DATA: . 30 00 24 18 18 01 04 11 18 06 19 07 15 07 02
EN PARITY: 05 31 31 19 14 16 14 14 31 24 05 04 05 15 10 29

L171 XMIT DATA: . 19 31 31 14 16 14 24 31 14 05 04 05 29 10 15
EN PARITY: 07 06 20 22 09 02 15 26 02 06 17 30 06 04 25 07

L172 XMIT DATA: . 22 20 06 15 02 09 06 02 26 06 30 17 07 25 04
EN PARITY: 05 11 24 09 15 02 13 20 11 30 03 14 18 25 02 06

L173 XMIT DATA: . 09 24 11 13 02 15 30 11 20 18 14 03 06 02 25
EN PARITY: 15 00 12 22 20 29 31 03 31 16 18 18 19 10 04 13

L174 XMIT DATA: . 22 12 00 31 29 20 16 31 03 19 18 18 13 04 10
EN PARITY: 28 14 30 22 10 00 01 26 07 31 06 27 29 26 20 01

L175 XMIT DATA: . 22 30 14 01 00 10 31 07 26 29 27 06 01 20 26
EN PARITY: 23 30 20 13 11 28 13 20 18 17 14 26 09 02 05 03

L176 XMIT DATA: . 13 20 30 13 28 11 17 18 20 09 26 14 03 05 02
EN PARITY: 04 14 06 04 02 00 13 24 27 05 16 21 24 24 01 12

L177 XMIT DATA: . 04 06 14 13 00 02 05 27 24 24 21 16 12 01 24
EN PARITY: 29 08 12 28 06 02 20 08 23 26 28 12 01 13 21 26

L178 XMIT DATA: . 28 12 08 20 02 06 26 23 08 01 12 28 26 21 13
EN PARITY: 19 09 23 02 27 18 31 12 29 17 14 06 30 20 21 16

L179 XMIT DATA: . 02 23 09 31 18 27 17 29 12 30 06 14 16 21 20
EN PARITY: 19 26 03 09 06 04 09 10 00 03 04 07 16 24 03 04

L180 XMIT DATA: . 09 03 26 09 04 06 03 00 10 16 07 04 04 03 24
EN PARITY: 06 10 28 01 06 16 02 07 27 04 11 10 16 20 01 11

L181 XMIT DATA: . 01 28 10 02 16 06 04 27 07 16 10 11 11 01 20
EN PARITY: 26 15 25 07 03 29 22 17 08 28 26 20 25 08 07 10

L182 XMIT DATA: . 07 25 15 22 29 03 28 08 17 25 20 26 10 07 08
EN PARITY: 27 16 20 06 11 07 17 02 01 03 01 05 20 09 12 09

L183 XMIT DATA: . 06 20 16 17 07 11 03 01 02 20 05 01 09 12 09
EN PARITY: 12 11 15 24 17 27 26 17 29 30 12 30 17 18 14 22

L184 XMIT DATA: . 24 15 11 26 27 17 30 29 17 17 30 12 22 14 18
EN PARITY: 19 08 03 09 27 07 02 28 29 26 06 27 15 29 14 04

L185 XMIT DATA: . 09 03 08 02 07 27 26 29 28 15 27 06 04 14 29
EN PARITY: 28 08 31 04 05 24 29 03 28 27 02 21 30 30 09 03

L186 XMIT DATA: . 04 31 08 29 24 05 27 28 03 30 21 02 03 09 30
EN PARITY: 12 31 13 26 07 16 28 21 27 06 29 09 30 19 19 24

L187 XMIT DATA: . 26 13 31 28 16 07 06 27 21 30 09 29 24 19 19
EN PARITY: 17 18 30 28 04 22 10 27 08 12 21 22 19 16 30 15

L188 XMIT DATA: . 28 30 18 10 22 04 12 08 27 19 22 21 15 30 16
EN PARITY: 09 27 30 07 31 20 04 05 01 00 02 11 11 10 23 10

L189 XMIT DATA: . 07 30 27 04 20 31 00 01 05 11 11 02 10 23 10
EN PARITY: 07 31 20 16 07 14 14 24 04 17 06 12 21 03 23 13

L190 XMIT DATA: . 16 20 31 14 14 07 17 04 24 21 12 06 13 23 03
EN PARITY: 19 00 25 11 29 03 25 31 01 20 14 31 01 26 13 10

L191 XMIT DATA: . 11 25 00 25 03 29 20 01 31 01 31 14 10 13 26
EN PARITY: 02 26 22 12 09 30 17 29 18 23 01 27 21 29 22 14

L192 XMIT DATA: . 12 22 26 17 30 09 23 18 29 21 27 01 14 22 29
EN PARITY: 19 04 26 02 18 07 15 20 00 27 03 16 23 12 15 15

L193 XMIT DATA: . 02 26 04 15 07 18 27 00 20 23 16 03 15 15 12
EN PARITY: 03 23 14 16 13 28 23 24 13 31 07 20 13 10 12 02

L194 XMIT DATA: . 16 14 23 23 28 13 31 13 24 13 20 07 02 12 10
EN PARITY: 04 29 26 07 14 17 23 30 02 30 01 29 06 05 25 00

L195 XMIT DATA: . 07 26 29 23 17 14 30 02 30 06 29 01 00 25 05
EN PARITY: 19 10 23 21 24 08 14 26 06 18 29 17 28 16 31 28

L196 XMIT DATA: . 21 23 10 14 08 24 18 06 26 28 17 29 28 31 16
EN PARITY: 28 10 23 18 09 10 28 17 30 18 07 29 04 18 10 05

L197 XMIT DATA: . 18 23 10 28 10 09 18 30 17 04 29 07 05 10 18
EN PARITY: 27 16 22 14 19 21 04 31 24 18 07 16 31 07 08 15

L198 XMIT DATA: . 14 22 16 04 21 19 18 24 31 31 16 07 15 08 07
EN PARITY: 11 14 15 05 23 31 25 06 21 24 15 28 11 03 26 23

L199 XMIT DATA: . 05 15 14 25 31 23 24 21 06 11 28 15 23 26 03
EN PARITY: 26 23 25 22 09 07 16 12 01 25 05 13 31 10 13 09

L200 XMIT DATA: . 22 25 23 16 07 09 25 01 12 31 13 05 09 13 10
EN PARITY: 27 25 26 02 26 11 02 30 05 31 17 22 25 06 27 24

L201 XMIT DATA: . 02 26 25 02 11 26 31 05 30 25 22 17 24 27 06
EN PARITY: 30 01 00 04 09 02 02 04 05 01 00 21 13 02 12 07

L202 XMIT DATA: . 04 00 01 02 02 09 01 05 04 13 21 00 07 12 02
EN PARITY: 03 27 19 17 08 11 29 18 00 13 15 21 13 25 02 07

L203 XMIT DATA: . 17 19 27 29 11 08 13 00 18 13 21 15 07 02 25
EN PARITY: 09 19 23 24 19 28 02 13 24 28 27 11 12 29 30 00

L204 XMIT DATA: . 24 23 19 02 28 19 28 24 13 12 11 27 00 30 29
EN PARITY: 22 14 26 21 23 10 31 27 16 15 14 29 04 19 13 28

L205 XMIT DATA: . 21 26 14 31 10 23 15 16 27 04 29 14 28 13 19
EN PARITY: 03 29 05 01 28 30 12 00 04 28 02 05 13 19 19 15

L206 XMIT DATA: . 01 05 29 12 30 28 28 04 00 13 05 02 15 19 19
EN PARITY: 19 10 21 20 24 24 22 00 28 22 09 17 14 09 04 16

L207 XMIT DATA: . 20 21 10 22 24 24 22 28 00 14 17 09 16 04 09
EN PARITY: 18 21 27 10 06 00 21 28 01 01 23 03 25 26 04 08

L208 XMIT DATA: . 10 27 21 21 00 06 01 01 28 25 03 23 08 04 26
EN PARITY: 05 18 25 07 00 25 22 07 00 17 17 02 01 02 14 27

L209 XMIT DATA: . 07 25 18 22 25 00 17 00 07 01 02 17 27 14 02

EN PARITY: 31 17 21 29 23 12 04 00 18 02 23 22 31 26 30 04

L210 XMIT DATA: . 29 21 17 04 12 23 02 18 00 31 22 23 04 30 26
EN PARITY: 04 11 18 01 30 00 04 17 24 09 05 15 05 02 21 29

L211 XMIT DATA: . 01 18 11 04 00 30 09 24 17 05 15 05 29 21 02
EN PARITY: 15 24 12 29 03 30 27 20 20 22 24 20 14 28 12 13

L212 XMIT DATA: . 29 12 24 27 30 03 22 20 20 14 20 24 13 12 28
EN PARITY: 17 13 27 31 13 27 13 21 28 09 17 09 25 17 00 25

L213 XMIT DATA: . 31 27 13 13 27 13 09 28 21 25 09 17 25 00 17
EN PARITY: 07 02 08 22 09 29 11 30 08 04 00 03 05 10 31 14

L214 XMIT DATA: . 22 08 02 11 29 09 04 08 30 05 03 00 14 31 10
EN PARITY: 30 18 08 14 09 11 28 16 18 21 09 11 25 06 05 13

L215 XMIT DATA: . 14 08 18 28 11 09 21 18 16 25 11 09 13 05 06
EN PARITY: 28 08 13 20 03 10 06 06 27 31 11 15 28 20 25 10

L216 XMIT DATA: . 20 13 08 06 10 03 31 27 06 28 15 11 10 25 20
EN PARITY: 00 18 04 12 31 28 25 17 15 14 08 01 23 23 28 16

L217 XMIT DATA: . 12 04 18 25 28 31 14 15 17 23 01 08 16 28 23
EN PARITY: 23 13 03 07 13 24 31 19 00 20 22 00 04 01 31 17

L218 XMIT DATA: . 07 03 13 31 24 13 20 00 19 04 00 22 17 31 01
EN PARITY: 09 04 10 19 07 31 25 19 04 14 31 07 16 31 10 12

L219 XMIT DATA: . 19 10 04 25 31 07 14 04 19 16 07 31 12 10 31
EN PARITY: 06 04 15 28 26 28 30 07 30 30 29 06 00 21 29 27

L220 XMIT DATA: . 28 15 04 30 28 26 30 30 07 00 06 29 27 29 21
EN PARITY: 24 19 08 31 01 04 30 11 30 27 30 08 10 18 23 06

L221 XMIT DATA: . 31 08 19 30 04 01 27 30 11 10 08 30 06 23 18
EN PARITY: 28 23 11 00 15 09 25 12 26 23 02 28 00 20 19 06

L222 XMIT DATA: . 00 11 23 25 09 15 23 26 12 00 28 02 06 19 20
EN PARITY: 24 31 04 31 24 20 21 16 22 23 15 25 22 12 20 23

L223 XMIT DATA: . 31 04 31 21 20 24 23 22 16 22 25 15 23 20 12
EN PARITY: 26 17 21 11 28 19 13 25 23 02 13 18 08 06 02 04

L224 XMIT DATA: . 11 21 17 13 19 28 02 23 25 08 18 13 04 02 06
EN PARITY: 31 30 22 10 23 29 00 21 17 22 16 25 19 15 08 23

L225 XMIT DATA: . 10 22 30 00 29 23 22 17 21 19 25 16 23 08 15
EN PARITY: 06 16 11 04 07 05 11 00 04 02 04 30 19 06 02 24

L226 XMIT DATA: . 04 11 16 11 05 07 02 04 00 19 30 04 24 02 06
EN PARITY: 31 18 11 07 22 16 08 07 06 20 31 27 16 00 22 09

L227 XMIT DATA: . 07 11 18 08 16 22 20 06 07 16 27 31 09 22 00
EN PARITY: 20 05 16 15 18 09 12 29 15 17 03 13 02 30 11 15

L228 XMIT DATA: . 15 16 05 12 09 18 17 15 29 02 13 03 15 11 30
EN PARITY: 19 23 12 07 21 30 20 02 13 31 22 05 07 02 02 20

L229 XMIT DATA: . 07 12 23 20 30 21 31 13 02 07 05 22 20 02 02
EN PARITY: 02 05 14 15 27 20 24 17 07 16 19 03 00 18 20 02

L230 XMIT DATA: . 15 14 05 24 20 27 16 07 17 00 03 19 02 20 18
EN PARITY: 03 23 23 14 04 05 17 22 09 15 08 28 14 25 17 00

L231 XMIT DATA: . 14 23 23 17 05 04 15 09 22 14 28 08 00 17 25
EN PARITY: 20 01 05 09 26 12 05 11 05 21 31 27 13 04 28 07

L232 XMIT DATA: . 09 05 01 05 12 26 21 05 11 13 27 31 07 28 04
EN PARITY: 00 13 06 10 08 03 12 07 12 29 03 29 15 19 02 05

L233 XMIT DATA: . 10 06 13 12 03 08 29 12 07 15 29 03 05 02 19
EN PARITY: 10 17 03 13 17 24 10 29 29 26 31 31 10 29 08 14

L234 XMIT DATA: . 13 03 17 10 24 17 26 29 29 10 31 31 14 08 29
EN PARITY: 00 16 30 00 03 15 01 16 12 31 18 01 23 16 16 05

L235 XMIT DATA: . 00 30 16 01 15 03 31 12 16 23 01 18 05 16 16
EN PARITY: 02 13 18 16 27 27 27 00 13 06 23 20 25 03 14 18

L236 XMIT DATA: . 16 18 13 27 27 27 06 13 00 25 20 23 18 14 03
EN PARITY: 21 01 25 24 13 06 31 03 21 18 20 14 12 04 19 19

L237 XMIT DATA: . 24 25 01 31 06 13 18 21 03 12 14 20 19 19 04
EN PARITY: 17 30 09 08 28 02 14 24 03 14 24 17 28 08 18 14

L238 XMIT DATA: . 08 09 30 14 02 28 14 03 24 28 17 24 14 18 08
EN PARITY: 12 08 05 10 27 21 06 21 11 12 09 01 07 07 12 00

L239 XMIT DATA: . 10 05 08 06 21 27 12 11 21 07 01 09 00 12 07
EN PARITY: 02 25 15 22 14 26 10 04 13 04 20 16 22 22 00 07

L240 XMIT DATA: . 22 15 25 10 26 14 04 13 04 22 16 20 07 00 22
EN PARITY: 02 06 01 15 13 30 27 08 08 19 04 19 24 09 27 18

L241 XMIT DATA: . 15 01 06 27 30 13 19 08 08 24 19 04 18 27 09
EN PARITY: 28 16 14 28 02 12 18 21 04 12 27 19 27 10 15 05

L242 XMIT DATA: . 28 14 16 18 12 02 12 04 21 27 19 27 05 15 10
EN PARITY: 14 12 02 18 26 19 05 01 31 23 04 12 21 27 21 13

L243 XMIT DATA: . 18 02 12 05 19 26 23 31 01 21 12 04 13 21 27
EN PARITY: 21 27 09 03 26 23 11 02 24 11 14 25 17 20 11 28

L244 XMIT DATA: . 03 09 27 11 23 26 11 24 02 17 25 14 28 11 20
EN PARITY: 10 06 05 05 30 20 22 25 16 09 00 09 29 17 20 09

L245 XMIT DATA: . 05 05 06 22 20 30 09 16 25 29 09 00 09 20 17
EN PARITY: 23 07 24 10 11 15 03 07 12 05 27 09 18 02 04 20

L246 XMIT DATA: . 10 24 07 03 15 11 05 12 07 18 09 27 20 04 02
EN PARITY: 14 03 08 09 26 21 22 14 10 28 14 19 08 08 22 04

L247 XMIT DATA: . 09 08 03 22 21 26 28 10 14 08 19 14 04 22 08
EN PARITY: 21 17 24 03 22 07 18 08 03 17 23 11 21 06 08 05

L248 XMIT DATA: . 03 24 17 18 07 22 17 03 08 21 11 23 05 08 06
EN PARITY: 02 27 03 09 16 14 05 07 20 01 29 04 06 29 22 06

L249 XMIT DATA: . 09 03 27 05 14 16 01 20 07 06 04 29 06 22 29
EN PARITY: 19 00 08 08 10 23 05 05 16 25 13 30 22 31 17 00

L250 XMIT DATA: . 08 08 00 05 23 10 25 16 05 22 30 13 00 17 31
EN PARITY: 11 10 31 01 09 09 24 05 19 13 30 13 22 22 06 17

L251 XMIT DATA: . 01 31 10 24 09 09 13 19 05 22 13 30 17 06 22
EN PARITY: 05 29 25 14 17 17 11 17 19 00 00 13 08 23 10 25

L252 XMIT DATA: . 14 25 29 11 17 17 00 19 17 08 13 00 25 10 23
EN PARITY: 25 00 29 08 02 16 22 16 11 10 15 30 02 25 17 00

L253 XMIT DATA: . 08 29 00 22 16 02 10 11 16 02 30 15 00 17 25
EN PARITY: 11 12 23 18 17 06 23 07 11 26 21 00 05 26 13 08

L254 XMIT DATA: . 18 23 12 23 06 17 26 11 07 05 00 21 08 13 26
EN PARITY: 06 28 08 28 02 00 01 31 14 09 21 27 06 01 04 22

L255 XMIT DATA: . 28 08 28 01 00 02 09 14 31 06 27 21 22 04 01
EN PARITY: 14 13 06 06 11 05 30 12 10 01 00 03 00 04 28 08

L256 XMIT DATA: . 06 06 13 30 05 11 01 10 12 00 03 00 08 28 04
EN PARITY: 24 13 09 06 06 14 17 23 29 23 22 14 20 12 21 28

L257 XMIT DATA: . 06 09 13 17 14 06 23 29 23 20 14 22 28 21 12
EN PARITY: 01 15 03 25 20 16 16 30 10 12 06 09 20 20 29 13

L258 XMIT DATA: . 25 03 15 16 16 20 12 10 30 20 09 06 13 29 20
EN PARITY: 06 14 20 02 06 30 31 08 09 31 13 09 30 28 16 18

L259 XMIT DATA: . 02 20 14 31 30 06 31 09 08 30 09 13 18 16 28
EN PARITY: 25 12 28 14 24 30 14 28 20 30 27 28 27 06 23 24

L260 XMIT DATA: . 14 28 12 14 30 24 30 20 28 27 28 27 24 23 06
EN PARITY: 05 17 15 30 28 18 22 28 03 04 27 16 10 30 31 08

L261 XMIT DATA: . 30 15 17 22 18 28 04 03 28 10 16 27 08 31 30
EN PARITY: 17 15 10 06 17 29 25 21 18 31 27 16 07 12 30 29

L262 XMIT DATA: . 06 10 15 25 29 17 31 18 21 07 16 27 29 30 12
EN PARITY: 11 29 28 06 02 26 09 09 07 29 03 04 05 02 15 19

L263 XMIT DATA: . 06 28 29 09 26 02 29 07 09 05 04 03 19 15 02
EN PARITY: 19 11 00 30 20 14 04 12 29 10 14 16 10 30 24 29

L264 XMIT DATA: . 30 00 11 04 14 20 10 29 12 10 16 14 29 24 30
EN PARITY: 14 25 01 20 17 12 26 02 18 06 26 23 31 25 10 06

L265 XMIT DATA: . 20 01 25 26 12 17 06 18 02 31 23 26 06 10 25
EN PARITY: 13 18 28 07 27 01 15 08 20 18 25 01 30 20 12 23

L266 XMIT DATA: . 07 28 18 15 01 27 18 20 08 30 01 25 23 12 20
EN PARITY: 18 24 29 30 12 12 18 15 17 26 24 11 11 06 03 07

L267 XMIT DATA: . 30 29 24 18 12 12 26 17 15 11 11 24 07 03 06
EN PARITY: 18 12 06 03 03 16 29 04 17 05 00 25 09 14 03 26

L268 XMIT DATA: . 03 06 12 29 16 03 05 17 04 09 25 00 26 03 14
EN PARITY: 06 22 05 31 06 25 29 15 22 16 18 30 26 18 19 24

L269 XMIT DATA: . 31 05 22 29 25 06 16 22 15 26 30 18 24 19 18
EN PARITY: 25 03 09 14 03 16 14 06 15 31 28 16 04 01 05 20

L270 XMIT DATA: . 14 09 03 14 16 03 31 15 06 04 16 28 20 05 01
EN PARITY: 03 25 10 29 17 05 10 02 06 21 26 30 17 11 31 27

L271 XMIT DATA: . 29 10 25 10 05 17 21 06 02 17 30 26 27 31 11

EN PARITY: 07 10 13 26 19 31 30 29 19 00 02 16 31 12 29 01

L272 XMIT DATA: . 26 13 10 30 31 19 00 19 29 31 16 02 01 29 12
EN PARITY: 25 04 08 04 10 13 22 10 16 14 06 17 19 14 31 23

L273 XMIT DATA: . 04 08 04 22 13 10 14 16 10 19 17 06 23 31 14
EN PARITY: 03 01 07 07 09 01 08 28 30 17 21 19 01 22 17 06

L274 XMIT DATA: . 07 07 01 08 01 09 17 30 28 01 19 21 06 17 22
EN PARITY: 12 26 04 01 17 12 15 24 17 05 05 05 12 27 02 18

L275 XMIT DATA: . 01 04 26 15 12 17 05 17 24 12 05 05 18 02 27
EN PARITY: 10 10 29 06 05 08 08 17 11 18 21 24 12 11 17 29

L276 XMIT DATA: . 06 29 10 08 08 05 18 11 17 12 24 21 29 17 11
EN PARITY: 14 05 23 06 21 26 20 25 12 22 07 10 23 26 24 31

L277 XMIT DATA: . 06 23 05 20 26 21 22 12 25 23 10 07 31 24 26
EN PARITY: 11 14 29 20 25 06 09 16 25 18 17 24 12 28 16 31

L278 XMIT DATA: . 20 29 14 09 06 25 18 25 16 12 24 17 31 16 28
EN PARITY: 07 31 24 02 11 23 08 23 06 22 03 30 05 01 12 01

L279 XMIT DATA: . 02 24 31 08 23 11 22 06 23 05 30 03 01 12 01
EN PARITY: 31 23 24 31 10 19 07 13 31 04 30 19 16 27 20 19

L280 XMIT DATA: . 31 24 23 07 19 10 04 31 13 16 19 30 19 20 27
EN PARITY: 01 03 05 10 28 00 30 20 26 17 26 04 00 26 29 24

L281 XMIT DATA: . 10 05 03 30 00 28 17 26 20 00 04 26 24 29 26
EN PARITY: 16 15 13 15 13 04 10 03 00 23 07 11 17 22 22 04

L282 XMIT DATA: . 15 13 15 10 04 13 23 00 03 17 11 07 04 22 22
EN PARITY: 22 11 25 31 23 04 09 03 04 06 31 01 06 07 11 27

L283 XMIT DATA: . 31 25 11 09 04 23 06 04 03 06 01 31 27 11 07
EN PARITY: 21 08 27 27 26 03 03 00 21 28 26 27 07 24 24 13

L284 XMIT DATA: . 27 27 08 03 03 26 28 21 00 07 27 26 13 24 24
EN PARITY: 04 01 10 29 05 08 12 27 00 09 05 26 03 10 20 15

L285 XMIT DATA: . 29 10 01 12 08 05 09 00 27 03 26 05 15 20 10
EN PARITY: 31 14 01 10 17 00 04 16 06 14 27 12 25 02 11 10

L286 XMIT DATA: . 10 01 14 04 00 17 14 06 16 25 12 27 10 11 02
EN PARITY: 05 24 03 27 03 07 16 10 28 25 30 14 13 15 04 12

L287 XMIT DATA: . 27 03 24 16 07 03 25 28 10 13 14 30 12 04 15
EN PARITY: 02 05 27 10 27 27 26 24 06 17 12 09 28 31 16 21

L288 XMIT DATA: . 10 27 05 26 27 27 17 06 24 28 09 12 21 16 31
EN PARITY: 16 09 06 00 24 28 19 09 19 28 13 22 30 04 08 28

L289 XMIT DATA: . 00 06 09 19 28 24 28 19 09 30 22 13 28 08 04
EN PARITY: 10 07 21 18 07 23 21 23 15 23 25 31 17 04 09 08

L290 XMIT DATA: . 18 21 07 21 23 07 23 15 23 17 31 25 08 09 04
EN PARITY: 21 07 30 26 25 21 01 03 07 06 28 06 07 14 02 12

L291 XMIT DATA: . 26 30 07 01 21 25 06 07 03 07 06 28 12 02 14
EN PARITY: 00 01 11 08 28 20 01 27 02 19 12 02 03 01 18 09

L292 XMIT DATA: . 08 11 01 01 20 28 19 02 27 03 02 12 09 18 01
EN PARITY: 02 31 25 12 12 09 02 00 22 24 05 00 21 06 03 28

L293 XMIT DATA: . 12 25 31 02 09 12 24 22 00 21 00 05 28 03 06
EN PARITY: 13 20 07 26 17 01 05 02 26 27 24 30 18 08 18 02

L294 XMIT DATA: . 26 07 20 05 01 17 27 26 02 18 30 24 02 18 08
EN PARITY: 29 25 19 18 15 13 03 13 09 14 00 31 19 30 06 25

L295 XMIT DATA: . 18 19 25 03 13 15 14 09 13 19 31 00 25 06 30
EN PARITY: 24 01 28 23 24 15 07 01 03 24 18 15 06 27 11 10

L296 XMIT DATA: . 23 28 01 07 15 24 24 03 01 06 15 18 10 11 27
EN PARITY: 30 06 31 19 20 01 31 14 03 09 22 20 06 18 02 01

L297 XMIT DATA: . 19 31 06 31 01 20 09 03 14 06 20 22 01 02 18
EN PARITY: 13 22 12 24 02 30 03 01 03 05 29 24 22 19 23 18

L298 XMIT DATA: . 24 12 22 03 30 02 05 03 01 22 24 29 18 23 19
EN PARITY: 27 22 10 28 02 17 17 29 01 08 28 02 09 19 02 24

L299 XMIT DATA: . 28 10 22 17 17 02 08 01 29 09 02 28 24 02 19
EN PARITY: 04 25 06 08 20 23 06 13 29 21 19 03 05 09 29 29

L300 XMIT DATA: . 08 06 25 06 23 20 21 29 13 05 03 19 29 29 09
EN PARITY: 02 19 28 07 15 05 08 04 17 16 25 10 05 18 00 28

L301 XMIT DATA: . 07 28 19 08 05 15 16 17 04 05 10 25 28 00 18
EN PARITY: 16 07 17 19 05 14 04 15 08 18 23 25 11 00 31 01

L302 XMIT DATA: . 19 17 07 04 14 05 18 08 15 11 25 23 01 31 00
EN PARITY: 17 06 20 18 04 29 02 17 01 00 02 11 26 21 08 26

L303 XMIT DATA: . 18 20 06 02 29 04 00 01 17 26 11 02 26 08 21
EN PARITY: 18 04 25 12 04 30 02 10 17 10 31 25 22 01 29 01

L304 XMIT DATA: . 12 25 04 02 30 04 10 17 10 22 25 31 01 29 01
EN PARITY: 11 09 19 14 30 00 24 29 07 09 08 22 25 30 07 14

L305 XMIT DATA: . 14 19 09 24 00 30 09 07 29 25 22 08 14 07 30
EN PARITY: 28 13 11 03 30 02 02 03 26 12 13 13 30 23 01 27

L306 XMIT DATA: . 03 11 13 02 02 30 12 26 03 30 13 13 27 01 23
EN PARITY: 14 31 22 18 02 18 02 19 20 11 13 22 10 07 15 30

L307 XMIT DATA: . 18 22 31 02 18 02 11 20 19 10 22 13 30 15 07
EN PARITY: 30 05 18 15 30 15 15 04 08 27 26 06 04 20 02 01

L308 XMIT DATA: . 15 18 05 15 15 30 27 08 04 04 06 26 01 02 20
EN PARITY: 24 01 14 02 07 08 13 13 00 24 10 04 11 20 28 06

L309 XMIT DATA: . 02 14 01 13 08 07 24 00 13 11 04 10 06 28 20
EN PARITY: 06 20 12 24 01 01 02 05 25 18 05 30 20 12 21 29

L310 XMIT DATA: . 24 12 20 02 01 01 18 25 05 20 30 05 29 21 12
EN PARITY: 19 12 26 27 04 22 02 01 26 14 01 29 17 00 05 27

L311 XMIT DATA: . 27 26 12 02 22 04 14 26 01 17 29 01 27 05 00
EN PARITY: 01 21 02 21 03 15 27 02 28 30 16 00 00 29 26 05

L312 XMIT DATA: . 21 02 21 27 15 03 30 28 02 00 00 16 05 26 29
EN PARITY: 31 21 22 24 24 20 06 08 08 05 29 17 10 11 24 26

L313 XMIT DATA: . 24 22 21 06 20 24 05 08 08 10 17 29 26 24 11
EN PARITY: 28 10 24 23 00 21 11 08 28 20 10 25 27 15 18 20

L314 XMIT DATA: . 23 24 10 11 21 00 20 28 08 27 25 10 20 18 15
EN PARITY: 04 19 13 14 31 05 20 03 07 02 06 30 23 05 11 19

L315 XMIT DATA: . 14 13 19 20 05 31 02 07 03 23 30 06 19 11 05
EN PARITY: 05 06 17 05 01 23 24 03 09 01 22 11 02 02 10 26

L316 XMIT DATA: . 05 17 06 24 23 01 01 09 03 02 11 22 26 10 02
EN PARITY: 00 08 06 02 30 17 27 02 06 03 00 31 29 17 04 02

L317 XMIT DATA: . 02 06 08 27 17 30 03 06 02 29 31 00 02 04 17
EN PARITY: 13 18 14 04 02 27 25 24 09 16 13 22 17 10 16 18

L318 XMIT DATA: . 04 14 18 25 27 02 16 09 24 17 22 13 18 16 10
EN PARITY: 02 25 05 09 05 21 12 24 29 15 24 22 13 28 05 28

L319 XMIT DATA: . 09 05 25 12 21 05 15 29 24 13 22 24 28 05 28
EN PARITY: 16 03 07 16 12 03 14 26 10 00 27 16 09 11 04 04

L320 XMIT DATA: . 16 07 03 14 03 12 00 10 26 09 16 27 04 04 11
EN PARITY: 29 21 06 19 13 28 00 26 29 18 12 15 08 00 21 18

L321 XMIT DATA: . 19 06 21 00 28 13 18 29 26 08 15 12 18 21 00
EN PARITY: 24 17 21 06 17 26 07 17 31 03 19 28 12 09 21 23

L322 XMIT DATA: . 06 21 17 07 26 17 03 31 17 12 28 19 23 21 09
EN PARITY: 28 12 12 18 03 08 31 10 25 30 02 12 03 21 02 15

L323 XMIT DATA: . 18 12 12 31 08 03 30 25 10 03 12 02 15 02 21
EN PARITY: 10 03 15 11 02 26 03 06 00 20 18 10 17 28 00 22

L324 XMIT DATA: . 11 15 03 03 26 02 20 00 06 17 10 18 22 00 28
EN PARITY: 07 24 28 16 05 11 04 07 25 07 17 26 10 10 12 31

L325 XMIT DATA: . 16 28 24 04 11 05 07 25 07 10 26 17 31 12 10
EN PARITY: 03 16 20 15 06 22 12 20 12 24 05 27 17 18 15 03

L326 XMIT DATA: . 15 20 16 12 22 06 24 12 20 17 27 05 03 15 18
EN PARITY: 21 19 22 01 23 23 15 27 05 12 06 02 27 06 10 21

L327 XMIT DATA: . 01 22 19 15 23 23 12 05 27 27 02 06 21 10 06
EN PARITY: 20 25 29 19 00 07 20 09 15 10 02 30 12 21 05 31

L328 XMIT DATA: . 19 29 25 20 07 00 10 15 09 12 30 02 31 05 21
EN PARITY: 02 09 25 23 22 24 17 00 14 11 25 07 20 10 08 27

L329 XMIT DATA: . 23 25 09 17 24 22 11 14 00 20 07 25 27 08 10
EN PARITY: 27 00 23 19 05 08 06 28 20 25 20 27 30 12 00 15

L330 XMIT DATA: . 19 23 00 06 08 05 25 20 28 30 27 20 15 00 12
EN PARITY: 23 26 07 29 10 30 17 29 05 02 29 09 09 14 20 14

L331 XMIT DATA: . 29 07 26 17 30 10 02 05 29 09 09 29 14 20 14
EN PARITY: 12 23 26 14 00 28 07 31 10 30 09 15 28 25 29 31

L332 XMIT DATA: . 14 26 23 07 28 00 30 10 31 28 15 09 31 29 25
EN PARITY: 17 21 30 24 29 12 10 00 04 29 27 04 22 06 07 01

L333 XMIT DATA: . 24 30 21 10 12 29 29 04 00 22 04 27 01 07 06

EN PARITY: 11 23 02 31 29 10 17 21 07 06 25 20 07 08 23 06

L334 XMIT DATA: . 31 02 23 17 10 29 06 07 21 07 20 25 06 23 08
EN PARITY: 26 22 08 01 06 18 20 22 01 01 05 23 18 21 26 04

L335 XMIT DATA: . 01 08 22 20 18 06 01 01 22 18 23 05 04 26 21
EN PARITY: 30 11 11 22 07 11 03 22 03 10 09 28 29 19 25 18

L336 XMIT DATA: . 22 11 11 03 11 07 10 03 22 29 28 09 18 25 19
EN PARITY: 29 01 25 23 11 15 23 18 04 23 20 03 20 17 12 23

L337 XMIT DATA: . 23 25 01 23 15 11 23 04 18 20 03 20 23 12 17
EN PARITY: 13 21 18 02 07 11 18 29 22 31 31 27 08 03 06 00

L338 XMIT DATA: . 02 18 21 18 11 07 31 22 29 08 27 31 00 06 03
EN PARITY: 24 16 21 11 21 02 24 14 05 08 25 22 22 31 11 10

L339 XMIT DATA: . 11 21 16 24 02 21 08 05 14 22 22 25 10 11 31
EN PARITY: 04 16 13 24 03 00 11 15 23 11 24 13 04 28 20 15

L340 XMIT DATA: . 24 13 16 11 00 03 11 23 15 04 13 24 15 20 28
EN PARITY: 15 16 24 17 24 22 14 21 31 16 00 03 17 18 24 30

L341 XMIT DATA: . 17 24 16 14 22 24 16 31 21 17 03 00 30 24 18
EN PARITY: 21 13 26 20 18 05 07 21 03 19 00 18 22 13 05 28

L342 XMIT DATA: . 20 26 13 07 05 18 19 03 21 22 18 00 28 05 13
EN PARITY: 05 30 26 13 12 26 12 05 15 17 23 14 02 02 06 23

L343 XMIT DATA: . 13 26 30 12 26 12 17 15 05 02 14 23 23 06 02
EN PARITY: 15 07 29 22 05 06 09 17 05 11 27 08 26 15 01 24

L344 XMIT DATA: . 22 29 07 09 06 05 11 05 17 26 08 27 24 01 15
EN PARITY: 20 07 15 26 11 22 20 27 02 22 10 00 29 19 26 10

L345 XMIT DATA: . 26 15 07 20 22 11 22 02 27 29 00 10 10 26 19
EN PARITY: 25 10 11 30 20 03 09 08 09 31 20 02 18 19 07 04

L346 XMIT DATA: . 30 11 10 09 03 20 31 09 08 18 02 20 04 07 19
EN PARITY: 23 26 04 13 01 27 26 09 28 05 31 06 17 14 08 05

L347 XMIT DATA: . 13 04 26 26 27 01 05 28 09 17 06 31 05 08 14
EN PARITY: 05 02 21 27 29 13 08 20 31 26 27 30 16 12 02 10

L348 XMIT DATA: . 27 21 02 08 13 29 26 31 20 16 30 27 10 02 12
EN PARITY: 09 00 24 17 09 30 26 14 22 15 31 26 28 21 02 13

L349 XMIT DATA: . 17 24 00 26 30 09 15 22 14 28 26 31 13 02 21
EN PARITY: 01 14 00 23 14 08 01 05 06 20 30 12 09 07 04 05

L350 XMIT DATA: . 23 00 14 01 08 14 20 06 05 09 12 30 05 04 07
EN PARITY: 30 28 02 01 16 18 21 31 12 18 02 15 06 03 18 31

L351 XMIT DATA: . 01 02 28 21 18 16 18 12 31 06 15 02 31 18 03
EN PARITY: 24 23 26 24 25 06 27 03 25 08 10 20 14 06 02 17

L352 XMIT DATA: . 24 26 23 27 06 25 08 25 03 14 20 10 17 02 06
EN PARITY: 28 08 18 05 22 31 25 31 22 15 26 07 31 27 05 09

L353 XMIT DATA: . 05 18 08 25 31 22 15 22 31 31 07 26 09 05 27
EN PARITY: 10 09 16 16 15 18 00 09 23 27 00 03 22 30 17 11

L354 XMIT DATA: . 16 16 09 00 18 15 27 23 09 22 03 00 11 17 30
EN PARITY: 21 20 09 17 11 25 15 30 00 30 01 17 14 16 29 27

L355 XMIT DATA: . 17 09 20 15 25 11 30 00 30 14 17 01 27 29 16
EN PARITY: 14 02 30 06 08 04 13 25 11 11 29 04 23 14 28 24

L356 XMIT DATA: . 06 30 02 13 04 08 11 11 25 23 04 29 24 28 14
EN PARITY: 22 02 04 12 12 19 16 20 13 05 06 01 27 09 25 30

L357 XMIT DATA: . 12 04 02 16 19 12 05 13 20 27 01 06 30 25 09
EN PARITY: 03 06 06 02 13 30 29 21 18 01 14 25 11 15 29 17

L358 XMIT DATA: . 02 06 06 29 30 13 01 18 21 11 25 14 17 29 15
EN PARITY: 00 30 23 29 10 22 21 09 27 10 20 11 26 17 17 19

L359 XMIT DATA: . 29 23 30 21 22 10 10 27 09 26 11 20 19 17 17
EN PARITY: 02 02 13 26 13 10 12 27 29 19 08 16 10 27 28 11

L360 XMIT DATA: . 26 13 02 12 10 13 19 29 27 10 16 08 11 28 27
EN PARITY: 06 09 21 30 26 13 20 11 24 08 30 01 16 22 10 01

L361 XMIT DATA: . 30 21 09 20 13 26 08 24 11 16 01 30 01 10 22
EN PARITY: 22 07 02 10 14 16 04 27 30 16 00 22 26 18 27 12

L362 XMIT DATA: . 10 02 07 04 16 14 16 30 27 26 22 00 12 27 18
EN PARITY: 27 14 04 15 31 15 31 08 12 31 01 06 14 16 25 20

L363 XMIT DATA: . 15 04 14 31 15 31 31 12 08 14 06 01 20 25 16
EN PARITY: 26 12 27 16 21 29 10 13 06 04 29 29 17 03 15 28

L364 XMIT DATA: . 16 27 12 10 29 21 04 06 13 17 29 29 28 15 03
EN PARITY: 25 10 02 13 26 25 07 16 31 07 07 16 05 16 10 05

L365 XMIT DATA: . 13 02 10 07 25 26 07 31 16 05 16 07 05 10 16
EN PARITY: 16 16 14 21 12 25 06 28 30 24 22 03 27 15 14 09

L366 XMIT DATA: . 21 14 16 06 25 12 24 30 28 27 03 22 09 14 15
EN PARITY: 21 01 24 28 28 05 10 24 30 22 14 19 01 02 11 12

L367 XMIT DATA: . 28 24 01 10 05 28 22 30 24 01 19 14 12 11 02
EN PARITY: 07 31 31 09 15 23 30 07 28 02 04 16 03 23 12 11

L368 XMIT DATA: . 09 31 31 30 23 15 02 28 07 03 16 04 11 12 23
EN PARITY: 28 18 09 00 21 10 01 25 13 15 25 18 04 26 18 03

L369 XMIT DATA: . 00 09 18 01 10 21 15 13 25 04 18 25 03 18 26
EN PARITY: 06 05 08 16 28 23 00 04 28 11 14 23 07 25 08 10

L370 XMIT DATA: . 16 08 05 00 23 28 11 28 04 07 23 14 10 08 25
EN PARITY: 01 17 23 15 21 01 14 12 09 09 26 06 09 26 28 18

L371 XMIT DATA: . 15 23 17 14 01 21 09 09 12 09 06 26 18 28 26
EN PARITY: 16 03 17 16 24 20 03 22 26 24 01 15 06 07 28 20

L372 XMIT DATA: . 16 17 03 03 20 24 24 26 22 06 15 01 20 28 07
EN PARITY: 26 06 09 10 10 01 23 06 17 15 28 30 07 19 10 16

L373 XMIT DATA: . 10 09 06 23 01 10 15 17 06 07 30 28 16 10 19
EN PARITY: 20 28 05 10 00 31 18 29 11 03 06 27 11 10 30 07

L374 XMIT DATA: . 10 05 28 18 31 00 03 11 29 11 27 06 07 30 10
EN PARITY: 16 17 22 29 00 31 21 17 09 10 13 28 01 20 20 15

L375 XMIT DATA: . 29 22 17 21 31 00 10 09 17 01 28 13 15 20 20
EN PARITY: 29 24 30 24 16 31 10 31 28 28 29 27 03 00 04 03

L376 XMIT DATA: . 24 30 24 10 31 16 28 28 31 03 27 29 03 04 00
EN PARITY: 30 06 02 02 17 15 06 10 06 10 28 30 02 07 14 15

L377 XMIT DATA: . 02 02 06 06 15 17 10 06 10 02 30 28 15 14 07
EN PARITY: 25 06 18 30 09 14 16 10 11 18 19 09 25 05 23 17

L378 XMIT DATA: . 30 18 06 16 14 09 18 11 10 25 09 19 17 23 05
EN PARITY: 21 15 06 29 05 01 00 29 30 19 24 15 08 30 17 28

L379 XMIT DATA: . 29 06 15 00 01 05 19 30 29 08 15 24 28 17 30
EN PARITY: 13 10 14 21 29 06 26 01 31 00 28 21 16 10 10 19

L380 XMIT DATA: . 21 14 10 26 06 29 00 31 01 16 21 28 19 10 10
EN PARITY: 19 23 11 10 30 12 05 08 11 10 23 24 27 20 27 11

L381 XMIT DATA: . 10 11 23 05 12 30 10 11 08 27 24 23 11 27 20
EN PARITY: 00 10 09 18 12 27 18 30 01 05 30 18 30 01 15 06

L382 XMIT DATA: . 18 09 10 18 27 12 05 01 30 30 18 30 06 15 01
EN PARITY: 08 29 22 26 24 15 05 22 31 16 14 18 04 01 28 01

L383 XMIT DATA: . 26 22 29 05 15 24 16 31 22 04 18 14 01 28 01
EN PARITY: 13 17 08 19 11 26 27 11 10 11 19 16 15 09 21 04

L384 XMIT DATA: . 19 08 17 27 26 11 11 10 11 15 16 19 04 21 09
EN PARITY: 09 30 02 21 29 17 13 01 02 03 06 11 00 26 06 07

L385 XMIT DATA: . 21 02 30 13 17 29 03 02 01 00 11 06 07 06 26
EN PARITY: 06 15 04 05 11 00 00 21 12 11 00 24 20 24 08 12

L386 XMIT DATA: . 05 04 15 00 00 11 11 12 21 20 24 00 12 08 24
EN PARITY: 04 26 28 31 13 31 16 05 30 03 30 08 23 16 20 29

L387 XMIT DATA: . 31 28 26 16 31 13 03 30 05 23 08 30 29 20 16
EN PARITY: 01 24 23 14 05 14 10 26 07 16 18 15 19 01 00 06

L388 XMIT DATA: . 14 23 24 10 14 05 16 07 26 19 15 18 06 00 01
EN PARITY: 21 06 08 07 06 20 10 04 27 19 31 27 19 28 29 22

L389 XMIT DATA: . 07 08 06 10 20 06 19 27 04 19 27 31 22 29 28
EN PARITY: 24 26 13 17 08 28 16 16 27 26 26 14 28 29 20 04

L390 XMIT DATA: . 17 13 26 16 28 08 26 27 16 28 14 26 04 20 29
EN PARITY: 17 09 23 27 01 14 01 00 16 20 31 16 26 25 15 07

L391 XMIT DATA: . 27 23 09 01 14 01 20 16 00 26 16 31 07 15 25
EN PARITY: 31 25 18 17 17 25 09 15 04 10 14 05 09 29 11 23

L392 XMIT DATA: . 17 18 25 09 25 17 10 04 15 09 05 14 23 11 29
EN PARITY: 11 00 09 11 16 08 13 07 11 25 31 22 15 00 29 18

L393 XMIT DATA: . 11 09 00 13 08 16 25 11 07 15 22 31 18 29 00
EN PARITY: 16 18 16 20 18 11 24 03 30 08 31 00 10 02 10 24

L394 XMIT DATA: . 20 16 18 24 11 18 08 30 03 10 00 31 24 10 02
EN PARITY: 10 10 15 01 05 21 15 16 01 07 27 02 18 18 10 07

L395 XMIT DATA: . 01 15 10 15 21 05 07 01 16 18 02 27 07 10 18

EN PARITY: 03 11 15 10 08 11 14 27 28 14 14 24 23 28 18 00

L396 XMIT DATA: . 10 15 11 14 11 08 14 28 27 23 24 14 00 18 28
EN PARITY: 23 23 04 05 14 06 13 22 27 17 09 26 03 20 22 28

L397 XMIT DATA: . 05 04 23 13 06 14 17 27 22 03 26 09 28 22 20
EN PARITY: 03 27 22 16 27 31 25 00 18 22 03 06 17 10 03 13

L398 XMIT DATA: . 16 22 27 25 31 27 22 18 00 17 06 03 13 03 10
EN PARITY: 23 13 04 06 27 28 18 06 03 15 08 18 14 11 25 14

L399 XMIT DATA: . 06 04 13 18 28 27 15 03 06 14 18 08 14 25 11
EN PARITY: 27 07 11 22 18 07 24 18 26 18 31 11 15 05 08 12

L400 XMIT DATA: . 22 11 07 24 07 18 18 26 18 15 11 31 12 08 05
EN PARITY: 22 25 00 22 09 10 09 12 04 06 28 14 18 10 30 19

L401 XMIT DATA: . 22 00 25 09 10 09 06 04 12 18 14 28 19 30 10
EN PARITY: 06 29 21 25 02 16 20 22 06 06 17 12 07 27 26 11

L402 XMIT DATA: . 25 21 29 20 16 02 06 06 22 07 12 17 11 26 27
EN PARITY: 09 02 06 27 01 13 30 26 30 23 29 00 22 08 01 09

L403 XMIT DATA: . 27 06 02 30 13 01 23 30 26 22 00 29 09 01 08
EN PARITY: 29 10 14 01 16 16 18 22 04 26 31 24 08 04 26 14

L404 XMIT DATA: . 01 14 10 18 16 16 26 04 22 08 24 31 14 26 04
EN PARITY: 25 10 28 08 13 23 05 10 27 18 21 23 28 27 19 08

L405 XMIT DATA: . 08 28 10 05 23 13 18 27 10 28 23 21 08 19 27
EN PARITY: 29 24 06 27 09 30 04 11 08 20 12 05 14 02 19 07

L406 XMIT DATA: . 27 06 24 04 30 09 20 08 11 14 05 12 07 19 02
EN PARITY: 25 02 24 00 00 07 10 08 13 11 24 23 20 06 07 12

L407 XMIT DATA: . 00 24 02 10 07 00 11 13 08 20 23 24 12 07 06
EN PARITY: 14 11 03 10 01 18 08 28 24 02 08 23 11 05 19 31

L408 XMIT DATA: . 10 03 11 08 18 01 02 24 28 11 23 08 31 19 05
EN PARITY: 24 03 24 04 22 03 24 25 26 19 13 19 28 31 01 15

L409 XMIT DATA: . 04 24 03 24 03 22 19 26 25 28 19 13 15 01 31
EN PARITY: 08 26 08 06 11 25 31 20 05 22 16 03 14 24 05 03

L410 XMIT DATA: . 06 08 26 31 25 11 22 05 20 14 03 16 03 05 24
EN PARITY: 04 16 03 30 10 10 02 00 22 05 28 22 20 30 16 02

L411 XMIT DATA: . 30 03 16 02 10 10 05 22 00 20 22 28 02 16 30
EN PARITY: 11 09 23 09 00 25 31 01 02 05 19 00 03 15 29 18

L412 XMIT DATA: . 09 23 09 31 25 00 05 02 01 03 00 19 18 29 15
EN PARITY: 09 31 16 05 20 23 17 16 29 25 10 17 24 21 02 29

L413 XMIT DATA: . 05 16 31 17 23 20 25 29 16 24 17 10 29 02 21
EN PARITY: 05 08 11 19 19 06 25 15 18 19 31 20 29 03 23 13

L414 XMIT DATA: . 19 11 08 25 06 19 19 18 15 29 20 31 13 23 03
EN PARITY: 00 10 13 21 22 17 03 16 29 17 27 19 26 25 18 05

L415 XMIT DATA: . 21 13 10 03 17 22 17 29 16 26 19 27 05 18 25
EN PARITY: 13 05 22 17 16 24 00 15 15 22 20 01 18 04 14 17

L416 XMIT DATA: . 17 22 05 00 24 16 22 15 15 18 01 20 17 14 04
EN PARITY: 30 15 27 31 23 00 00 11 31 07 17 08 17 25 11 25

L417 XMIT DATA: . 31 27 15 00 00 23 07 31 11 17 08 17 25 11 25
EN PARITY: 08 21 28 19 01 07 10 26 03 00 00 07 22 15 02 18

L418 XMIT DATA: . 19 28 21 10 07 01 00 03 26 22 07 00 18 02 15
EN PARITY: 04 06 23 14 16 27 19 18 08 18 04 20 02 25 12 09

L419 XMIT DATA: . 14 23 06 19 27 16 18 08 18 02 20 04 09 12 25
EN PARITY: 13 02 13 04 13 08 23 20 12 30 03 05 26 21 15 20

L420 XMIT DATA: . 04 13 02 23 08 13 30 12 20 26 05 03 20 15 21
EN PARITY: 21 25 03 01 05 16 16 01 02 10 28 04 26 30 13 13

L421 XMIT DATA: . 01 03 25 16 16 05 10 02 01 26 04 28 13 13 30
EN PARITY: 28 28 14 25 00 06 18 00 10 09 25 31 18 28 12 04

L422 XMIT DATA: . 25 14 28 18 06 00 09 10 00 18 31 25 04 12 28
EN PARITY: 09 31 08 14 18 09 24 30 11 14 12 12 22 04 28 27

L423 XMIT DATA: . 14 08 31 24 09 18 14 11 30 22 12 12 27 28 04
EN PARITY: 04 23 24 17 08 03 17 21 10 21 31 07 18 31 19 15

L424 XMIT DATA: . 17 24 23 17 03 08 21 10 21 18 07 31 15 19 31
EN PARITY: 02 29 27 05 22 15 08 14 08 12 26 24 31 13 02 12

L425 XMIT DATA: . 05 27 29 08 15 22 12 08 14 31 24 26 12 02 13
EN PARITY: 05 11 12 10 08 09 24 18 05 02 23 05 11 26 31 05

L426 XMIT DATA: . 10 12 11 24 09 08 02 05 18 11 05 23 05 31 26
EN PARITY: 25 03 21 13 24 13 29 30 13 20 06 12 26 10 05 21

L427 XMIT DATA: . 13 21 03 29 13 24 20 13 30 26 12 06 21 05 10
EN PARITY: 17 06 17 00 05 07 24 20 06 17 06 27 14 20 06 19

L428 XMIT DATA: . 00 17 06 24 07 05 17 06 20 14 27 06 19 06 20
EN PARITY: 11 25 29 08 09 22 16 21 17 03 05 05 27 16 16 05

L429 XMIT DATA: . 08 29 25 16 22 09 03 17 21 27 05 05 05 16 16
EN PARITY: 25 16 23 10 20 12 08 16 02 04 13 27 16 23 14 31

L430 XMIT DATA: . 10 23 16 08 12 20 04 02 16 16 27 13 31 14 23
EN PARITY: 16 27 28 23 20 28 16 03 30 08 17 26 10 04 24 02

L431 XMIT DATA: . 23 28 27 16 28 20 08 30 03 10 26 17 02 24 04
EN PARITY: 22 16 00 13 29 14 11 23 13 30 01 23 19 20 10 04

L432 XMIT DATA: . 13 00 16 11 14 29 30 13 23 19 23 01 04 10 20
EN PARITY: 14 08 18 03 22 23 15 21 10 12 27 12 20 09 08 17

L433 XMIT DATA: . 03 18 08 15 23 22 12 10 21 20 12 27 17 08 09
EN PARITY: 02 18 26 31 06 21 05 23 09 00 00 21 27 22 00 07

L434 XMIT DATA: . 31 26 18 05 21 06 00 09 23 27 21 00 07 00 22
EN PARITY: 11 05 28 13 28 28 04 01 11 31 04 05 13 01 04 08

L435 XMIT DATA: . 13 28 05 04 28 28 31 11 01 13 05 04 08 04 01
EN PARITY: 29 21 23 18 02 09 04 11 06 23 16 10 12 31 19 07

L436 XMIT DATA: . 18 23 21 04 09 02 23 06 11 12 10 16 07 19 31
EN PARITY: 13 31 30 18 30 11 22 24 12 27 31 13 18 23 12 30

L437 XMIT DATA: . 18 30 31 22 11 30 27 12 24 18 13 31 30 12 23
EN PARITY: 19 07 09 00 31 31 22 12 03 12 27 05 02 31 11 15

L438 XMIT DATA: . 00 09 07 22 31 31 12 03 12 02 05 27 15 11 31
EN PARITY: 03 06 31 15 29 30 10 28 28 18 31 03 06 18 08 14

L439 XMIT DATA: . 15 31 06 10 30 29 18 28 28 06 03 31 14 08 18
EN PARITY: 25 08 03 23 31 04 25 29 02 08 00 21 24 19 24 21

L440 XMIT DATA: . 23 03 08 25 04 31 08 02 29 24 21 00 21 24 19
EN PARITY: 19 24 31 25 00 12 12 25 09 15 14 31 06 29 31 16

L441 XMIT DATA: . 25 31 24 12 12 00 15 09 25 06 31 14 16 31 29
EN PARITY: 25 29 28 05 25 08 26 15 01 18 28 20 11 12 22 27

L442 XMIT DATA: . 05 28 29 26 08 25 18 01 15 11 20 28 27 22 12
EN PARITY: 31 21 12 10 14 05 08 13 21 20 24 27 02 03 03 12

L443 XMIT DATA: . 10 12 21 08 05 14 20 21 13 02 27 24 12 03 03
EN PARITY: 25 22 14 28 12 15 04 14 14 00 20 11 06 26 10 13

L444 XMIT DATA: . 28 14 22 04 15 12 00 14 14 06 11 20 13 10 26
EN PARITY: 29 28 08 31 21 07 05 07 02 07 25 24 12 25 19 25

L445 XMIT DATA: . 31 08 28 05 07 21 07 02 07 12 24 25 25 19 25
EN PARITY: 17 05 04 16 04 18 18 10 02 15 19 05 07 07 22 18

L446 XMIT DATA: . 16 04 05 18 18 04 15 02 10 07 05 19 18 22 07
EN PARITY: 05 25 22 07 12 17 26 10 14 15 14 31 08 13 19 14

L447 XMIT DATA: . 07 22 25 26 17 12 15 14 10 08 31 14 14 19 13
EN PARITY: 11 08 13 24 03 09 03 15 26 13 06 14 12 20 20 05

L448 XMIT DATA: . 24 13 08 03 09 03 13 26 15 12 14 06 05 20 20
EN PARITY: 15 14 30 29 12 17 13 05 18 01 16 05 07 24 28 29

L449 XMIT DATA: . 29 30 14 13 17 12 01 18 05 07 05 16 29 28 24
EN PARITY: 04 21 28 10 05 03 20 21 11 12 18 24 28 18 06 16

L450 XMIT DATA: . 10 28 21 20 03 05 12 11 21 28 24 18 16 06 18
EN PARITY: 23 29 03 27 01 28 28 20 03 21 09 02 19 03 29 30

L451 XMIT DATA: . 27 03 29 28 28 01 21 03 20 19 02 09 30 29 03
EN PARITY: 13 19 12 04 13 13 07 26 00 31 23 15 14 30 05 06

L452 XMIT DATA: . 04 12 19 07 13 13 31 00 26 14 15 23 06 05 30
EN PARITY: 10 24 11 04 10 06 25 05 18 14 03 19 09 00 27 20

L453 XMIT DATA: . 04 11 24 25 06 10 14 18 05 09 19 03 20 27 00
EN PARITY: 18 26 23 19 28 14 13 31 29 24 06 08 24 03 27 05

L454 XMIT DATA: . 19 23 26 13 14 28 24 29 31 24 08 06 05 27 03
EN PARITY: 19 24 31 02 09 18 21 27 29 27 19 18 19 10 02 15

L455 XMIT DATA: . 02 31 24 21 18 09 27 29 27 19 18 19 15 02 10
EN PARITY: 04 07 09 17 03 31 19 05 07 19 11 27 16 07 25 01

L456 XMIT DATA: . 17 09 07 19 31 03 19 07 05 16 27 11 01 25 07
EN PARITY: 05 14 13 10 15 20 30 10 21 13 15 11 20 10 09 14

L457 XMIT DATA: . 10 13 14 30 20 15 13 21 10 20 11 15 14 09 10

EN PARITY: 02 05 19 21 25 15 31 12 03 21 16 08 22 11 16 23

L458 XMIT DATA: . 21 19 05 31 15 25 21 03 12 22 08 16 23 16 11
EN PARITY: 21 17 22 13 09 23 17 27 00 22 08 06 21 13 28 16

L459 XMIT DATA: . 13 22 17 17 23 09 22 00 27 21 06 08 16 28 13
EN PARITY: 18 00 09 13 07 11 14 18 26 30 09 15 18 21 13 06

L460 XMIT DATA: . 13 09 00 14 11 07 30 26 18 18 15 09 06 13 21
EN PARITY: 00 11 08 24 17 08 00 21 26 27 11 22 25 21 09 17

L461 XMIT DATA: . 24 08 11 00 08 17 27 26 21 25 22 11 17 09 21
EN PARITY: 00 11 24 29 00 01 03 10 00 00 26 16 05 20 02 09

L462 XMIT DATA: . 29 24 11 03 01 00 00 00 10 05 16 26 09 02 20
EN PARITY: 07 28 15 00 12 29 27 27 28 22 23 00 24 02 23 09

L463 XMIT DATA: . 00 15 28 27 29 12 22 28 27 24 00 23 09 23 02
EN PARITY: 12 19 31 23 22 07 16 20 28 10 15 06 17 01 12 11

L464 XMIT DATA: . 23 31 19 16 07 22 10 28 20 17 06 15 11 12 01
EN PARITY: 05 30 08 13 17 31 00 08 16 09 09 11 06 01 28 04

L465 XMIT DATA: . 13 08 30 00 31 17 09 16 08 06 11 09 04 28 01
EN PARITY: 07 01 00 10 23 22 08 25 06 00 25 25 17 15 23 00

L466 XMIT DATA: . 10 00 01 08 22 23 00 06 25 17 25 25 00 23 15
EN PARITY: 22 18 05 24 03 00 20 07 25 30 15 22 10 03 21 01

L467 XMIT DATA: . 24 05 18 20 00 03 30 25 07 10 22 15 01 21 03
EN PARITY: 22 29 13 26 13 08 22 07 22 27 25 02 28 18 13 11

L468 XMIT DATA: . 26 13 29 22 08 13 27 22 07 28 02 25 11 13 18
EN PARITY: 30 11 29 20 12 19 02 24 25 15 14 29 30 27 18 07

L469 XMIT DATA: . 20 29 11 02 19 12 15 25 24 30 29 14 07 18 27
EN PARITY: 04 02 09 14 10 18 22 28 15 04 07 04 18 26 10 10

L470 XMIT DATA: . 14 09 02 22 18 10 04 15 28 18 04 07 10 10 26
EN PARITY: 07 04 30 26 00 14 11 20 15 09 31 25 03 07 01 08

L471 XMIT DATA: . 26 30 04 11 14 00 09 15 20 03 25 31 08 01 07
EN PARITY: 12 03 02 25 08 15 05 23 20 22 19 27 30 18 02 02

L472 XMIT DATA: . 25 02 03 05 15 08 22 20 23 30 27 19 02 02 18
EN PARITY: 16 04 19 25 13 15 21 31 15 21 21 00 27 07 23 13

L473 XMIT DATA: . 25 19 04 21 15 13 21 15 31 27 00 21 13 23 07
EN PARITY: 13 07 02 30 10 15 20 10 11 21 30 06 16 24 13 18

L474 XMIT DATA: . 30 02 07 20 15 10 21 11 10 16 06 30 18 13 24
EN PARITY: 00 18 02 20 14 07 19 05 18 07 03 16 25 26 11 08

L475 XMIT DATA: . 20 02 18 19 07 14 07 18 05 25 16 03 08 11 26
EN PARITY: 24 30 00 04 17 18 15 08 13 28 11 19 00 11 03 16

L476 XMIT DATA: . 04 00 30 15 18 17 28 13 08 00 19 11 16 03 11
EN PARITY: 11 03 11 28 19 10 04 20 28 16 13 20 08 04 21 25

L477 XMIT DATA: . 28 11 03 04 10 19 16 28 20 08 20 13 25 21 04
EN PARITY: 19 23 01 11 14 19 11 17 04 08 31 02 20 02 13 01

L478 XMIT DATA: . 11 01 23 11 19 14 08 04 17 20 02 31 01 13 02
EN PARITY: 25 20 29 27 30 12 30 17 02 27 20 03 03 22 00 22

L479 XMIT DATA: . 27 29 20 30 12 30 27 02 17 03 03 20 22 00 22
EN PARITY: 14 15 23 10 12 01 21 30 05 15 28 05 10 16 02 12

L480 XMIT DATA: . 10 23 15 21 01 12 15 05 30 10 05 28 12 02 16
EN PARITY: 24 04 21 22 04 16 10 07 30 08 28 12 01 29 17 25

L481 XMIT DATA: . 22 21 04 10 16 04 08 30 07 01 12 28 25 17 29
EN PARITY: 04 21 12 06 25 05 00 08 04 04 04 24 10 31 08 06

L482 XMIT DATA: . 06 12 21 00 05 25 04 04 08 10 24 04 06 08 31
EN PARITY: 30 21 03 08 15 07 20 29 23 26 10 18 11 11 20 25

L483 XMIT DATA: . 08 03 21 20 07 15 26 23 29 11 18 10 25 20 11
EN PARITY: 19 17 07 12 01 14 08 19 22 10 25 19 31 14 19 20

L484 XMIT DATA: . 12 07 17 08 14 01 10 22 19 31 19 25 20 19 14
EN PARITY: 23 01 05 10 25 09 25 28 01 03 20 11 15 19 09 02

L485 XMIT DATA: . 10 05 01 25 09 25 03 01 28 15 11 20 02 09 19
EN PARITY: 29 05 21 30 03 06 02 21 19 28 22 11 08 09 11 23

L486 XMIT DATA: . 30 21 05 02 06 03 28 19 21 08 11 22 23 11 09
EN PARITY: 30 25 02 19 19 19 24 29 19 26 19 00 24 28 15 08

L487 XMIT DATA: . 19 02 25 24 19 19 26 19 29 24 00 19 08 15 28
EN PARITY: 06 27 26 17 10 02 02 15 10 19 02 11 12 22 12 23

L488 XMIT DATA: . 17 26 27 02 02 10 19 10 15 12 11 02 23 12 22
EN PARITY: 24 31 07 13 04 16 03 28 01 02 31 26 10 13 12 08

L489 XMIT DATA: . 13 07 31 03 16 04 02 01 28 10 26 31 08 12 13
EN PARITY: 04 24 26 05 26 16 17 06 29 25 31 09 19 08 07 11

L490 XMIT DATA: . 05 26 24 17 16 26 25 29 06 19 09 31 11 07 08
EN PARITY: 08 24 27 02 10 21 02 29 17 24 15 25 09 28 25 03

L491 XMIT DATA: . 02 27 24 02 21 10 24 17 29 09 25 15 03 25 28
EN PARITY: 07 28 29 30 03 10 24 03 24 22 05 00 03 10 25 24

L492 XMIT DATA: . 30 29 28 24 10 03 22 24 03 03 00 05 24 25 10
EN PARITY: 15 22 17 04 03 01 03 07 00 22 09 04 31 31 13 09

L493 XMIT DATA: . 04 17 22 03 01 03 22 00 07 31 04 09 09 13 31
EN PARITY: 17 29 02 16 24 12 27 05 20 02 10 01 01 22 20 27

L494 XMIT DATA: . 16 02 29 27 12 24 02 20 05 01 01 10 27 20 22
EN PARITY: 23 01 23 13 13 04 09 02 21 25 29 04 31 02 24 05

L495 XMIT DATA: . 13 23 01 09 04 13 25 21 02 31 04 29 05 24 02
EN PARITY: 27 14 24 00 22 21 28 03 17 09 15 14 29 20 23 05

L496 XMIT DATA: . 00 24 14 28 21 22 09 17 03 29 14 15 05 23 20
EN PARITY: 22 12 09 14 19 24 26 04 23 29 02 31 19 30 26 04

L497 XMIT DATA: . 14 09 12 26 24 19 29 23 04 19 31 02 04 26 30
EN PARITY: 11 02 26 08 04 20 31 08 27 00 11 04 20 00 16 17

L498 XMIT DATA: . 08 26 02 31 20 04 00 27 08 20 04 11 17 16 00
EN PARITY: 23 20 14 10 13 27 17 05 31 08 25 14 17 03 25 14

L499 XMIT DATA: . 10 14 20 17 27 13 08 31 05 17 14 25 14 25 03
EN PARITY: 14 27 14 29 04 10 25 13 16 23 08 22 28 29 23 25

L500 XMIT DATA: . 29 14 27 25 10 04 23 16 13 28 22 08 25 23 29
EN PARITY: 28 07 13 30 22 25 19 26 30 17 18 06 19 13 31 11

L501 XMIT DATA: . 30 13 07 19 25 22 17 30 26 19 06 18 11 31 13
EN PARITY: 19 06 25 20 18 21 02 20 18 18 07 21 03 20 18 13

L502 XMIT DATA: . 20 25 06 02 21 18 18 18 20 03 21 07 13 18 20
EN PARITY: 26 12 31 21 18 27 28 08 16 16 26 08 19 25 24 28

L503 XMIT DATA: . 21 31 12 28 27 18 16 16 08 19 08 26 28 24 25
EN PARITY: 17 06 26 18 19 08 22 12 07 04 28 14 18 22 27 19

L504 XMIT DATA: . 18 26 06 22 08 19 04 07 12 18 14 28 19 27 22
EN PARITY: 17 12 13 21 16 15 23 00 26 30 14 10 26 18 22 14

L505 XMIT DATA: . 21 13 12 23 15 16 30 26 00 26 10 14 14 22 18
EN PARITY: 14 15 10 28 25 29 20 18 00 05 31 04 24 00 27 29

L506 XMIT DATA: . 28 10 15 20 29 25 05 00 18 24 04 31 29 27 00
EN PARITY: 28 23 10 26 08 03 02 03 21 18 28 22 22 07 24 17

L507 XMIT DATA: . 26 10 23 02 03 08 18 21 03 22 22 28 17 24 07
EN PARITY: 19 17 05 25 26 29 23 23 05 11 29 22 21 17 21 20

L508 XMIT DATA: . 25 05 17 23 29 26 11 05 23 21 22 29 20 21 17
EN PARITY: 18 22 05 00 13 10 22 26 06 23 28 25 14 18 31 18

L509 XMIT DATA: . 00 05 22 22 10 13 23 06 26 14 25 28 18 31 18
EN PARITY: 12 16 28 13 26 20 11 19 01 16 16 01 15 07 24 06

L510 XMIT DATA: . 13 28 16 11 20 26 16 01 19 15 01 16 06 24 07
EN PARITY: 21 07 05 00 19 04 29 21 11 07 30 05 13 19 06 28

L511 XMIT DATA: . 00 05 07 29 04 19 07 11 21 13 05 30 28 06 19
EN PARITY: 17 07 22 12 10 03 27 15 30 28 25 28 24 15 21 17

L512 XMIT DATA: . 12 22 07 27 03 10 28 30 15 24 28 25 17 21 15
EN PARITY: 29 21 17 01 27 10 16 07 23 22 05 07 23 26 02 05

L513 XMIT DATA: . 01 17 21 16 10 27 22 23 07 23 07 05 05 02 26
EN PARITY: 31 16 00 16 23 25 00 06 30 28 03 19 20 08 19 25

L514 XMIT DATA: . 16 00 16 00 25 23 28 30 06 20 19 03 25 19 08
EN PARITY: 12 19 13 30 04 10 04 17 10 18 00 13 17 14 26 20

L515 XMIT DATA: . 30 13 19 04 10 04 18 10 17 17 13 00 20 26 14
EN PARITY: 14 00 14 12 10 08 00 05 17 11 13 28 05 02 24 24

L516 XMIT DATA: . 12 14 00 00 08 10 11 17 05 05 28 13 24 24 02
EN PARITY: 17 15 17 10 10 02 27 15 06 16 17 15 04 17 11 18

L517 XMIT DATA: . 10 17 15 27 02 10 16 06 15 04 15 17 18 11 17
EN PARITY: 07 07 12 00 30 06 29 24 11 14 20 16 11 31 25 23

L518 XMIT DATA: . 00 12 07 29 06 30 14 11 24 11 16 20 23 25 31
EN PARITY: 29 08 01 09 08 28 15 17 24 03 06 27 14 02 12 29

L519 XMIT DATA: . 09 01 08 15 28 08 03 24 17 14 27 06 29 12 02

EN PARITY: 27 11 17 00 11 07 27 12 26 06 22 00 26 09 17 06

L520 XMIT DATA: . 00 17 11 27 07 11 06 26 12 26 00 22 06 17 09
EN PARITY: 14 12 03 12 31 22 17 30 05 04 17 12 08 18 11 10

L521 XMIT DATA: . 12 03 12 17 22 31 04 05 30 08 12 17 10 11 18
EN PARITY: 28 22 16 14 05 27 03 20 31 16 01 31 09 03 00 18

L522 XMIT DATA: . 14 16 22 03 27 05 16 31 20 09 31 01 18 00 03
EN PARITY: 00 00 06 07 12 07 02 29 29 10 00 22 24 05 28 01

L523 XMIT DATA: . 07 06 00 02 07 12 10 29 29 24 22 00 01 28 05
EN PARITY: 09 13 31 00 03 09 20 18 07 17 06 27 24 16 02 13

L524 XMIT DATA: . 00 31 13 20 09 03 17 07 18 24 27 06 13 02 16
EN PARITY: 21 24 18 26 21 22 19 11 00 30 13 20 14 11 08 03

L525 XMIT DATA: . 26 18 24 19 22 21 30 00 11 14 20 13 03 08 11
EN PARITY: 22 18 07 12 10 03 30 28 06 02 26 01 20 07 24 02

L526 XMIT DATA: . 12 07 18 30 03 10 02 06 28 20 01 26 02 24 07
EN PARITY: 00 08 12 11 05 10 11 09 00 25 10 07 17 27 28 19

L527 XMIT DATA: . 11 12 08 11 10 05 25 00 09 17 07 10 19 28 27
EN PARITY: 12 02 26 20 15 29 26 13 14 28 13 23 29 30 20 09

L528 XMIT DATA: . 20 26 02 26 29 15 28 14 13 29 23 13 09 20 30
EN PARITY: 03 11 27 13 03 06 10 09 29 11 15 00 31 28 01 25

L529 XMIT DATA: . 13 27 11 10 06 03 11 29 09 31 00 15 25 01 28
EN PARITY: 11 29 12 18 26 09 21 00 27 08 09 30 18 29 09 08

L530 XMIT DATA: . 18 12 29 21 09 26 08 27 00 18 30 09 08 09 29
EN PARITY: 11 17 27 14 07 25 05 06 31 10 26 16 07 27 24 21

L531 XMIT DATA: . 14 27 17 05 25 07 10 31 06 07 16 26 21 24 27
EN PARITY: 06 10 02 11 15 22 31 10 18 05 14 28 21 13 02 30

L532 XMIT DATA: . 11 02 10 31 22 15 05 18 10 21 28 14 30 02 13
EN PARITY: 05 29 14 08 22 00 26 27 20 14 10 21 16 30 15 18

L533 XMIT DATA: . 08 14 29 26 00 22 14 20 27 16 21 10 18 15 30
EN PARITY: 28 11 01 30 19 16 04 14 01 05 04 20 04 19 12 16

L534 XMIT DATA: . 30 01 11 04 16 19 05 01 14 04 20 04 16 12 19
EN PARITY: 14 17 29 19 13 09 19 30 12 06 22 18 11 25 11 21

L535 XMIT DATA: . 19 29 17 19 09 13 06 12 30 11 18 22 21 11 25
EN PARITY: 10 27 03 07 24 18 26 16 12 00 25 17 22 00 12 13

L536 XMIT DATA: . 07 03 27 26 18 24 00 12 16 22 17 25 13 12 00
EN PARITY: 04 04 27 26 23 31 06 18 13 21 13 19 10 25 26 25

L537 XMIT DATA: . 26 27 04 06 31 23 21 13 18 10 19 13 25 26 25
EN PARITY: 15 04 22 15 17 08 10 04 24 17 21 31 31 05 02 19

L538 XMIT DATA: . 15 22 04 10 08 17 17 24 04 31 31 21 19 02 05
EN PARITY: 27 05 05 25 06 18 04 30 02 05 27 16 28 08 04 02

L539 XMIT DATA: . 25 05 05 04 18 06 05 02 30 28 16 27 02 04 08
EN PARITY: 16 05 23 02 12 01 26 19 16 08 08 10 05 02 20 04

L540 XMIT DATA: . 02 23 05 26 01 12 08 16 19 05 10 08 04 20 02
EN PARITY: 16 17 20 11 20 01 25 00 23 00 14 24 19 30 08 11

L541 XMIT DATA: . 11 20 17 25 01 20 00 23 00 19 24 14 11 08 30
EN PARITY: 10 24 03 03 21 03 04 13 02 19 25 30 19 00 13 02

L542 XMIT DATA: . 03 03 24 04 03 21 19 02 13 19 30 25 02 13 00
EN PARITY: 14 28 09 00 12 13 18 09 30 30 09 23 16 09 21 02

L543 XMIT DATA: . 00 09 28 18 13 12 30 30 09 16 23 09 02 21 09
EN PARITY: 04 26 18 14 02 20 11 20 16 21 21 05 17 23 02 26

L544 XMIT DATA: . 14 18 26 11 20 02 21 16 20 17 05 21 26 02 23
EN PARITY: 30 01 24 28 11 13 06 29 12 31 00 07 02 14 04 00

L545 XMIT DATA: . 28 24 01 06 13 11 31 12 29 02 07 00 00 04 14
EN PARITY: 02 10 08 27 01 16 13 08 13 02 11 01 17 17 24 25

L546 XMIT DATA: . 27 08 10 13 16 01 02 13 08 17 01 11 25 24 17
EN PARITY: 14 14 21 11 29 05 10 26 20 04 04 28 00 30 14 07

L547 XMIT DATA: . 11 21 14 10 05 29 04 20 26 00 28 04 07 14 30
EN PARITY: 05 08 21 26 23 30 20 25 18 00 24 19 31 31 21 27

L548 XMIT DATA: . 26 21 08 20 30 23 00 18 25 31 19 24 27 21 31
EN PARITY: 03 29 15 03 10 06 30 19 20 09 14 10 01 07 30 29

L549 XMIT DATA: . 03 15 29 30 06 10 09 20 19 01 10 14 29 30 07
EN PARITY: 22 30 16 05 28 25 28 24 31 10 14 18 25 25 08 05

L550 XMIT DATA: . 05 16 30 28 25 28 10 31 24 25 18 14 05 08 25
EN PARITY: 13 15 18 01 23 02 11 30 24 02 04 05 17 18 03 23

L551 XMIT DATA: . 01 18 15 11 02 23 02 24 30 17 05 04 23 03 18
EN PARITY: 15 06 21 20 17 06 07 22 12 12 26 22 07 17 30 30

L552 XMIT DATA: . 20 21 06 07 06 17 12 12 22 07 22 26 30 30 17
EN PARITY: 11 15 19 04 19 25 29 01 05 13 10 01 01 20 20 11

L553 XMIT DATA: . 04 19 15 29 25 19 13 05 01 01 01 10 11 20 20
EN PARITY: 25 14 20 07 05 00 12 01 10 04 17 09 12 15 21 09

L554 XMIT DATA: . 07 20 14 12 00 05 04 10 01 12 09 17 09 21 15
EN PARITY: 17 07 03 02 02 09 09 24 07 21 31 13 10 12 04 31

L555 XMIT DATA: . 02 03 07 09 09 02 21 07 24 10 13 31 31 04 12
EN PARITY: 21 06 20 14 21 11 12 06 27 11 02 26 25 21 22 00

L556 XMIT DATA: . 14 20 06 12 11 21 11 27 06 25 26 02 00 22 21
EN PARITY: 19 25 30 28 25 25 15 19 16 24 21 19 07 04 31 20

L557 XMIT DATA: . 28 30 25 15 25 25 24 16 19 07 19 21 20 31 04
EN PARITY: 17 31 14 06 17 15 15 00 28 20 06 14 13 16 28 11

L558 XMIT DATA: . 06 14 31 15 15 17 20 28 00 13 14 06 11 28 16
EN PARITY: 17 04 20 02 17 31 24 28 04 05 01 16 09 27 15 02

L559 XMIT DATA: . 02 20 04 24 31 17 05 04 28 09 16 01 02 15 27
EN PARITY: 06 19 09 02 24 31 16 10 07 09 02 24 19 30 18 22

L560 XMIT DATA: . 02 09 19 16 31 24 09 07 10 19 24 02 22 18 30
EN PARITY: 04 16 14 29 21 17 20 18 14 06 08 27 29 20 22 03

L561 XMIT DATA: . 29 14 16 20 17 21 06 14 18 29 27 08 03 22 20
EN PARITY: 30 02 04 04 30 01 15 27 06 20 01 18 09 22 22 26

L562 XMIT DATA: . 04 04 02 15 01 30 20 06 27 09 18 01 26 22 22
EN PARITY: 30 06 13 01 11 29 25 28 11 28 12 05 07 29 16 13

L563 XMIT DATA: . 01 13 06 25 29 11 28 11 28 07 05 12 13 16 29
EN PARITY: 23 28 27 14 23 18 28 07 23 04 30 18 22 30 14 02

L564 XMIT DATA: . 14 27 28 28 18 23 04 23 07 22 18 30 02 14 30
EN PARITY: 03 08 13 14 06 01 04 02 29 02 22 12 21 17 14 24

L565 XMIT DATA: . 14 13 08 04 01 06 02 29 02 21 12 22 24 14 17
EN PARITY: 12 24 00 15 31 08 27 19 17 25 26 29 18 18 19 28

L566 XMIT DATA: . 15 00 24 27 08 31 25 17 19 18 29 26 28 19 18
EN PARITY: 01 20 14 08 30 02 27 05 21 02 16 14 30 01 05 15

L567 XMIT DATA: . 08 14 20 27 02 30 02 21 05 30 14 16 15 05 01
EN PARITY: 30 13 14 11 23 22 21 01 09 30 14 10 17 29 00 15

L568 XMIT DATA: . 11 14 13 21 22 23 30 09 01 17 10 14 15 00 29
EN PARITY: 08 13 28 14 05 03 14 02 01 10 25 01 12 01 09 24

L569 XMIT DATA: . 14 28 13 14 03 05 10 01 02 12 01 25 24 09 01
EN PARITY: 02 30 19 30 23 19 25 22 09 26 27 05 20 29 04 18

L570 XMIT DATA: . 30 19 30 25 19 23 26 09 22 20 05 27 18 04 29
EN PARITY: 07 02 24 13 22 10 21 31 03 29 26 04 05 22 29 06

L571 XMIT DATA: . 13 24 02 21 10 22 29 03 31 05 04 26 06 29 22
EN PARITY: 16 12 29 20 23 26 20 11 06 30 05 22 06 29 00 31

L572 XMIT DATA: . 20 29 12 20 26 23 30 06 11 06 22 05 31 00 29
EN PARITY: 09 14 25 29 02 11 02 14 15 21 10 03 17 28 08 01

L573 XMIT DATA: . 29 25 14 02 11 02 21 15 14 17 03 10 01 08 28
EN PARITY: 12 30 07 14 09 30 27 12 15 01 21 27 00 28 14 26

L574 XMIT DATA: . 14 07 30 27 30 09 01 15 12 00 27 21 26 14 28
EN PARITY: 01 18 20 11 01 13 30 29 07 26 22 11 09 13 09 20

L575 XMIT DATA: . 11 20 18 30 13 01 26 07 29 09 11 22 20 09 13
EN PARITY: 25 18 02 08 26 07 02 14 04 00 21 23 20 06 24 01

L576 XMIT DATA: . 08 02 18 02 07 26 00 04 14 20 23 21 01 24 06
EN PARITY: 09 01 23 16 09 05 16 07 14 01 19 07 02 01 16 24

L577 XMIT DATA: . 16 23 01 16 05 09 01 14 07 02 07 19 24 16 01
EN PARITY: 06 23 28 03 13 24 17 05 12 23 18 00 08 00 31 24

L578 XMIT DATA: . 03 28 23 17 24 13 23 12 05 08 00 18 24 31 00
EN PARITY: 13 11 29 24 22 30 09 13 12 22 31 04 02 08 15 10

L579 XMIT DATA: . 24 29 11 09 30 22 22 12 13 02 04 31 10 15 08
EN PARITY: 10 31 21 12 29 24 25 28 01 18 01 05 13 20 28 29

L580 XMIT DATA: . 12 21 31 25 24 29 18 01 28 13 05 01 29 28 20
EN PARITY: 23 31 20 29 13 03 21 07 18 24 01 05 21 20 31 01

L581 XMIT DATA: . 29 20 31 21 03 13 24 18 07 21 05 01 01 31 20

EN PARITY: 17 26 08 27 05 31 20 25 05 01 12 06 22 30 15 20

L582 XMIT DATA: . 27 08 26 20 31 05 01 03 25 22 06 12 20 15 30
EN PARITY: 22 02 18 04 06 27 03 30 03 13 19 25 07 30 27 29

L583 XMIT DATA: . 04 18 02 03 27 06 13 03 30 07 25 19 29 27 30
EN PARITY: 28 04 28 24 05 11 26 22 02 15 18 29 06 28 15 27

L584 XMIT DATA: . 24 28 04 26 11 05 15 02 22 06 29 18 27 15 28
EN PARITY: 01 25 13 19 25 18 29 27 06 15 11 02 06 18 03 23

L585 XMIT DATA: . 19 13 25 29 18 25 15 06 27 06 02 11 23 03 18
EN PARITY: 02 17 29 08 30 07 10 18 19 19 04 18 27 13 12 28

L586 XMIT DATA: . 08 29 17 10 07 30 19 19 18 27 18 04 28 12 13
EN PARITY: 16 06 18 04 07 10 29 06 21 20 16 29 02 22 23 31

L587 XMIT DATA: . 04 18 06 29 10 07 20 21 06 02 29 16 31 23 22
EN PARITY: 03 04 00 17 12 20 00 29 08 02 01 05 09 08 06 12

L588 XMIT DATA: . 17 00 04 00 20 12 02 08 29 09 05 01 12 06 08
EN PARITY: 17 00 02 22 26 22 24 11 00 28 15 08 08 24 17 22

L589 XMIT DATA: . 22 02 00 24 22 26 28 00 11 08 08 15 22 17 24
EN PARITY: 06 12 06 14 31 07 17 29 04 01 15 18 11 13 19 02

L590 XMIT DATA: . 14 06 12 17 07 31 01 04 29 11 18 15 02 19 13
EN PARITY: 08 16 20 00 03 18 19 25 11 08 29 21 23 14 18 07

L591 XMIT DATA: . 00 20 16 19 18 03 08 11 25 23 21 29 07 18 14
EN PARITY: 31 19 26 28 12 11 24 31 08 28 19 22 26 18 31 24

L592 XMIT DATA: . 28 26 19 24 11 12 28 08 31 26 22 19 24 31 18
EN PARITY: 17 00 12 05 08 20 05 09 04 20 18 20 04 25 03 17

L593 XMIT DATA: . 05 12 00 05 20 08 20 04 09 04 20 18 17 03 25
EN PARITY: 22 28 10 03 10 10 14 15 07 09 03 25 19 09 05 21

L594 XMIT DATA: . 03 10 28 14 10 10 09 07 15 19 25 03 21 05 09
EN PARITY: 05 00 21 00 16 22 30 24 21 05 00 11 16 00 01 14

L595 XMIT DATA: . 00 21 00 30 22 16 05 21 24 16 11 00 14 01 00
EN PARITY: 17 22 21 02 16 06 10 26 18 22 08 06 06 21 08 12

L596 XMIT DATA: . 02 21 22 10 06 16 22 18 26 06 06 08 12 08 21
EN PARITY: 23 02 17 20 17 02 27 21 26 18 08 18 18 06 30 11

L597 XMIT DATA: . 20 17 02 27 02 17 18 26 21 18 18 08 11 30 06
EN PARITY: 10 13 13 10 17 23 17 06 30 26 03 26 24 13 06 01

L598 XMIT DATA: . 10 13 13 17 23 17 26 30 06 24 26 03 01 06 13
EN PARITY: 11 30 21 16 11 28 14 30 12 06 19 16 00 27 20 07

L599 XMIT DATA: . 16 21 30 14 28 11 06 12 30 00 16 19 07 20 27
EN PARITY: 06 30 30 12 05 19 06 15 18 26 13 15 08 10 30 26

L600 XMIT DATA: . 12 30 30 06 19 05 26 18 15 08 15 13 26 30 10
EN PARITY: 23 25 04 24 14 10 08 04 10 18 29 15 20 07 23 14

L601 XMIT DATA: . 24 04 25 08 10 14 18 10 04 20 15 29 14 23 07
EN PARITY: 06 12 16 05 22 31 19 21 06 13 29 07 18 26 19 19

L602 XMIT DATA: . 05 16 12 19 31 22 13 06 21 18 07 29 19 19 26
EN PARITY: 30 11 17 20 19 23 15 30 30 03 06 01 19 18 28 10

L603 XMIT DATA: . 20 17 11 15 23 19 03 30 30 19 01 06 10 28 18
EN PARITY: 20 28 12 25 02 25 18 06 25 06 07 13 31 31 03 12

L604 XMIT DATA: . 25 12 28 18 25 02 06 25 06 31 13 07 12 03 31
EN PARITY: 25 20 04 04 22 02 10 22 27 00 06 07 31 06 07 03

L605 XMIT DATA: . 04 04 20 10 02 22 00 27 22 31 07 06 03 07 06
EN PARITY: 06 22 19 08 22 00 12 17 11 04 24 08 15 05 23 26

L606 XMIT DATA: . 08 19 22 12 00 22 04 11 17 15 08 24 26 23 05
EN PARITY: 02 10 17 13 31 15 08 12 21 04 20 11 16 30 17 27

L607 XMIT DATA: . 13 17 10 08 15 31 04 21 12 16 11 20 27 17 30
EN PARITY: 09 15 10 24 18 19 16 07 00 09 22 15 24 16 11 18

L608 XMIT DATA: . 24 10 15 16 19 18 09 00 07 24 15 22 18 11 16
EN PARITY: 07 02 24 24 07 23 16 29 24 18 04 25 28 08 24 25

L609 XMIT DATA: . 24 24 02 16 23 07 18 24 29 28 25 04 25 24 08
EN PARITY: 22 17 23 08 06 15 03 17 11 31 18 30 29 09 30 25

L610 XMIT DATA: . 08 23 17 03 15 06 31 11 17 29 30 18 25 30 09
EN PARITY: 27 17 13 05 06 29 15 28 26 10 31 27 23 10 00 27

L611 XMIT DATA: . 05 13 17 15 29 06 10 26 28 23 27 31 27 00 10
EN PARITY: 14 04 04 09 03 16 25 17 13 18 18 14 15 14 23 20

L612 XMIT DATA: . 09 04 04 25 16 03 18 13 17 15 14 18 20 23 14
EN PARITY: 22 20 30 15 21 04 28 11 27 12 09 20 06 25 24 14

L613 XMIT DATA: . 15 30 20 28 04 21 12 27 11 06 20 09 14 24 25
EN PARITY: 25 12 19 02 27 19 20 07 30 22 22 21 10 01 16 00

L614 XMIT DATA: . 02 19 12 20 19 27 22 30 07 10 21 22 00 16 01
EN PARITY: 04 08 25 10 20 13 06 04 07 07 27 21 16 00 29 13

L615 XMIT DATA: . 10 25 08 06 13 20 07 07 04 16 21 27 13 29 00
EN PARITY: 14 13 05 06 31 19 03 11 29 04 21 30 02 19 18 04

L616 XMIT DATA: . 06 05 13 03 19 31 04 29 11 02 30 21 04 18 19
EN PARITY: 21 06 29 30 19 26 10 02 03 28 15 22 11 10 28 14

L617 XMIT DATA: . 30 29 06 10 26 19 28 03 02 11 22 15 14 28 10
EN PARITY: 09 06 07 24 23 29 01 24 30 30 16 24 27 09 25 10

L618 XMIT DATA: . 24 07 06 01 29 23 30 30 24 27 24 16 10 25 09
EN PARITY: 16 09 26 30 29 25 18 20 18 28 31 03 28 18 21 06

L619 XMIT DATA: . 30 26 09 18 25 29 28 18 20 28 03 31 06 21 18
EN PARITY: 17 02 08 06 23 20 24 26 30 14 13 09 07 21 26 12

L620 XMIT DATA: . 06 08 02 24 20 23 14 30 26 07 09 13 12 26 21
EN PARITY: 18 00 23 28 30 04 17 12 22 00 09 29 08 12 23 25

L621 XMIT DATA: . 28 23 00 17 04 30 00 22 12 08 29 09 25 23 12
EN PARITY: 04 17 05 13 25 11 12 27 07 03 24 09 30 10 11 00

L622 XMIT DATA: . 13 05 17 12 11 25 03 07 27 30 09 24 00 11 10
EN PARITY: 02 12 13 10 01 10 20 12 19 08 17 07 16 18 19 30

L623 XMIT DATA: . 10 13 12 20 10 01 08 19 12 16 07 17 30 19 18
EN PARITY: 00 11 30 06 18 11 13 00 07 11 06 12 19 07 31 06

L624 XMIT DATA: . 06 30 11 13 11 18 11 07 00 19 12 06 06 31 07
EN PARITY: 18 24 04 25 06 26 16 30 29 01 28 13 13 08 03 07

L625 XMIT DATA: . 25 04 24 16 26 06 01 29 30 13 13 28 07 03 08
EN PARITY: 26 30 18 09 22 29 10 02 01 09 20 04 24 15 01 30

L626 XMIT DATA: . 09 18 30 10 29 22 09 01 02 24 04 20 30 01 15
EN PARITY: 08 12 05 27 25 30 11 13 27 02 12 14 11 00 15 02

L627 XMIT DATA: . 27 05 12 11 30 25 02 27 13 11 14 12 02 15 00
EN PARITY: 25 03 27 31 18 03 13 09 21 27 08 01 10 28 24 24

L628 XMIT DATA: . 31 27 03 13 03 18 27 21 09 10 01 08 24 24 28
EN PARITY: 13 22 22 24 01 01 11 28 06 15 15 16 16 15 24 15

L629 XMIT DATA: . 24 22 22 11 01 01 15 06 28 16 16 15 15 24 15
EN PARITY: 13 05 27 26 06 27 30 01 07 09 07 11 05 19 28 12

L630 XMIT DATA: . 26 27 05 30 27 06 09 07 01 05 11 07 12 28 19
EN PARITY: 09 25 30 21 01 01 13 10 20 15 18 22 03 11 15 21

L631 XMIT DATA: . 21 30 25 13 01 01 15 20 10 03 22 18 21 15 11
EN PARITY: 01 30 29 03 18 30 10 20 12 12 26 20 04 28 14 01

L632 XMIT DATA: . 03 29 30 10 30 18 12 12 20 04 20 26 01 14 28
EN PARITY: 29 02 18 21 22 09 22 10 15 08 06 02 05 23 00 28

L633 XMIT DATA: . 21 18 02 22 09 22 08 15 10 05 02 06 28 00 23
EN PARITY: 04 04 12 14 08 11 30 26 22 31 14 23 28 10 01 02

L634 XMIT DATA: . 14 12 04 30 11 08 31 22 26 28 23 14 02 01 10
EN PARITY: 06 01 08 16 07 04 04 14 04 13 17 16 10 06 09 15

L635 XMIT DATA: . 16 08 01 04 04 07 13 04 14 10 16 17 15 09 06
EN PARITY: 25 24 22 27 10 01 18 31 01 01 24 17 30 03 18 08

L636 XMIT DATA: . 27 22 24 18 01 10 01 01 31 30 17 24 08 18 03
EN PARITY: 00 23 25 03 23 30 11 28 13 19 08 15 11 12 29 02

L637 XMIT DATA: . 03 25 23 11 30 23 19 13 28 11 15 08 02 29 12
EN PARITY: 12 18 03 02 30 24 14 15 08 04 06 11 09 12 30 08

L638 XMIT DATA: . 02 03 18 14 24 30 04 08 15 09 11 06 08 30 12
EN PARITY: 02 09 12 27 08 07 27 31 29 20 09 00 29 27 08 04

L639 XMIT DATA: . 27 12 09 27 07 08 20 29 31 29 00 09 04 08 27
EN PARITY: 19 02 30 16 22 11 31 01 14 10 07 13 27 16 25 07

L640 XMIT DATA: . 16 30 02 31 11 22 10 14 01 27 13 07 07 25 16
EN PARITY: 28 13 27 07 18 23 29 28 13 15 20 27 22 28 16 01

L641 XMIT DATA: . 07 27 13 29 23 18 15 13 28 22 27 20 01 16 28
EN PARITY: 13 07 21 05 02 10 01 07 24 03 13 10 24 01 19 23

L642 XMIT DATA: . 05 21 07 01 10 02 03 24 07 24 10 13 23 19 01
EN PARITY: 02 20 17 16 13 17 20 07 31 07 01 25 29 21 22 10

L643 XMIT DATA: . 16 17 20 20 17 13 07 31 07 29 25 01 10 22 21

EN PARITY: 05 21 08 24 31 00 10 18 19 28 15 07 05 19 05 26

L644 XMIT DATA: . 24 08 21 10 00 31 28 19 18 05 07 15 26 05 19
EN PARITY: 28 16 21 23 02 25 30 26 11 18 21 26 27 08 14 08

L645 XMIT DATA: . 23 21 16 30 25 02 18 11 26 27 26 21 08 14 08
EN PARITY: 15 23 24 07 11 23 22 30 11 13 13 03 27 17 26 24

L646 XMIT DATA: . 07 24 23 22 23 11 13 11 30 27 03 13 24 26 17
EN PARITY: 25 28 20 30 18 22 25 16 31 06 29 14 10 25 03 24

L647 XMIT DATA: . 30 20 28 25 22 18 06 31 16 10 14 29 24 03 25
EN PARITY: 20 26 01 26 22 15 04 10 21 31 29 17 31 17 08 04

L648 XMIT DATA: . 26 01 26 04 15 22 31 21 10 31 17 29 04 08 17
EN PARITY: 09 00 14 09 22 03 09 02 11 29 29 12 30 21 03 29

L649 XMIT DATA: . 09 14 00 09 03 22 29 11 02 30 12 29 29 03 21
EN PARITY: 12 24 21 22 17 30 13 05 27 27 20 02 04 10 30 26

L650 XMIT DATA: . 22 21 24 13 30 17 27 27 05 04 02 20 26 30 10
EN PARITY: 25 05 11 03 14 19 08 18 30 28 30 29 23 29 07 10

L651 XMIT DATA: . 03 11 05 08 19 14 28 30 18 23 29 30 10 07 29
EN PARITY: 15 13 05 15 18 15 31 06 06 00 06 09 09 25 28 29

L652 XMIT DATA: . 15 05 13 31 15 18 00 06 06 09 09 06 29 28 25
EN PARITY: 09 31 10 11 03 21 11 25 19 04 27 04 22 08 04 29

L653 XMIT DATA: . 11 10 31 11 21 03 04 19 25 22 04 27 29 04 08
EN PARITY: 15 31 29 11 02 06 27 09 01 12 10 20 23 29 06 27

L654 XMIT DATA: . 11 29 31 27 06 02 12 01 09 23 20 10 27 06 29
EN PARITY: 17 09 21 09 15 03 08 01 28 00 13 03 26 24 17 18

L655 XMIT DATA: . 09 21 09 08 03 15 00 28 01 26 03 13 18 17 24
EN PARITY: 28 29 01 15 08 24 21 00 07 14 24 20 27 01 01 30

L656 XMIT DATA: . 15 01 29 21 24 08 14 07 00 27 20 24 30 01 01
EN PARITY: 11 29 16 01 12 05 15 14 12 00 18 23 29 27 25 30

L657 XMIT DATA: . 01 16 29 15 05 12 00 12 14 29 23 18 30 25 27
EN PARITY: 27 16 03 28 15 17 04 06 18 27 14 11 03 30 03 21

L658 XMIT DATA: . 28 03 16 04 17 15 27 18 06 03 11 14 21 03 30
EN PARITY: 17 12 07 01 25 30 09 23 20 15 07 08 29 13 25 15

L659 XMIT DATA: . 01 07 12 09 30 25 15 20 23 29 08 07 15 25 13
EN PARITY: 08 13 24 05 04 02 11 05 16 31 08 31 29 16 00 31

L660 XMIT DATA: . 05 24 13 11 02 04 31 16 05 29 31 08 31 00 16
EN PARITY: 27 00 02 13 23 18 25 27 02 27 26 09 07 18 10 16

L661 XMIT DATA: . 13 02 00 25 18 23 27 02 27 07 09 26 16 10 18
EN PARITY: 25 21 22 26 19 14 24 18 17 04 20 10 07 07 01 24

L662 XMIT DATA: . 26 22 21 24 14 19 04 17 18 07 10 20 24 01 07
EN PARITY: 03 29 17 02 02 07 12 12 00 08 03 01 07 02 01 26

L663 XMIT DATA: . 02 17 29 12 07 02 08 00 12 07 01 03 26 01 02
EN PARITY: 27 06 02 22 21 25 10 08 27 31 09 13 07 26 11 29

L664 XMIT DATA: . 22 02 06 10 25 21 31 27 08 07 13 09 29 11 26
EN PARITY: 02 07 15 12 26 17 19 09 28 18 19 09 07 13 23 15

L665 XMIT DATA: . 12 15 07 19 17 26 18 28 09 07 09 19 15 23 13
EN PARITY: 05 01 01 19 22 11 12 19 29 31 04 25 29 01 18 25

L666 XMIT DATA: . 19 01 01 12 11 22 31 29 19 29 25 04 25 18 01
EN PARITY: 31 16 04 17 03 00 18 07 00 31 00 20 12 24 25 31

L667 XMIT DATA: . 17 04 16 18 00 03 31 00 07 12 20 00 31 25 24
EN PARITY: 24 08 06 16 28 28 29 04 10 10 08 10 31 00 17 16

L668 XMIT DATA: . 16 06 08 29 28 28 10 10 04 31 10 08 16 17 00
EN PARITY: 11 29 06 31 29 15 13 11 14 31 25 04 04 28 11 02

L669 XMIT DATA: . 31 06 29 13 15 29 31 14 11 04 04 25 02 11 28
EN PARITY: 12 25 20 08 30 10 30 10 17 13 02 19 11 27 20 00

L670 XMIT DATA: . 08 20 25 30 10 30 13 17 10 11 19 02 00 20 27
EN PARITY: 23 31 13 11 23 18 28 06 31 11 21 18 20 01 08 20

L671 XMIT DATA: . 11 13 31 28 18 23 11 31 06 20 18 21 20 08 01
EN PARITY: 18 30 08 23 04 04 20 29 22 21 07 03 26 03 06 06

L672 XMIT DATA: . 23 08 30 20 04 04 21 22 29 26 03 07 06 06 03
EN PARITY: 31 00 13 04 20 26 29 23 20 02 25 31 31 24 14 11

L673 XMIT DATA: . 04 13 00 29 26 20 02 20 23 31 31 25 11 14 24
EN PARITY: 26 05 05 12 30 21 09 20 01 28 19 17 29 19 12 19

L674 XMIT DATA: . 12 05 05 09 21 30 28 01 20 29 17 19 19 12 19
EN PARITY: 17 16 31 01 08 05 27 30 20 14 02 28 04 04 26 14

L675 XMIT DATA: . 01 31 16 27 05 08 14 20 30 04 28 02 14 26 04
EN PARITY: 19 05 31 01 16 14 12 26 17 10 21 12 30 09 03 20

L676 XMIT DATA: . 01 31 05 12 14 16 10 17 26 30 12 21 20 03 09
EN PARITY: 10 01 21 11 06 31 05 07 21 09 24 15 29 10 29 21

L677 XMIT DATA: . 11 21 01 05 31 06 09 21 07 29 15 24 21 29 10
EN PARITY: 27 27 14 09 12 18 08 06 25 12 03 26 23 05 12 02

L678 XMIT DATA: . 09 14 27 08 18 12 12 25 06 23 26 03 02 12 05
EN PARITY: 07 20 30 18 17 26 29 20 14 16 14 28 17 25 28 14

L679 XMIT DATA: . 18 30 20 29 26 17 16 14 20 17 28 14 14 28 25
EN PARITY: 06 31 27 07 08 30 03 13 22 25 14 20 10 14 09 21

L680 XMIT DATA: . 07 27 31 03 30 08 25 22 13 10 20 14 21 09 14
EN PARITY: 18 17 23 15 21 27 03 19 16 00 17 11 04 05 29 08

L681 XMIT DATA: . 15 23 17 03 27 21 00 16 19 04 11 17 08 29 05
EN PARITY: 24 26 18 26 05 00 10 22 08 20 24 13 25 26 14 00

L682 XMIT DATA: . 26 18 26 10 00 05 20 08 22 25 13 24 00 14 26
EN PARITY: 24 24 11 24 03 23 00 25 03 24 07 21 29 08 01 29

L683 XMIT DATA: . 24 11 24 00 23 03 24 03 25 29 21 07 29 01 08
EN PARITY: 03 16 30 18 23 27 26 15 31 07 08 18 30 15 04 09

L684 XMIT DATA: . 18 30 16 26 27 23 07 31 15 30 18 08 09 04 15
EN PARITY: 16 03 20 20 21 20 00 21 04 18 06 04 28 23 18 27

L685 XMIT DATA: . 20 20 03 00 20 21 18 04 21 28 04 06 27 18 23
EN PARITY: 12 21 03 28 06 13 23 12 20 25 17 28 28 31 21 21

L686 XMIT DATA: . 28 03 21 23 13 06 25 20 12 28 28 17 21 21 31
EN PARITY: 18 06 18 04 14 24 04 27 18 03 12 09 30 29 15 13

L687 XMIT DATA: . 04 18 06 04 24 14 03 18 27 30 09 12 13 15 29
EN PARITY: 13 11 08 28 10 17 25 13 14 31 08 08 26 02 01 14

L688 XMIT DATA: . 28 08 11 25 17 10 31 14 13 26 08 08 14 01 02
EN PARITY: 05 13 24 20 21 25 14 30 24 25 25 24 23 08 24 07

L689 XMIT DATA: . 20 24 13 14 25 21 25 24 30 23 24 25 07 24 08
EN PARITY: 21 15 13 27 28 30 03 14 14 26 03 17 30 25 10 30

L690 XMIT DATA: . 27 13 15 03 30 28 26 14 14 30 17 03 30 10 25
EN PARITY: 00 22 27 16 17 16 20 07 16 01 12 22 31 14 07 29

L691 XMIT DATA: . 16 27 22 20 16 17 01 16 07 31 22 12 29 07 14
EN PARITY: 20 27 30 10 15 26 22 30 26 09 15 16 18 21 05 06

L692 XMIT DATA: . 10 30 27 22 26 15 09 26 30 18 16 15 06 05 21
EN PARITY: 10 21 02 06 20 09 13 16 31 31 10 23 26 25 29 23

L693 XMIT DATA: . 06 02 21 13 09 20 31 31 16 26 23 10 23 29 25
EN PARITY: 13 09 20 19 03 14 24 17 15 29 06 22 24 09 22 16

L694 XMIT DATA: . 19 20 09 24 14 03 29 15 17 24 22 06 16 22 09
EN PARITY: 02 27 16 20 16 25 19 18 17 21 15 14 19 21 23 29

L695 XMIT DATA: . 20 16 27 19 25 16 21 17 18 19 14 15 29 23 21
EN PARITY: 30 30 06 28 19 19 26 16 02 31 18 29 16 28 05 20

L696 XMIT DATA: . 28 06 30 26 19 19 31 02 16 16 29 18 20 05 28
EN PARITY: 14 17 16 17 19 11 18 21 24 04 13 10 30 02 19 28

L697 XMIT DATA: . 17 16 17 18 11 19 04 24 21 30 10 13 28 19 02
EN PARITY: 16 05 10 00 31 16 28 12 30 27 15 11 15 09 13 03

L698 XMIT DATA: . 00 10 05 28 16 31 27 30 12 15 11 15 03 13 09
EN PARITY: 26 11 18 03 08 24 16 00 29 03 17 00 18 28 06 28

L699 XMIT DATA: . 03 18 11 16 24 08 03 29 00 18 00 17 28 06 28
EN PARITY: 28 17 09 29 26 24 19 26 02 25 29 30 19 26 24 01

L700 XMIT DATA: . 29 09 17 19 24 26 25 02 26 19 30 29 01 24 26
EN PARITY: 06 23 19 02 07 00 00 04 17 15 30 15 07 07 14 15

L701 XMIT DATA: . 02 19 23 00 00 07 15 17 04 07 15 30 15 14 07
EN PARITY: 27 10 26 04 31 22 03 13 21 11 23 28 15 03 27 05

L702 XMIT DATA: . 04 26 10 03 22 31 11 21 13 15 28 23 05 27 03
EN PARITY: 15 26 03 18 13 12 09 10 23 05 23 18 10 07 19 28

L703 XMIT DATA: . 18 03 26 09 12 13 05 23 10 10 18 23 28 19 07
EN PARITY: 03 21 26 02 19 19 29 13 30 04 15 04 16 10 11 10

L704 XMIT DATA: . 02 26 21 29 19 19 04 30 13 16 04 15 10 11 10
EN PARITY: 22 25 00 00 08 00 11 27 05 15 22 14 00 21 29 21

L705 XMIT DATA: . 00 00 25 11 00 08 15 05 27 00 14 22 21 29 21

L706 XMIT DATA: . 29 20 09 00 23 30 05 28 26 18 04 31 26 10 08
EN PARITY: 19 23 08 18 17 14 01 08 15 11 04 30 17 10 07 20

L707 XMIT DATA: . 18 08 23 01 14 17 11 15 08 17 30 04 20 07 10
EN PARITY: 22 06 02 20 05 05 26 28 21 26 23 29 03 18 20 19

L708 XMIT DATA: . 20 02 06 26 05 05 26 21 28 03 29 23 19 20 18
EN PARITY: 00 23 06 15 18 26 04 11 01 30 03 31 17 31 07 19

L709 XMIT DATA: . 15 06 23 04 26 18 30 01 11 17 31 03 19 07 31
EN PARITY: 23 02 23 27 18 13 00 19 02 12 07 01 24 24 03 21

L710 XMIT DATA: . 27 23 02 00 13 18 12 02 19 24 01 07 21 03 24
EN PARITY: 02 18 06 07 25 21 05 31 07 01 20 27 00 16 11 00

L711 XMIT DATA: . 07 06 18 05 21 25 01 07 31 00 27 20 00 11 16
EN PARITY: 08 27 17 01 06 26 30 16 31 11 25 05 17 02 22 10

L712 XMIT DATA: . 01 17 27 30 26 06 11 31 16 17 05 25 10 22 02
EN PARITY: 17 29 25 10 05 19 14 31 14 13 18 30 08 00 16 21

L713 XMIT DATA: . 10 25 29 14 19 05 13 14 31 08 30 18 21 16 00
EN PARITY: 19 02 11 22 04 25 08 07 23 26 14 23 30 08 13 16

L714 XMIT DATA: . 22 11 02 08 25 04 26 23 07 30 23 14 16 13 08
EN PARITY: 23 27 27 08 08 20 23 28 13 30 09 22 01 07 13 30

L715 XMIT DATA: . 08 27 27 23 20 08 30 13 28 01 22 09 30 13 07
EN PARITY: 24 03 16 16 00 15 21 04 14 03 00 25 14 14 00 05

L716 XMIT DATA: . 16 16 03 21 15 00 03 14 04 14 25 00 05 00 14
EN PARITY: 12 27 15 16 23 02 24 26 19 25 26 10 02 16 05 09

L717 XMIT DATA: . 16 15 27 24 02 23 25 19 26 02 10 26 09 05 16
EN PARITY: 29 30 29 11 05 18 01 10 30 23 15 25 27 18 24 06

L718 XMIT DATA: . 11 29 30 01 18 05 23 30 10 27 25 15 06 24 18
EN PARITY: 19 16 16 03 03 14 00 12 20 19 21 07 15 07 12 04

L719 XMIT DATA: . 03 16 16 00 14 03 19 20 12 15 07 21 04 12 07
EN PARITY: 15 29 05 12 20 20 12 19 29 12 28 23 19 26 23 23

L720 XMIT DATA: . 12 05 29 12 20 20 12 29 19 19 23 28 23 23 26
EN PARITY: 00 10 08 18 03 17 01 21 15 05 13 13 19 04 11 29

L721 XMIT DATA: . 18 08 10 01 17 03 05 15 21 19 13 13 29 11 04
EN PARITY: 15 27 31 08 01 06 26 12 03 14 07 18 01 14 15 11

L722 XMIT DATA: . 08 31 27 26 06 01 14 03 12 01 18 07 11 15 14
EN PARITY: 13 31 13 21 21 14 07 02 27 06 04 27 29 11 03 08

L723 XMIT DATA: . 21 13 31 07 14 21 06 27 02 29 27 04 08 03 11
EN PARITY: 02 18 10 19 05 23 18 12 21 31 25 10 07 29 03 31

L724 XMIT DATA: . 19 10 18 18 23 05 31 21 12 07 10 25 31 03 29
EN PARITY: 11 20 04 01 31 26 08 16 17 19 02 01 22 22 24 26

L725 XMIT DATA: . 01 04 20 08 26 31 19 17 16 22 01 02 26 24 22
EN PARITY: 20 23 24 23 26 24 23 23 19 31 25 12 03 20 02 19

L726 XMIT DATA: . 23 24 23 23 24 26 31 19 23 03 12 25 19 02 20
EN PARITY: 21 10 09 02 06 18 26 22 16 23 16 17 13 05 03 01

L727 XMIT DATA: . 02 09 10 26 18 06 23 16 22 13 17 16 01 03 05
EN PARITY: 20 07 22 04 03 25 18 14 16 03 06 08 21 18 18 07

L728 XMIT DATA: . 04 22 07 18 25 03 03 16 14 21 08 06 07 18 18
EN PARITY: 29 05 16 30 10 17 03 31 03 30 16 24 15 29 14 11

L729 XMIT DATA: . 30 16 05 03 17 10 30 03 31 15 24 16 11 14 29
EN PARITY: 22 08 21 22 29 26 00 18 24 00 23 20 01 03 01 16

L730 XMIT DATA: . 22 21 08 00 26 29 00 24 18 01 20 23 16 01 03
EN PARITY: 12 08 14 00 19 05 09 29 02 24 16 12 00 13 23 21

L731 XMIT DATA: . 00 14 08 09 05 19 24 02 29 00 12 16 21 23 13
EN PARITY: 23 14 17 02 13 24 28 19 11 29 31 06 23 22 24 01

L732 XMIT DATA: . 02 17 14 28 24 13 29 11 19 23 06 31 01 24 22
EN PARITY: 24 09 04 11 22 26 13 24 30 11 27 18 17 31 13 17

L733 XMIT DATA: . 11 04 09 13 26 22 11 30 24 17 18 27 17 13 31
EN PARITY: 06 15 10 10 01 05 01 27 30 00 18 07 05 08 20 04

L734 XMIT DATA: . 10 10 15 01 05 01 00 30 27 05 07 18 04 20 08
EN PARITY: 21 02 25 26 17 13 03 05 07 28 17 04 16 12 20 13

L735 XMIT DATA: . 26 25 02 03 13 17 28 07 05 16 04 17 13 20 12
EN PARITY: 26 08 25 17 10 06 04 11 12 25 10 16 04 25 21 14

L736 XMIT DATA: . 17 25 08 04 06 10 25 12 11 04 16 10 14 21 25
EN PARITY: 25 10 28 06 24 15 28 31 03 26 24 16 31 31 07 23

L737 XMIT DATA: . 06 28 10 28 15 24 26 03 31 31 16 24 23 07 31
EN PARITY: 31 28 19 14 30 19 04 09 01 29 30 31 31 29 07 29

L738 XMIT DATA: . 14 19 28 04 19 30 29 01 09 31 31 30 29 07 29
EN PARITY: 14 13 00 29 03 17 17 17 12 13 07 01 27 28 12 18

L739 XMIT DATA: . 29 00 13 17 17 03 13 12 17 27 01 07 18 12 28
EN PARITY: 14 22 25 22 22 10 17 27 00 19 04 15 27 20 24 07

L740 XMIT DATA: . 22 25 22 17 10 22 19 00 27 27 15 04 07 24 20
EN PARITY: 04 30 22 22 22 12 11 13 01 02 21 09 19 10 10 28

L741 XMIT DATA: . 22 22 30 11 12 22 02 01 13 19 09 21 28 10 10
EN PARITY: 00 09 04 15 29 15 20 11 27 12 31 03 09 16 15 24

L742 XMIT DATA: . 15 04 09 20 15 29 12 27 11 09 03 31 24 15 16
EN PARITY: 18 00 12 01 28 27 01 08 28 05 03 29 19 18 25 11

L743 XMIT DATA: . 01 12 00 01 27 28 05 28 08 19 29 03 11 25 18
EN PARITY: 27 02 20 30 22 29 01 19 07 18 05 05 07 00 01 26

L744 XMIT DATA: . 30 20 02 01 29 22 18 07 19 07 05 05 26 01 00
EN PARITY: 12 29 29 03 13 01 25 06 20 02 09 16 06 00 18 03

L745 XMIT DATA: . 03 29 29 25 01 13 02 20 06 06 16 09 03 18 00
EN PARITY: 04 22 09 27 12 25 29 31 20 04 00 09 15 18 02 19

L746 XMIT DATA: . 27 09 22 29 25 12 04 20 31 15 09 00 19 02 18
EN PARITY: 11 01 21 04 21 23 02 28 00 11 24 22 18 03 09 05

L747 XMIT DATA: . 04 21 01 02 23 21 11 00 28 18 22 24 05 09 03
EN PARITY: 16 08 18 25 31 02 28 21 27 00 03 07 20 14 06 21

L748 XMIT DATA: . 25 18 08 28 02 31 00 27 21 20 07 03 21 06 14
EN PARITY: 18 15 07 05 17 19 00 29 09 30 17 05 11 11 18 19

L749 XMIT DATA: . 05 07 15 00 19 17 30 09 29 11 05 17 19 18 11
EN PARITY: 09 26 15 21 30 22 24 08 15 02 20 04 31 06 13 28

L750 XMIT DATA: . 21 15 26 24 22 30 02 15 08 31 04 20 28 13 06
EN PARITY: 02 01 24 01 00 03 26 30 17 14 10 10 09 06 24 27

L751 XMIT DATA: . 01 24 01 26 03 00 14 17 30 09 10 10 27 24 06
EN PARITY: 09 27 30 03 00 25 26 16 01 10 12 10 23 17 19 28

L752 XMIT DATA: . 03 30 27 26 25 00 10 01 16 23 10 12 28 19 17
EN PARITY: 30 08 11 14 08 07 28 20 19 22 29 27 14 30 16 02

L753 XMIT DATA: . 14 11 08 28 07 08 22 19 20 14 27 29 02 16 30
EN PARITY: 01 10 10 26 07 12 22 28 07 02 22 23 02 09 01 25

L754 XMIT DATA: . 26 10 10 22 12 07 02 07 28 02 23 22 25 01 09
EN PARITY: 23 06 25 26 01 24 22 30 17 14 15 24 22 13 28 04

L755 XMIT DATA: . 26 25 06 22 24 01 14 17 30 22 24 15 04 28 13
EN PARITY: 20 30 01 23 31 20 23 29 11 30 04 17 26 25 02 20

L756 XMIT DATA: . 23 01 30 23 20 31 30 11 29 26 17 04 20 02 25
EN PARITY: 11 05 15 10 21 17 31 28 03 14 03 12 08 21 17 17

L757 XMIT DATA: . 10 15 05 31 17 21 14 03 28 08 12 03 17 17 21
EN PARITY: 06 06 13 00 06 21 04 26 08 12 04 01 06 23 18 19

L758 XMIT DATA: . 00 13 06 04 21 06 12 08 26 06 01 04 19 18 23
EN PARITY: 01 15 06 27 31 02 12 12 18 27 08 20 19 18 19 09

L759 XMIT DATA: . 27 06 15 12 02 31 27 18 12 19 20 08 09 19 18
EN PARITY: 05 20 05 09 01 07 13 02 28 27 31 14 00 09 08 11

L760 XMIT DATA: . 09 05 20 13 07 01 27 28 02 00 14 31 11 08 09
EN PARITY: 30 20 26 11 03 13 30 12 05 20 10 05 20 28 25 24

L761 XMIT DATA: . 11 26 20 30 13 03 20 05 12 20 05 10 24 25 28
EN PARITY: 00 06 03 15 29 23 17 03 03 05 02 24 06 30 12 19

L762 XMIT DATA: . 15 03 06 17 23 29 05 03 03 06 24 02 19 12 30
EN PARITY: 16 27 25 29 08 01 09 15 10 30 08 01 30 04 24 28

L763 XMIT DATA: . 29 25 27 09 01 08 30 10 15 30 01 08 28 24 04
EN PARITY: 13 21 19 30 21 31 24 14 10 03 00 26 23 12 15 00

L764 XMIT DATA: . 30 19 21 24 31 21 03 10 14 23 26 00 00 15 12
EN PARITY: 18 31 19 17 29 03 01 21 26 29 08 30 16 02 04 08

L765 XMIT DATA: . 17 19 31 01 03 29 29 26 21 16 30 08 08 04 02
EN PARITY: 20 15 05 30 21 08 08 05 31 17 20 15 24 03 11 26

L766 XMIT DATA: . 30 05 15 08 08 21 17 31 05 24 15 20 26 11 03
EN PARITY: 03 30 19 24 03 28 04 04 11 09 01 21 29 12 12 31

L767 XMIT DATA: . 24 19 30 04 28 03 09 11 04 29 21 01 31 12 12

EN PARITY: 23 24 06 30 08 27 20 25 12 24 11 03 16 17 15 22

L768 XMIT DATA: . 30 06 24 20 27 08 24 12 25 16 03 11 22 15 17
EN PARITY: 03 14 01 22 31 22 11 09 01 00 31 10 20 20 31 14

L769 XMIT DATA: . 22 01 14 11 22 31 00 01 09 20 10 31 14 31 20
EN PARITY: 21 21 28 05 11 00 28 28 07 10 07 00 13 11 19 30

L770 XMIT DATA: . 05 28 21 28 00 11 10 07 28 13 00 07 30 19 11
EN PARITY: 03 16 25 06 09 17 09 25 15 18 10 05 14 26 23 14

L771 XMIT DATA: . 06 25 16 09 17 09 18 15 25 14 05 10 14 23 26
EN PARITY: 26 08 01 14 11 25 13 12 18 00 27 19 09 25 08 10

L772 XMIT DATA: . 14 01 08 13 25 11 00 18 12 09 19 27 10 08 25
EN PARITY: 31 04 02 22 25 19 04 20 10 28 20 04 21 27 08 10

L773 XMIT DATA: . 22 02 04 04 19 25 28 10 20 21 04 20 10 08 27
EN PARITY: 10 01 21 17 03 09 14 09 22 22 03 25 29 21 30 00

L774 XMIT DATA: . 17 21 01 14 09 03 22 22 09 29 25 03 00 30 21
EN PARITY: 22 09 04 14 15 21 01 00 23 23 03 11 10 21 30 03

L775 XMIT DATA: . 14 04 09 01 21 15 23 23 00 10 11 03 03 30 21
EN PARITY: 09 06 10 28 23 18 03 29 01 19 11 30 10 13 10 28

L776 XMIT DATA: . 28 10 06 03 18 23 19 01 29 10 30 11 28 10 13
EN PARITY: 12 14 04 13 10 24 02 31 18 17 24 18 18 26 17 28

L777 XMIT DATA: . 13 04 14 02 24 10 17 18 31 18 18 24 28 17 26
EN PARITY: 13 30 22 02 14 09 19 18 22 22 00 15 05 13 17 08

L778 XMIT DATA: . 02 22 30 19 09 14 22 22 18 05 15 00 08 17 13
EN PARITY: 21 06 11 17 24 07 23 03 06 02 21 08 19 11 27 08

L779 XMIT DATA: . 17 11 06 23 07 24 02 06 03 19 08 21 08 27 11
EN PARITY: 11 25 20 22 26 14 14 15 17 05 17 29 04 30 02 06

L780 XMIT DATA: . 22 20 25 14 14 26 05 17 15 04 29 17 06 02 30
EN PARITY: 00 27 22 06 15 29 04 31 28 09 09 01 10 14 20 21

L781 XMIT DATA: . 06 22 27 04 29 15 09 28 31 10 01 09 21 20 14
EN PARITY: 06 09 28 27 17 01 29 01 15 31 06 09 06 21 25 20

L782 XMIT DATA: . 27 28 09 29 01 17 31 15 01 06 09 06 20 25 21
EN PARITY: 15 29 11 01 22 15 16 13 16 13 20 00 18 17 05 21

L783 XMIT DATA: . 01 11 29 16 15 22 13 16 13 18 00 20 21 05 17
EN PARITY: 13 05 14 15 12 12 25 16 12 12 11 28 31 04 16 13

L784 XMIT DATA: . 15 14 05 25 12 12 12 12 16 31 28 11 13 16 04
EN PARITY: 12 30 28 26 26 26 30 03 18 07 31 05 18 14 24 28

L785 XMIT DATA: . 26 28 30 30 26 26 07 18 03 18 05 31 28 24 14
EN PARITY: 11 21 31 29 16 12 24 20 14 14 11 31 10 21 16 04

L786 XMIT DATA: . 29 31 21 24 12 16 14 14 20 10 31 11 04 16 21
EN PARITY: 25 09 28 27 01 08 20 18 00 22 14 17 16 19 23 05

L787 XMIT DATA: . 27 28 09 20 08 01 22 00 18 16 17 14 05 23 19
EN PARITY: 05 31 31 28 07 22 14 22 02 19 09 20 31 25 20 06

L788 XMIT DATA: . 28 31 31 14 22 07 19 02 22 31 20 09 06 20 25
EN PARITY: 30 10 07 18 29 20 18 14 03 08 07 19 00 05 03 11

L789 XMIT DATA: . 18 07 10 18 20 29 08 03 14 00 19 07 11 03 05
EN PARITY: 29 03 24 02 00 17 00 08 23 09 15 17 16 27 09 20

L790 XMIT DATA: . 02 24 03 00 17 00 09 23 08 16 17 15 20 09 27
EN PARITY: 15 17 03 18 04 15 20 20 21 23 16 00 04 00 29 01

L791 XMIT DATA: . 18 03 17 20 15 04 23 21 20 04 00 16 01 29 00
EN PARITY: 26 31 12 11 25 28 10 20 14 27 11 03 18 18 15 30

L792 XMIT DATA: . 11 12 31 10 28 25 27 14 20 18 03 11 30 15 18
EN PARITY: 07 27 05 07 29 12 04 04 04 10 07 04 29 14 12 20

L793 XMIT DATA: . 07 05 27 04 12 29 10 04 04 29 04 07 20 12 14
EN PARITY: 17 20 29 08 17 22 03 02 05 22 01 20 02 25 22 07

L794 XMIT DATA: . 08 29 20 03 22 17 22 05 02 02 20 01 07 22 25
EN PARITY: 01 27 04 00 01 06 22 00 29 23 09 17 12 13 18 02

L795 XMIT DATA: . 00 04 27 22 06 01 23 29 00 12 17 09 02 18 13
EN PARITY: 28 07 05 20 25 07 14 12 22 13 06 25 12 00 07 26

L796 XMIT DATA: . 20 05 07 14 07 25 13 22 12 12 25 06 26 07 00
EN PARITY: 18 28 23 09 17 13 25 19 13 15 18 07 09 05 06 01

L797 XMIT DATA: . 09 23 28 25 13 17 15 13 19 09 07 18 01 06 05
EN PARITY: 14 01 03 25 09 06 31 31 14 28 20 04 31 12 14 05

L798 XMIT DATA: . 25 03 01 31 06 09 28 14 31 31 04 20 05 14 12
EN PARITY: 28 01 04 04 30 17 14 09 17 18 20 30 24 21 26 10

L799 XMIT DATA: . 04 04 01 14 17 30 18 17 09 24 30 20 10 26 21
EN PARITY: 13 17 21 20 22 04 17 01 12 26 14 22 19 24 12 25

L800 XMIT DATA: . 20 21 17 17 04 22 26 12 01 19 22 14 25 12 24
EN PARITY: 08 19 04 25 00 05 20 28 10 24 24 15 15 18 24 12

L801 XMIT DATA: . 25 04 19 20 05 00 24 10 28 15 15 24 12 24 18
EN PARITY: 22 13 04 05 16 20 31 22 12 07 12 22 04 19 12 00

L802 XMIT DATA: . 05 04 13 31 20 16 07 12 22 04 22 12 00 12 19
EN PARITY: 21 01 02 01 06 02 30 01 31 04 17 19 13 00 19 26

L803 XMIT DATA: . 01 02 01 30 02 06 04 31 01 13 19 17 26 19 00
EN PARITY: 19 24 21 00 28 19 21 11 18 05 04 21 26 04 00 04

L804 XMIT DATA: . 00 21 24 21 19 28 05 18 11 26 21 04 04 00 04
EN PARITY: 08 06 00 23 09 27 28 26 00 07 31 14 24 19 00 15

L805 XMIT DATA: . 23 00 06 28 27 09 07 00 26 24 14 31 15 00 19
EN PARITY: 17 23 30 28 15 19 28 09 16 15 30 18 09 29 03 05

L806 XMIT DATA: . 28 30 23 28 19 15 15 16 09 09 18 30 05 03 29
EN PARITY: 25 02 22 19 07 18 18 15 23 02 24 28 21 07 03 05

L807 XMIT DATA: . 19 22 02 18 18 07 02 23 15 21 28 24 05 03 07
EN PARITY: 14 27 10 05 21 26 12 02 24 14 17 09 02 10 01 01

L808 XMIT DATA: . 05 10 27 12 26 21 14 24 02 02 09 17 01 01 10
EN PARITY: 18 25 19 26 00 08 03 17 03 19 30 04 07 03 29 21

L809 XMIT DATA: . 26 19 25 03 08 00 19 03 17 07 04 30 21 29 03
EN PARITY: 18 09 28 09 09 20 29 02 15 31 27 17 14 27 29 30

L810 XMIT DATA: . 09 28 09 29 20 09 31 15 02 14 17 27 30 29 27
EN PARITY: 03 20 31 29 28 29 23 25 14 00 00 04 07 27 15 06

L811 XMIT DATA: . 29 31 20 23 29 28 00 14 25 07 04 00 06 15 27
EN PARITY: 19 13 18 02 22 31 24 20 21 15 16 28 15 19 15 31

L812 XMIT DATA: . 02 18 13 24 31 22 15 21 20 15 28 16 31 15 19
EN PARITY: 06 28 00 11 08 06 13 15 09 30 02 22 11 13 23 24

L813 XMIT DATA: . 11 00 28 13 06 08 30 09 15 11 22 02 24 23 13
EN PARITY: 16 28 00 05 28 18 12 19 10 27 06 01 15 28 21 16

L814 XMIT DATA: . 05 00 28 12 18 28 27 10 19 15 01 06 16 21 28
EN PARITY: 27 08 15 28 00 03 13 26 26 22 10 17 18 01 21 02

L815 XMIT DATA: . 28 15 08 13 03 00 22 26 26 18 17 10 02 21 01
EN PARITY: 12 02 26 11 28 02 25 15 26 26 00 08 31 16 18 08

L816 XMIT DATA: . 11 26 02 25 02 28 26 26 15 31 08 00 08 18 16
EN PARITY: 15 28 22 27 02 30 01 19 02 26 17 07 14 27 21 15

L817 XMIT DATA: . 27 22 28 01 30 02 26 02 19 14 07 17 15 21 27
EN PARITY: 22 24 21 00 08 24 25 17 23 11 04 31 07 14 28 16

L818 XMIT DATA: . 00 21 24 25 24 08 11 23 17 07 31 04 16 28 14
EN PARITY: 30 01 30 21 03 16 12 28 23 19 19 13 25 25 20 27

L819 XMIT DATA: . 21 30 01 12 16 03 19 23 28 25 13 19 27 20 25
EN PARITY: 21 16 16 05 22 21 08 10 23 22 21 03 28 25 17 05

L820 XMIT DATA: . 05 16 16 08 21 22 22 23 10 28 03 21 05 17 25
EN PARITY: 06 22 20 30 17 22 03 00 11 08 09 04 24 17 19 21

L821 XMIT DATA: . 30 20 22 03 22 17 08 11 00 24 04 09 21 19 17
EN PARITY: 28 21 29 18 13 16 20 26 17 10 17 28 10 31 29 19

L822 XMIT DATA: . 18 29 21 20 16 13 10 17 26 10 28 17 19 29 31
EN PARITY: 10 24 10 08 10 30 10 05 16 25 29 30 16 27 03 16

L823 XMIT DATA: . 08 10 24 10 30 10 25 16 05 16 30 29 16 03 27
EN PARITY: 06 11 19 01 27 12 29 11 02 18 14 29 13 10 11 22

L824 XMIT DATA: . 01 19 11 29 12 27 18 02 11 13 29 14 22 11 10
EN PARITY: 22 12 26 00 27 30 04 14 15 27 04 29 14 17 00 18

L825 XMIT DATA: . 00 26 12 04 30 27 27 15 14 14 29 04 18 00 17
EN PARITY: 08 18 25 31 04 17 16 06 03 00 23 02 25 27 06 07

L826 XMIT DATA: . 31 25 18 16 17 04 00 03 06 25 02 23 07 06 27
EN PARITY: 03 24 20 13 13 31 06 15 23 22 16 27 19 20 17 21

L827 XMIT DATA: . 13 20 24 06 31 13 22 23 15 19 27 16 21 17 20
EN PARITY: 28 03 10 24 14 26 09 17 03 27 27 13 12 08 21 09

L828 XMIT DATA: . 24 10 03 09 26 14 27 03 17 12 13 27 09 21 08
EN PARITY: 02 02 30 24 29 16 04 07 22 11 03 08 18 15 23 24

L829 XMIT DATA: . 24 30 02 04 16 29 11 22 07 18 08 03 24 23 15

EN PARITY: 09 31 01 01 29 27 30 18 03 23 27 00 02 02 12 31

L830 XMIT DATA: . 01 01 31 30 27 29 23 03 18 02 00 27 31 12 02
EN PARITY: 26 04 31 28 13 12 05 16 12 04 09 21 26 28 15 31

L831 XMIT DATA: . 28 31 04 05 12 13 04 12 16 26 21 09 31 15 28
EN PARITY: 28 02 12 02 27 10 07 27 25 15 22 02 15 19 17 09

L832 XMIT DATA: . 02 12 02 07 10 27 15 25 27 15 02 22 09 17 19
EN PARITY: 04 10 02 01 20 26 24 11 04 19 17 02 21 22 28 09

L833 XMIT DATA: . 01 02 10 24 26 20 19 04 11 21 02 17 09 28 22
EN PARITY: 22 17 11 22 09 12 20 14 18 22 19 04 14 03 07 07

L834 XMIT DATA: . 22 11 17 20 12 09 22 18 14 14 04 19 07 07 03
EN PARITY: 24 30 30 27 00 19 08 03 14 04 06 29 23 08 04 21

L835 XMIT DATA: . 27 30 30 08 19 00 04 14 03 23 29 06 21 04 08
EN PARITY: 19 23 22 06 18 22 24 27 10 09 18 28 00 26 29 24

L836 XMIT DATA: . 06 22 23 24 22 18 09 10 27 00 28 18 24 29 26
EN PARITY: 04 06 04 31 19 12 06 13 09 00 04 05 11 29 31 16

L837 XMIT DATA: . 31 04 06 06 12 19 00 09 13 11 05 04 16 31 29
EN PARITY: 17 08 31 19 07 06 25 15 22 05 22 13 13 18 21 10

L838 XMIT DATA: . 19 31 08 25 06 07 05 22 15 13 13 22 10 21 18
EN PARITY: 05 28 30 22 18 02 03 25 28 07 30 00 12 17 09 29

L839 XMIT DATA: . 22 30 28 03 02 18 07 28 25 12 00 30 29 09 17
EN PARITY: 10 07 11 18 18 06 03 25 22 28 22 05 27 29 30 27

L840 XMIT DATA: . 18 11 07 03 06 18 28 22 25 27 05 22 27 30 29
EN PARITY: 16 13 06 00 20 26 13 28 06 17 20 22 08 00 12 16

L841 XMIT DATA: . 00 06 13 13 26 20 17 06 28 08 22 20 16 12 00
EN PARITY: 12 22 10 14 09 20 06 14 17 01 25 25 01 15 09 19

L842 XMIT DATA: . 14 10 22 06 20 09 01 17 14 01 25 25 19 09 15
EN PARITY: 21 07 20 23 05 17 00 21 04 01 20 30 07 13 16 28

L843 XMIT DATA: . 23 20 07 00 17 05 01 04 21 07 30 20 28 16 13
EN PARITY: 24 31 06 29 26 01 07 05 30 29 00 19 03 17 20 09

L844 XMIT DATA: . 29 06 31 07 01 26 29 30 05 03 19 00 09 20 17
EN PARITY: 20 23 21 27 14 18 01 25 16 12 26 18 00 27 07 17

L845 XMIT DATA: . 27 21 23 01 18 14 12 16 25 00 18 26 17 07 27
EN PARITY: 06 05 01 29 01 06 03 30 12 28 23 18 17 19 17 01

L846 XMIT DATA: . 29 01 05 03 06 01 28 12 30 17 18 23 01 17 19
EN PARITY: 30 21 26 20 06 20 18 02 21 19 31 12 05 03 20 16

L847 XMIT DATA: . 20 26 21 18 20 06 19 21 02 05 12 31 16 20 03
EN PARITY: 02 15 14 00 27 01 10 05 26 03 26 02 13 11 09 02

L848 XMIT DATA: . 00 14 15 10 01 27 03 26 05 13 02 26 02 09 11
EN PARITY: 02 21 00 28 22 04 30 30 19 05 13 02 12 23 20 23

L849 XMIT DATA: . 28 00 21 30 04 22 05 19 30 12 02 13 23 20 23
EN PARITY: 10 21 03 00 14 19 20 27 20 21 30 00 01 21 25 18

L850 XMIT DATA: . 00 03 21 20 19 14 21 20 27 01 00 30 18 25 21
EN PARITY: 17 25 01 31 10 01 22 30 17 26 00 04 08 17 27 06

L851 XMIT DATA: . 31 01 25 22 01 10 26 17 30 08 04 00 06 27 17
EN PARITY: 08 15 15 19 12 29 05 17 27 09 10 00 13 30 13 18

L852 XMIT DATA: . 19 15 15 05 29 12 09 27 17 13 00 10 18 13 30
EN PARITY: 09 14 29 00 15 13 11 02 03 11 08 20 31 07 27 31

L853 XMIT DATA: . 00 29 14 11 13 15 11 03 02 31 20 08 31 27 07
EN PARITY: 15 05 25 03 23 26 17 31 01 03 19 31 00 31 02 29

L854 XMIT DATA: . 03 25 05 17 26 23 03 01 31 00 31 19 29 02 31
EN PARITY: 03 27 12 29 10 26 06 29 26 01 30 24 14 20 15 16

L855 XMIT DATA: . 29 12 27 06 26 10 01 26 29 14 24 30 16 15 20
EN PARITY: 13 05 23 24 30 16 26 05 18 27 20 24 26 27 30 01

L856 XMIT DATA: . 24 23 05 26 16 30 27 18 05 26 24 20 01 30 27
EN PARITY: 19 06 18 03 00 04 31 24 10 08 25 04 08 26 09 00

L857 XMIT DATA: . 03 18 06 31 04 00 08 10 24 08 04 25 00 09 26
EN PARITY: 08 01 23 12 15 14 09 29 14 28 06 29 03 13 08 27

L858 XMIT DATA: . 12 23 01 09 14 15 28 14 29 03 29 06 27 08 13
EN PARITY: 24 28 30 01 11 06 00 03 14 13 28 25 05 26 31 04

L859 XMIT DATA: . 01 30 28 00 06 11 13 14 03 05 25 28 04 31 26
EN PARITY: 16 00 00 11 26 07 29 13 27 15 03 15 20 11 22 28

L860 XMIT DATA: . 11 00 00 29 07 26 15 27 13 20 15 03 28 22 11
EN PARITY: 23 09 16 16 06 02 07 26 17 07 10 07 07 11 06 29

L861 XMIT DATA: . 16 16 09 07 02 06 07 17 26 07 07 10 29 06 11
EN PARITY: 19 18 17 21 12 05 17 29 31 15 08 17 10 09 04 21

L862 XMIT DATA: . 21 17 18 17 05 12 15 31 29 10 17 08 21 04 09
EN PARITY: 01 14 31 04 05 07 31 22 28 29 00 15 14 24 17 08

L863 XMIT DATA: . 04 31 14 31 07 05 29 28 22 14 15 00 08 17 24
EN PARITY: 20 31 27 26 25 14 14 06 05 06 29 17 25 28 13 14

L864 XMIT DATA: . 26 27 31 14 14 25 06 05 06 25 17 29 14 13 28
EN PARITY: 01 11 21 22 24 09 17 02 27 24 17 06 25 01 02 22

L865 XMIT DATA: . 22 21 11 17 09 24 24 27 02 25 06 17 22 02 01
EN PARITY: 23 23 25 30 24 20 26 04 11 12 28 16 20 24 05 13

L866 XMIT DATA: . 30 25 23 26 20 24 12 11 04 20 16 28 13 05 24
EN PARITY: 02 27 04 10 06 10 17 20 12 23 02 14 05 07 04 19

L867 XMIT DATA: . 10 04 27 17 10 06 23 12 20 05 14 02 19 04 07
EN PARITY: 28 30 18 02 19 20 26 30 09 10 00 15 24 04 30 10

L868 XMIT DATA: . 02 18 30 26 20 19 10 09 30 24 15 00 10 30 04
EN PARITY: 17 25 13 30 14 06 00 00 10 15 06 04 31 01 15 14

L869 XMIT DATA: . 30 13 25 00 06 14 15 10 00 31 04 06 14 15 01
EN PARITY: 20 01 08 19 00 11 27 13 07 11 25 27 15 05 21 05

L870 XMIT DATA: . 19 08 01 27 11 00 11 07 13 15 27 25 05 21 05
EN PARITY: 08 15 14 06 03 26 16 29 03 25 06 00 21 29 06 02

L871 XMIT DATA: . 06 14 15 16 26 03 25 03 29 21 00 06 02 06 29
EN PARITY: 26 12 16 19 27 21 10 17 00 00 20 03 01 31 30 29

L872 XMIT DATA: . 19 16 12 10 21 27 00 00 17 01 03 20 29 30 31
EN PARITY: 01 09 30 10 30 27 12 26 19 31 29 18 09 09 14 19

L873 XMIT DATA: . 10 30 09 12 27 30 31 19 26 09 18 29 19 14 09
EN PARITY: 23 13 02 09 00 20 18 23 04 10 17 23 12 24 23 02

L874 XMIT DATA: . 09 02 13 18 20 00 10 04 23 12 23 17 02 23 24
EN PARITY: 26 01 09 13 20 12 21 15 27 01 27 30 25 02 07 13

L875 XMIT DATA: . 13 09 01 21 12 20 01 27 15 25 30 27 13 07 02
EN PARITY: 12 05 31 14 15 27 21 23 12 28 19 18 17 02 24 01

L876 XMIT DATA: . 14 31 05 21 27 15 28 12 23 17 18 19 01 24 02
EN PARITY: 15 07 26 23 25 28 27 01 18 01 00 24 10 23 06 18

L877 XMIT DATA: . 23 26 07 27 28 25 01 18 01 10 24 00 18 06 23
EN PARITY: 28 30 00 23 01 28 09 26 28 07 12 05 15 15 03 29

L878 XMIT DATA: . 23 00 30 09 28 01 07 28 26 15 05 12 29 03 15
EN PARITY: 14 31 21 01 23 05 25 10 00 09 12 18 09 30 18 06

L879 XMIT DATA: . 01 21 31 25 05 23 09 00 10 09 18 12 06 18 30
EN PARITY: 19 29 22 24 19 07 24 05 17 31 14 28 21 14 18 15

L880 XMIT DATA: . 24 22 29 24 07 19 31 17 05 21 28 14 15 18 14
EN PARITY: 11 26 05 17 18 29 22 02 10 05 29 23 00 01 18 28

L881 XMIT DATA: . 17 05 26 22 29 18 05 10 02 00 23 29 28 18 01
EN PARITY: 19 01 12 29 12 26 10 31 30 12 29 00 02 19 25 29

L882 XMIT DATA: . 29 12 01 10 26 12 12 30 31 02 00 29 29 25 19
EN PARITY: 22 23 31 03 25 12 01 27 21 31 00 23 17 01 06 09

L883 XMIT DATA: . 03 31 23 01 12 25 31 21 27 17 23 00 09 06 01
EN PARITY: 23 09 01 15 00 11 26 06 03 13 03 30 11 11 18 27

L884 XMIT DATA: . 15 01 09 26 11 00 13 03 06 11 30 03 27 18 11
EN PARITY: 13 05 05 05 28 17 00 05 13 24 25 05 30 18 20 14

L885 XMIT DATA: . 05 05 05 00 17 28 24 13 05 30 05 25 14 20 18
EN PARITY: 20 08 23 21 03 12 30 09 07 28 26 22 16 17 21 08

L886 XMIT DATA: . 21 23 08 30 12 03 28 07 09 16 22 26 08 21 17
EN PARITY: 25 02 26 00 10 01 00 31 19 28 29 00 04 00 13 22

L887 XMIT DATA: . 00 26 02 00 01 10 28 19 31 04 00 29 22 13 00
EN PARITY: 18 05 01 08 14 20 10 06 17 13 20 26 04 29 25 25

L888 XMIT DATA: . 08 01 05 10 20 14 13 17 06 04 26 20 25 25 29
EN PARITY: 24 07 05 00 23 21 07 30 16 08 18 04 17 20 06 10

L889 XMIT DATA: . 00 05 07 07 21 23 08 16 30 17 04 18 10 06 20
EN PARITY: 25 14 21 11 09 29 23 17 24 11 17 00 08 26 00 21

L890 XMIT DATA: . 11 21 14 23 29 09 11 24 17 08 00 17 21 00 26
EN PARITY: 07 02 30 28 02 26 04 24 15 01 02 19 16 16 30 23

L891 XMIT DATA: . 28 30 02 04 26 02 01 15 24 16 19 02 23 30 16

EN PARITY: 24 04 28 12 13 17 05 27 09 20 02 28 03 14 29 21

L892 XMIT DATA: . 12 28 04 05 17 13 20 09 27 03 28 02 21 29 14
EN PARITY: 21 12 29 14 26 28 29 18 26 24 06 20 05 19 01 26

L893 XMIT DATA: . 14 29 12 29 28 26 24 26 18 05 20 06 26 01 19
EN PARITY: 12 27 11 19 27 25 24 04 03 03 00 07 10 01 16 23

L894 XMIT DATA: . 19 11 27 24 25 27 03 03 04 10 07 00 23 16 01
EN PARITY: 27 16 20 23 04 28 26 15 06 23 08 09 14 12 10 04

L895 XMIT DATA: . 23 20 16 26 28 04 23 06 15 14 09 08 04 10 12
EN PARITY: 22 05 21 09 31 17 16 00 08 28 04 00 19 15 22 04

L896 XMIT DATA: . 09 21 05 16 17 31 28 08 00 19 00 04 04 22 15
EN PARITY: 09 02 11 25 30 22 01 14 22 25 27 21 29 00 22 08

L897 XMIT DATA: . 25 11 02 01 22 30 25 22 14 29 21 27 08 22 00
EN PARITY: 09 31 21 09 23 09 04 16 18 27 28 19 22 24 14 00

L898 XMIT DATA: . 09 21 31 04 09 23 27 18 16 22 19 28 00 14 24
EN PARITY: 05 29 10 23 22 29 07 23 11 21 30 00 18 17 14 01

L899 XMIT DATA: . 23 10 29 07 29 22 21 11 23 18 00 30 01 14 17
EN PARITY: 05 16 24 00 20 17 21 26 25 10 26 30 14 23 00 20

L900 XMIT DATA: . 00 24 16 21 17 20 10 25 26 14 30 26 20 00 23
EN PARITY: 15 25 01 10 09 03 16 19 02 12 18 26 31 27 14 21

L901 XMIT DATA: . 10 01 25 16 03 09 12 02 19 31 26 18 21 14 27
EN PARITY: 31 01 28 24 20 28 04 30 10 08 21 28 00 00 03 23

L902 XMIT DATA: . 24 28 01 04 28 20 08 10 30 00 28 21 23 03 00
EN PARITY: 25 23 22 17 24 22 19 07 18 07 28 11 08 16 06 11

L903 XMIT DATA: . 17 22 23 19 22 24 07 18 07 08 11 28 11 06 16
EN PARITY: 23 00 20 25 21 09 15 20 10 17 20 25 11 01 18 08

L904 XMIT DATA: . 25 20 00 15 09 21 17 10 20 11 25 20 08 18 01
EN PARITY: 13 11 06 20 08 23 24 24 27 20 04 12 06 16 22 07

L905 XMIT DATA: . 20 06 11 24 23 08 20 27 24 06 12 04 07 22 16
EN PARITY: 14 17 24 03 01 09 28 28 01 10 19 31 13 08 00 27

L906 XMIT DATA: . 03 24 17 28 09 01 10 01 28 13 31 19 27 00 08
EN PARITY: 15 27 00 22 30 06 01 15 02 31 08 24 07 26 21 09

L907 XMIT DATA: . 22 00 27 01 06 30 31 02 15 07 24 08 09 21 26
EN PARITY: 04 17 16 26 29 01 22 03 31 06 09 00 11 08 10 17

L908 XMIT DATA: . 26 16 17 22 01 29 06 31 03 11 00 09 17 10 08
EN PARITY: 18 20 25 31 24 01 21 14 04 11 23 20 17 06 20 19

L909 XMIT DATA: . 31 25 20 21 01 24 11 04 14 17 20 23 19 20 06
EN PARITY: 07 20 30 24 12 01 28 08 01 01 01 05 24 06 08 09

L910 XMIT DATA: . 24 30 20 28 01 12 01 01 08 24 05 01 09 08 06
EN PARITY: 19 00 14 13 24 16 30 26 25 31 12 20 30 30 16 12

L911 XMIT DATA: . 13 14 00 30 16 24 31 25 26 30 20 12 12 16 30
EN PARITY: 31 16 20 10 20 17 18 24 25 29 05 17 28 21 05 14

L912 XMIT DATA: . 10 20 16 18 17 20 29 25 24 28 17 05 14 05 21
EN PARITY: 17 10 11 12 19 12 25 00 21 07 22 06 12 05 22 14

L913 XMIT DATA: . 12 11 10 25 12 19 07 21 00 12 06 22 14 22 05
EN PARITY: 15 00 10 22 15 22 09 19 06 14 30 29 27 19 27 30

L914 XMIT DATA: . 22 10 00 09 22 15 14 06 19 27 29 30 30 27 19
EN PARITY: 04 19 02 09 21 13 29 27 24 17 07 28 26 03 29 10

L915 XMIT DATA: . 09 02 19 29 13 21 17 24 27 26 28 07 10 29 03
EN PARITY: 20 22 26 11 02 12 27 26 00 27 07 03 15 27 13 01

L916 XMIT DATA: . 11 26 22 27 12 02 27 00 26 15 03 07 01 13 27
EN PARITY: 20 02 13 27 02 05 13 24 02 30 06 26 04 01 31 13

L917 XMIT DATA: . 27 13 02 13 05 02 30 02 24 04 26 06 13 31 01
EN PARITY: 12 26 24 02 12 08 19 05 24 07 10 15 28 08 14 19

L918 XMIT DATA: . 02 24 26 19 08 12 07 24 05 28 15 10 19 14 08
EN PARITY: 21 06 24 01 21 16 11 21 14 11 04 26 28 13 02 00

L919 XMIT DATA: . 01 24 06 11 16 21 11 14 21 28 26 04 00 02 13
EN PARITY: 00 21 06 20 02 18 28 26 00 06 18 18 15 21 30 15

L920 XMIT DATA: . 20 06 21 28 18 02 06 00 26 15 18 18 15 30 21
EN PARITY: 09 00 01 20 11 18 15 07 22 09 16 10 11 13 15 19

L921 XMIT DATA: . 20 01 00 15 18 11 09 22 07 11 10 16 19 15 13
EN PARITY: 27 11 10 17 26 20 17 16 00 24 04 21 04 21 14 29

L922 XMIT DATA: . 17 10 11 17 20 26 24 00 16 04 21 04 29 14 21
EN PARITY: 22 14 01 16 07 03 09 18 08 31 24 24 16 10 18 21

L923 XMIT DATA: . 16 01 14 09 03 07 31 08 18 16 24 24 21 18 10
EN PARITY: 01 26 04 19 08 25 27 27 10 30 03 08 08 30 09 09

L924 XMIT DATA: . 19 04 26 27 25 08 30 10 27 08 08 03 09 09 30
EN PARITY: 07 14 01 28 03 04 07 18 29 09 23 20 21 08 20 10

L925 XMIT DATA: . 28 01 14 07 04 03 09 29 18 21 20 23 10 20 08
EN PARITY: 00 17 01 02 01 20 14 24 04 31 23 09 03 23 22 19

L926 XMIT DATA: . 02 01 17 14 20 01 31 04 24 03 09 23 19 22 23
EN PARITY: 04 28 23 31 07 10 29 26 02 08 00 25 23 23 30 27

L927 XMIT DATA: . 31 23 28 29 10 07 08 02 26 23 25 00 27 30 23
EN PARITY: 03 19 29 08 04 16 06 01 27 17 03 02 13 07 20 11

L928 XMIT DATA: . 08 29 19 06 16 04 17 27 01 13 02 03 11 20 07
EN PARITY: 17 31 18 13 01 17 26 06 12 00 16 26 16 03 27 05

L929 XMIT DATA: . 13 18 31 26 17 01 00 12 06 16 26 16 05 27 03
EN PARITY: 27 07 01 11 25 07 00 26 06 16 09 16 16 20 01 30

L930 XMIT DATA: . 11 01 07 00 07 25 16 06 26 16 16 09 30 01 20
EN PARITY: 00 06 21 19 01 14 26 14 25 06 05 03 08 06 17 10

L931 XMIT DATA: . 19 21 06 26 14 01 06 25 14 08 03 05 10 17 06
EN PARITY: 16 03 03 06 18 11 14 05 03 13 03 27 12 30 01 06

L932 XMIT DATA: . 06 03 03 14 11 18 13 03 05 12 27 03 06 01 30
EN PARITY: 06 09 14 27 04 18 05 11 15 17 31 30 29 30 25 06

L933 XMIT DATA: . 27 14 09 05 18 04 17 15 11 29 30 31 06 25 30
EN PARITY: 02 01 09 21 29 26 00 03 20 19 31 00 03 05 28 00

L934 XMIT DATA: . 21 09 01 00 26 29 19 20 03 03 00 31 00 28 05
EN PARITY: 21 13 24 06 16 30 15 08 28 21 15 20 01 13 22 17

L935 XMIT DATA: . 06 24 13 15 30 16 21 28 08 01 20 15 17 22 13
EN PARITY: 16 17 02 23 30 15 20 30 06 22 15 28 30 20 13 06

L936 XMIT DATA: . 23 02 17 20 15 30 22 06 30 30 28 15 06 13 20
EN PARITY: 31 05 21 18 15 29 31 10 07 27 02 18 29 30 27 00

L937 XMIT DATA: . 18 21 05 31 29 15 27 07 10 29 18 02 00 27 30
EN PARITY: 30 21 27 30 13 20 21 25 28 00 07 01 10 31 22 28

L938 XMIT DATA: . 30 27 21 21 20 13 00 28 25 10 01 07 28 22 31
EN PARITY: 15 19 16 23 21 26 18 25 22 17 04 26 10 07 10 09

L939 XMIT DATA: . 23 16 19 18 26 21 17 22 25 10 26 04 09 10 07
EN PARITY: 07 30 31 07 15 11 06 30 01 10 07 14 20 31 08 02

L940 XMIT DATA: . 07 31 30 06 11 15 10 01 30 20 14 07 02 08 31
EN PARITY: 19 15 13 07 27 26 12 24 19 29 25 30 07 22 19 11

L941 XMIT DATA: . 07 13 15 12 26 27 29 19 24 07 30 25 11 19 22
EN PARITY: 00 07 00 03 05 08 30 23 05 01 26 26 23 13 30 02

L942 XMIT DATA: . 03 00 07 30 08 05 01 05 23 23 26 26 02 30 13
EN PARITY: 28 21 15 29 19 12 12 10 04 06 19 25 04 09 05 31

L943 XMIT DATA: . 29 15 21 12 12 19 06 04 10 04 25 19 31 05 09
EN PARITY: 07 17 02 05 18 31 28 01 10 05 05 14 15 22 03 30

L944 XMIT DATA: . 05 02 17 28 31 18 05 10 01 15 14 05 30 03 22
EN PARITY: 15 06 06 08 17 01 04 02 14 26 14 03 15 31 30 06

L945 XMIT DATA: . 08 06 06 04 01 17 26 14 02 15 03 14 06 30 31
EN PARITY: 10 14 09 09 04 23 13 07 05 26 27 26 00 05 06 18

L946 XMIT DATA: . 09 09 14 13 23 04 26 05 07 00 26 27 18 06 05
EN PARITY: 16 16 29 12 18 12 29 03 10 10 21 12 05 31 17 12

L947 XMIT DATA: . 12 29 16 29 12 18 10 10 03 05 12 21 12 17 31
EN PARITY: 10 02 14 31 13 21 15 30 26 24 30 06 20 08 21 05

L948 XMIT DATA: . 31 14 02 15 21 13 24 26 30 20 06 30 05 21 08
EN PARITY: 26 27 04 06 02 07 30 16 26 19 22 12 10 14 16 07

L949 XMIT DATA: . 06 04 27 30 07 02 19 26 16 10 12 22 07 16 14
EN PARITY: 09 31 10 30 26 19 08 19 13 08 05 05 08 28 15 05

L950 XMIT DATA: . 30 10 31 08 19 26 08 13 19 08 05 05 05 15 28
EN PARITY: 22 30 17 24 15 29 24 31 08 29 00 28 23 03 08 06

L951 XMIT DATA: . 24 17 30 24 29 15 29 08 31 23 28 00 06 08 03
EN PARITY: 17 19 28 19 11 24 19 01 29 05 04 02 01 11 04 21

L952 XMIT DATA: . 19 28 19 19 24 11 05 29 01 01 02 04 21 04 11
EN PARITY: 21 02 13 27 31 10 23 25 19 03 29 13 24 29 08 28

L953 XMIT DATA: . 27 13 02 23 10 31 03 19 25 24 13 29 28 08 29

L954 XMIT DATA: . 26 31 24 19 08 05 20 23 24 19 28 08 05 20 02
EN PARITY: 31 24 18 18 20 01 20 28 01 17 01 07 25 16 29 18

L955 XMIT DATA: . 18 18 24 20 01 20 17 01 28 25 07 01 18 29 16
EN PARITY: 20 00 26 24 13 06 18 13 06 21 23 26 16 20 23 20

L956 XMIT DATA: . 24 26 00 18 06 13 21 06 13 16 26 23 20 23 20
EN PARITY: 13 15 23 27 16 24 29 01 12 30 18 04 04 20 26 06

L957 XMIT DATA: . 27 23 15 29 24 16 30 12 01 04 04 18 06 26 20
EN PARITY: 06 22 30 28 03 06 00 03 29 16 03 28 29 30 16 18

L958 XMIT DATA: . 28 30 22 00 06 03 16 29 03 29 28 03 18 16 30
EN PARITY: 14 10 29 08 00 15 05 02 04 07 21 24 30 03 26 05

L959 XMIT DATA: . 08 29 10 05 15 00 07 04 02 30 24 21 05 26 03
EN PARITY: 29 18 13 12 29 28 06 22 28 27 14 11 27 30 19 27

L960 XMIT DATA: . 12 13 18 06 28 29 27 28 22 27 11 14 27 19 30
EN PARITY: 30 05 05 18 31 06 10 21 16 00 06 06 12 10 02 07

L961 XMIT DATA: . 18 05 05 10 06 31 00 16 21 12 06 06 07 02 10
EN PARITY: 04 17 21 15 10 30 27 09 03 17 01 25 12 08 09 21

L962 XMIT DATA: . 15 21 17 27 30 10 17 03 09 12 25 01 21 09 08
EN PARITY: 29 26 25 18 03 26 23 29 11 11 20 07 06 01 12 19

L963 XMIT DATA: . 18 25 26 23 26 03 11 11 29 06 07 20 19 12 01
EN PARITY: 19 14 16 03 03 19 22 04 27 13 24 31 28 04 07 14

L964 XMIT DATA: . 03 16 14 22 19 03 13 27 04 28 31 24 14 07 04
EN PARITY: 16 10 05 24 13 00 25 24 09 12 02 04 30 17 27 09

L965 XMIT DATA: . 24 05 10 25 00 13 12 09 24 30 04 02 09 27 17
EN PARITY: 24 24 12 17 12 15 01 01 19 08 06 14 10 20 03 07

L966 XMIT DATA: . 17 12 24 01 15 12 08 19 01 10 14 06 07 03 20
EN PARITY: 20 27 14 21 18 29 20 22 03 31 14 21 03 24 18 20

L967 XMIT DATA: . 21 14 27 20 29 18 31 03 22 03 21 14 20 18 24
EN PARITY: 28 29 04 09 29 08 16 15 26 19 12 06 26 31 00 09

L968 XMIT DATA: . 09 04 29 16 08 29 19 26 15 26 06 12 09 00 31
EN PARITY: 15 22 20 28 22 02 12 23 13 24 00 22 17 04 14 24

L969 XMIT DATA: . 28 20 22 12 02 22 24 13 23 17 22 00 24 14 04
EN PARITY: 21 24 01 19 13 23 16 25 16 27 21 17 21 14 03 31

L970 XMIT DATA: . 19 01 24 16 23 13 27 16 25 21 17 21 31 03 14
EN PARITY: 20 29 02 26 31 13 16 16 27 22 05 06 26 25 23 30

L971 XMIT DATA: . 26 02 29 16 13 31 22 27 16 26 06 05 30 23 25
EN PARITY: 28 11 18 17 01 19 03 14 15 18 24 29 14 02 31 08

L972 XMIT DATA: . 17 18 11 03 19 01 18 15 14 14 29 24 08 31 02
EN PARITY: 17 01 11 21 19 09 20 01 07 12 00 06 11 21 21 28

L973 XMIT DATA: . 21 11 01 20 09 19 12 07 01 11 06 00 28 21 21
EN PARITY: 03 03 21 08 30 04 02 17 19 04 31 08 21 26 13 11

L974 XMIT DATA: . 08 21 03 02 04 30 04 19 17 21 08 31 11 13 26
EN PARITY: 14 00 18 11 18 26 05 24 13 14 22 08 29 16 05 27

L975 XMIT DATA: . 11 18 00 05 26 18 14 13 24 29 08 22 27 05 16
EN PARITY: 03 00 19 09 13 00 30 25 26 24 28 09 05 20 14 15

L976 XMIT DATA: . 09 19 00 30 00 13 24 26 25 05 09 28 15 14 20
EN PARITY: 23 16 22 25 09 01 18 24 26 19 29 02 11 16 26 28

L977 XMIT DATA: . 25 22 16 18 01 09 19 26 24 11 02 29 28 26 16
EN PARITY: 13 30 14 01 25 02 21 06 03 25 10 02 11 21 01 28

L978 XMIT DATA: . 01 14 30 21 02 25 25 03 06 11 02 10 28 01 21
EN PARITY: 31 30 02 12 29 30 27 01 30 30 30 28 15 27 27 16

L979 XMIT DATA: . 12 02 30 27 30 29 30 30 01 15 28 30 16 27 27
EN PARITY: 11 27 10 02 24 31 28 22 15 23 29 23 09 07 03 09

L980 XMIT DATA: . 02 10 27 28 31 24 23 15 22 09 23 29 09 03 07
EN PARITY: 18 10 17 27 07 07 16 14 04 17 00 08 18 31 29 19

L981 XMIT DATA: . 27 17 10 16 07 07 17 04 14 18 08 00 19 29 31
EN PARITY: 09 11 30 20 26 13 31 18 19 16 08 03 03 05 10 21

L982 XMIT DATA: . 20 30 11 31 13 26 16 19 18 03 03 08 21 10 05
EN PARITY: 00 13 26 11 21 21 06 22 25 06 27 27 23 01 02 13

L983 XMIT DATA: . 11 26 13 06 21 21 06 25 22 23 27 27 13 02 01
EN PARITY: 30 20 18 03 27 16 07 08 24 02 30 21 13 31 28 10

L984 XMIT DATA: . 03 18 20 07 16 27 02 24 08 13 21 30 10 28 31
EN PARITY: 12 10 26 22 15 09 06 27 08 01 18 03 05 25 31 14

L985 XMIT DATA: . 22 26 10 06 09 15 01 08 27 05 03 18 14 31 25
EN PARITY: 16 02 21 30 13 29 08 22 00 25 19 17 27 17 18 06

L986 XMIT DATA: . 30 21 02 08 29 13 25 00 22 27 17 19 06 18 17
EN PARITY: 10 17 15 03 25 28 02 10 08 11 23 25 06 09 31 29

L987 XMIT DATA: . 03 15 17 02 28 25 11 08 10 06 25 23 29 31 09
EN PARITY: 21 17 15 25 24 30 14 28 24 00 10 05 01 14 09 21

L988 XMIT DATA: . 25 15 17 14 30 24 00 24 28 01 05 10 21 09 14
EN PARITY: 31 13 03 07 07 06 01 23 31 29 03 29 22 30 27 22

L989 XMIT DATA: . 07 03 13 01 06 07 29 31 23 22 29 03 22 27 30
EN PARITY: 28 29 13 07 18 20 24 29 01 17 28 19 13 25 31 30

L990 XMIT DATA: . 07 13 29 24 20 18 17 01 29 13 19 28 30 31 25
EN PARITY: 02 04 23 24 10 06 00 03 24 10 08 20 16 27 24 22

L991 XMIT DATA: . 24 23 04 00 06 10 10 24 03 16 20 08 22 24 27
EN PARITY: 26 13 18 16 07 30 25 00 11 15 11 03 19 29 14 16

L992 XMIT DATA: . 16 18 13 25 30 07 15 11 00 19 03 11 16 14 29
EN PARITY: 19 06 13 28 25 15 18 19 07 01 11 09 01 29 19 01

L993 XMIT DATA: . 28 13 06 18 15 25 01 07 19 01 09 11 01 19 29
EN PARITY: 04 16 09 23 27 23 08 23 12 20 11 31 20 31 17 22

L994 XMIT DATA: . 23 09 16 08 23 27 20 12 23 20 31 11 22 17 31
EN PARITY: 28 13 20 02 27 04 19 05 18 19 01 18 20 22 22 04

L995 XMIT DATA: . 02 20 13 19 04 27 19 18 05 20 18 01 04 22 22
EN PARITY: 23 03 07 04 03 12 00 05 02 04 14 15 27 03 08 27

L996 XMIT DATA: . 04 07 03 00 12 03 04 02 05 27 15 14 27 08 03
EN PARITY: 09 17 08 12 04 20 06 31 27 30 30 00 14 15 10 22

L997 XMIT DATA: . 12 08 17 06 20 04 30 27 31 14 00 30 22 10 15
EN PARITY: 07 31 26 06 12 26 01 05 31 15 11 01 01 24 04 09

L998 XMIT DATA: . 06 26 31 01 26 12 15 31 05 01 01 11 09 04 24
EN PARITY: 04 25 04 15 18 08 01 15 06 22 23 14 17 00 02 29

JTIDS O.S.
REQUEST?

APPENDIX D

TEST DATA SHEETS

REED SOLOMON ENCODER/DECODER

Prepared for Naval Air Development Center
Under Contract Number N62269-75-C-0503

by

ITT Avionics Division
500 Washington Avenue
Nutley, N.J. 07110

Test Performed By: Michael Ferraro ITTAV

Test Witnessed By: Valerie J. Quinn

Test Performed
1/19/1976

Data Sheets

Issue B Date 1/16/76

Sheet ___ of ___

D11724

RSED Test Data Sheet

Test Encoder Accuracy Par. 3.1.1.1-1

A P

WORD	POSITION	INPUT AREA	TRANS WORD	ENCODER AREA	RESULTS	
					PASS	FAIL
H S 808	01	10	10	10	✓	
	02 } Data	04	04	04	✓	
	03	11	11	11	✓	
	04	15	15	15	✓	
	05		14	14	✓	
	06		31	31	✓	
	07		22	22	✓	
	08 } Parity		07	07	✓	
	09		28	28	✓	
	10		10	10	✓	
	11		07	07	✓	
	12		11	11	✓	
	13		13	13	✓	
	14		10	10	✓	
	15		05	06	✓	
	16		03	03	✓	

Test Encoder Accuracy Par. 3.1.1. 1 - 2

WORD	POSITION	INPUT AREA	TRANS WORD	ENCODER AREA	RESULTS	
					PASS	FAIL
W1 L011	01	20	20	20	✓	
	02	09	09	09	✓	
	03	07	07	07	✓	
	04 } Data	22	22	22	✓	
	05	20	20	20	✓	
	06	24	24	24	✓	
	07	22	22	22	✓	
	08	28	28	28	✓	
	09	04	04	04	✓	
	10	20	20	20	✓	
	11	11	11	11	✓	
	12	27	27	27	✓	
	13	12	12	12	✓	
	14	12	12	12	✓	
	15	16	16	16	✓	
	16		22	22	✓	
	17		07	07	✓	
	18		30	30	✓	
	19		31	31	✓	
	20		04	04	✓	
	21 } Parity		17	17	✓	
	22		07	07	✓	
	23		14	14	✓	
	24		15	15	✓	
	25		10	10	✓	
	26		05	05	✓	
	27		19	19	✓	
	28		17	17	✓	
	29		29	29	✓	
	30		16	16	✓	
	31		20	20	✓	

Test Encoder Accuracy Par. 3.1.1. 1-3

WORD	POSITION	INPUT AREA	TRANS WORD	ENCODER AREA	RESULTS	
					PASS	FAIL
W2 L 098	01	04	04	04		
	02	26	26	26	✓	
	03	19	19	19	✓	
	04	Data 13	13	13	✓	
	05	29	29	29	✓	
	06	28	28	28	✓	
	07	04	04	04	✓	
	08	01	01	01	✓	
	09	06	06	06	✓	
	10	02	02	02	✓	
	11	03	03	03	✓	
	12	07	07	07	✓	
	13	24	24	24	✓	
	14	00	00	00	✓	
	15	27	27	27	✓	
	16		31	31	✓	
	17		03	03	✓	
	18		27	27	✓	
	19		02	02	✓	
	20		21	21	✓	
	21	Parity	04	04	✓	
	22		19	19	✓	
	23		04	04	✓	
	24		08	08	✓	
	25		20	20	✓	
	26		27	27	✓	
	27		21	21	✓	
	28		18	18	✓	
	29		14	14	✓	
	30		09	09	✓	
	31		00	00	✓	

Test Encoder Accuracy Par. 3.1.1. 1-4

WORD	POSITION	INPUT AREA	TRANS WORD	ENCODER AREA	RESULTS	
					PASS	FAIL
W3 L174	01	22	22	22	✓	
	02	12	12	12		
	03	00	00	00		
	04	Data 31	31	31		
	05	29	29	29		
	06	20	20	20		
	07	16	16	16		
	08	31	31	31		
	09	03	03	03		
	10	19	19	19		
	11	18	18	18		
	12	18	18	18		
	13	13	13	13		
	14	04	04	04		
	15	10	10	10		
	16		28	28		
	17		14	14		
	18		30	30		
	19		22	22		
	20		10	10		
	21	Parity	00	00		
	22		01	01		
	23		26	26		
	24		07	07		
	25		31	31		
	26		06	06		
	27		27	27		
	28		29	29		
	29		26	26		
	30		20	20		
	31		01	01	✓	

RSED Test Data Sheet

Test Encoder Accuracy Par. 3.1.1.2-1


A P

WORD	POSITION	INPUT AREA	TRANS WORD	ENCODER AREA	RESULTS	
					PASS	FAIL
H 5224	01	20	20	20	✓	
	02 } Data	27	27	27		
	03	30	30	30		
	04	00	00	00		
	05		18	18		
	06		04	04		
	07		08	08		
	08 Parity		13	13		
	09		30	30		
	10		08	08		
	11		17	17		
	12		02	02		
	13		10	10		
	14		09	09		
	15		31	31	✓	
	16		19	19		

Test Encoder Accuracy Par. 3.1.1. 2-2

WORD	POSITION	INPUT AREA	TRANS WORD	ENCODER AREA	RESULTS	
					PASS	FAIL
<u>W1</u> <u>L 156</u>	01	19	19	19	✓	
	02	16	16	16		
	03	08	08	08		
	04 } Data	18	18	18		
	05	23	23	23		
	06	24	24	24		
	07	06	06	06		
	08	00	00	00		
	09	11	11	11		
	10	16	16	16		
	11	22	22	22		
	12	00	00	00		
	13	00	00	00		
	14	16	16	16		
	15	22	22	24		
	16		04	04		
	17		01	01		
	18		10	10		
	19		14	14		
	20		10	10		
	21 } Parity		10	10		
	22		25	26		
	23		28	28		
	24		04	04		
	25		01	01		
	26		15	15		
	27		23	23		
	28		09	09		
	29		24	24		
	30		06	06		
	31		22	22		

Test Encoder Accuracy Par. 3.1.1. 2-3

WORD	POSITION	INPUT AREA	TRANS WORD	ENCODER AREA	RESULTS	
					PASS	FAIL
<u>W2</u>					✓	
<u>L181</u>	01	01	01	01		
	02	28	28	28		
	03	10	10	10		
	04 } Data	02	02	02		
	05	16	16	16		
	06	06	06	06		
	07	04	04	04		
	08	27	27	27		
	09	07	07	07		
	10	16	16	16		
	11	10	10	10		
	12	11	11	11		
	13	11	11	11		
	14	01	01	01		
	15	20	20	20		
	16		26	26		
	17		15	15		
	18		25	25		
	19		07	07		
	20		03	03		
	21 } Parity		29	29		
	22		22	22		
	23		17	17		
	24		08	08		
	25		28	28		
	26		26	26		
	27		20	20		
	28		25	25		
	29		08	08		
	30		07	07		
	31		10	10		

Test Encoder Accuracy

Par. 3.1.1.

2-4

WORD	POSITION	INPUT AREA	TRANS WORD	ENCODER AREA	RESULTS	
					PASS	FAIL
W3 1172	01	22	22	22	✓	
	02	20	20	20		
	03	06	06	06		
	04 Data	15	15	15		
	05	02	02	02		
	06	09	09	09		
	07	06	06	06		
	08	02	02	02		
	09	26	26	26		
	10	06	06	06		
	11	30	30	30		
	12	17	17	17		
	13	07	07	07		
	14	25	25	26		
	15	04	04	04		
	16		05	05		
	17		11	11		
	18		24	24		
	19		09	09		
	20		15	15		
	21 Parity		02	02		
	22		13	13		
	23		20	20		
	24		11	11		
	25		30	30		
	26		03	03		
	27		14	14		
	28		18	18		
	29		25	25		
	30		02	02		
	31		06	06		

RSED Test Data Sheet

Test Encoder Accuracy Par. 3.1.1.3-1

NT2

WORD	POSITION	INPUT AREA	TRANS WORD	ENCODER AREA	RESULTS	
					PASS	FAIL
# 5619	01	19	19	19	✓	
	02 } Data	13	13	13		
	03	09	09	09		
	04	02	02	02		
	05		06	06		
	06		28	28		
	07		03	03		
	08 } Parity		01	01		
	09		09	09		
	10		21	21		
	11		03	03		
	12		30	30		
	13		27	27		
	14		28	28		
	15		30	30	↓	
	16		31	31		

Test Encoder Accuracy Par. 3.1.1. 3-2

WORD	POSITION	INPUT AREA	TRANS WORD	ENCODER AREA	RESULTS	
					PASS	FAIL
L14 W-1	01	02	02	02	✓	
	02	25	25	25		
	03	12	12	12		
	04 Data	23	23	23		
	05	20	20	20		
	06	12	12	12		
	07	22	22	22		
	08	26	26	26		
	09	31	31	31		
	10	03	03	03		
	11	20	20	20		
	12	09	09	09		
	13	18	18	18		
	14	25	25	25		
	15	23	23	23		
	16		22	22		
	17		05	05		
	18		11	11		
	19		31	31		
	20		31	31		
	21 Parity		24	24		
	22		10	10		
	23		25	25		
	24		08	08		
	25		27	27		
	26		31	31		
	27		16	16		
	28		01	01		
	29		00	00		
	30		19	19		
	31		29	29		

Test Encoder Accuracy Par. 3.1.1. 3-3

WORD	POSITION	INPUT AREA	TRANS WORD	ENCODER AREA	RESULTS	
					PASS	FAIL
<u>W2</u> <u>2084</u>	01	31	31	31	✓	
	02	16	16	16		
	03	06	06	06		
	04	Data 28	28	28		
	05	31	31	31		
	06	13	13	13		
	07	00	00	00		
	08	18	18	18		
	09	21	21	21		
	10	28	28	28		
	11	27	27	27		
	12	08	08	08		
	13	08	08	08		
	14	05	05	05		
	15	18	18	18		
	16		16	16		
	17		26	26		
	18		01	01		
	19		14	14		
	20		27	27		
	21	Parity	06	06		
	22		15	15		
	23		21	21		
	24		22	22		
	25		10	10		
	26		24	24		
	27		01	01		
	28		19	19		
	29		08	08		
	30		31	31		
	31		28	28	✓	

Test Encoder Accuracy Par. 3.1.1.3-4

WORD	POSITION	INPUT AREA	TRANS WORD	ENCODER AREA	RESULTS	
					PASS	FAIL
10-3	01	20	20	20	✓	
1342	02	26	26	26		
	03	13	13	13		
	04 Data	07	07	07		
	05	05	05	05		
	06	18	18	18		
	07	19	19	19		
	08	03	03	03		
	09	21	21	21		
	10	22	22	22		
	11	18	18	18		
	12	00	00	00		
	13	28	28	28		
	14	05	05	05		
	15	13	13	13		
	16		05	05		
	17		30	30		
	18		26	26		
	19		13	13		
	20		12	12		
	21 Parity		26	26		
	22		12	12		
	23		05	05		
	24		15	15		
	25		17	17		
	26		23	23		
	27		14	14		
	28		02	02		
	29		02	02		
	30		06	06		
	31		23	23	✓	

RSED Test Data Sheet

Test Encoder Accuracy Par. 3.1.1.4-1

WORD	POSITION	INPUT AREA	TRANS WORD	ENCODER AREA	RESULTS	
					PASS	FAIL
H S006	01	26	26	26		
	02 } Data	17	17	17		
	03	06	06	06		
	04	27	27	27		
	05		01	01		
	06		04	04		
	07		28	28		
	08 } Parity		03	03		
	09		28	28		
	10		12	12		
	11		30	30		
	12		07	07		
	13		25	25		
	14		26	26		
	15		19	19		
	16		15	15		

Test Encoder Accuracy Par. 3.1.1. 4 - 2

WORD	POSITION	INPUT AREA	TRANS WORD	ENCODER AREA	RESULTS	
					PASS	FAIL
W1 — L514	01	16	16	16		
	02	00	00	00		
	03	16	16	16		
	04 } Data	00	00	00		
	05	25	25	25		
	06	23	23	23		
	07	28	28	28		
	08	30	30	30		
	09	06	06	06		
	10	20	20	20		
	11	19	19	19		
	12	03	03	03		
	13	25	25	25		
	14	19	19	19		
	15	08	08	08		
	16		12	12		
	17		19	19		
	18		13	13		
	19		30	30		
	20		04	04		
	21 } Parity		10	10		
	22		04	04		
	23		17	17		
	24		10	10		
	25		18	18		
	26		00	00		
	27		13	13		
	28		17	17		
	29		14	14		
	30		26	26		
	31		20	20		

Test Encoder Accuracy Par. 3.1.1. 4 - 3

WORD	POSITION	INPUT AREA	TRANS WORD	ENCODER AREA	RESULTS	
					PASS	FAIL
W2 — 4652	01	15	15	15		
	02	05	05	05		
	03	13	13	13		
	04 } Data	31	31	31		
	05	15	15	15		
	06	18	18	18		
	07	00	00	00		
	08	06	06	06		
	09	06	06	06		
	10	09	09	09		
	11	09	09	09		
	12	06	06	06		
	13	29	29	29		
	14	28	28	28		
	15	25	25	25		
	16		09	09		
	17		31	31		
	18		10	10		
	19		11	11		
	20		03	03		
	21 } Parity		21	21		
	22		11	11		
	23		25	25		
	24		19	19		
	25		04	04		
	26		27	27		
	27		04	04		
	28		22	22		
	29		08	08		
	30		04	04		
	31		29	29		

Test Encoder Accuracy Par. 3.1.1. 4 - 4

WORD	POSITION	INPUT AREA	TRANS WORD	ENCODER AREA	RESULTS	
					PASS	FAIL
W3 L348	01	27	27	27		
	02	21	21	21		
	03	02	02	02		
	04 } Data	08	08	08		
	05	13	13	13		
	06	29	29	29		
	07	26	26	26		
	08	31	31	31		
	09	20	20	20		
	10	16	16	16		
	11	30	30	30		
	12	27	27	27		
	13	10	10	10		
	14	02	02	02		
	15	12	12	12		
	16		09	09		
	17		00	00		
	18		24	24		
	19		17	17		
	20		09	09		
	21 } Parity		30	30		
	22		26	26		
	23		14	14		
	24		22	22		
	25		15	15		
	26		31	31		
	27		26	26		
	28		28	28		
	29		21	21		
	30		02	02		
	31		13	13		

RSED Test Data Sheet


Test Encoder Accuracy Par. 3.1.1.5-1

WORD	POSITION	INPUT AREA	TRANS WORD	ENCODER AREA	RESULTS	
					PASS	FAIL
# 3012	01	28	28	28		
	02 } Data	30	30	30		
	03	28	28	28		
	04	04	04	04		
	05		13	13		
	06		18	18		
	07		06	06		
	08 } Parity		11	11		
	09		19	19		
	10		14	14		
	11		03	03		
	12		11	11		
	13		25	25		
	14		18	18		
	15		21	21		
	16		21	21		

Test Encoder Accuracy Par. 3.1.1. 5-2

WORD	POSITION	INPUT AREA	TRANS WORD	ENCODER AREA	RESULTS	
					PASS	FAIL
W-1 L727	01	02	02	02		
	02	09	09	09		
	03	10	10	10		
	04 } Data	26	26	26		
	05	18	18	18		
	06	06	06	06		
	07	23	23	23		
	08	16	16	16		
	09	22	22	22		
	10	13	13	13		
	11	17	17	17		
	12	16	16	16		
	13	01	01	01		
	14	03	03	03		
	15	05	05	05		
	16		20	20		
	17		07	07		
	18		22	22		
	19		04	04		
	20		03	03		
	21 } Parity		25	25		
	22		18	18		
	23		14	14		
	24		16	16		
	25		03	03		
	26		06	06		
	27		08	08		
	28		21	21		
	29		18	18		
	30		18	18		
	31		07	07		

Test Encoder Accuracy Par. 3.1.1. 53

WORD	POSITION	INPUT AREA	TRANS WORD	ENCODER AREA	RESULTS	
					PASS	FAIL
W-2 L031	01	17	17	17		
	02	01	01	01		
	03	24	24	24		
	04 } Data	17	17	17		
	05	10	10	10		
	06	09	09	09		
	07	20	20	20		
	08	17	17	17		
	09	06	06	06		
	10	19	19	19		
	11	11	11	11		
	12	05	05	05		
	13	01	01	01		
	14	10	10	10		
	15	07	07	07		
	16		15	15		
	17		14	14		
	18		09	09		
	19		13	13		
	20		11	11		
	21 } Parity		03	03		
	22		30	30		
	23		09	09		
	24		18	18		
	25		28	28		
	26		20	20		
	27		01	01		
	28		13	13		
	29		30	30		
	30		21	21		
	31		28	28		

Test Encoder Accuracy

Par. 3.1.1. 5-4

WORD	POSITION	INPUT AREA	TRANS WORD	ENCODER AREA	RESULTS	
					PASS	FAIL
<u>W-3</u> <u>1270</u>	01	14	14	14		
	02	09	09	09		
	03	03	03	03		
	04 } Data	14	14	14		
	05	16	16	16		
	06	03	03	03		
	07	31	31	31		
	08	15	15	15		
	09	06	06	06		
	10	04	04	04		
	11	16	16	16		
	12	28	28	28		
	13	20	20	20		
	14	05	05	05		
	15	01	01	01		
	16		03	03		
	17		25	25		
	18		10	10		
	19		29	29		
	20		17	17		
	21 } Parity		05	05		
	22		10	10		
	23		02	02		
	24		06	06		
	25		21	21		
	26		26	26		
	27		30	30		
	28		17	17		
	29		11	11		
	30		31	31		
	31		27	27		

RSED Test Data Sheet

Test Encoder Accuracy Par. 3.1.1.6-1

ATP

WORD	POSITION	INPUT AREA	TRANS WORD	ENCODER AREA	RESULTS	
					PASS	FAIL
H S-415	01	02	02	02	✓	
	02 } Data	20	20	20		
	03	27	27	29		
	04	18	18	18		
	05		07	07		
	06		29	29		
	07		26	26		
	08 Parity		15	16		
	09		17	17		
	10		22	22		
	11		18	18		
	12		00	00		
	13		20	20		
	14		17	17		
	15		24	24		
	16		31	31	✓	

Test Encoder Accuracy Par. 3.1.1.6-2

WORD	POSITION	INPUT AREA	TRANS WORD	ENCODER AREA	RESULTS	
					PASS	FAIL
W-1	01	27	27	27	✓	
L-146	02	23	23	23		
	03	21	21	21		
	04 Data	17	17	17		
	05	13	13	13		
	06	08	08	08		
	07	20	20	20		
	08	30	30	30		
	09	03	03	03		
	10	18	18	18		
	11	00	00	00		
	12	15	16	15		
	13	12	12	12		
	14	17	17	17		
	15	21	21	21		
	16		02	02		
	17		04	04		
	18		28	28		
	19		16	16		
	20		29	29		
	21 Parity		10	10		
	22		14	14		
	23		01	01		
	24		07	07		
	25		06	06		
	26		11	11		
	27		19	19		
	28		00	00		
	29		04	04		
	30		24	24		
	31		13	13	✓	

Test Encoder Accuracy Par. 3.1.1. 6-3

WORD	POSITION	INPUT AREA	TRANS WORD	ENCODER AREA	RESULTS	
					PASS	FAIL
<u>W-2</u>	01	13	13	13	✓	
<u>L-32</u>	02	09	09	09		
	03	14	14	14		
	04 } Data	30	30	30		
	05	13	03	03		
	06	11	11	11		
	07	28	28	28		
	08	18	18	18		
	09	09	09	09		
	10	13	13	13		
	11	01	01	01		
	12	20	20	20		
	13	28	28	28		
	14	21	21	21		
	15	30	30	30		
	16		23	23		
	17		18	18		
	18		27	27		
	19		05	05		
	20		11	11		
	21 } Parity		15	15		
	22		03	03		
	23		15	15		
	24		22	22		
	25		09	09		
	26		31	31		
	27		28	28		
	28		30	30		
	29		09	09		
	30		00	00	✓	
	31		02	02		

Test Encoder Accuracy Par. 3.1.1.6-4

WORD	POSITION	INPUT AREA	TRANS WORD	ENCODER AREA	RESULTS	
					PASS	FAIL
W.3 L-641	01	07	07	07	✓	
	02	27	27	27		
	03	13	13	13		
	04 Data	27	27	27		
	05	23	23	23		
	06	18	18	18		
	07	15	15	15		
	08	13	13	13		
	09	28	28	28		
	10	22	22	22		
	11	27	27	27		
	12	20	20	20		
	13	01	01	01		
	14	16	16	16		
	15	28	28	28		
	16		13	13		
	17		07	07		
	18		21	21		
	19		05	05		
	20		02	02		
	21 Par. ty		10	10		
	22		01	01		
	23		07	07		
	24		24	24		
	25		03	03		
	26		13	13		
	27		10	10		
	28		24	24		
	29		01	01		
	30		19	19		
	31		23	23	✓	

RSED Test Data Sheet

Encoder Timing

Par. 3.1.2

Header 120

Allowed 300 microseconds max.

W1 240

Allowed 300 microseconds max.

W2 240

Allowed 300 microseconds max.

W3 240

Allowed 300 microseconds max.

RSFD Test Data Sheet

Test Decoder Accuracy

Par. 3.2.1. L-1

WORD	POSITION	INPUT AREA	TRANS WORD	ERRATA AREA	INSERTED ERRATA	DECODER AREA	RESULTS	
							PASS	FAIL
# Header 3016	05 (Qual)					00		
	01	06	06	06	06			
	02 Data	31	31	31	31			
	03	26	26	26	26			
	04	05	05	05	05			
	05		25	25	25			
	06		22	22	22			
	07 Parity		17	17	17			
	08		30	30	30			
	09		23	23	23			
	10		06	06	06			
	11		30	30	30			
	12		26	26	26			
	13		24	24	24			
	14		06	06	06			
	15		03	03	03			
	16		01	01	01			

Test Summary: Number of Errors 0 Pass Fail

Number of Erasures 0

Measured Time

Test Decoder Accuracy Par. 3.2.1. 1-2

WORD	POSITION	INPUT AREA	TRANS WORD	ERRATA AREA	INSERTED ERRATA	DECODER AREA	RESULTS	
							PASS	FAIL
W1 L123	16 (Qual)					00		
	01	12	12	12	12			
	02	22	22	22	00E			
	03	15	15	15	15			
	04	28	28	28	00E			
	05 Data	21	21	21	21			
	06	01	01	01	01			
	07	25	25	25	25			
	08	29	29	29	29			
	09	02	02	02	02			
	10	28	28	28	28			
	11	18	18	18	18			
	12	29	29	29	29			
	13	21	21	21	21			
	14	03	03	03	00E			
	15	28	28	28	28			
	16		26	26	26			
	17		10	10	10			
	18		05	05	05			
	19 Parity		06	06	06			
	20		03	03	03			
	21		07	07	07			
	22		12	12	12			
	23		31	31	31			
	24		17	17	17			
	25		22	22	22			
	26		19	19	19			
	27		00	00	00			
	28		11	11	11			
	29		30	30	30			
	30		28	28	00E			
	31		19	19	19			

Test Summary: Number of Errors 0 Pass Fail
Number of Erasures 4

Test Decoder Accuracy Par. 3.2.1. 1-3

WORD	POSITION	INPUT AREA	TRANS WORD	ERRATA AREA	INSERTED ERRATA	DECODER AREA	RESULTS	
							PASS	FAIL
<u>W2</u> L998	16 (Qual)					00		
	01	06	06	06	06			
	02	26	26	26	26			
	03	31	31	31	31			
	04	01	01	01	01			
	05 Data	26	26	26	00E			
	06	12	12	12	12			
	07	15	15	15	15			
	08	31	31	31	31			
	09	05	05	05	05			
	10	01	01	01	00E			
	11	01	01	01	00E			
	12	11	11	11	00E			
	13	09	09	09	00E			
	14	04	04	04	00E			
	15	24	24	24	24			
	16		04	04	04			
	17		25	25	25			
	18		04	04	04			
	19 Parity		15	15	15			
	20		18	18	00E			
	21		08	08	00E			
	22		01	01	01			
	23		15	15	15			
	24		06	06	06			
	25		22	22	22			
	26		23	23	23			
	27		14	14	14			
	28		17	17	17			
	29		00	00	00			
	30		02	02	02			
	31		29	29	29			

Test Summary: Number of Errors 0 Pass Fail
 Number of Erasures 8

Test Decoder Accuracy Par. 3.2.1.1-4

WORD	POSITION	INPUT AREA	TRANS WORD	ERRATA AREA	INSERTED ERRATA	DECODER AREA	RESULTS	
							PASS	FAIL
W3 L669	16 (Qual)					00		
	01	31	31	31	00E			
	02	06	06	06	00E			
	03	29	29	29	00E			
	04	13	13	13	00E			
	05 Data	15	15	15	00E			
	06	29	29	29	00E			
	07	31	31	31	00E			
	08	14	14	14	14			
	09	11	11	11	11			
	10	04	04	04	04			
	11	04	04	04	04			
	12	25	25	25	25			
	13	02	02	02	02			
	14	11	11	11	11			
	15	28	28	28	00E			
	16		12	12	00E			
	17		25	25	00E			
	18		20	20	20			
	19 Parity		08	08	08			
	20		30	30	00E			
	21		10	10	00E			
	22		30	30	00E			
	23		10	10	00E			
	24		17	17	17			
	25		13	13	13			
	26		02	02	02			
	27		19	19	19			
	28		11	11	00E			
	29		27	27	00E			
	30		20	20	20			
	31		00	00	00			

Test Summary: Number of Errors 0 Pass Fail
Number of Erasures 16

RSED Test Data Sheet

Test Decoder Accuracy

Par. 3.2.1. 2-1

WORD	POSITION	INPUT AREA	TRANS WORD	ERRATA AREA	INSERTED ERRATA	DECODER AREA	RESULTS	
							PASS	FAIL
H Header S335	05 (Qual)					01		
	01	19	19	19	19			
	02 Data	00	00	00	00			
	03	06	06	06	012			
	04	01	01	01	01			
	05		20	20	20			
	06		19	19	19			
	07 Parity		03	03	03			
	08		20	20	20			
	09		14	14	14			
	10		03	03	03			
	11		05	05	05			
	12		14	14	14			
	13		09	09	09			
	14		24	24	24			
	15		14	14	14			
	16		12	12	12			

Test Summary: Number of Errors 1 Pass Fail

Number of Erasures 0

Measured Time

Test Decoder Accuracy Par. 3.2.1. 2-2

WORD	POSITION	INPUT AREA	TRANS WORD	ERRATA AREA	INSERTED ERRATA	DECODER AREA	RESULTS	
							PASS	FAIL
<u>W1</u> L383	16 (Qual)					02		
	01	26	26	26	26			
	02	22	22	22	00 E			
	03	29	29	29	29			
	04	05	05	05	05			
	05 Data	15	15	15	00 E			
	06	24	24	24	24			
	07	16	16	16	16			
	08	31	31	31	00 E			
	09	22	22	22	22			
	10	04	04	04	04			
	11	18	18	18	21 e			
	12	14	14	14	14			
	13	01	01	01	01			
	14	28	28	28	28			
	15	01	01	01	01			
	16		13	13	13			
	17		17	17	00 E			
	18		08	08	08			
	19 Parity		19	19	19			
	20		11	11	11			
	21		26	26	26			
	22		27	27	27			
	23		11	11	11			
	24		10	10	00 E			
	25		11	11	11			
	26		19	19	19			
	27		16	16	16			
	28		15	15	15			
	29		09	09	09			
	30		21	21	21			
	31		04	04	07 e			

Test Summary: Number of Errors 2 Pass Fail
Number of Erasures 5

Test Decoder Accuracy Par. 3.2.1. 2-3

WORD	POSITION	INPUT AREA	TRANS WORD	ERRATA AREA	INSERTED ERRATA	DECODER AREA	RESULTS	
							PASS	FAIL
<u>W2</u> L781	16 (Qual)					04		
	01	06	06	06	06			
	02	22	22	22	11 e			
	03	27	27	27	27			
	04	04	04	04	04			
	05 Data	29	29	29	06 e			
	06	15	15	15	15			
	07	09	09	09	00 E			
	08	28	28	28	28			
	09	31	31	31	31			
	10	10	10	10	00 E			
	11	01	01	01	01			
	12	09	09	09	09			
	13	21	21	21	21			
	14	20	20	20	17 e			
	15	14	14	14	14			
	16		06	06	00 E			
	17		09	09	09			
	18		28	28	28			
	19 Parity		27	27	00 E			
	20		17	17	17			
	21		01	01	00 E			
	22		29	29	29			
	23		01	01	01			
	24		15	15	00 E			
	25		31	31	31			
	26		06	06	06			
	27		09	09	25 e			
	28		06	06	06			
	29		21	21	00 E			
	30		25	25	25			
	31		20	20	00 E			

Test Summary: Number of Errors 4 Pass Fail
Number of Erasures 8

Test Decoder Accuracy Par. 3.2.1. 2-4

WORD	POSITION	INPUT AREA	TRANS WORD	ERRATA AREA	INSERTED ERRATA	DECODER AREA	RESULTS	
							PASS	FAIL
<u>W3</u>	16 (Qual)					03		
L782	01	27	27	27	13 e			
	02	28	28	28	28			
	03	09	09	09	00 E			
	04	29	29	29	29			
	05 Data	01	01	01	00 E			
	06	17	17	17	17			
	07	31	31	31	00 E			
	08	15	15	15	15			
	09	01	01	01	01			
	10	06	06	06	00 E			
	11	09	09	09	09			
	12	06	06	06	15 e			
	13	20	20	20	20			
	14	25	25	25	25			
	15	21	21	21	04 e			
	16		15	15	15			
	17		29	29	00 E			
	18		11	11	11			
	19 Parity		01	01	00 E			
	20		22	22	22			
	21		15	15	00 E			
	22		16	16	16			
	23		13	13	13			
	24		16	16	16			
	25		13	13	00 E			
	26		20	20	00 E			
	27		00	00	00			
	28		18	18	18			
	29		17	17	17			
	30		05	05	00 E			
	31		21	21	21			

Test Summary: Number of Errors 3 Pass Fail
Number of Erasures 10

RSED Test Data Sheet

Test Decoder Accuracy

Par. 3.2.1 2-1

WORD	POSITION	INPUT AREA	TRANS WORD	ERRATA AREA	INSERTED ERRATA	DECODER AREA	RESULTS	
							PASS	FAIL
Header S106	05 (Qual)					05		
	01	07	07	07	03e			
	02 } Data	12	12	12	12			
	03	18	18	18	18			
	04	03	03	03	03			
	05		21	21	15e			
	06		27	27	27			
	07 } Parity		31	31	31			
	08		24	24	19e			
	09		16	16	16			
	10		10	10	07e			
	11		04	04	04			
	12		23	23	23			
	13		00	00	00			
	14		01	01	01			
	15		31	31	31			
	16		14	14	05e			

Test Summary: Number of Errors 5 Pass Fail

Number of Erasures 0

Measured Time

Test Decoder Accuracy

Par. 3.2.1

3-2

WORD	POSITION	INPUT AREA	TRANS WORD	ERRATA AREA	INSERTED ERRATA	DECODER AREA	RESULTS	
							PASS	FAIL
W-1	16 (Qual)					06		
1051	01	23	23	23	23			
	02	03	03	03	03			
	03	05	05	05	05			
	04	27	27	27	15e			
	05 Data	01	01	01	01			
	06	20	20	20	20			
	07	31	31	31	31			
	08	25	25	25	25			
	09	27	27	27	27			
	10	06	06	06	03e			
	11	15	15	15	09e			
	12	27	27	27	27			
	13	05	05	05	05			
	14	09	09	09	09			
	15	22	22	22	17e			
	16		08	08	08			
	17		31	31	31			
	18		22	22	22			
	19 Parity		20	20	20			
	20		29	29	22e			
	21		12	12	12			
	22		06	06	06			
	23		23	23	11e			
	24		15	15	15			
	25		13	13	00E			
	26		01	01	01			
	27		30	30	30			
	28		28	28	00E			
	29		28	28	28			
	30		05	05	05			
	31		05	05	05			

Test Summary: Number of Errors 6 Pass Fail
 Number of Erasures 2

Test Decoder Accuracy Par. 3.2.1. 33

WORD	POSITION	INPUT AREA	TRANS WORD	ERRATA AREA	INSERTED ERRATA	DECODER AREA	RESULTS	
							PASS	FAIL
W-2 L897	16 (Qual)					05		
	01	25	25	25	07e			
	02	11	11	11	11			
	03	02	02	02	02			
	04	01	01	01	01			
	05 Data	22	22	22	22			
	06	30	30	30	01e			
	07	25	25	25	25			
	08	22	22	22	22			
	09	14	14	14	00E			
	10	29	29	29	29			
	11	21	21	21	21			
	12	27	27	27	27			
	13	08	08	08	08			
	14	22	22	22	14e			
	15	00	00	00	00			
	16		09	09	09			
	17		31	31	00E			
	18		21	21	21			
	19 Parity		09	09	00E			
	20		23	23	23			
	21		09	09	09			
	22		04	04	00E			
	23		16	16	16			
	24		18	18	18			
	25		27	27	19e			
	26		28	28	12e			
	27		19	19	19			
	28		22	22	00E			
	29		24	24	00E			
	30		14	14	14			
	31		00	00	00			

Test Summary: Number of Errors 5 Pass Fail
 Number of Erasures 6

Test Decoder Accuracy

Par. 3.2.1

3-4

WORD	POSITION	INPUT AREA	TRANS WORD	ERRATA AREA	INSERTED ERRATA	DECODER AREA	RESULTS	
							PASS	FAIL
W3 1273	16 (Qual)					08		
	01	04	04	04	04			
	02	08	08	08	02e			
	03	04	04	04	04			
	04	22	22	22	22			
	05 Data	13	13	13	07e			
	06	10	10	10	10			
	07	14	14	14	14			
	08	16	16	16	13e			
	09	10	10	10	10			
	10	19	19	19	19			
	11	17	17	17	17			
	12	06	06	06	06			
	13	23	23	23	11e			
	14	31	31	31	31			
	15	14	14	14	14			
	16		03	03	03			
	17		01	01	01			
	18		07	07	07			
	19 Parity		07	07	01e			
	20		09	09	09			
	21		01	01	01			
	22		08	08	08			
	23		28	28	28			
	24		30	30	21e			
	25		17	17	17			
	26		21	21	12e			
	27		19	19	19			
	28		01	01	01			
	29		22	22	22			
	30		17	17	17e			
	31		06	06	06			

Test Summary: Number of Errors 8 Pass Fail
 Number of Erasures 0

ESD Test Data Sheet

ATP

Test Decoder Accuracy

Par. 3.2.1. —

WORD	POSITION	INPUT AREA	TRANS WORD	ERRATA AREA	INSERTED ERRATA	DECODER AREA	RESULTS	
							PASS	FAIL
Header S415	05 (Qual)					05	✓	
	01	02	02	02	13	02	✓	
	02 } Data	20	20	20	20	20	✓	
	03	29	29	29	29	29	✓	
	04	18	18	18	10	18	✓	
	05		07	07	22			
	06		29	29	29			
	07 } Parity		26	26	26			
	08		15	15	15			
	09		17	17	17			
	10		22	22	27			
	11		18	18	18			
	12		00	00	00			
	13		20	20	20			
	14		17	17	16			
	15		24	24	24			
	16		31	31	31			

Test Summary: Number of Errors 5 Pass ✓ Fail —

Number of Erasures 0

Measured Time 3.061 ms

Test Decoder Accuracy Par. 3.2.1. _____

WORD	POSITION	INPUT AREA	TRANS WORD	ERRATA AREA	INSERTED ERRATA	DECODER AREA	RESULTS	
							PASS	FAIL
W-1 L-146	16 (Qual)					06	✓	
	01	27	27	27	27	27		
	02	23	23	23	23	23		
	03	21	21	21	21	21		
	04	17	17	17	17	17		
	05 Data	13	13	13	13	13		
	06	08	08	08	08	08		
	07	20	20	20	20	20		
	08	30	30	30	30	30		
	09	03	03	03	03	03		
	10	18	18	18	18	18		
	11	00	00	00	00	00		
	12	15	15	15	15	15		
	13	12	12	12	12	12		
	14	17	17	17	17	17		
	15	21	21	21	21	21	✓	
	16		22	02	02			
	17		04	04	04			
	18		28	28	28			
	19 Parity		16	16	16			
	20		29	29	29			
	21		10	10	10			
	22		14	14	14			
	23		01	01	01			
	24		07	07	07			
	25		06	06	06			
	26		11	11	02 e			
	27		19	19	02 e			
	28		00	00	02 e			
	29		04	04	02 e			
	30		24	24	02 e			
	31		13	13	02 e			

Test Summary: Number of Errors 6 Pass ☒ Fail ☐
 Number of Erasures 0

Test Decoder Accuracy Par. 3.2.1. _____

WORD	POSITION	INPUT AREA	TRANS WORD	ERRATA AREA	INSERTED ERRATA	DECODER AREA	RESULTS	
							PASS	FAIL
W-2 L-032	16 (Qual)					09	✓	
	01	13		13	13	13		
	02	09		09	09	09		
	03	14		14	14	14		
	04	30		30	30	30		
	05 Data	03		8	03	03		
	06	11		11	11	11		
	07	28		28	28	28		
	08	18		18	18	18		
	09	09		09	15e	09		
	10	13		13	27e	13		
	11	01		01	03e	01		
	12	20		20	06e	20		
	13	28		28	27e	28		
	14	21		21	14e	21		
	15	30		30	16e	30	✓	
	16			23	23			
	17			18	18			
	18			27	27			
	19 Parity			05	05			
	20			11	11			
	21			15	15			
	22			03	03			
	23			15	15			
	24			22	22			
	25			09	09			
	26			31	31			
	27			28	28			
	28			30	30			
	29			09	09			
	30			00	00			
	31			02	02			

Test Summary: Number of Errors 7 Pass ✓ Fail
 Number of Erasures 0

Test Decoder Accuracy Par. 3.2.1. _____

WORD	POSITION	INPUT AREA	TRANS WORD	ERRATA AREA	INSERTED ERRATA	DECODER AREA	RESULTS	
							PASS	FAIL
W3 L-641	16 (Qual)					08	✓	
	01	07		07	07	07		
	02	27		27	27	27		
	03	13		13	23e	13		
	04	27		29	29	29		
	05 Data	23		23	23	23		
	06	18		18	18	18		
	07	15		15	27e	15		
	08	13		13	13	13		
	09	28		28	28	28		
	10	22		22	22	22		
	11	27		27	15e	27		
	12	20		20	20	20		
	13	01		01	01	01		
	14	16		16	16	16		
	15	28		28	00e	28	✓	
	16			13	13			
	17			07	07			
	18			21	21			
	19 Parity			05	01e			
	20			02	02			
	21			10	10			
	22			01	01			
	23			07	30e			
	24			24	24			
	25			03	03			
	26			13	13			
	27			10	28e			
	28			24	24			
	29			01	01			
	30			19	19			
	31			23	28e			

Test Summary: Number of Errors 8 Pass ✓ Fail
 Number of Erasures 0

3.061/2

Trail own 4553

ATP

RSED Test Data Sheet

Test Decoder Accuracy
Par. 3.2.1. 4-1

WORD	POSITION	INPUT AREA	TRANS WORD	ERRATA AREA	INSERTED ERRATA	DECODER AREA	RESULTS	
							PASS	FAIL
Header S-415	05 (Qual)					06	✓	
	01	02		02	23e	02	↓	
	02	20		20	10e	20	↓	
	03	29		29	13e	29	↓	
	04	18		18	18	18	↓	
	05			07	07			
	06			29	29			
	07			26	26			
	08			15	15			
	09			17	17			
	10			22	22			
	11			18	18			
	12			00	00			
	13			20	20			
	14			17	20e			
	15			24	00e			
	16			31	01e			

Test Summary: Number of Errors 6 Pass ✓ Fail
 Number of Erasures 0
 Measured Time 3.748ms

Worst case tested 4.149

Test Decoder Accuracy Par. 3.2.1. 4-2

WORD	POSITION	INPUT AREA	TRANS WORD	ERRATA AREA	INSERTED ERRATA	DECODER AREA	RESULTS	
							PASS	FAIL
W1 L146	16 (Qual)							
	01	27		27 15	27	27 08		
	02	23		23 15	23	23		
	03	21		21 15	21	21		
	04	17		17 15	17	17		
	05 Data	13		13 15	13	13		
	06	08		08	08	08		
	07	20		20	20	20		
	08	30		30	00 E	30 00		
	09	03		03	00 E	03 00		
	10	18		18	00 E	18 00		
	11	00		00	00 E	00 00		
	12	15		15	00 E	15 00		
	13	12		12	00 E	12 00		
	14	17		17	00 E	17 00		
	15	21		21	00 E	21 00		
	16			02	00 E			
	17			04	00 E			
	18			28	00 E			
	19 Parity			16	00 E			
	20			29	00 E			
	21			10	00 E			
	22			14	00 E			
	23			01	00 E			
	24			07	07			
	25			06	06			
	26			11	11			
	27			19	19			
	28			00	00			
	29			04	04			
	30			24	24			
	31			13	13			

Test Summary: Number of Errors 1 Pass 16 Fail 0
 Number of Erasures 16

1.66 / sec - 4 predict words - 1.356 MS

- 1) First test 16 Erasures - passed decode
- 2) Second test 16 " + 1 error - detected failure (codeword - KSED did not)
- 3) Third " " " 2 errors - Same as above test (2)

Test Decoder Accuracy Par. 3.2.1. 4-3

WORD	POSITION	INPUT AREA	TRANS WORD	ERRATA AREA	INSERTED ERRATA	DECODER AREA	RESULTS	
							PASS	FAIL
W2 L632	16 (Qual)					08	✓	
	01	13		13	16e	03		
	02	09		09	16e	09		
	03	14		14	16e	14		
	04	30		30	16e	30		
	05 Data	03		03	~~02~~ 16e	03		
	06	11		11	11	11		
	07	28		28	28	28		
	08	18		18	18	18		
	09	09		09	09	09		
	10	13		13	13	13		
	11	01		01	01	01		
	12	20		20	20	20		
	13	28		28	28	28		
	14	21		21	21	21		
	15	30		30	30	30		
	16			23	23			
	17			18	18			
	18			27	27			
	19 Parity			05	05			
	20			11	11			
	21			15	15			
	22			03	03			
	23			15	15			
	24			22	22			
	25			09	09			
	26			31	31			
	27			28	28			
	28			30	30			
	29			07	26e			
	30			00	26e			
	31			02	26e			

Test Summary: Number of Errors 8 Pass ✓ Fail
 Number of Erasures 0

Test Decoder Accuracy

Par. 3.2.1. 4-4

WORD	POSITION	INPUT AREA	TRANS WORD	ERRATA AREA	INSERTED ERRATA	DECODER AREA	RESULTS	
							PASS	FAIL
W3 L-641	16 (Qual)					08		
	01	07		07	17e	07		
	02	27		27	17e	27		
	03	13		13	17e	13		
	04	29		29	17e	29		
	05 Data	23		23	17e	23		
	06	18		18		18		
	07	15		15		15		
	08	13		13		13		
	09	28		28		28		
	10	22		22		22		
	11	27		27		27		
	12	20		20		20		
	13	01		01		01		
	14	16		16		16		
	15	28		28		28		
	16			13				
	17			07				
	18			21				
	19 Parity			05				
	20			02				
	21			10				
	22			01				
	23			07				
	24			24				
	25			03				
	26			13				
	27			10				
	28			24				
	29			01	27e			
	30			17	27e			
	31			23	27e			

Test Summary: Number of Errors 8 Pass ☒ Fail ☐
 Number of Erasures 0

Time H-W3 3.748ms

RSED Test Data Sheet

Test Decoder Accuracy

Par. 3.2.1. 5-1

WORD	POSITION	INPUT AREA	TRANS WORD	ERRATA AREA	INSERTED ERRATA	DECODER AREA	RESULTS	
							PASS	FAIL
H Header S 335	05 (Qual)					16		
	01	19	19	19	032			
	02 } Data	00	00	00	00E			
	03	06	06	06	192			
	04	01	01	01	252			
	05		20	20	20			
	06		19	19	00E			
	07 } Parity		03	03	03			
	08		20	20	00E			
	09		14	14	14			
	10		03	03	03			
	11		05	05	00E			
	12		14	14	14			
	13		09	09	00E			
	14		24	24	112			
	15		14	14	14			
	16		12	12	12			

Test Summary: Number of Errors 5 Pass Fail

Number of Erasures 10

Measured Time

Test Decoder Accuracy Par. 3.2.1. 5-2

WORD	POSITION	INPUT AREA	TRANS WORD	ERRATA AREA	INSERTED ERRATA	DECODER AREA	RESULTS	
							PASS	FAIL
<u>W1</u> L383	16 (Qual)					16		
	01	26	26	26	11 2			
	02	22	22	22	22			
	03	29	29	29	00 E			
	04	05	05	05	05			
	05 Data	15	15	15	17 2			
	06	24	24	24	24			
	07	16	16	16	00 E			
	08	31	31	31	00 E			
	09	22	22	22	22			
	10	04	04	04	20 2			
	11	18	18	18	00 E			
	12	14	14	14	14			
	13	01	01	01	00 E			
	14	28	28	28	28			
	15	01	01	01	30 2			
	16		13	13	13			
	17		17	17	00 E			
	18		08	08	00 E			
	19 Parity		19	19	19			
	20		11	11	00 E			
	21		26	26	26			
	22		27	27	27			
	23		11	11	00 E			
	24		10	10	10			
	25		11	11	00 E			
	26		19	19	19			
	27		16	16	00 E			
	28		15	15	15 2			
	29		09	09	09			
	30		21	21	00 E			
	31		04	04	07 2			

Test Summary: Number of Errors 0 Pass Fail
Number of Erasures 12

Test Decoder Accuracy

Par. 3.2.1. 5-3

WORD	POSITION	INPUT AREA	TRANS WORD	ERRATA AREA	INSERTED ERRATA	DECODER AREA	RESULTS	
							PASS	FAIL
<u>W2</u>	16 (Qual)					16		
<u>L781</u>	01	06	06	06	06			
	02	22	22	22	11 e			
	03	27	27	27	27			
	04	04	04	04	04			
	05 Data	29	29	29	06 e			
	06	15	15	15	15			
	07	09	09	09	00 E			
	08	28	28	28	28			
	09	31	31	31	31			
	10	10	10	10	00 E			
	11	01	01	01	01			
	12	09	09	09	21 e			
	13	21	21	21	21			
	14	20	20	20	17 e			
	15	14	14	14	14			
	16		06	06	00 E			
	17		09	09	09			
	18		28	28	28			
	19 Parity		27	27	00 E			
	20		17	17	17			
	21		01	01	00 E			
	22		29	29	29			
	23		01	01	01			
	24		15	15	00 E			
	25		31	31	31			
	26		06	06	06			
	27		09	09	25 e			
	28		06	06	06			
	29		21	21	00 E			
	30		25	25	25			
	31		20	20	00 E			

Test Summary: Number of Errors 5 Pass Fail
 Number of Erasures 8

Test Decoder Accuracy

Par. 3.2.1.

5-4

WORD	POSITION	INPUT AREA	TRANS WORD	ERRATA AREA	INSERTED ERRATA	DECODER AREA	RESULTS	
							PASS	FAIL
<u>W3</u>	16 (Qual)					16		
L782	01	27	27	27	13 e			
	02	28	28	28	28			
	03	09	09	09	00 E			
	04	29	29	29	29			
	05 Data	01	01	01	00 E			
	06	17	17	17	17			
	07	31	31	31	00 E			
	08	15	15	15	15			
	09	01	01	01	25 e			
	10	06	06	06	00 E			
	11	09	09	09	09			
	12	06	06	06	15 e			
	13	20	20	20	20			
	14	25	25	25	25			
	15	21	21	21	04 e			
	16		15	15	15			
	17		29	29	00 E			
	18		11	11	11			
	19 Parity		01	01	00 E			
	20		22	22	22			
	21		15	15	00 E			
	22		16	16	16			
	23		13	13	13			
	24		16	16	00 E			
	25		13	13	00 E			
	26		20	20	20			
	27		00	00	00			
	28		18	18	00 E			
	29		17	17	17			
	30		05	05	00 E			
	31		21	21	21			

Test Summary: Number of Errors 4 Pass Fail
 Number of Erasures 11

RSED Test Data Sheet

Test RTT Tests

Par. 3.3.1.1. - 1

WORD	POSITION	INPUT AREA	RTT DONOR ADDRESS	ERRATA AREA	INSERTED ERRATA	RTT RECOGNITION FLAG
RTT S855	01	19	19	19	00e	Allowed Time: 75 microsec. max. Measured Time: <u>16.90</u> microsec. Pass ☒ Fail ☐
	02 Data	14	14	14	14	
	03	29	29	29	20e	
	04	09	09	09	18e	
	05		03	03	03	RTT Processing Time Allowed Time: 375 microsec. max. Measured Time: <u>230</u> microsec. Pass ☒ Fail ☐
	06		25	25	00E	
	07		27	27	00E	
	08		18	18	00E	
	09		21	21	21	
	10		17	17	17	
	11		00	00	00	
	12		17	17	00E	
	13		28	28	28	
	14		27	27	00E	
	15		12	12	12	
	16		24	24	00E	

336
1690

ATP

RSED Test Data Sheet

ATP

Test RTT Tests

Par. 3.3.1.1. - 2

WORD	POSITION	INPUT AREA	RTT DONOR ADDRESS	ERRATA AREA	INSERTED ERRATA	RTT RECOGNITION FLAG
RTT S492	01	02	02	02	02	Allowed Time: 75 microsec. max.
	02 Data	11	11	11	11	Measured Time: 17.5 microsec.
	03	09	09	09	09	Pass ☒ Fail ☐
	04	28	28	28	28	RTT Processing Time
	05		04	04	11e	Allowed Time: 375 microsec. max.
	06		26	26	26	Measured Time: 240 microsec.
	07		01	01	13e	Pass ☒ Fail ☐
	08		29	29	30e	
	09		10	10	10	
	10		25	25	25	
	11		00	00	02e	
	12		25	25	25	
	13		22	22	22	
	14		01	01	02e	
	15		16	16	17e	
	16		05	05	05	

RSED Test Data Sheet

Test RTT Tests

Par. 3.3.1.1.-3

WORD	POSITION	INPUT AREA	RTT DONOR ADDRESS	ERRATA AREA	INSERTED ERRATA	RTT RECOGNITION FLAG
RTT S...	01					Allowed Time: 75 microsec. max.
	02 Data					
	03					Measured Time: ____ microsec.
	04					Pass ____ Fail ____
	05					RTT Processing Time
	06					
	07					Allowed Time: 375 microsec. max.
	08					Measured Time: ____ microsec.
	09					Pass ____ Fail ____
	10					
	11					
	12					
	13					
	14					
	15					
	16					

RTT Test Data Sheet

ATP

Test RTT Address Recognition

Par. 3.3.1.2.-1

WORD	POSITION	INPUT AREA	RTT DONOR ADDRESS	ERRATA AREA	RTT RECOGNITION FLAG
RTT S961	01	25	25	24e	No Flag Present ☒
	02	26	26	04e	Flag Present ☐
	03	30	30	00e	
	04	26	26	12e	Pass ☒ Fail ☐
	05		07	31e ⁽¹⁾	
	06		01	29e	
	07		16	20e	
	08		10	11e	
	09		29	29	
	10		06	06	
	11		19	19	
	12		13	13	
	13		14	14	
	14		21	21	
	15		27	27	
	16		09	09	

NOTE: No flag should be present during this test.

RSED Test Data Sheet

ATP

Test RTT Address Recognition

Par. 3.3.1.2.-2

WORD	POSITION	INPUT AREA	RTT DONOR ADDRESS	ERRATA AREA	RTT RECOGNITION FLAG
RTT S035	01	17	17	00E	No Flag Present ☒ Flag Present _____ Pass ☒ Fail _____
	02	24	24	00E	
	03	02	02	00E	
	04	29	29	00E	
	05		10	00E	NOTE: No flag should be present during this test.
	06		08	00E	
	07		23	00E	
	08		00	00E	
	09		07	00E	
	10		01	00E	
	11		22	00E	
	12		27	00E	
	13		04	04	
	14		06	06	
	15		26	00E	
	16		25	00E	

RSMD Test Data Sheet

Test RTT Address Recognition

Par. 3.3.1.2.-3

WORD	POSITION	INPUT AREA	RTT DONOR ADDRESS	ERRATA AREA	RTT RECOGNITION FLAG
RTT S195	01	04	04	07e	No Flag Present _____ Flag Present _____
	02	22	22	03e	
	03	18	18		Pass _____ Fail _____
	04	29	29	(10)e	
	05		08		NOTE: No flag should be present during this test.
	06		17		
	07		02		
	08		31		
	09		20		
	10		23	00E	
	11		00		
	12		23	00E	
	13		24	00E	
	14		02	22e	
	15		05	10e	
	16		10		

ATP

RSED Test Data Sheet

Multifunction RSED Tests

Par. 3.4.1

3.4.1(D) Slot Time

Measured Time 7.8127 milliseconds

Allowed Time 7.8125 msec $\pm$ 1%

3.4.1(E) Decoder Input Data

Header

Measured Transitions	<u>16</u>
Allowed	<u>16</u>

W1

Measured Transitions	<u>31</u>
Allowed	<u>31</u>

W2

Measured Transitions	<u>31</u>
Allowed	<u>31</u>

W3

Measured Transitions	<u>31</u>
Allowed	<u>31</u>

3.4.1(F) Decoder Output Data

Header

Measured Transitions	<u>4</u>
Allowed	<u>4</u>

W1

Measured Transitions	<u>15</u>
Allowed	<u>15</u>

W2

Measured Transitions
Allowed

15
15

W3

Measured Transitions
Allowed

15
15

3.4.1(G) Encoder Input Data

Header

Measured Transitions
Allowed

4
4

W1

Measured Transitions
Allowed.

15
15

OK

W2

Measured Transitions
Allowed

15
15

W3

Measured Transitions
Allowed

15
15

3.4.1(H) Encode Output Data

Header

Measured Transitions
Allowed

16
16

W1

Measured Transitions
Allowed

31
31

W2

Measured Transitions
Allowed

31
31

W3

Measured Transitions

31

Allowed

31

3.4.1(I) RTT Trial

Measured Transitions

16

Allowed

16

3.4.1(J) RTT Active

Measured Time

17

microseconds

Allowed

75 microsec. max.

3.4.1(K) RTT Turnaround Time

Measured Time

230

microseconds

Allowed Time

375 microsec. max.

3.4.1(L) Read Out RTT

Measured Transitions

16

Allowed

16

APPENDIX E

RSED ACCEPTANCE TEST PLAN

Prepared Under Contract N62269-75-C-0503

For

Department of the Navy, Naval Air Development Center

By: ITT Avionics Division
500 Washington Avenue
Nutley, New Jersey 07110

RSED ACCEPTANCE TEST PLAN

	<u>Page Number</u>
I. INTRODUCTION	1
II. REED-SOLOMON MODULE REQUIREMENTS	1
1.0 Encoder	1
1.1 Short Code	1
1.2 Standard Code	1
2.0 Decoder	1
2.1 Errata Correction Capability	1
2.2 Message Throughput Rate	1
2.3 Maximum Decoder Delay	4
2.4 Decoder Failure	4
3.0 Round Trip Timing (RTT)	4
3.1 RTT Decode	4
3.2 RTT Turn Around Time	4
III. RSED TEST PLAN	4
1.0 Encoder Test	4
1.1 Encoder Accuracy Test	4
1.2 Encoder Timing Test	5

CONTINUED

	<u>Page Number</u>
2.0 Decoder Tests	6
2.1 Decoder Accuracy Test	6
2.2 Decoder Timing Test - Single Word	6
2.2.1 Worst Case Decoding Time	6
2.2.2 Decoding Time Profile	6
2.3 Decoder Timing Test - Messages	9
2.4 Decoder Failure Test	9
3.0 Round Trip Timing (RTT) Message Processing Tests	9
3.1 RTT Message Recognition Accuracy	9
3.2 RTT Recognition Processing Time	9
3.3 Total RTT Turnaround Time	10
4.0 Multifunction RSED Tests	10
4.1 Decode Slot "n" - Encode Slot "n + 1"	10
4.2 Decode Slot "n" - RTT Decode/Encode Slot "n"	10
4.3 RTT Decode/Encode Slot "n" - Encode Slot "n + 1"	10
IV. TEST RESULTS SUMMARY	11

FIGURES

		<u>Page Number</u>
Figure 1	RSED BLOCK DIAGRAM	2
Figure 2	ENCODING ALGORITHM	3

TABLES

Table 1	ERRATA CORRECTION CAPABILITY OF REED-SOLOMON CODES	5
Table 2	DECODER ACCURACY TEST CASES	7
Table 3	WORST CASE DECODING TIME CANDIDATE	8

I. INTRODUCTION

The purpose of these tests is to demonstrate that the Reed-Solomon Encoder/Decoder (RSED) module will satisfy the requirements presented in the Statement of Work. These requirements are discussed in Section II. The test data will be presented to the RSED via the User Test Panel and provide for testing from a prior prepared list of test message patterns. These test messages will include verification of the encoding and decoding processes RTT recognition and reply and overall message timing. See Figure 1 for RSED Block Diagram.

II. REED-SOLOMON MODULE REQUIREMENTS

1.0 Encoder

1.1 Short Code

The encoder will accept twenty information bits grouped into four characters (5 bits each) and encode them into a (16,4) Reed-Solomon word consisting of the four original characters and twelve additional parity check characters. The time to encode the word shall not exceed 300 usec.

1.2 Standard Code

The encoder will accept seventy-five information bits grouped into fifteen characters (5 bits each) and encode them into a (31,15) Reed-Solomon word consisting of the fifteen original characters and sixteen additional parity check characters. The time to encode the word shall not exceed 300 usec.

Figure 2 shows the form required of the encoding algorithm.


2.0 DECODER

2.1 Errata Correction Capability

The RSED module has the capability to reconstruct the original information bits when the received characters of above encoded words are within the errata correction capabilities of the Reed-Solomon code are given in Table 1. The module will correct all standard (31,15) and short (16,4) encoded words with errors and erasures inserted up to and including the maximum capability.

2.2 Message Throughput Rate

The RSED module will decode a message of 109 (5 bits plus erasure bit) characters consisting of one (16,4) and three (31,15) code words at the rate of 128 messages per second.



RSED BLOCK DIAGRAM

Figure 1


$$\begin{aligned}
 P_{15} &= h_0 M_{14} \oplus h_1 M_{13} \dots \oplus h_{14} M_0 \\
 P_{14} &= h_0 M_{13} \oplus h_1 M_{12} \dots \oplus h_{14} P_{15} \\
 P_{13} &= h_0 M_{12} \oplus h_2 M_{11} \dots \oplus h_{14} P_{14} \\
 P_0 &= h_0 P_{15} \oplus h_1 P_{14} \dots \oplus h_{14} P_1
 \end{aligned}$$

Constants

$h_0 \rightarrow h_{14}$

Variables

M = DATA CHARACTERS
 P = PARITY CHARACTERS



ENCODING ALGORITHM

Figure 2

2.3 Maximum Decoder Delay

The maximum time to decode a standard message consisting of 1 Header plus 3 long words shall be consistent with the required throughput. Specifically, the average delay must be less than 7.8125 msec. For certain applications the maximum permissible delay is ≈ 6.7 msec, and the decoder delay vs. errata profiles and related probabilities will be measured to determine what percentage of time does the decoder exceed 6.7 msec. A message loss rate of 1 message in 10^4 messages is acceptable.

2.4 Decoder Failure

When the number of errata exceeds the decoding capability of the Reed-Solomon code the decoding algorithm will detect this condition. The RSED module will generate a decoding failure condition in this event. The module will always generate a failure when the number of declared erasures exceed 16, for the (31,15) code and 12 for the (16,4) code.

3.0 ROUND TRIP TIMING (RTT)

3.1 RTT Decode

The RSED module will accept a (16,4) Reed-Solomon code word and determine if it is an RTT interrogation matching a specific stored reference. The reference is a 20 bit message encoded into a (16,4) codeword. It shall correctly recognize the code word containing errata up to the maximum capability of the (16,4) code shown in Table 1.

The RTT decode time shall not exceed 75 usec measured from the receipt of the last character in the code word.

3.2 RTT Turn Around Time

For a RTT interrogation message matching the stored reference the module will generate a recognition signal and accept a twenty bit reply message for encoding in a (16,4) code word. The time to complete the recognition and encoding shall not exceed 375 usec measured from the receipt of the last character of the RTT interrogation message.

III. RSED TEST PLAN

1.0 Encoder Test

1.1 Encoder Accuracy Test

This test will be conducted on a message basis to verify the correctness of the encoding process. A large class of code words with variable data characters for the (31,15) and (16,4) codes will be presented to the RSED via the User Test Panel and the encoder output will be compared with the correct output presented in the test data sheets.

The encoding algorithm is shown in block form in Figure 2.

Number of Errors	Maximum Number of Erasures		
	(31,15)	(16,4)	
0	> 16	> 12	Decoder Failure
0	16	12	
1	14	10	
2	12	8	
3	10	6	
4	8	4	
5	6	2	
6	4	0	
7	2	---	
8	0	---	
> 8	---	---	Decoder Failure

Table 1. ERRATA CORRECTION CAPABILITY OF THE REED-SOLOMON CODES

1.2 Encoder Timing Test

This test will be conducted using message blocks consisting of one (16,4) and three (31,15) code words. Each code word of the message block will be timed using front panel test points with standard laboratory test equipment and shall not exceed 300 microseconds for the respective code word.

2.0 Decoder Tests

2.1 Decoder Accuracy Test

This test will be conducted on a message block basis to verify the decoding process. A set of test words containing the number of errors and erasures shown in Table 2 will be prepared and presented in the test data sheets. The decoded word is compared with the transmitted word and the results of this comparison shall be noted on the test data sheet. A quality word shall be displayed on the User Test Panel for each code word which indicates "A Cannot Decode Code Word" and also displays the number of errors.

2.2 Decoder Timing Test - Single Word

This test will determine the decoding time of the code words as a function of the number of errata (errors and erasures) and their location in the words. The objective will be to find the worst case decoding time and determine those errata cases to be used in the message decoding timing tests.

2.2.1 Worst Case Decoding Time

The candidates for the worst case decoding times are shown in Table 3. It is expected that the worst cases are 8 errors and 6 errors for the (31,15) and (16,4) codes respectively. The time to decode these words will be determined. The parameters of number of errata and locations will be varied to determine the trend of decoding times and the worst case established.

2.2.2 Decoding Time Profile

Using the worst case errata locations the decoding time as a function of errata will be determined. This test will identify those errata cases which might cause the RSED message decoding time to exceed the message throughput rate and maximum decoding delay specifications. The timing profile will be used to estimate message decoding times and then messages, consisting of one (16,4) code word and three (31,15) code words will be prepared and presented to the RSED hardware.

Number of Errors	Number of Erasures (31,15) (16,4)	Number of Erasures (31,15) only
0	0, 4, 8, 12,	13, 16
1	0, 3, 6, 10,	12, 14
2	0, 1, 5, 8,	11, 12
3	0, 3, 5, 6,	7, 10
4	0, 2, 3, 4,	6, 8,
5	0, 1, 2,	4, 6,
6	0	1, 2, 4,
7	-----	0, 1, 2,
8	-----	-----

Table 2. DECODER ACCURACY TEST CASES

Number of Errata		Position of Errata
Errors	Erasures (31,15), (16,4) (31,15) only	
8	-----	0
0	12	16
3	6	10
4	4	8
5	2	6
6	0	4
7	----	2
		Errors in last 3 parity characters, other errors in information characters.
		All erasures concentrated in information characters.
		Errors in last 3 parity characters all other errata in information characters.

Table 3. WORST CASE DECODING TIME CANDIDATE

2.3 Decoder Timing Test - Messages

The time to decode messages as a function of errata content, using a distribution of errata and also worst case errata location, will be determined. If the worst case message decoding times exceed the specifications of message throughput or maximum decoding delay then a statistical analysis will be used to determine the probability of message loss due to excess decoding time.

2.4 Decoder Failure Test

Using the same procedure as in the decode accuracy test, Sec. 2.1 code words whose errata content exceeds the code capability shown in Table 1 will be presented to the RSED. It will be demonstrated that if the number of erasures exceeds 16 or 12 for the (31,15) and (16,4) codes respectively the RSED module will generate a decoding failure. The performance of the RSED for errata patterns that exceed the code capability will be investigated. It is noted that the decoding algorithm does not guarantee any performance in this event.

3.0 Round Trip Timing (RTT) Message Processing Tests

3.1 RTT Message Recognition Accuracy

RTT messages, (16,4) code words, will be presented to RSED module for processing. It will be demonstrated that message addressed to the terminal will be recognized correctly when errata is inserted up to the correction capability of the (16,4) code shown in Table 1. The cases to be tested will be those shown in Table 2 for the (16,4) code. It will also be demonstrated that messages not addressed to the terminal will be rejected by the RTT recognition process. In this case the twenty bit address message of the terminal will be encoded with one of the twenty bits changed. The resulting (16,4) code word will be presented to the RSED module for RTT processing with the same previously tested errata combinations.

3.2 RTT Recognition Processing Time

This test will determine the time required to successfully recognize an RTT message addressed to the terminal. This time will be measured from the receipt of the last of the sixteen code word characters to the generation of the RTT recognition flag. A set of correct messages with errata inserted, as in Table 2, in various positions will be presented to the RSED module. Standard Laboratory test shall be used to measure the RTT Recognition Processing time. These times will not exceed 0.075 msec.

3.3 Total RTT Turnaround Time

This test will measure the time required to recognize an RTT message addressed to the terminal and subsequently encode a (16,4) code word reply. This time will be measured from the receipt of the last code character until the last encoded character is presented at the RSED encoder output. It is assumed that since every time slot is a possible RTT interrogation that the RTT reply will be prepared for each time slot and is immediately available at the Encoder input when the RTT recognition flag is generated by the RSED module. The set of messages used in 3.1 will be presented to the module and a test message presented to the encoder when the recognition flag is generated. Timing measurements will be made to verify that the total RTT turnaround time does not exceed 375 microseconds.

4.0 Multifunction RSED Tests

This series of tests will demonstrate the RSED module is capable of performing combinations of encode/decode/RTT (as specified by the SOW) as described below.

4.1 Decode Slot "n" - Encode Slot "n + 1"

This test will demonstrate that the RSED module is capable of decoding a standard message consisting of 1 Header plus 3 Standard Words in time slot "n," to be followed by encode of 1 Header plus 3 Standard Words for transmission in slot n + 1.

It will be shown that the encoding can be performed while the decoding process is continuing. Both decode and encode operation will be within specified timing limits during this test.

4.2 Decode Slot "n" - RTT Decode/Encode Slot "n"

This test will demonstrate that the RSED module is capable of decoding a standard message consisting of 1 Header plus 3 Standard Words in time slot "n" and at the same time (during time slot "n") process a RTT Decode/Encode without interrupting the ongoing decode process. Both the decode and the RTT Decode/Encode will be performed with specified timing limits during this test.

4.3 RTT Decode/Encode Slot "n" - Encode Slot "n + 1"

This test will demonstrate that the RSED module is capable of processing a RTT Decode/Encode in slot "n" and is able to then encode a short message consisting of 1 Header (e.g. RTT interrogation) or a Standard Message consisting of 1 Header plus 3 Standard Words, in slot "n + 1".

IV. TEST RESULTS SUMMARY

In addition to the test data taken during the RSED Acceptance Test a summary of the test results will be prepared. This document will summarize the results of each test and include a comparison between system requirements and actual performance.